

the Options attribute, using the OptionsMask and OptionsOverride Fields. Each bit of the temporary Options bitmap SHALL be determined as follows:

Each bit in the Options attribute SHALL determine the corresponding bit in the temporary Options bitmap, unless the OptionsMask field is present and has the corresponding bit set to 1, in which case the corresponding bit in the OptionsOverride field SHALL determine the corresponding bit in the temporary Options bitmap.

The resulting temporary Options bitmap SHALL then be processed as defined in section [Options](#).

3.2.8.4. MoveToHue Command

This command will move the device to the requested hue value using a transition.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Hue	uint8	max 254			M
1	Direction	DirectionEnum	all			M
2	Transition-Time	uint16	max 65534			M
3	Options-Mask	Options-Bitmap	desc			M
4	OptionsOverride	Options-Bitmap	desc			M

3.2.8.4.1. Hue Field

This field SHALL indicate the hue to be moved to.

3.2.8.4.2. Direction Field

This field SHALL indicate the movement direction.

3.2.8.4.3. TransitionTime Field

This field SHALL indicate, in 1/10ths of a second, the time that SHALL be taken to move to the new hue.

3.2.8.4.4. OptionsMask and OptionsOverride Fields

These fields SHALL be processed according to section [Use of the OptionsMask and OptionsOverride Fields](#).

3.2.8.4.5. Effect on Receipt

On receipt of this command, a device SHALL also set the ColorMode attribute to the value 0 and then SHALL move from its current hue to the value given in the Hue field.