

NOTE

Here the TransitionTime data field is of data type uint8, where uint16 is more common for TransitionTime data fields in other clusters / commands.

3.2.8.6.4. OptionsMask and OptionsOverride Fields

These fields SHALL be processed according to section [Use of the OptionsMask and OptionsOverride Fields](#).

3.2.8.6.5. Effect on Receipt

On receipt of this command, if the StepSize field has a value of zero, the command has no effect and a response SHALL be returned with the status code set to INVALID_COMMAND.

Otherwise, a device SHALL set the ColorMode attribute to the value 0 (CurrentHueAndCurrentSaturation) and SHALL then move from its current hue in an up or down direction by one step, as detailed in the table.

StepMode	Action on Receipt
Up	Increase the device's hue by one step, in a continuous fashion. If the hue value reaches the maximum value then wraparound and proceed from the minimum allowed value.
Down	Decrease the device's hue by one step, in a continuous fashion. If the hue value reaches the minimum value then wraparound and proceed from the maximum allowed value.

3.2.8.7. MoveToSaturation Command

This command will move the device to the requested saturation value using a transition.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Saturation	uint8	max 254			M
1	Transition-Time	uint16	max 65534			M
2	Options-Mask	Options-Bitmap	desc			M
3	OptionsOverride	Options-Bitmap	desc			M

3.2.8.7.1. OptionsMask and OptionsOverride Fields

These fields SHALL be processed according to section [Use of the OptionsMask and OptionsOverride Fields](#).