

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	RateX	int16	all			M
1	RateY	int16	all			M
2	Options-Mask	Options-Bitmap	desc			M
3	OptionsOverride	Options-Bitmap	desc			M

3.2.8.12.1. RateX Field

This field SHALL indicate the rate of movement in steps per second. A step is a change in the device's CurrentX attribute of one unit.

3.2.8.12.2. RateY Field

This field SHALL indicate the rate of movement in steps per second. A step is a change in the device's CurrentY attribute of one unit.

3.2.8.12.3. OptionsMask and OptionsOverride Fields

These fields SHALL be processed according to section [Use of the OptionsMask and OptionsOverride Fields](#).

3.2.8.12.4. Effect on Receipt

On receipt of this command, if both the RateX and RateY fields contain a value of zero, no movement SHALL be carried out, and the command execution SHALL have no effect other than stopping the operation of any previously received command of this cluster. While this command (when used with both the RateX and RateY fields set to zero) can be used to stop any operation of this cluster, it is recommended to instead use the [StopMoveStep](#) command to achieve this goal.

Otherwise, a device SHALL set the value of the ColorMode attribute, where implemented, to 1 (CurrentXAndCurrentY), and SHALL then move from its current color in a continuous fashion according to the rates specified. This movement SHALL continue until the target color for the next step cannot be implemented on this device.

3.2.8.13. StepColor Command

This command will move the device to the requested color using a step transition.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	StepX	int16	all			M
1	StepY	int16	all			M
2	Transition-Time	uint16	max 65534			M