

ID	Name	Type	Constraint	Quality	Fallback	Conformance
3	Options-Mask	Options-Bitmap	desc			M
4	OptionsOverride	Options-Bitmap	desc			M

3.2.8.13.1. StepX and StepY Fields

These fields SHALL indicate the change to be added to the device's CurrentX attribute and CurrentY attribute respectively.

3.2.8.13.2. TransitionTime Field

The field SHALL indicate, in 1/10ths of a second, the time that SHALL be taken to perform the color change.

3.2.8.13.3. OptionsMask and OptionsOverride Fields

These fields SHALL be processed according to section [Use of the OptionsMask and OptionsOverride Fields](#).

3.2.8.13.4. Effect on Receipt

On receipt of this command, if both the StepX and StepY fields contain a value of zero, the command has no effect and a response SHALL be returned with the status code set to INVALID_COMMAND.

Otherwise, a device SHALL set the value of the ColorMode attribute, where implemented, to 1 (CurrentXAndCurrentY), and SHALL then move from its current color by the color step indicated.

The movement SHALL be continuous, i.e., not a step function, and the time taken to move to the new color SHALL be equal to the TransitionTime field, in 1/10ths of a second.

The path through color space taken during the transition is not specified, but it is recommended that the shortest path is taken through color space, i.e., movement is 'in a straight line' across the CIE xyY Color Space.

Note also that if the required step is larger than can be represented by signed 16-bit integers then more than one step command SHOULD be issued.

3.2.8.14. MoveToColorTemperature Command

This command will move the device to the requested color temperate using a transition.