

ID	Name	Type	Constraint	Quality	Fallback	Conformance
1	Direction	DirectionEnum	all			M
2	Transition-Time	uint16	max 65534			M
3	Options-Mask	Options-Bitmap	desc			M
4	OptionsOverride	Options-Bitmap	desc			M

3.2.8.15.1. EnhancedHue Field

This field SHALL indicate the target extended hue for the light.

3.2.8.15.2. Direction Field

This field SHALL indicate the movement direction.

3.2.8.15.3. TransitionTime Field

This field SHALL indicate the transition time, as described in the [MoveToHue](#) command.

3.2.8.15.4. OptionsMask and OptionsOverride Fields

These fields SHALL be processed according to section [Use of the OptionsMask and OptionsOverride Fields](#).

3.2.8.15.5. Effect on Receipt

On receipt of this command, a device SHALL set the ColorMode attribute to 0 (CurrentHueAndCurrentSaturation) and set the EnhancedColorMode attribute to the value 3 (EnhancedCurrentHueAndCurrentSaturation). The device SHALL then move from its current enhanced hue to the value given in the EnhancedHue field.

The movement SHALL be continuous, i.e., not a step function, and the time taken to move to the new enhanced hue SHALL be equal to the TransitionTime field.

3.2.8.16. EnhancedMoveHue Command

This command allows the light to start a continuous transition starting from their current hue.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	MoveMode	MoveModeEnum	desc			M
1	Rate	uint16	all			M