

3.2.8.17.5. Effect on Receipt

On receipt of this command, if the StepSize field has a value of zero, the command has no effect and a response SHALL be returned with the status code set to INVALID_COMMAND.

Otherwise, a device SHALL set the ColorMode attribute to 0 (CurrentHueAndCurrentSaturation) and the EnhancedColorMode attribute to the value 3 (EnhancedCurrentHueAndCurrentSaturation). The device SHALL then move from its current enhanced hue in an up or down direction by one step, as detailed in the table.

StepMode	Action on Receipt
Up	Increase the device's enhanced hue by one step. If the enhanced hue reaches the maximum allowed for the device, wraparound and proceed from its minimum allowed value.
Down	Decrease the device's enhanced hue by one step. If the hue reaches the minimum allowed for the device, wraparound and proceed from its maximum allowed value.

3.2.8.18. EnhancedMoveToHueAndSaturation Command

This command allows the light to be moved in a smooth continuous transition from their current hue to a target hue and from their current saturation to a target saturation.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Enhanced-Hue	uint16	all			M
1	Saturation	uint8	max 254			M
2	Transition-Time	uint16	max 65534			M
3	Options-Mask	Options-Bitmap	desc			M
4	OptionsOverride	Options-Bitmap	desc			M

3.2.8.18.1. EnhancedHue Field

This field SHALL indicate the target extended hue for the light.

3.2.8.18.2. Saturation Field

This field SHALL indicate the saturation, as described in the [MoveToHueAndSaturation](#) command.