

3.2.8.18.3. TransitionTime Field

This field SHALL indicate the transition time, as described in the [MoveToHue](#) command.

3.2.8.18.4. OptionsMask and OptionsOverride Fields

These fields SHALL be processed according to section [Use of the OptionsMask and OptionsOverride Fields](#).

3.2.8.18.5. Effect on Receipt

On receipt of this command, a device SHALL set the ColorMode attribute to the value 0 (CurrentHueAndCurrentSaturation) and set the EnhancedColorMode attribute to the value 3 (EnhancedCurrentHueAndCurrentSaturation). The device SHALL then move from its current enhanced hue and saturation to the values given in the EnhancedHue and Saturation fields.

The movement SHALL be continuous, i.e., not a step function, and the time taken to move to the new color SHALL be equal to the TransitionTime field, in 1/10ths of a second.

The path through color space taken during the transition is not specified, but it is recommended that the shortest path is taken through color space, i.e., movement is 'in a straight line' across the CIE xyY Color Space.

3.2.8.19. ColorLoopSet Command

This command allows a color loop to be activated such that the color light cycles through its range of hues.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	UpdateFlags	UpdateFlags- Bitmap	all			M
1	Action	Color- LoopActionEnum	all			M
2	Direction	ColorLoopDirectionEnum	all			M
3	Time	uint16	all			M
4	StartHue	uint16	all			M
5	Options-Mask	Options- Bitmap	desc			M
6	OptionsOverride	Options- Bitmap	desc			M

3.2.8.19.1. UpdateFlags Field

This field SHALL indicate which color loop attributes to update (from the values supplied in the other fields, see field descriptions below) before the color loop is started.