

mand.

A value of null SHALL indicate the duration is not set, meaning that the valve will remain open until closed by the user or some other automation.

4.6.8.1.2. TargetLevel Field

This field SHALL indicate the target level used for this specific Open command.

4.6.8.1.3. Effect on Receipt

If the device has registered a fault, that prevents it from performing the requested action, the command SHALL be ignored and a FailureDueToFault status SHALL be returned.

The device SHALL set the [TargetState](#) attribute to the Open value and set the [CurrentState](#) attribute to the Transitioning value.

If the OpenDuration field is present, the value of the [OpenDuration](#) attribute SHALL be set to the value of the OpenDuration field.

If the OpenDuration field is not present, the value of [OpenDuration](#) attribute SHALL be set to the value of the [DefaultOpenDuration](#) attribute.

If the [OpenDuration](#) attribute is null, it SHALL indicate that there is no auto close defined for the current Open action and the device SHALL set the [RemainingDuration](#) attribute to null. If the device supports the TimeSync feature, the device SHALL set the [AutoCloseTime](#) attribute to null.

If the [OpenDuration](#) attribute is not null, it indicates that an auto close duration is defined for the current open action and the device SHALL set the value of the [RemainingDuration](#) attribute equal to the value of the [OpenDuration](#) attribute. If the device supports the TimeSync feature, the device SHALL set the [AutoCloseTime](#) attribute to the UTC value of the time when command was received plus the value of the [OpenDuration](#) attribute.

If the [LevelStep](#) attribute and the TargetLevel field are both present and the value of the TargetLevel field is not 100, the value of the TargetLevel field SHALL be a supported value as defined by the [LevelStep](#) attribute, such that (Value of TargetLevel field) % (Value of [LevelStep](#) attribute) equals 0. If the resulting value is not 0, the requested TargetLevel value is considered an unsupported value and a CONSTRAINT_ERROR status SHALL be returned.

If the device supports the Level feature, the [TargetLevel](#) attribute SHALL be set to the value of the TargetLevel field, if present. If the TargetLevel field is not present, the [TargetLevel](#) attribute SHALL be set to the value of the [DefaultOpenLevel](#) attribute, if implemented. If the [DefaultOpenLevel](#) attribute is not present, the [TargetLevel](#) attribute SHALL be set to 100.

When the relevant target and duration attributes have been set, the device SHALL start the movement towards the target value and start the countdown of the [RemainingDuration](#) attribute. If the device supports the Level feature, the device SHALL update the [CurrentLevel](#) attribute at the start of the movement, and SHOULD update it as appropriate during movement, especially if it is slow. When the movement is complete, the device SHALL set the [CurrentState](#) attribute to the Open value.