

5.2.6.4.5. AutoRelockTime Bit

This bit SHALL indicate the state related to auto relock time:

- 0 = Auto relock time value is 0
- 1 = Auto relock time value is equal to something other than 0

5.2.6.4.6. LEDSettings Bit

This bit SHALL indicate the state related to LED settings:

- 0 = LED settings value is 0 (NoLEDSignal)
- 1 = LED settings value is equal to something other than 0

5.2.6.5. LocalProgrammingFeaturesBitmap Type

This data type is derived from map8.

Bit	Name	Summary	Conformance
0	AddUsersCredentialsSchedules	The state of the ability to add users, credentials or schedules on the device	M
1	ModifyUsersCredentialsSchedules	The state of the ability to modify users, credentials or schedules on the device	M
2	ClearUsersCredentialsSchedules	The state of the ability to clear users, credentials or schedules on the device	M
3	AdjustSettings	The state of the ability to adjust settings on the device	M

5.2.6.5.1. AddUsersCredentialsSchedules Bit

This bit SHALL indicate whether the door lock is able to add Users/Credentials/Schedules locally:

- 0 = This ability is disabled
- 1 = This ability is enabled

5.2.6.5.2. ModifyUsersCredentialsSchedules Bit

This bit SHALL indicate whether the door lock is able to modify Users/Credentials/Schedules locally:

- 0 = This ability is disabled
- 1 = This ability is enabled