

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	PINSlotIndex	uint16	1 to NumberOfPINUsersSupported, 0xFFFE			M

For each PIN Code cleared whose user doesn't have a RFID Code or other credential type, then corresponding user record's UserStatus value SHALL be set to Available, and UserType value SHALL be set to UnrestrictedUser and all schedules SHALL be cleared.

5.2.10.7.1. PINSlotIndex Field

This field SHALL specify a valid PIN code slot index or 0xFFFE to indicate all PIN code slots SHALL be cleared.

5.2.10.8. ClearAllPINCodes Command

Clear out all PINs on the lock.

NOTE

On the server, the clear all PIN codes command SHOULD have the same effect as the ClearPINCode command with respect to the setting of user status, user type and schedules.

5.2.10.9. SetUserStatus Command

Set the status of a user ID.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	UserID	uint16	desc			M
1	UserStatus	UserStatusEnum	desc			M

5.2.10.9.1. UserID Field

This field SHALL indicate the user ID. The value of the UserID field SHALL be between 0 and the value of the NumberOfPINUsersSupported attribute.

5.2.10.9.2. UserStatus Field

UserStatus value of Available is not allowed. In order to clear a user id, the ClearUser Command SHALL be used. For user status value please refer to [UserStatusEnum](#).

5.2.10.10. GetUserStatus Command

Get the status of a user.