

Use Case	Description
Modify credential for a Programming User	• OperationType SHALL be set to Modify. • UserIndex SHALL be null. • INVALID_COMMAND SHALL be returned if the accessing fabric index doesn't match the CreatorFabricIndex in the credential record pointed to by the CredentialIndex field value of the Credential parameter. • CredentialType in CredentialStruct SHALL be set to ProgrammingPIN. • CredentialIndex in CredentialStruct SHALL be 0. • UserStatus SHALL be null. • UserType SHALL be set to ProgrammingUser. CreatorFabricIndex SHALL NOT be changed in the credential record. LastModifiedFabricIndex in the credential record SHALL be set to the accessing fabric index. A LockUserChange event SHALL be generated after successfully modifying a ProgrammingUser PIN code.

5.2.10.36.1. OperationType Field

This field SHALL indicate the set credential operation type requested.

5.2.10.36.2. Credential Field

This field SHALL contain a credential structure that contains the [CredentialTypeEnum](#) and the credential index (if applicable or 0 if not) to set.

5.2.10.36.3. CredentialData Field

This field SHALL indicate the credential data to set for the credential being added or modified. The length of the credential data SHALL conform to the limits of the CredentialType specified in the Credential structure otherwise an INVALID_COMMAND status SHALL be returned in the [SetCredential-Response](#) command.

5.2.10.36.4. UserIndex Field

This field SHALL indicate the user index to the user record that corresponds to the credential being added or modified. This SHALL be null if OperationType is add and a new credential and user is being added at the same time.