

rated attribute to FALSE.

6.13.8.10. SetOnDemandRatingThreshold Command

The purpose of this command is to set the OnDemandRatingThreshold attribute.

Upon receipt of the SetOnDemandRatingThreshold command, the media device SHALL check if the Rating field is one of values present in the OnDemandRatings attribute. If not, then a response with InvalidRating error status SHALL be returned.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Rating	string	max 8			M

6.13.8.10.1. Rating

This field indicates a threshold rating for filtering on-demand content. This field SHALL be set to one of the values present in the OnDemandRatings attribute

6.13.8.11. SetScheduledContentRatingThreshold Command

The purpose of this command is to set ScheduledContentRatingThreshold attribute.

Upon receipt of the SetScheduledContentRatingThreshold command, the media device SHALL check if the Rating field is one of values present in the ScheduledContentRatings attribute. If not, then a response with InvalidRating error status SHALL be returned.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Rating	string	max 8			M

6.13.8.11.1. Rating

This field indicates a threshold rating for filtering scheduled content. This field SHALL be set to one of the values present in the ScheduledContentRatings attribute.

6.13.8.12. AddBlockChannels command

The purpose of this command is to set BlockChannelList attribute.

Upon receipt of the AddBlockChannels command, the media device SHALL check if the channels passed in this command are valid. If the channel is invalid, then a response with InvalidChannel error Status SHALL be returned.

If there is at least one channel in Channels field which is not in the BlockChannelList attribute, the media device SHALL process the request by adding these new channels into the BlockChannelList attribute and return a successful Status Response. During this process, the media device SHALL assign one unique index to BlockChannelIndex field for every channel passed in this command.

If all channels in Channel field already exist in the BlockChannelList attribute, then a response with