

ChannelAlreadyExist error Status SHALL be returned.

| ID | Name            | Type                     | Constraint | Quality | Fallback | Conformance |
|----|-----------------|--------------------------|------------|---------|----------|-------------|
| 0  | <b>Channels</b> | list[BlockChannelStruct] | all        |         |          | M           |

#### 6.13.8.12.1. Channels Field

This field indicates a set of channels that SHALL be blocked when the Content Control feature is activated. This field SHALL be set to values present in ChannelList attribute in the Channel cluster. The BlockChannelIndex field passed in this command SHALL be NULL.

#### 6.13.8.13. RemoveBlockChannels command

The purpose of this command is to remove channels from the BlockChannelList attribute.

Upon receipt of the RemoveBlockChannels command, the media device SHALL check if the channels indicated by ChannelIndexes passed in this command are present in BlockChannelList attribute. If one or more channels indicated by ChannelIndexes passed in this command field are not present in the BlockChannelList attribute, then a response with ChannelNotExist error Status SHALL be returned.

| ID | Name                  | Type         | Constraint | Quality | Fallback | Conformance |
|----|-----------------------|--------------|------------|---------|----------|-------------|
| 0  | <b>ChannelIndexes</b> | list[uint16] | all        |         |          | M           |

#### 6.13.8.13.1. ChannelIndexes Field

This field SHALL specify a set of indexes indicating Which channels SHALL be removed from the BlockChannelList attribute.

#### 6.13.8.14. AddBlockApplications Command

The purpose of this command is to set applications to the BlockApplicationList attribute.

Upon receipt of the AddBlockApplications command, the media device SHALL check if the Applications passed in this command are installed. If there is an application in Applications field which is not identified by media device, then a response with UnidentifiableApplication error Status MAY be returned.

If there is one or more applications which are not present in BlockApplicationList attribute, the media device SHALL process the request by adding the new application to the BlockApplicationList attribute and return a successful Status Response.

If all applications in Applications field are already present in BlockApplicationList attribute, then a response with ApplicationAlreadyExist error Status SHALL be returned.