Example Response	{
	   "response_code":0
	}

4.9. setAirPlayPin

For setting AirPlay PIN. This is valid only when "airplay" exists in "func_list" found in /system/getFuncStatus.

Request Parameters

name	type	required	description
pin	string	yes	Specifies AirPlay PIN (printable ASCII (0x20-0x7E) within 63 characters).

URI	<BaseURL>/v1/system/setAirPlayPin
Method	POST
Example Request (URI)	http://{host}/YamahaExtendedControl/v1/system/setAirPlayPin

Example Request (json)	{
	   "pin":"abc123"
	}

Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to "Response Code List" for details

Example Response	{
	   "response_code":0
	}

4.10. getMacAddressFilter

For retrieving setup of MAC Address Filter

Request Parameters

URI	<BaseURL>/v1/system/getMacAddressFilter
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/system/getMacAddressFilter

Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to "Response Code List" for details
filter	boolean	Returns whether or not Filter is valid
address_1	string	Returns MAC Address [1] (12 digit ASCII)
...	...	...
address_10	string	Returns MAC Address [10] (12 digit ASCII)