

Example Response	<pre>{   "response_code":0,   "model_name":"RX-V679",   "destination":"U",   "system_id":"ABADCAFE",   "system_version":1.10,   "api_version":1.00,   "netmodule_generation":2,   "netmodule_version":"0200",   "netmodule_checksum":"878059DD",   "operation_mode":"normal",   "update_error_code"."00000000" }</pre>
------------------	--

## 4.2. getFeatures

For retrieving feature information equipped with a Device

### Request Parameters

URI	<BaseURL>/v1/system/getFeatures
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/system/getFeatures

### Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to " <a href="#">Response Code List</a> " for details
system	object	Returns system's overall info
- func_list	string array	Returns valid functions Values: "wired_lan" / "wireless_lan" / "wireless_direct" / "extend_1_band" / "dfs_option" / "network_standby" / "network_standby_auto" / "bluetooth_standby" / "bluetooth_tx_setting" / "auto_power_standby" / "ir_sensor" / "speaker_a" / "speaker_b" / "headphone" / "dimmer" / "zone_b_volume_sync" / "hdmi_out_1" / "hdmi_out_2" / "hdmi_out_3" / "airplay" / "stereo_pair" / "speaker_settings" / "disklavier_settings" / "background_download" / "remote_info" / "network_reboot" / "system_reboot" / "auto_play" / "speaker_pattern" / "party_mode"
- zone_num	integer	Returns Zone numbers. Zone B is treated as Zone2 in YXC so a Device with ZoneB returns 2. A Device without Zones returns 1
- input_list	array	Returns a list of inputs
- id	string	Returns Input ID Refer to " <a href="#">All ID List</a> " for details
- distribution_enable	boolean	Returns whether an input can be a source of Link distribution
- rename_enable	boolean	Returns whether an input can be renamed
- account_enable	boolean	Return whether an input comes with an account info
- play_info_type	string	Returns a type of playback info. Depending on this type, use