Example Response	{
	"response_code":0,
	"filter":true,
	"address_1":"00A0DE1BFFFA",
	"address_2":"00A0DE1BFFFB",
	"address_3":"00A0DE1BFFFC",
	"address_4":"00A0DE1BFFFD",
	"address_5":"00A0DE1BFFFE",
	"address_6":"000000000000",
	"address_7":"000000000000",
	"address_8":"000000000000",
	"address_9":"000000000000",
	"address_10":"00A0DE1BFFFF"
	}

4.11. setMacAddressFilter

For setting MAC Address Filter

Request Parameters

name	type	required	description
filter	boolean	no	Specifies valid/invalid setup of Filter
address_1	string	no	Specifies MAC Address [1] (12 digit ASCII)
...	...	...	...
address_10	string	no	Specifies MAC Address [10] (12 digit ASCII)

URI	<BaseURL>/v1/system/setMacAddressFilter
Method	POST
Example Request (URI)	http://{host}/YamahaExtendedControl/v1/system/setMacAddressFilter
Example Request (json)	{
	"filter":true,
	"address_1":"00A0DE1BFFFA",
	"address_2":"00A0DE1BFFFB",
	"address_3":"00A0DE1BFFFC",
	"address_10":"00A0DE1BFFFF"
	}

Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to "Response Code List" for details

Example Response	{
	"response_code":0
	}