

**Request Parameters**

name	type	required	description
from	integer	yes	Specifies source preset number Values: one in the range gotten via /system/getFeatures
to	integer	yes	Specifies destination preset number Values: one in the range gotten via /system/getFeatures

URI	<BaseURL>/v1/netusb/movePreset?from=<from>&to=<to>		
Method	GET		
Example Request	http://{host}/YamahaExtendedControl/v1/netusb/movePreset?from=10&to=3		

**Response Parameters**

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to " <a href="#">Response Code List</a> " for details

Example Response	{ "response_code":0 }
------------------	-----------------------------

**7.16. getSettings**

For retrieving setup of Net/USB

**Request Parameters**

URI	<BaseURL>/v1/netusb/getSettings
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/netusb/getSettings

**Response Parameters**

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to " <a href="#">Response Code List</a> " for details
qobuz	object	Returns information related to Qobuz. Retrievable only when products are equipped with Qobuz functions.
- quality	object	Returns information related to Streaming Quality
- value	string	Returns current Streaming Quality Values: "hr_192_24" (HiRes - 24bits / up to 192kHz) "hr_96_24" (HiRes - 24bits / up to 96kHz) "cd_44_16" (CD - 16bits / 44.1kHz) "mp3_320" (MP3 - 320kbps)
- value_list	array	Returns a list of Streaming Quality available
- value	string	Returns value Values: "hr_192_24" / "hr_96_24" / "cd_44_16" / "mp3_320"
- attribute	integer	Returns attribute info. Attributes are expressed as OR of bit field as