

		main zone's one above.
zone3	object	Returns information related to Zone3. This data format is same as main zone's one above.
zone4	object	Returns information related to Zone4. This data format is same as main zone's one above.
protection_history	string array	Returns protection history (max size is 8 and top is the latest one)

Example Response	<pre>{   "response_code":0,   "model_name":"RX-V483",   "destination":"U",   "manufacture":"Yamaha Corporation",   "system_version":1.10,   "api_version":1.00,   "netmodule_version":"0200 ",   "netmodule_checksum":"878059DD",   "serial_number":"123456789abcdef",   "ip_address":"192.168.0.10",   "mac_address":{"     "wired_lan":"00A0DE012345",     "wireless_lan":"78A501012345",     "wireless_direct":"78A501012346"   },   "network_standby":"auto",   "main":{"     "power":"on",     "input":"siriusxm"   },   "zone2":{"     "power":"on",     "input":"cd"   },   "protection_history":[     "DC",     "PS2",     ...     "..."] }</pre>
------------------	---

#### 4.37. requestNetworkReboot

For requesting Network module reboot. Available only when " network\_reboot " exists in system - func\_list under /system/getFeatures.

##### **Request Parameters**

URI	<BaseURL>/v1/system/requestNetworkReboot
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/system/requestNetworkReboot