

		Values: "none" / "wep" / "wpa2-psk(aes)" / "mixed_mode"
- key	string	Reserved
- ch	integer	Returns a channel number of connected AP. Returns 0 when disconnected
- strength	integer	Returns wireless strength. Returns -1 when Link is down status Value Range: -1 (Link Down)、 0 ~ 100
wireless_direct	object	Returns information related to wireless network (Wireless Direct)
- ssid	string	Returns SSID
- type	string	Returns encryption type Values: "none" / "wpa2-psk(aes)"
- key	string	Reserved
musiccast_network	object	Returns information related to MusicCast Network
- ready	boolean	Returns a status whether or not a Device joins to MusicCast Network
- device_type	string	Returns a type of MusicCast Network on a Device. Returns "unknown" If not joined to MusicCast Network yet Values: "root" / "node" / "leaf" / "standard" / "unknown"
- child_num	integer	Returns clients number connected to a Device
- ch	integer	Returns a channel number that a Device discloses. Returns 0 when device_type is other than root or node
- initial_join_running	boolean	Returns whether or not Initial Join is being executed
- extend_1_band	string	Reserved
- wlan1_ch	integer	Reserved
- dfs	object	Reserved
- option	boolean	Reserved
- radar_ch	integer	Reserved
mac_address	object	Returns MAC Address (12 digit ASCII)
- wired_lan	string	Returns wired MAC Address
- wireless_lan	string	Returns wireless (Wi-Fi) MAC Address
- wireless_direct	string	Returns wireless (Wireless Direct) MAC Address
vtuner_id	string	Reserved
airplay_pin	string	Returns AirPlay PIN

Example Response	<pre>{ "response_code":0, "network_name":"Yamaha AVR", "connection":"wireless_lan", "dhcp":true, "ip_address":"192.168.0.10", "subnet_mask":"255.255.255.0", "default_gateway":"192.168.0.1", "dns_server_1":"192.168.0.1", "dns_server_2":"192.168.0.2", "wireless":{ "ssid":"AP1-2.4GHz", "type":"wpa2-psk(aes)", "key":"abadcafe", "strength":88 }, }</pre>
------------------	--