

## ZKTeco Laravel Library

☆ 6 stars    🍴 7 forks

☆ Star

🔔 Notifications

<> Code

🔔 Issues 4

🔗 Pull requests

🎬 Actions

📁 Projects

🛡 Security

📈 Insights

🔗 master ▾

Go to file



raihanafroz Update README.md ...

on Nov 27, 2020 ⌚ 24

[View code](#)

README.md

# ZKTeco - Laravel Library

issues 4 open   forks 7   stars 6   downloads 290   license MIT

The `rats/zkteco` package provides easy to use functions to ZKTeco Device activities.

**Requires: Laravel >= 6.0**

**License:** MIT or later

## Installation:

You can install the package via composer:

```
composer require rats/zkteco
```

The package will automatically register itself.

You have to enable your php socket if it is not enable.

## Usage

1. Create a object of ZKTeco class.

```
use Rats\Zkteco\Lib\ZKTeco;

// 1 s't parameter is string $ip Device IP Address
// 2 nd parameter is integer $port Default: 4370

$zk = new ZKTeco('192.168.1.201');

// or you can use with port
// $zk = new ZKTeco('192.168.1.201', 8080);
```

## 2. Call ZKTeco methods

- **Connect**

```
// connect
// this return bool
$zk->connect();
```

- **Disconnect**

```
// disconnect
// this return bool

$zk->disconnect();
```

- **Enable Device**

```
// enable
// this return bool/mixed

$zk->enableDevice();
```

**NOTE:** You have to call after read/write any info of Device.

- **Disable Device**

```
// disable
// this return bool/mixed

$zk->disableDevice();
```

**NOTE:** You have to call before read/write any info of Device.

- **Device Version**

```
//    get device version
//    this return bool/mixed
```

```
$zk->version();
```

- **Device Os Version**

```
//    get device os version
//    this return bool/mixed
```

```
$zk->osVersion();
```

- **Platform**

```
//    get platform
//    this return bool/mixed
```

```
$zk->platform();
```

- **Firmware Version**

```
//    get firmware version
//    this return bool/mixed
```

```
$zk->fmVersion();
```

- **Work Code**

```
//    get work code
//    this return bool/mixed
```

```
$zk->workCode();
```

- **SSR**

```
//    get SSR
//    this return bool/mixed
```

```
$zk->ssr();
```

- **Pin Width**

```
//    get Pin Width
//    this return bool/mixed
```

```
$zk->pinWidth();
```

- **Serial Number**

```
//    get device serial number  
//    this return bool/mixed
```

```
$zk->serialNumber();
```

- **Device Name**

```
//    get device name  
//    this return bool/mixed
```

```
$zk->deviceName();
```

- **Get Device Time**

```
//    get device time  
  
//    return bool/mixed bool|mixed Format: "Y-m-d H:i:s"
```

```
$zk->getTime();
```

- **Set Device Time**

```
//    set device time  
//    parameter string $t Format: "Y-m-d H:i:s"  
//    return bool/mixed
```

```
$zk->setTime();
```

- **Get Users**

```
//    get User  
//    this return array[]
```

```
$zk->getUser();
```

- **Set Users**

```
//    set user  
  
//    1 s't parameter int $uid Unique ID (max 65535)
```

```
// 2 nd parameter int|string $userid ID in DB (same like $uid, max length = 9, only numbers
// 3 rd parameter string $name (max length = 24)
// 4 th parameter int|string $password (max length = 8, only numbers - depends device setti
// 5 th parameter int $role Default Util::LEVEL_USER
// 6 th parameter int $cardno Default 0 (max length = 10, only numbers

// return bool|mixed

$zk->setUser();
```

### • Clear All Admin

```
// remove all admin
// return bool|mixed

$zk->clearAdmin();
```

### • Clear All Users

```
// remove all users
// return bool|mixed

$zk->clearAdmin();
```

### • Remove A User

```
// remove a user by $uid
// parameter integer $uid
// return bool|mixed

$zk->removeUser();
```

### • Get Attendance Log

```
// get attendance log

// return array[]

// like as 0 => array:5 [▼
//      "uid" => 1      /* serial number of the attendance */
//      "id" => "1"     /* user id of the application */
//      "state" => 1    /* the authentication type, 1 for Fingerprint, 4 for RF Card e
//      "timestamp" => "2020-05-27 21:21:06" /* time of attendance */
//      "type" => 255   /* attendance type, like check-in, check-out, overtime-in, ove
//      ]

$zk->getAttendance();
```

- Clear Attendance Log

```
// clear attendance log

// return bool/mixed

$zk->clearAttendance();
```

# end

---

## Releases 1



First Releases

Latest

on Aug 19, 2020

## Packages

No packages published

## Languages

● PHP 100.0%