LC4 Instruction Set		
Mnemonic	**Semantics**	**Encoding**
Instructions		
NOP	Do Nothing	0000000---------
BRn IMM9 <LABEL>	N ? PC = PC+1+SEXT(IMM9)	0000100IIIIIIIII
BRnz IMM9 <LABEL>	N|Z ? PC = PC+1+SEXT(IMM9)	0000110IIIIIIIII
BRnp IMM9 <LABEL>	N|P ? PC = PC+1+SEXT(IMM9)	0000101IIIIIIIII
BRz IMM9 <LABEL>	Z ? PC = PC+1+SEXT(IMM9)	0000010IIIIIIIII
BRzp IMM9 <LABEL>	Z|P ? PC = PC+1+SEXT(IMM9)	0000011IIIIIIIII
BRp IMM9 <LABEL>	P ? PC = PC+1+SEXT(IMM9)	0000001IIIIIIIII
BRnzp IMM9 <LABEL>	PC = PC+1+SEXT(IMM9)	0000111IIIIIIIII
ADD Rd Rs Rt	Rd = Rs + Rt	0001dddsss000ttt
MUL Rd Rs Rt	Rd = Rs * Rt	0001dddsss001ttt
SUB Rd Rs Rt	Rd = Rs - Rt	0001dddsss010ttt
DIV Rd Rs Rt	Rd = Rs / Rt	0001dddsss011ttt
ADD Rd Rs IMM5	Rd = Rs + SEXT(IMM5)	0001dddsss1IIIII
CMP Rs Rt	NZP = signed-CC(Rs-Rt)	0010sss00----ttt
CMPU Rs Rt	NZP = unsigned-CC(Rs-Rt)	0010sss01----ttt
CMPI Rs IMM7	NZP = signed-CC(Rs-SEXT(IMM7))	0010sss10IIIIIII
CMPIU Rs UIMM7	NZP = unsigned-CC(Rs-UIMM7)	0010sss11UUUUUUU
JSR IMM11 <LABEL>	R7 = PC + 1; PC = (PC & 0x8000) | (IMM11 << 4)	01001IIIIIIIIIII
JSRR Rs	R7 = PC + 1; PC = Rs	01000--sss------
AND Rd Rs Rt	Rd = Rs & Rt	0101dddsss000ttt
NOT Rd Rs	Rd = ~Rs	0101dddsss001---
OR Rd Rs Rt	Rd = Rs | Rt	0101dddsss010ttt
XOR Rd Rs Rt	Rd = Rs ^ Rt	0101dddsss011ttt
AND Rd Rs IMM5	Rd = Rs & SEXT(IMM5)	0101dddsss1IIIII
LDR Rd Rs IMM6	Rd = dmem[Rs + SEXT(IMM6)]	0110dddsssIIIIII
STR Rt Rs IMM6	dmem[Rs + SEXT(IMM6)] = Rt	0111tttsssIIIIII
RTI	PC = R7; PSR[15] = 0	1000------------
CONST Rd IMM9	Rd = SEXT(IMM9)	1001dddIIIIIIIII
SLL Rd Rs UIMM4	Rd = Rs << UIMM4	1010dddsss00UUUU
SRA Rd Rs UIMM4	Rd = Rs >>> UIMM4	1010dddsss01UUUU
SRL Rd Rs UIMM4	Rd = Rs >> UIMM4	1010dddsss10UUUU
MOD Rd Rs Rt	Rd = Rs % Rt	1010dddsss11-ttt
JMPR Rs	PC = Rs	11000--sss------
JMP IMM11 <LABEL>	PC = PC+1+SEXT(IMM11)	11001IIIIIIIIIII
HICONST Rd, UIMM8	Rd = (Rd & 0xFF) | (UIMM8 << 8)	1101ddd1UUUUUUUU
TRAP UIMM8	R7 = PC + 1; PC = (x8000 | UIMM8); PSR[15] = 1	1111----UUUUUUUU
Pseudo-Instructions		
RET	JMPR R7	
LEA R1 <LABEL>	R1 = address of label	
LC R1 <LABEL>	R1 = constant at label	
Assembly Directives		
.DATA	current memory is data	
.CODE	current memory is code	
.ADDR UIMM16	set current address to UIMM16	
.FALIGN	pad current address to 16-word boundary	
.FILL IMM16	set value at current address to IMM16	IIIIIIIIIIIIIIII
.BLKW UIMM16	reserve UIMM16 words at current address	0000000000000000
.CONST IMM16	associate IMM16 with preceding label	
.UCONST UIMM16	associate UIMM16 with preceding label	

001: opcode or sub-opcode
ddd: d-register, sss: s-register, ttt: t-register
III: signed immediate, UUU: unsigned immediate, ---: don't care