

ADI TFLITE MICRO SHARCFX

Product Description

ADI TFLITE Micro SHARC-FX is a library built using Google's TFLM (TensorFlow Lite for Microcontrollers) front-end with custom optimizations for select kernels enabling massive performance improvements as compared to the reference TFLM kernels. It has been tested on the EagleHP chips, ADSP 21835 and SC-835.

Product Highlights

ADI TFLITE Micro SHARC-FX module has been highly optimized to run on the EagleHP hardware using SHARC-FX intrinsics, to achieve performance improvements over vanilla TFLM.

To optimize the performance, bugs were fixed, and best practises were used according to industry standards.

This release supports optimization support for select kernels and features few example applications that the optimized library can enable running on SHARC-FX based chips (EagleHP).

The module provides a framework for users to get familiar with the library and encourages them to use it as part of their own applications, using the example applications as reference. The example applications contain projects that work on both file IO input as well as real-time input. This release features 4 applications (audio denoiser, keyword spotter, genre identification and Urbansound classification) that work both in File I/O and real-time modes.

Cycle count Summary Table

The cycle count results for the library kernels vary for different input and kernel configurations, a handful of which are summarized in the table below. The second table also describes the cycle counts for the applications that are real-time ready. The numbers mentioned are obtained from running the library/applications with the simulator in CCES. We have verified that the simulator numbers closely match the numbers we get from running them on the board(emulator).

Currently, there are 2 configurations of Convolution2D kernel, the kernel that gets selected based on the condition of which gives us the most speedup in each case.

CONV2D Generic Conv2d							
InHeight	InWidth	InChannels	FilterWidth	FilterHeight	FilterCh	FilterStride	CycleCount

ADI TFLITE Micro SHARC-FX Product Specification Sheet

128	128	1	3	3	64	1	13.723069 MCycles
32	32	8	3	3	64	1	1.584605 MCycles
32	32	16	3	3	64	1	3.073143 MCycles

CONV2D With RADD							
InHeight	InWidth	InChannels	FilterWidth	FilterHeight	FilterCh	FilterStride	CycleCount
128	128	1	3	3	64	1	309.191562 MCycles
32	32	8	3	3	64	1	18.992811 MCycles
16	16	512	3	3	64	1	11.907781 MCycles

DEPTHCONV2D							
InHeight	InWidth	InChannels	FilterH	FilterW	FilterCh	FilterStride	Cycle Count
25	5	64	3	3	64	1	0.067231 MCycles
13	5	276	3	3	276	1	0.147619MCycles

Fully Connected		
InNeurons	OutNeurons	Cycle Count
2048	1024	0.852112 MCycles

ADI TFLITE Micro SHARC-FX Product Specification Sheet

256	10	0.152445 MCycles
64	12	0.002094 MCycles

LSTM				
Batch	Timesteps	Input features	State dimension	Cycle Count
2	3	2	2	0.018977 MCycles
1	5	20	10	0.028556 MCycles
1	10	20	20	0.09395 MCycles
1	5	50	10	0.030291 MCycles

Application	Cycle Count
Keyword Spotter (per forward pass*)	1.359 MCycles
DTLN Denoiser (per forward pass*)	1.029 MCycles
Genre Identification (per forward pass*)	2.6 GCycles
Urbansound Classification (per forward pass*)	2.6 GCycles

(*) Keyword Spotter – 1 forward pass takes in 1 s of audio as input at 16KHz sampling rate.

(*) DTLN Denoiser – 1 forward pass takes in 32 ms of audio as input at 16KHz sampling rate.

(*) Genre Identification – 1 forward pass takes in 2.7 s of audio as input at 48000 Hz sampling rate.

(*) Urbansound classification – 1 forward pass takes in 2.7 s of audio as input at 48000 Hz sampling rate.

Deliverables

- ADI TFLITE Micro SHARC-FX Release package contains the optimized NN library with the TFLM frontend. It also contains the example applications both with File IO and real-time input for DTLN Denoiser, Keyword Spotter, Genre Identification and Urbansound Classification.
- Detailed documentation, for the user to get familiar with the project in the Getting Started Guide.
- Detailed steps to run the example applications on the simulator (in CCES) and emulator (board) and visualize the results in the User Guide.

Availability

This module is available in source code format after acceptance of ADI's Software License Agreement.

For support on any of our software modules, please contact local FAE.

Copyright, Disclaimer & Trademark Statements

Copyright Information

Copyright © 2021 Analog Devices, Inc. All Rights Reserved. This software is proprietary and confidential to Analog Devices, Inc. and its licensors. This document may not be reproduced in any form without prior, express written consent from Analog Devices, Inc.

Disclaimer

Analog Devices, Inc. ("Analog Devices") reserves the right to change this product without prior notice. Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use; nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under the patent rights of Analog Devices.

Trademark and Service Mark Notice

Analog Devices, the Analog Devices logo is the exclusive trademarks and/or registered trademarks of Analog Devices, Inc (Analog Devices).

All other brand and product names are trademarks or service marks of their respective owners.

Analog Devices' Trademarks and Service Marks may not be used without the express written consent of Analog Devices, such consent only to be provided in a separate written agreement signed by Analog Devices. Subject to the foregoing, such Trademarks and Service Marks must be used according to Analog Devices' Trademark Usage guidelines. Any licensee wishing to use Analog Devices' Trademarks and Service Marks must obtain and follow these guidelines for the specific marks at issue.