

# A N A L O G U E D E S K C O .

## INDEX-01 / User Manual

**Model:** INDEX-01

**Batch:** 001

**Creator:** Analogue Desk Co.

---

### 01 / THE CONCEPT

INDEX-01 bridges the gap between the ephemeral nature of digital data and the tactile permanence of instrumentation. Whether tracking market volatility or environmental signals, you now have a physical anchor for your most important data.

Thank you for acquiring a unit from Batch 001, the Founder's Batch.

### 02 / PRE-FLIGHT CHECK

Before powering the device for the first time, please note:

- **Power Input:** Use the provided USB-C cable. Connect to a standard 5V DC (0.5A) USB power source.
- **WiFi:** INDEX-01 is designed for stability on 2.4GHz WPA2 Home Networks. It is not compatible with 5GHz-only bands or other networks requiring a secondary login (Captive Portals).
- **Mechanical Care:** The needle is driven by a precision stepper motor. Do not manually rotate the needle, as this may misalign the needle and/or damage the internal gearing.

### 03 / SETUP WIFI

1. **Power On:** Connect the USB-C cable to the rear USB socket. The device will glow deep blue, indicating WiFi needs to be set up.
2. **Temporary Access Point:** On your smartphone or laptop, look for a WiFi network named **INDEX-01\_setup**. Connect to it.
3. **Portal:** A configuration page should open automatically. If it doesn't, navigate to <http://192.168.4.1> in your browser.
  - a. Use the password 'analoguedeskco'.
4. **Credentials:** Select your home WiFi network and enter your password.
5. **Save:** The device will reboot and begin initialisation.

## 04 / INITIALISATION

Once INDEX-01 has Wifi setup, the device initialisation sequence has several phases, indicated by the color of the unit:

- White (5 seconds): Reset mode. In this phase, it's possible to [factory reset](#) the device. Then:
- Light blue: Motor zeroing. The needle will sweep through its full range. If it buzzes lightly at one extreme, this is normal behaviour.
- Green: Centering. Pointer moves to midpoint.

The device then enters its current operating [mode](#). By default, this is the 'clock' mode, with the 'glacier' ambience.

## 05 / CONFIGURATION

- INDEX-01 runs an internal configuration portal allowing excellent customization options, of both mode and ambience, accessed by your normal web browser.
- In the browser, navigate to <http://index.local>.
  - It can take a little while after startup for your local network to recognise the new <http://index.local> address. Typically, you'll get ERR\_NAME\_NOT\_RESOLVED.
  - Please be patient. Try every minute for 10 minutes. Try different devices.
  - If this address does not work after this time, look up the IP address of INDEX-01 in your router's device list, or via a network scanner (like <http://www.fing.com>). Enter the IP address into a browser address bar.
  - It might be named differently depending on your local network. Look for a device with the manufacturer, 'Espressif'. This is the brand of the pre-certified microcontroller built into INDEX-01.
- In the Configuration UI:
  - **MODE:** select a data source
  - **AMBIENCE:** modify the LED lighting effects and night mode

- **ADVANCED:** diagnostic tools, reset options
- NOTE: The configuration UI is not available during the following situations.
  - Start up
  - Initialization
  - [Setup wifi mode](#)
  - Reboot
- NOTE: The configuration UI can take a few minutes to be available. Please retry if not found.

## 06 / MODE

Use this page to choose what data source INDEX-01 should reference. Each option has its own parameters.

- A simple clock function.
  - The hand sweeps across its range over 12 or 24 hours.
  - Timezones are supported
  - The default mode when new or factory reset.
- CoinMarketCap crypto price trends.
  - Enter a crypto ticker (BTC, ETH, etc.) to see changes over 24h, between -5% and +5%
  - A CMC API key is required. Sign up for a free one at <https://coinmarketcap.com/api/>
- CoinMarketCap Fear & Greed Index.
  - A CMC API key is required. Sign up for a free one at <https://coinmarketcap.com/api/>
- [Alt.me](#) Fear & Greed Index:
  - Similar to the above but no API key is required.
- Stock price trends
  - Enter a ticker symbol to see changes over 24h between -5% and +5%
- Temperature
  - Uses the supplied city location, and temperature range
- Air Quality Index
  - Uses the supplied city location
- Pomodoro timer
  - Pointer counts down from the provided duration, defaulting to 25 minutes.
- Test
  - Pointer cycles through min and max positions every 10 seconds
- Off
  - Pointer resets to vertical position useful for [calibration](#)

## 07 / AMBIENCE

Adjust the lighting effect, including night mode.

Any animated modes use CYCLE DURATION to control the speed of change. We recommend long durations like 600 seconds.

Modes:

- Static
  - A single unchanging colour. Mood.
- Pulse
  - A slowly undulating single colour mode. Like breathing.
- Glacial
  - Our favourite mode, breathless whites and ice blues.
- Aurora
  - Great for low-light. Electromagnetic storms of green and blue.
- Sunset
  - Hot colours to end a day.
- Chromatic
  - A dazzling spectrum of colours, best enjoyed with a truly extended CYCLE DURATION.

We'd love to hear your ideas for future Ambience modes: [hello@analoguedesk.co](mailto:hello@analoguedesk.co)

### 07.1 / AMBIENCE / NIGHT MODE

Adjust the lighting effect, including night mode. Ensure you have set your [timezone](#) if required.

## 08 / ADVANCED

Further capabilities and controls not needed for regular operation.

### 08.1 / ADVANCED / DIAGNOSTICS

This page provides useful troubleshooting information. You may be asked to copy and include this information in any support request. It includes things like:

- Software version

- Wifi status
- DNS name (defaults to index.local) - See [Device Name](#)
- Event log, showing control output messages including pointer position between 0 and 1

## 08.2 / ADVANCED / POINTER CALIBRATION

If the pointer is slightly misaligned, you can tweak it in software. Set the MODE to off in the [mode selection page](#). The pointer can be adjusted by  $-10^{\circ}$  to  $+10^{\circ}$ .

## 08.3 / ADVANCED / TIMEZONE

By default INDEX-01 is set to UTC (universal time). To ensure [night mode](#) works as expected, adjust to match your local timezone here.

## 08.4 / ADVANCED / DEVICE NAME

If you have more than one device on the same network, the device name should be changed to make each unique. The supplied name is used as a suffix for DNS and LAN identification. Once changed you need to navigate to the new config page, eg:

- `http://index-<suffix>.local`

## 08.5 / ADVANCED / REBOOT DEVICE

Perform a simple reboot. Settings are preserved.

## 08.6 / ADVANCED / RESET WIFI

Force the device to forget its current wifi connection settings and reboot. It will enter [Setup Wifi mode](#) and show deep blue.

## 08.7 / ADVANCED / FIRMWARE UPDATE

However INDEX-01 does have OTA (Over-The-Air) update capabilities via ElegantOTA.

Press select file and choose the .bin file to install.

No guarantee or support is provided for any software updates.

## 08.8 / ADVANCED / SOFTWARE FACTORY RESET

Use this option to reset the device. It will clear all settings (device name, mode, ambience) reboot and enter [Setup Wifi mode](#).

## 09 / HARDWARE FACTORY RESET

If you are unable to access the configuration portal after repeated attempts, and want to perform factory reset, follow these steps:

- Cycle the power 3 times, turning off while the device is in the White 'Reset Mode' phase of initialisation.
- When the device shows magenta colour, it has been factory reset.
- Refer to [Setup Wifi](#) to reconfigure the Wifi connection.

## 10 / CARE & MAINTENANCE

- **Acrylic Surfaces:** The case is constructed from layered, laser-cut acrylic. Clean only with a dry microfibre cloth. **Do not use isopropyl alcohol or glass cleaners**, as these can cause "crazing" (micro-cracks) in the material.
- **Hardware:** Periodically check that the M3 stainless steel bolts in the corners remain finger-tight. Do not overtighten.
- **Environmental:** For indoor use only. Keep dry.

## 11 / REGULATORY & SAFETY

- **Disposal:** This product is marked with the WEEE symbol. It must not be disposed of with household waste. Please return to a certified E-waste recycling centre.
- **Compliance:** Analogue Desk Co. declares that this device is in compliance with the essential requirements and other relevant provisions of the Radio Equipment Regulations 2017.
  - See the enclosed Declaration of Conformity for full details.

## 12 / COLOURS

INDEX-01 uses colours at launch to talk to you:

|       |                                                                       |
|-------|-----------------------------------------------------------------------|
| WHITE | Starting up. You have 5 seconds to trigger <a href="#">reset mode</a> |
| BLUE  | Waiting for <a href="#">Wifi setup</a>                                |
| CYAN  | Initialising motor                                                    |
| GREEN | Moving to mid-point, then into active                                 |

|         |                                                   |
|---------|---------------------------------------------------|
|         | <a href="#">mode</a> and <a href="#">ambience</a> |
| MAGENTA | Hardware reset complete                           |

## 13 / SUPPORT

This works both ways.

Thank you for supporting our dream.

Contact [support@analoguedesk.co](mailto:support@analoguedesk.co) with any further issues. We'll endeavour to assist!