Coupled Oscillations: Analysis of Symmetric and Asymmetric Modes

Andrés Vinuesa Espinosa Jose María Martínez Herrada

April 24, 2026

Abstract

This report analyzes coupled oscillations in a rigid bar connected to two springs. Frequency-response measurements were used to identify the natural, symmetric, and asymmetric modes of motion and to characterize mode splitting due to coupling. A superposition experiment was also examined to recover the slow and fast components of the composite signal. The results are consistent with the expected normal-mode behavior of a linear two-degree-of-freedom oscillator.

1 Introduction and Objectives

1.1 Theoretical Background

Coupled oscillatory systems are fundamental in physics, the phenomena although simple is most profound than what it appears. We can describe a wide range of phenomena, from the vibrations of molecules to the behavior of coupled pendulums, and even we can study waves as an infinite superposition of coupled oscillators. For gaining an intuitive understanding of the behavior of coupled oscillators, we use a simple model of one rod connected by two springs

For the uncoupled coordinates z_1 and z_2, the kinetic and potential energies are

$$T = \frac{1}{2}m\dot{z}_{CM}^2 + \frac{1}{2}I_{CM}\omega^2 = \frac{1}{8}m(\dot{z}_1 + \dot{z}_2)^2 + \frac{1}{24}m(\dot{z}_1 - \dot{z}_2)^2 \tag{1}$$

$$U = \frac{1}{2}kz_1^2 + \frac{1}{2}kz_2^2 \tag{2}$$

where m is the mass, k is the restoring constant of each spring and z_1 and z_2 are the displacements from equilibrium.

Then, we will decouple the system by diagonalizing the kinetic and potential energy matrices, which is easier to do in the normal coordinates

$$z_s = \frac{z_1 + z_2}{\sqrt{2}}, \qquad z_a = \frac{z_1 - z_2}{\sqrt{2}}. \tag{3}$$

Step 1: Define the Mass (M) and Stiffness (K) Matrices

Based on the kinetic and potential energy equations, the matrices are:

$$M = \frac{m}{6}\begin{pmatrix} 2 & 1 \\ 1 & 2 \end{pmatrix}, \quad K = \begin{pmatrix} k & 0 \\ 0 & k \end{pmatrix} \tag{4}$$

Step 2: Set up the Eigenvalue Problem

To find the natural frequencies (ω), we solve the characteristic equation by setting the determinant of $(K - \omega^2 M)$ to zero. Let $\lambda = \omega^2$:

$$\det(K - \lambda M) = 0 \tag{5}$$

Substituting our matrices into the equation:

$$K - \lambda M = \begin{pmatrix} k & 0 \\ 0 & k \end{pmatrix} - \lambda\frac{m}{6}\begin{pmatrix} 2 & 1 \\ 1 & 2 \end{pmatrix} = \begin{pmatrix} k - \frac{m}{3}\lambda & -\frac{m}{6}\lambda \\ -\frac{m}{6}\lambda & k - \frac{m}{3}\lambda \end{pmatrix} \tag{6}$$

Step 3: Calculate the Determinant

Now, calculate the determinant of the resulting matrix and set it to zero:

$$\left(k - \frac{m}{3}\lambda\right)^2 - \left(-\frac{m}{6}\lambda\right)^2 = 0 \tag{7}$$

This is a difference of squares ($A^2 - B^2 = 0$), which implies $A = \pm B$:

$$k - \frac{m}{3}\lambda = \pm\frac{m}{6}\lambda \tag{8}$$

Step 4: Solve for the Eigenvalues and Natural Frequencies

Case 1 (Positive):

$$k = \frac{m}{3}\lambda + \frac{m}{6}\lambda \implies k = \frac{m}{2}\lambda \implies \lambda_1 = \frac{2k}{m} \tag{9}$$

Since $\lambda = \omega^2$, the first natural frequency is:

$$\omega_1 = \sqrt{\frac{2k}{m}} \tag{10}$$

Case 2 (Negative):

$$k = \frac{m}{3}\lambda - \frac{m}{6}\lambda \implies k = \frac{m}{6}\lambda \implies \lambda_2 = \frac{6k}{m} \tag{11}$$

Since $\lambda = \omega^2$, the second natural frequency is:

$$\omega_2 = \sqrt{\frac{6k}{m}} \tag{12}$$

Diagonalizing the system is easier in the normal coordinates

$$z_s = \frac{z_1 + z_2}{\sqrt{2}}, \qquad z_a = \frac{z_1 - z_2}{\sqrt{2}}. \tag{13}$$

In these coordinates, the equations of motion decouple into

$$m\ddot{z}_s + 2kz_s = 0, \tag{14}$$

$$m\ddot{z}_a + 6kz_a = 0. \tag{15}$$

Therefore, the characteristic frequencies are

$$\omega_s = \sqrt{\frac{2k}{m}}, \tag{16}$$

$$\omega_a = \sqrt{\frac{6k}{m}}, \tag{17}$$

corresponding to the symmetric (slow) and asymmetric (fast) modes, respectively.

1.2 Measurement Methodology

The system was driven in four configurations: one fixed end for the natural mode, equal displacement for the symmetric mode, opposite displacement for the asymmetric mode. For every configuration we made sure that the displacement was small enough to ensure that linear behaviour holds, by giving a small initial displacement to the system, in the form of a small push, and then letting it vibrate freely, whilst the *DataStudio* software recorded the force signals from both ends. and one end excitation for the superposition case, without any constraints so it can vibrate as a superposition of the two modes. The force signals were recorded with PASCO sensors that measured the force of each end, and analyzed by sinusoidal fitting in the first three cases and sinusoidal fitting in the last one, and FFT peak identification.

The data analyzed with DataStudio software, presents the advantage of having built-in uncertainties for the fitting parameters, which are used to report the uncertainties in the measured frequencies. Nonetheless, we decided that due to the nature of the measurements, a fast fourier transform (FFT) analysis would be more appropriate for the superposition case, as it allows us to identify the individual frequency components, by taking the relatives maxima of the spectrum, and then we took the uncertainty as the sample standard deviation of the repeated measurements, we should note that the uncertainty reported by the software should be the main consideration to analyze the results, as it is based on the fitting procedure, a much more powerful algorithm that the standard deviation.

2 Materials and Methods

2.1 Experimental Setup

The apparatus consists of a rigid bar suspended by two identical springs and monitored with two force sensors. The system then is supported on air by a metallic apparatus that also serves as a way to carry the different experiments.

2.2 Data Acquisition and Analysis

Frequency sweeps were performed for the center reference and left/right configurations. The measured frequencies were converted from cycles per second to angular frequency using $\omega = 2\pi f$.

For repeated measurements, the reported uncertainty is the sample standard deviation of the repeated values unless the source file explicitly provides a different uncertainty.

3 Results and Data Analysis

As the two methods are different at a fundamental level, we have decided to report the results of the two methods separately, then we will compare the results of the two methods and see if they are consistent with each other, which should be the case if the model describes the system correctly, and if the measurements are accurate enough.

3.1 Measured Frequencies

Table 1 summarizes the characteristic frequencies extracted from the frequency-response measurements.

Mode	**FFT** (rad/s)	**Fit** (rad/s)	**Description**
Natural (ω_0)	14.84 ± 0.13	14.66 ± 0.23	Center reference oscillator
Symmetric (ω_s)	12.720 ± 0.060	12.51 ± 0.47	Both oscillators in phase
Asymmetric (ω_a)	19.80 ± 0.16	19.95 ± 0.11	Oscillators out of phase

Table 1: Measured angular frequencies for the three characteristic vibrational modes of the coupled oscillator system. FFT values are reported with their sample-standard-deviation uncertainty; fitting values are left as placeholders.

3.2 Mode Superposition

When one end of the bar is displaced while the other remains at rest, the motion contains two frequency components. These were identified as the slow and fast peaks of the spectrum.

Mode	**FFT** (rad/s)	**Fit** (rad/s)	**Description**
Minimum (ω_{min})	12.80 ± 0.10	12.77 ± 0.30	Superposition slow mode
Maximum (ω_{max})	19.31 ± 0.49	13.41 ± 0.30	Superposition fast mode

Table 2: Extracted angular frequencies from the superposed motion. FFT values are reported with sample-standard-deviation uncertainty; fitting values are left as placeholders.

3.3 Normal Coordinates Analysis

To further analyze the system's dynamics, the complex motion recorded in the superposition experiment was treated to extract the normal coordinates. Although the sensors measure individual forces, these are proportional to the vertical displacements z_1 and z_2. Thus, the normal coordinates were calculated as:

$$z_{CM} = z_1 + z_2, \qquad z_{12} = z_1 - z_2. \tag{18}$$

By applying the Fast Fourier Transform (FFT) to the composite signal, the two fundamental frequency components were isolated. These frequencies, representing the symmetric and asymmetric modes within the superposed motion, are presented in Table 3 and compared with the pure modes measured in Section 3.1.

Coordinate	**FFT Freq.** (rad/s)	**Pure Mode** (rad/s)	**Rel. Error (%)**
z_{CM} (Symmetric)	$\omega_{CM} = 12.83 \pm 0.10$	$\omega_s = 12.51 \pm 0.47$	2.56%
z_{12} (Asymmetric)	$\omega_{12} = 19.34 \pm 0.49$	$\omega_a = 19.95 \pm 0.11$	3.06%

Table 3: Comparison between frequencies extracted from normal coordinates via FFT and the previously measured pure modes.

The resulting time evolution of these coordinates was simulated using the experimental frequencies to visualize the decoupling of the motion (see Figure 1).



Figure 1: Time evolution of the isolated normal coordinates z_{CM} (blue) and z_{12} (red). The plot shows the transition from a complex beating pattern to two independent harmonic oscillations.

4 Discussion and Conclusions

4.1 Comparative Analysis of Theoretical Ratios and Experimental Data

The validity of the physical model is based on the consistency of the relationships between the frequencies of the normal modes. According to the theoretical development presented in section 1.1, the angular frequencies for the natural (ω_0), symmetric (ω_s), and asymmetric (ω_a) modes are governed by the system's constants (k and m). From the theoretical equations, the following ideal proportions are derived:

$$\frac{\omega_s}{\omega_0} = \sqrt{\frac{2}{3}} \approx 0.816, \qquad \frac{\omega_a}{\omega_0} = \sqrt{2} \approx 1.414, \qquad \frac{\omega_a}{\omega_s} = \sqrt{3} \approx 1.732. \tag{19}$$

When contrasting these values with our experimental results, we observe coherent behavior but with systematic

deviations that merit analysis. Using the data obtained through Fast Fourier Transform (FFT) analysis, the resulting ratios are:

$$\frac{\omega_{s,\text{fft}}}{\omega_{0,\text{fft}}} = \frac{12.72}{14.84} \approx 0.86, \qquad \frac{\omega_{a,\text{fft}}}{\omega_{0,\text{fft}}} = \frac{19.80}{14.84} \approx 1.33, \qquad \frac{\omega_{a,\text{fft}}}{\omega_{s,\text{fft}}} = \frac{19.80}{12.72} \approx 1.56. \tag{20}$$

On the other hand, the values extracted from the sinusoidal fit (*Fit*) in the time domain yield similar proportions:

$$\frac{\omega_{s,\text{fit}}}{\omega_{0,\text{fit}}} = \frac{12.51}{14.66} \approx 0.85, \qquad \frac{\omega_{a,\text{fit}}}{\omega_{0,\text{fit}}} = \frac{19.95}{14.66} \approx 1.36, \qquad \frac{\omega_{a,\text{fit}}}{\omega_{s,\text{fit}}} = \frac{19.95}{12.51} \approx 1.59. \tag{21}$$

The most notable discrepancy is found in the ω_a/ω_s factor, where the experimental value (≈ 1.58) falls below the theoretical one (1.73). This deviation indicates that the real system presents a lower effective stiffness in the asymmetric mode than what the ideal rigid bar model predicts. Factors such as the finite elasticity of the bar, friction in the supports, and the possible lack of linearity in the springs under large extensions contribute to this result. But in general, we can observe that despite the discrepancies present, the obtained data fits the theory in question.

4.2 Discussion on Methodology: Sinusoidal Fitting vs. Spectral Analysis

One of the key points of this analysis has been to evaluate data processing techniques for complex signals. The sinusoidal fit proved to be the most accurate tool for characterizing the pure modes ($\omega_0, \omega_s, \omega_a$), since the signal is interpreted by the program itself using the data provided, and the minimization of the squared error by the DataStudio software is extremely efficient in these cases.

However, this technique failed critically when analyzing the superposition experiment. As detailed in Table 2, the sinusoidal fit for the high-frequency component in superposition yielded a value of 13.41 ± 0.30 rad/s. This result lacks physical sense, as it should approach the ~ 19 rad/s of the asymmetric mode. The explanation may be due to a failure of the program itself, since in the rest of the modes it yields what it should and in this case it does not, yet if we take the program's data and run it through the FFT, it gives a value quite close to the theoretical one.

In contrast, the FFT has proven to be the superior method for studying coupled systems. By transforming the signal to the frequency domain, the FFT allows us to visually and mathematically "decouple" the motion components. The spectral peaks in the superposition turned out to be $\omega_{min} = 12.83$ rad/s and $\omega_{max} = 19.34$ rad/s. When comparing these values with the independently measured pure mode frequencies ($\omega_s = 12.72$ and $\omega_a = 19.80$), the relative errors are below 3%. This constitutes definitive proof that the observed complex motion is a linear superposition of the system's normal modes.

4.3 Interpretation of Normal Coordinates and Decoupling

Looking at Table 3, we can see that the theory of normal modes holds up perfectly in the lab. The errors between the frequencies hidden inside that motion and the pure modes we measured earlier are really low (under 3.1%). This basically proves that when the bar does that motion, it isn't doing anything new; it's just playing the symmetric and asymmetric modes at the same time.

Calculating z_{CM} and z_{12} is a great way to see how it actually works in real life. If we just look at the raw sensor data (z_1 and z_2), the springs and the bar are pushing against each other, passing energy back and forth (which creates the beats). But when we switch to normal coordinates (the sum and the difference), it's like looking at two completely independent oscillators.

Physically, the sum (ω_{CM}) is just the whole bar bouncing up and down. The difference (ω_{12}) is the bar rocking back and forth. This second motion oscillates much faster because the springs are stretching in opposite directions, making the whole setup feel much stiffer.

4.4 Final Remarks

In conclusion, the experiment conforms to the theory of coupled oscillators and the phenomenon of mode splitting. It has been verified that the degree of coupling of the system, determined by the interaction of the springs through the

inertia of the bar, defines a characteristic frequency spectrum that remains constant regardless of the initial displacement conditions.

The results highlight the importance of using tools such as the FFT when working with this type of system, as conventional fitting methods prove insufficient to resolve simultaneous frequency components. Finally, the observed deviations from the theoretical proportions provide a measure of the non-ideality of the experimental setup, suggesting that energy dissipation and the actual mass distribution are factors that must be considered in more advanced models. Nevertheless, the internal consistency of the data and results obtained during this practice show that the experiment aligns with the theory.

References