Machine Translated by Google

Farasis Energy (Ganzhou) Co., Ltd.

Battery cell product specification sheet

Model Number: MP06160231S35C

Machine Translated by Google

Revised resume (document creation and revision resume)

Version	Release date (date of revision)	Changes in Modification (Revision and Development Summary)	Maker (Reviser)	Approver
A0	2025-12-31	New release	Qiu Lelin, Wen	Shilong/Wang Lihong

Machine Translated by Google

Table of contents

Table of Contents.....3
1. Scope of Application.....4 2. Product Electrical Performance Indicators (BOL).....4
2.1 Summary 4
2.2 Charge mode/parameter (begin of life) (BOL).....5
2.2.1 Step charging (SC) mode Fast charging mode.....5
2.2.2 Simplified Step Charging (SC) Mode (Simplified Fast Charging Mode.....5)
2.3 Impulse charging mode (BOL).....6
2.3.1 Allow pulse charge current and duration.....6
2.4 Impulse Discharging Mode (BOL) 6
2.4.1 Allow pulse discharge current and duration.....6
2.5 Other continuous discharge conditions (C) 8
2.6 High and low temperature discharge capacity (BOL) 8
3 Static SOC-OCV (BOL) .....8 4 Security and Reliability (BOL) .....9 5 Storage Performance (BOL) .....10 6 Application Conditions.....10
6.1 The BMS shall include the following basic monitoring and control features: 10
7. Product End of Life Management.....13 8. Safety Usage Specification.....13 9. Disclaimer.....14
10. Accessories: Cell drawings.....15

Machine Translated by Google

1. **Scope** of Application

This specification describes the performance, specifications, and operating conditions of the MP06160231S35C battery cell manufactured by Farasis.

2. **Product electrical** performance indicators (BOL)

2.1 Summary

No. Serial Number	Parameter	Product Specification Product Specifications	Condition
2.1.1	Standard capacity (nominal capacity 1)	35.0Ah	@1/3C@4.35~2.5V@25ÿ 1/3C CCCV charging, 0.02C cutoff.
2.1.2	Standard capacity (nominal capacity 2)	33.7Ah	@1C@4.35~2.5V@25ÿ 1/3C CCCV charging, 0.02C cutoff.
2.1.3	Nominal voltage 1	3.73V	@1/3C@4.35~2.5V@25ÿ
2.1.4	Nominal voltage 2	3.63V	@1C@4.35~2.5V@25ÿ
2.1.5	Weight energy density Weight energy density	265Wh/Kg	@1/3C@4.35~2.5V@25ÿ
2.1.6	Volumetric energy density Volumetric energy density	581Wh/L	@1/3C@4.35~2.5V@25ÿ
2.1.7	Operating voltage range Operating voltage range 1	2.5~4.35V	10ÿÿTÿ60ÿ
2.1.8	Operating voltage range Operating voltage range 2	2.3~4.35V	0ÿÿTÿ10ÿ
2.1.9	Operating voltage range Operating voltage range 3	2.1~4.35V	-30ÿÿTÿ0ÿ
2.1.10 AC internal resistance < 3.0mÿ			~55%SOC@25ÿÿ1KHZ
2.1.11 DC internal resistance < 4.0mÿ			~55%SOC@25ÿÿ1C10s
2.1.12	Charging operating temperature Operating temperature (charging)	-15~55ÿ	Includes all charging modes (body temperature).
2.1.13	Discharging operating temperature Operating temperature (discharge)	-30~60ÿ	Includes all discharge modes (body temperature).
2.1.14	Cycle life 1 Cycle life 1	ÿ2000	@0.5C/1C@4.3~3.0V @25ÿ to 80%SOH
2.1.15 Recommended charging cutoff voltage		4.3V	Includes all charging operating temperatures
2.1.16 Battery weight		498±15g	Maximum weight: 513g
2.1.17 Cell size		Thickness: 6.15±0.15mm (0.2 MPa pressure, pressurize for 20-30 seconds, read) number) Width: 160±1mm (tested by pressing the folded edge) Height: 231±1mm	Maximum thickness: 6.3mm (0.2MPa pressure) (Read the value after pressurizing for 20-30 seconds) Maximum width: 161mm (measured upon pressing and folding the edge) try) Maximum height: 232mm
2.1.18 Cell Expansion Coefficient		6%	/
2.1.19 Maximum continuous discharge current		3C	@25ÿ

Machine Translated by Google

2.2 Charge mode/parameter (begin of life) (BOL)

2.2.1 Step charging (SC) mode (fast charging mode)

Fast charging maximum allowable continuous charging current meter (required for the announcement version of the software) (without this meter: the battery cannot be fast charged) BOL 1C=35A, charging cutoff upper limit voltage 4.30V.																		
SOC limit 100%		temperature																
No.	Voltage/ In	<-15ÿ	-15ÿ -10ÿ		-5ÿ	0ÿ	5ÿ	10ÿ	15ÿ	20ÿ	25ÿ	30ÿ	35ÿ	40ÿ	45ÿ	50ÿ	52ÿ	55ÿ >55ÿ	
1	ÿ2.75	Do not charge not Allow charging	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	Do not charge not Allow charging
2	3.3		0.100	0.160	0.225	0.400	0.450	0.450	1.125	1.200	1.200	1.200	1.200	1.200	0.900	0.330	0.100	0.100	
3	3.750		0.100	0.160	0.225	0.400	0.450	0.450	1.125	1.200	1.200	1.200	1.200	1.200	0.900	0.330	0.100	0.100	
4	3.800		0.055	0.113	0.225	0.400	0.450	0.450	1.125	1.200	1.200	1.200	1.200	1.200	0.900	0.330	0.100	0.100	
5	3.840		0.048	0.097	0.143	0.300	0.450	0.450	1.125	1.200	1.200	1.200	1.200	1.200	0.900	0.330	0.100	0.100	
6	3.870		0.045	0.093	0.128	0.252	0.450	0.450	1.125	1.200	1.200	1.200	1.200	1.200	0.900	0.330	0.100	0.100	
7	3.900		0.043	0.089	0.121	0.237	0.450	0.450	0.923	1.200	1.200	1.200	1.200	1.200	0.900	0.330	0.100	0.100	
8	3.940		0.041	0.084	0.115	0.224	0.438	0.450	0.765	1.200	1.200	1.200	1.200	1.200	0.900	0.330	0.100	0.100	
9	3.960		0.038	0.081	0.109	0.213	0.393	0.450	0.637	1.200	1.200	1.200	1.200	1.200	0.900	0.330	0.100	0.100	
10	3.970		0.038	0.081	0.108	0.209	0.379	0.450	0.596	1.010	1.167	1.167	1.073	0.933	0.700	0.330	0.100	0.100	
11	4.010		0.034	0.075	0.101	0.193	0.341	0.373	0.533	0.775	0.925	0.925	0.851	0.740	0.555	0.330	0.100	0.100	
12	4.050		0.030	0.067	0.093	0.177	0.315	0.338	0.494	0.690	0.820	0.820	0.754	0.656	0.492	0.330	0.100	0.100	
13	4.100		0.029	0.059	0.084	0.157	0.284	0.323	0.450	0.641	0.722	0.722	0.664	0.577	0.433	0.330	0.100	0.100	
14	4.150		0.024	0.053	0.074	0.139	0.259	0.309	0.405	0.579	0.639	0.639	0.588	0.511	0.383	0.330	0.100	0.100	
15	4.200		0.020	0.046	0.064	0.122	0.234	0.295	0.354	0.498	0.540	0.540	0.496	0.432	0.324	0.291	0.100	0.100	
16	4.220		0.020	0.043	0.061	0.115	0.224	0.277	0.336	0.469	0.510	0.510	0.469	0.408	0.306	0.275	0.100	0.100	
17	4.240		0.019	0.040	0.057	0.109	0.216	0.277	0.324	0.441	0.484	0.484	0.446	0.388	0.291	0.262	0.100	0.100	
18	4.245		0.018	0.040	0.056	0.107	0.213	0.274	0.320	0.436	0.477	0.477	0.439	0.382	0.286	0.258	0.100	0.100	
19	4.250		0.018	0.040	0.055	0.107	0.211	0.269	0.315	0.431	0.472	0.472	0.434	0.377	0.283	0.255	0.100	0.100	
20	4.255		0.017	0.038	0.053	0.105	0.208	0.269	0.313	0.425	0.460	0.460	0.423	0.368	0.276	0.248	0.100	0.100	
21	4.260		0.017	0.038	0.052	0.103	0.204	0.263	0.308	0.420	0.458	0.458	0.421	0.366	0.275	0.247	0.100	0.100	
22	4.265		0.017	0.037	0.050	0.101	0.203	0.261	0.303	0.415	0.452	0.452	0.416	0.362	0.271	0.244	0.100	0.100	
23	4.270		0.016	0.037	0.049	0.099	0.199	0.257	0.303	0.390	0.445	0.445	0.409	0.356	0.267	0.240	0.100	0.100	
24	4.275		0.015	0.035	0.047	0.080	0.196	0.254	0.298	0.338	0.439	0.439	0.403	0.351	0.263	0.237	0.100	0.100	
25	4.280		0.014	0.035	0.046	0.070	0.195	0.249	0.294	0.299	0.308	0.308	0.283	0.246	0.185	0.166	0.100	0.100	
26	4.285		0.013	0.034	0.044	0.060	0.150	0.188	0.225	0.233	0.240	0.240	0.221	0.192	0.144	0.130	0.100	0.100	
27	4.295		0.012	0.033	0.043	0.050	0.075	0.113	0.135	0.143	0.150	0.150	0.138	0.120	0.090	0.081	0.100	0.100	
28	4.300		0.010	0.010	0.010	0.010	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	

Remarks: Notes

1. Charging is not allowed at a temperature of less than -15ÿ and greater than 55ÿ

Charging is not permitted at temperatures below -15ÿ and above 55ÿ.

2.Voltage range that can be charged:4.3-2.5V(room temperature)

Permissible charging voltage range: 4.3-2.5V (room temperature);

3.The charging rate changes with aging. After aging, the charging rate is BOL charging rate *SOH.

The charging rate changes with aging. After aging, the charging rate is BOL = charging rate * SOH.

2.2.2 Simplified Step charging (SC) mode

Fast charging maximum allowable continuous charging current meter (required for the announcement version of the software) (without this meter: the battery cannot be fast charged) BOL 1C=35A, charging cutoff upper limit voltage 4.30V.																		
SOC limit 100%		temperature																
No.	Voltage/ In	<-15ÿ	-15ÿ -10ÿ		-5ÿ	0ÿ	5ÿ	10ÿ	15ÿ	20ÿ	25ÿ	30ÿ	35ÿ	40ÿ	45ÿ	50ÿ	52ÿ	55ÿ >55ÿ	
1	ÿ2.75	Do not charge not Allow charging	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	Do not charge not Allow charging
2	3.3		0.100	0.160	0.225	0.400	0.450	0.450	1.125	1.200	1.200	1.200	1.200	1.200	0.900	0.330	0.100	0.100	
3	3.750		0.100	0.160	0.225	0.400	0.450	0.450	1.125	1.200	1.200	1.200	1.200	1.200	0.900	0.330	0.100	0.100	
4	3.840		0.048	0.097	0.143	0.300	0.450	0.450	1.125	1.200	1.200	1.200	1.200	1.200	0.900	0.330	0.100	0.100	
5	3.900		0.043	0.089	0.121	0.237	0.450	0.450	0.923	1.200	1.200	1.200	1.200	1.200	0.900	0.330	0.100	0.100	
6	3.940		0.041	0.084	0.115	0.224	0.438	0.450	0.765	1.200	1.200	1.200	1.200	1.200	0.900	0.330	0.100	0.100	
7	3.970		0.038	0.081	0.108	0.209	0.379	0.450	0.596	1.010	1.167	1.167	1.073	0.933	0.700	0.330	0.100	0.100	
8	4.010		0.034	0.075	0.101	0.193	0.341	0.373	0.533	0.775	0.925	0.925	0.851	0.740	0.555	0.330	0.100	0.100	
9	4.100		0.029	0.059	0.084	0.157	0.284	0.323	0.450	0.641	0.722	0.722	0.664	0.577	0.433	0.330	0.100	0.100	
10	4.150		0.024	0.053	0.074	0.139	0.259	0.309	0.405	0.579	0.639	0.639	0.588	0.511	0.383	0.330	0.100	0.100	
11	4.220		0.020	0.043	0.061	0.115	0.224	0.277	0.336	0.469	0.510	0.510	0.469	0.408	0.306	0.275	0.100	0.100	
12	4.245		0.018	0.040	0.056	0.107	0.213	0.274	0.320	0.436	0.477	0.477	0.439	0.382	0.286	0.258	0.100	0.100	
13	4.255		0.017	0.038	0.053	0.105	0.208	0.269	0.313	0.425	0.460	0.460	0.423	0.368	0.276	0.248	0.100	0.100	
14	4.265		0.017	0.037	0.050	0.101	0.203	0.261	0.303	0.415	0.452	0.452	0.416	0.362	0.271	0.244	0.100	0.100	
15	4.275		0.015	0.035	0.047	0.080	0.196	0.254	0.298	0.338	0.439	0.439	0.403	0.351	0.263	0.237	0.100	0.100	
16	4.295		0.012	0.033	0.043	0.050	0.075	0.113	0.135	0.143	0.150	0.150	0.138	0.120	0.090	0.081	0.100	0.100	
17	4.300		0.010	0.010	0.010	0.010	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	0.050	

Remarks: Notes

1. Charging is not allowed at a temperature of less than -15ÿ and greater than 55ÿ

Charging is not permitted at temperatures below -15ÿ and above 55ÿ.

2.Voltage range that can be charged:4.3-2.5V(room temperature)

Permissible charging voltage range: 4.3-2.5V (room temperature);

3.The charging rate changes with aging. After aging, the charging rate is BOL charging rate *SOH.

The charging rate changes with aging. After aging, the charging rate is BOL = charging rate * SOH.

Machine Translated by Google

2.3 Impulse charging mode (BOL)

2.3.1 Allow pulse charge current and duration

2.3.1.1 Pulse (10s) charge current map

SOC -20ÿ -15ÿ -10ÿ -5ÿ 0ÿ						5ÿ 10ÿ 15ÿ 20ÿ 25ÿ 30ÿ 35ÿ 40ÿ 45ÿ 50ÿ 55ÿ 60ÿ												
0% 2.88 10%		6.48	10.32	15.96	21.60	33.60	45.60	70.40	84.00	84.00	84.00	84.00	84.00	84.00	84.00	84.00	45.60	21.60
2.48 20% 2.24		5.08	8.16	12.96	18.40	26.00	34.08	53.92	73.76	84.00	84.00	84.00	84.00	84.00	84.00	84.00	34.08	17.76
30% 2.17 40%		4.40	6.96	11.16	15.36	22.20	29.04	44.16	59.28	74.40	84.00	84.00	84.00	84.00	84.00	78.35	29.04	15.36
2.04		4.18	6.24	10.32	14.40	21.24	28.08	41.39	54.69	68.00	79.60	84.00	84.00	84.00	84.00	67.40	28.08	14.40
		3.68	5.76	9.60	13.44	20.40	27.36	39.84	52.32	64.80	73.20	81.60	84.00	84.00	84.00	59.57	27.36	13.44
50%	1.92	3.36	5.28	8.76	12.24	18.36	24.48	36.32	48.16	60.00	67.20	74.40	80.78	82.81	82.81	53.64	24.48	12.24
60%	1.76	3.08	4.80	7.80	10.80	16.20	21.60	29.60	37.60	45.60	55.20	64.80	73.66	78.39	78.39	49.99	21.60	10.80
70%	1.52	2.92	4.32	6.84	9.36	13.68	18.00	26.40	34.80	43.20	51.60	60.00	67.72	71.66	71.66	44.83	18.00	9.36
80%	1.36	2.60	3.84	6.16	8.64	12.36	16.56	24.64	32.72	40.80	48.00	55.20	61.78	64.93	64.93	40.75	16.56	8.16
90% 1.20 95%		1.92	3.12	5.04	7.52	11.28	15.60	23.20	30.80	38.40	43.20	48.00	52.27	53.72	53.72	34.66	15.60	6.96
0.96		1.48	2.00	4.16	6.56	8.08	9.60	13.63	18.14	22.65	31.33	40.00	48.19	50.74	50.74	29.93	9.12	4.32

2.3.1.2 Pulse (30s) charge current map

SOC -20ÿ -15ÿ -10ÿ -5ÿ 0ÿ						5ÿ 10ÿ 15ÿ 20ÿ 25ÿ 30ÿ 35ÿ 40ÿ 45ÿ 50ÿ 55ÿ 60ÿ												
0% 2.64 10%		5.96	9.04	14.92	20.80	30.56	20.80	40.32	59.04	77.76	84.00	84.00	84.00	84.00	84.00	77.76	40.32	82.80	82.80	66.40
2.00 20% 1.84		4.88	7.28	12.84	17.76	25.92	18.40	33.60	50.00	66.40	82.80	82.80	82.80	33.60	67.20	67.20	54.24	28.32		
		4.44	6.64	10.72	14.80	21.56	14.80	28.32	41.28	54.24	67.20	67.20	67.20							
30% 1.76 40%		4.04	5.92	9.76	13.60	20.00	26.40	37.92	49.44	60.96	60.96	60.96	60.96	60.96	49.44	26.40	59.52	59.52	48.16	13.60
1.60 50% 1.44		3.66	5.28	9.04	12.80	19.12	25.44	36.80	48.16	59.52	59.52	59.52	25.44	54.72	54.72	44.48	24.00			12.80
		3.36	4.80	8.40	12.00	18.00	24.00	34.24	44.48	54.72	54.72	54.72								12.00
60% 1.36 70%		3.08	4.40	7.52	10.64	15.40	20.16	26.72	33.28	39.84	39.84	39.84	39.84	39.84	33.28	37.20	37.20	20.16		10.64
1.20 80% 0.96		2.84	4.16	6.68	9.20	12.88	16.56	23.44	30.32	37.20	37.20	37.20	30.32					16.56		9.20
		2.52	3.68	6.00	8.16	12.24	15.84	22.48	29.12	35.76	35.76	35.76	35.76	35.76	29.12			15.84		8.64
90% 0.72 95%		1.84	2.48	5.00	6.96	10.96	14.40	20.24	26.08	31.92	31.92	31.92	31.92	31.92	26.08	18.48	18.48	14.40		7.52
0.48		1.36	1.76	3.16	4.32	6.72	9.12	12.56	15.52	18.48	18.48	18.48	15.52					9.60		6.56

2.3.1.3 Pulse (60s) charge current map

SOC -20ÿ -15ÿ -10ÿ -5ÿ 0ÿ						5ÿ 10ÿ 15ÿ 20ÿ 25ÿ 30ÿ 35ÿ 40ÿ 45ÿ 50ÿ 55ÿ 60ÿ												
0% 0.48 10%		0.72	2.40	4.80	4.80	9.60	15.60	21.60	25.20	28.80	28.80	28.80	28.80	28.80	28.80	14.40	28.80	28.80	28.80	28.80	8.64
0.48 20% 0.48		0.72	2.40	4.80	4.80	9.60	15.60	21.60	25.20	28.80	14.40	28.80	28.80	28.80	28.80	28.80	28.80	14.40			8.64
		0.72	1.92	4.80	4.80	9.60	15.60	21.60	25.20												7.14
30% 0.24 40%		0.72	1.68	3.84	4.80	9.60	15.60	21.60	25.20	28.80	28.80	28.80	28.80	28.80	28.80	14.40	28.80	28.80	28.80	28.80	6.53
0.24 50% 0.24		0.48	1.68	3.36	4.80	8.40	12.60	16.80	22.80	28.80	14.40	26.40	26.40	26.40	26.40	26.40	26.40	13.20			6.22
		0.48	1.44	3.12	3.84	7.20	9.60	12.00	19.20												5.76
60% 0.24 70%		0.48	1.20	2.64	3.60	6.00	8.76	11.52	14.16	16.80	16.80	16.80	16.80	16.80	16.80	16.80	8.40				4.38
0.12 80% 0.12		0.24	1.20	2.16	3.12	5.04	7.32	9.60	13.20	16.80	16.80	16.80	16.80	16.80	16.80	16.80	8.40				4.15
		0.24	0.72	1.20	2.40	3.84	5.52	7.20	10.80	14.40	14.40	14.40	14.40	14.40	14.40	14.40	7.20				3.92
90% 0.08 95%		0.24	0.72	1.20	1.92	3.12	4.56	6.00	7.80	9.60	9.60	9.60	9.60	9.60	9.60	9.60	4.80				3.69
0.08		0.24	0.48	0.96	1.68	2.40	2.88	3.36	4.08	4.80	4.80	4.80	4.80	4.80	4.80	4.80	2.40				2.40

Remark:

ÿThe current unit in the pulse charging map table in section 2.4 is A;

ÿ Define SOC at 25ÿ.

2.4 Impulse Discharging Mode (BOL)

2.4.1 Allow pulse discharge current and duration

2.4.1.1 Pulse (10s) discharge current map

SOC -30ÿ -25ÿ -20ÿ -15ÿ -10ÿ -5ÿ 0ÿ 5ÿ 10ÿ 15ÿ 20ÿ 25ÿ 30ÿ 35ÿ 40ÿ 45ÿ 50ÿ 52ÿ 55ÿ 60ÿ																								
5% 12.05 20.09 40.18 50.49 60.80 66.88 72.96 83.20 93.44 107.84 120.16 132.48 132.48 132.48 132.48 132.48 119.23 99.36 79.49 66.24																								
10% 12.30 20.50 41.00 52.50 64.00 75.20 86.40 90.88 95.36 119.04 133.12 147.20 147.20 147.20 147.20 147.20 132.48 110.40 88.32 73.60																								
20% 14.04 23.39 46.78 56.99 67.20 81.92 96.64 102.72 108.80 137.44 154.80 168.00 168.00 168.00 168.00 168.00 154.94 129.12 103.30 86.08																								
30% 14.40 24.00 48.00 59.84 71.68 89.60 107.52 116.16 124.80 152.48 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 141.60 113.28 94.40																								
40% 15.94 26.56 53.12 64.90 76.67 102.02 127.36 134.08 140.80 167.84 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 151.20 120.96 100.80																								
50% 18.62 31.04 62.08 73.28 84.48 108.16 131.84 149.12 166.40 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 162.72 130.18 108.48																								
60% 22.27 37.12 74.24 86.34 98.43 124.42 150.40 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 176.64 141.31 117.76																								
70% 25.68 42.79 85.59 100.07 114.56 141.76 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 147.49 122.91																								
80% 27.63 46.05 92.10 114.43 136.77 163.74 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 155.14 129.28																								
90% 29.84 49.73 99.46 127.17 154.88 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 163.97 136.64																								
100% 31.49 52.48 104.96 135.68 166.40 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.00 168.96 140.80																								

Machine Translated by Google

2.4.1.2 Pulse (30s) discharge current map

SOC -30ÿ -25ÿ -20ÿ -15ÿ -10ÿ -5ÿ 0ÿ 5ÿ 10ÿ 15ÿ 20ÿ 25ÿ 30ÿ 35ÿ 40ÿ 45ÿ 50ÿ 52ÿ 55ÿ 60ÿ																					
5% 8.54 14.24 28.48 36.96 45.44 51.52 57.60 61.12 64.64 68.32 71.92 75.52 75.52 75.52 75.52 75.52 67.97 56.64 45.31 37.76 10% 9.22 15.36 30.72 40.00																					
49.28 55.36 61.44 65.60 69.76 77.76 83.84 89.92 89.92 89.92 89.92 89.92 89.92 80.93 67.44 53.95 44.96 20% 9.98 16.64 33.28 44.48 55.68 61.44 67.20 73.60 80.00																					
86.72 93.28 99.84 99.84 99.84 99.84 99.84 89.86 74.88 59.90 49.92 30% 11.15 18.58 37.15 49.30 61.44 67.20 72.96 79.68 86.40 96.80 105.36 113.92 113.92																					
113.92 113.92 113.92 102.53 85.44 68.35 56.96 40% 13.44 22.40 44.80 54.88 64.96 71.52 78.08 87.36 96.64 105.44 114.48 123.52 123.52 123.52 123.52 123.52																					
111.17 92.64 74.11 61.76 50% 13.82 23.04 46.08 61.12 76.16 81.92 87.68 96.35 105.02 115.06 124.41 133.76 133.76 133.76 133.76 133.76 120.38 100.32 80.26																					
66.88 60% 14.59 24.32 48.64 64.64 80.64 87.87 95.10 103.10 111.10 125.15 136.18 147.20 147.20 147.20 147.20 147.20 132.48 110.40 88.32 73.60 70% 15.17																					
25.28 50.56 67.94 85.31 93.38 101.44 108.64 115.84 133.04 145.24 157.44 157.44 157.44 157.44 157.44 141.70 118.08 94.46 78.72 80% 17.28 28.80 57.60																					
75.07 92.54 100.67 108.80 118.08 127.36 140.96 152.40 163.84 163.84 163.84 163.84 163.84 163.84 147.46 122.88 98.30 81.92 90% 22.77 37.95 75.90 85.34 94.78																					
105.44 116.10 123.97 131.84 147.74 159.63 168.00 168.00 168.00 168.00 168.00 168.00 154.37 128.64 102.91 85.76 100% 24.13 40.22 80.45 89.50 98.56 110.08																					
121.60 130.56 139.52 156.16 168.00 168.00 168.00 168.00 168.00 168.00 168.00 163.58 136.32 109.06 90.88																					

2.4.1.3 Pulse (60s) discharge current map

SOC -30ÿ -25ÿ -20ÿ -15ÿ -10ÿ -5ÿ 0ÿ 5ÿ 10ÿ 15ÿ 20ÿ 25ÿ 30ÿ 35ÿ 40ÿ 45ÿ 50ÿ 52ÿ 55ÿ 60ÿ																					
5% 5.80 9.66 19.33 26.46 33.60 35.36 37.12 40.64 44.16 43.20 44.48 45.76 45.76 45.76 45.76 45.76 41.18 34.32 27.46 22.88 10% 6.14 10.24 20.48 28.48 36.48 39.68 42.88 44.80 46.72 52.80																					
56.80 60.80 60.80 60.80 60.80 60.80 54.72 45.60 36.48 30.40 20% 7.24 12.06 24.13 32.54 40.96 43.52 46.08 50.56 55.04 61.12 66.40 71.68 71.68 71.68 71.68 71.68 64.51 53.76 43.01 35.84 30%																					
8.08 13.47 26.94 35.87 44.80 48.32 51.84 56.64 61.44 68.64 74.64 80.64 80.64 80.64 80.64 80.64 72.58 60.48 48.38 40.32 40% 9.14 15.23 30.46 39.78 49.09 53.02 56.96 63.36 69.76 78.08 85.44																					
92.80 92.80 92.80 92.80 92.80 83.52 69.60 55.68 46.40 50% 9.43 15.71 31.42 41.22 51.01 56.86 62.72 69.76 76.80 86.08 94.24 102.40 102.40 102.40 102.40 102.40 92.16 76.80 61.44 51.20 60%																					
10.87 18.11 36.22 46.78 57.34 63.17 68.99 75.78 82.56 95.17 104.86 114.56 114.56 114.56 114.56 114.56 103.10 85.92 68.74 57.28 70% 11.87 19.78 39.55 51.46 63.36 69.18 75.01 82.62 90.24																					
101.79 111.38 120.96 120.96 120.96 120.96 120.96 108.86 90.72 72.58 60.48 80% 13.09 21.82 43.65 53.82 64.00 72.77 81.54 87.49 93.44 109.22 120.08 130.94 130.94 130.94 130.94 130.94																					
117.85 98.21 78.57 65.47 90% 14.21 23.68 47.36 58.24 69.12 78.27 87.42 93.63 99.84 116.10 127.33 138.56 138.56 138.56 138.56 138.56 124.70 103.92 83.14 69.28 100% 17.09 28.48 56.96																					
67.55 78.14 85.79 93.44 101.76 110.08 126.08 138.24 150.40 150.40 150.40 150.40 150.40 135.36 112.80 90.24 75.20																					

2.4.1.4 Pulse (300s) discharge current map

SOC -30ÿ -25ÿ -20ÿ -15ÿ -10ÿ -5ÿ 0ÿ 5ÿ 10ÿ 15ÿ 20ÿ 25ÿ 30ÿ 35ÿ 40ÿ 45ÿ 50ÿ 52ÿ 55ÿ 60ÿ																					
5% 2.36 3.94 7.87 10% 2.46 9.18 10.50 11.74 12.99 12.58 12.16 12.69 12.74 12.80 12.80 12.80 12.80 12.80 11.52 9.60 7.68 6.40 9.66 11.14 13.31 15.49 17.02 18.56 18.43 19.14 19.84																					
4.10 8.19 19.84 19.84 19.84 19.84 17.86 14.88 11.90 9.92																					
20% 3.13 5.22 10.43 14.40 18.37 18.82 19.26 21.60 23.94 26.16 28.44 30.72 30.72 30.72 30.72 30.72 27.65 23.04 18.43 15.36 30% 4.49 7.49 14.98 18.59 22.21 25.63 29.06 33.47 37.89 39.14																					
41.97 44.80 44.80 44.80 44.80 44.80 40.32 33.60 26.88 22.40 40% 5.59 9.31 18.62 22.11 25.60 30.94 36.29 39.90 43.52 46.83 50.30 53.76 53.76 53.76 53.76 53.76 48.38 40.32 32.26 26.88 50%																					
6.24 10.40 20.80 24.80 28.80 35.04 41.28 45.76 50.24 53.22 56.94 60.67 60.67 60.67 60.67 60.67 54.60 45.50 36.40 30.34 60% 6.72 11.20 22.40 27.65 32.90 39.90 46.91 50.66 54.40 59.25 63.54																					
67.84 67.84 67.84 67.84 67.84 61.06 50.88 40.70 33.92 70% 7.10 11.84 23.68 30.08 36.48 42.11 47.74 53.31 58.88 64.42 69.97 75.52 75.52 75.52 75.52 75.52 67.97 56.64 45.31 37.76 80% 7.68																					
12.80 25.60 32.00 38.40 45.76 53.12 58.56 64.00 69.92 75.60 81.28 81.28 81.28 81.28 81.28 73.15 60.96 48.77 40.64 90% 8.45 14.08 28.16 33.92 39.68 47.07 54.46 61.15 67.84 74.10 80.57 87.04																					
87.04 87.04 87.04 87.04 78.34 65.28 52.22 43.52 100% 10.27 17.12 34.24 44.90 55.55 58.62 61.70 67.33 72.96 79.10 84.99 90.88 90.88 90.88 90.88 90.88 81.79 68.16 54.53 45.44																					

Notes:

ÿ The current unit in the pulse discharge map table in Section

2.4 is A; ÿ SOC is defined at 25ÿ.

Machine Translated by Google

2.5 Other continuous discharge conditions (C)

SOC 0 ÿ-25ÿ 0		5%	10% 20% 30% 40% 50% 60% 70% 80%							90% 100%	
		0	0	0	0	0	0	0	0	0	0	0
-25ÿ	0	0.1	0.1	0.2	0.2	0.3	0.3	0.4	0.4	0.4	0.5	0.6
-20ÿ	0	0.3	0.3	0.3	0.5	0.6	0.7	0.7	0.8	0.9	0.9	1.1
-15ÿ	0	0.3	0.3	0.5	0.6	0.7	0.8	0.9	1.0	1.1	1.1	1.5
-10ÿ	0	0.4	0.4	0.7	0.9	1.0	1.5	1.7	1.9	2.0	2.0	2.8
-5ÿ	0	0.4	0.5	0.7	1.0	1.3	1.8	2.0	2.1	2.3	2.4	3.0
0ÿ	0	0.4	0.6	0.8	1.1	1.5	2.1	2.4	2.4	2.7	2.8	3.0
5ÿ	0	0.4	0.6	0.9	1.2	1.6	2.3	2.6	2.7	3.0	3.0	3.0
10ÿ	0	0.5	0.6	0.9	1.3	1.8	2.6	2.8	3.0	3.0	3.0	3.0
15ÿ	0	0.5	0.7	1.0	1.5	1.9	2.7	3.0	3.0	3.0	3.0	3.0
20ÿ	0	0.5	0.7	1.1	1.7	2.1	2.9	3.0	3.0	3.0	3.0	3.0
25ÿ	0	0.5	0.8	1.3	1.8	2.2	3.0	3.0	3.0	3.0	3.0	3.0
30ÿ	0	0.5	0.9	1.3	1.9	2.4	3.0	3.0	3.0	3.0	3.0	3.0
35ÿ	0	0.6	0.9	1.4	2.0	2.5	3.0	3.0	3.0	3.0	3.0	3.0
40ÿ	0	0.6	0.9	1.4	2.1	2.7	3.0	3.0	3.0	3.0	3.0	3.0
45ÿ	0	0.6	1.0	1.5	2.2	2.9	3.0	3.0	3.0	3.0	3.0	3.0
50ÿ	0	0.4	0.7	1.1	1.5	2.0	2.8	3.0	3.0	3.0	3.0	3.0
52ÿ	0	0.3	0.5	0.8	1.1	1.3	1.5	1.7	1.9	2.0	2.2	2.3
55ÿ	0	0.3	0.4	0.6	0.9	1.1	1.2	1.4	1.5	1.6	1.7	1.8
57ÿ	0	0.3	0.3	0.3	0.3	0.3	0.3	0.3	0.3	0.3	0.3	0.3
60ÿ ÿ	0	0.2	0.2	0.2	0.2	0.2	0.2	0.2	0.2	0.2	0.2	0.2
60ÿ 0		0	0	0	0	0	0	0	0	0	0	0

Remark:

ÿThe current unit in the other discharge condition mode table in Section 2.5 is C;

ÿ Define SOC at 25ÿ;

ÿ Applicable to the cell level; heat dissipation factors need to be considered for module and battery pack levels.

ÿ The discharge current in this table is a suggested value and should not be used as a current limiting value.

2.6 High and low temperature discharge capacity (BOL)

Temperature temperature	Voltage range Voltage window	C/3 Discharge		1C Discharge	
		Capacity/Ah Capacity/Ah	Energy/Wh Energy/Wh	Capacity/Ah Capacity/Ah	Energy/Wh Energy/Wh
45ÿ	2.5~4.35V	37.10	137.95	36.34	132.25
25ÿ		35.06	130.34	33.73	122.10
10ÿ		32.67	119.94	31.38	110.65
0ÿ	2.3~4.35V	30.80	111.21	29.77	101.94
-10ÿ	2.1~4.35V	28.67	100.23	28.32	92.60
-20ÿ		26.03	87.55	26.41	81.99

Notes: 1. The test was conducted in a constant temperature chamber, using single-layer foam and aluminum plate under pressure; 2. The test data are average values.

3. Static SOC-OCV (BOL)

Type	Static charge Static charging (V)	Static discharge Static discharge (V)

Machine Translated by Google

Temperature 25ÿ		25ÿ
100%	4.276	4.302
97%	4.247	4.244
95%	4.223	4.219
90%	4.173	4.168
85%	4.119	4.112
80%	4.059	4.050
75%	4.002	3.988
70%	3.981	3.955
65%	3.929	3.920
60%	3.873	3.864
55%	3.814	3.805
50%	3.742	3.733
45%	3.704	3.694
40%	3.678	3.668
35%	3.658	3.649
30%	3.642	3.632
25%	3.626	3.615
20%	3.606	3.585
15%	3.574	3.550
10%	3.530	3.511
5%	3.475	3.463
3%	3.459	3.447
1%	3.443	3.434
0%	3.428	3.425

Note: Static SOC-OCV test method: At an ambient temperature of 25ÿ, the battery cell is charged at a constant current and constant voltage of 0.33C to 4.35V, and cut off at 0.05C; after standing for 3 hours,

Adjust the current to the target SOC at 0.33C, repeating this process to obtain the discharge static SOC-OCV. Conversely, after the cell discharges to the lower voltage limit, adjust the current at 0.33C...

The charging current is adjusted to the target SOC and left to stand for 3 hours to obtain the static SOC-OCV.

4. Safety and Reliability (BOL)

No. Serial Number	Parameter parameter	Product Specification Product Specifications	Condition condition
1	Over charge Overcharge test	Pass	GB 43854-2024
2	Over discharge Over-discharge test	Pass	GB 43854-2024
3	Thermal abuse Heat abuse	Pass	GB 43854-2024
4	External short circuit External short circuit test	Pass	GB 43854-2024
5	Nail Penetration Needle prick test	Pass	GB 43854-2024

Machine Translated by Google

6	Sign logo	Pass	GB 43854-2024

5. Storage performance (BOL)

No. Serial Number	Parameter parameter	Temperature Temperature / °C	Product Specification Product Specifications	Condition condition
1	Room temperature recoverable capacity(short term) Recoverable capacity at room temperature (short-term)	25±2	ÿ98%	30days@100%SOC
2	High temperature recoverable capacity(short term) High-temperature recoverable capacity (short-term)	55±2	ÿ95%	7days@100%SOC
3	Room temperature storageÿshort termÿ Store at room temperature (short term)	-20~40	/	30d@50%SOC
4	Room temperature storageÿlong termÿ Store at room temperature (long-term)	25±5	ÿ95%	1year@50%SOC
5	Room temperature storage (voltage drop) Room temperature storage (pressure drop)	25±2	40mV	30d@50%SOC

6 Application conditions

6.1 The BMS shall include the following monitoring and control features. The battery management system must meet the following basic requirements.

This testing and control requirements

No. sequence Number	Parameter parameter	Product Specification Product Specifications	Condition condition	Protective measures Protective measures
1	Charging cut off voltage Charging cutoff voltage	4.30V	@-15~55ÿ	Triggering this threshold: Accelerates SOC correction, system alarm. Prompt to terminate charging
2	First stage overcharge protection voltage Overcharge protection voltage	4.31V	@-15~55ÿ	This threshold is triggered: BMS forcibly terminates charging.
3	Second stage overcharge protection voltage Second-stage overcharge protection voltage	4.35V	@-15~55ÿ	Triggering this threshold: terminates charging and locks the battery module. The system will be managed until the technicians resolve the issue.

Machine Translated by Google

4	Discharging cutoff voltage Discharge cutoff voltage	2.6V 2.4V 2.2V	10ÿÿTÿ60ÿ 0ÿÿTÿ10ÿ -30ÿÿTÿ0ÿ	This threshold is triggered: BMS: Reduces power consumption and accelerates correction to lower SOC; VCU: No processing
5	First stage over-discharge protection voltage First-stage over-discharge protection voltage	2.5V 2.3V 2.1V	10ÿÿTÿ60ÿ 0ÿÿTÿ10ÿ -30ÿÿTÿ0ÿ	This threshold is triggered. BMS: Do not process; VCU: Power-down initiation (only when SOC=0%)
6	Second stage discharge over-protection voltage Second-stage over-discharge protection voltage	2.4V 2.2V 2.0V	10ÿÿTÿ60ÿ 0ÿÿTÿ10ÿ -30ÿÿTÿ0ÿ	This threshold is triggered. BMS: SOC immediately corrected to 0, reporting unit undervoltage. Fault, and high voltage disconnected VCU: Power off
7	Short circuit protection Short circuit protection	Short circuits are not allowed.		In the event of a short circuit, the overcurrent device disconnects the battery (circuit).
8	Over current protection Overcurrent protection	Do not exceed electric current	/	The battery management system controls the discharge current to meet specifications.
9	Over temperature protection Overheat protection	Refer to Part 1 Product performance indicators	/	Charging will terminate when the temperature exceeds the specifications outlined in this document. /discharge

Note: The above No. 2,3,5,6 are the warning clause, draw the attention of customers: When the battery reaches any of the terms described in the above, means that the battery has been used beyond the specifications, the customer shall take protective measures on the battery in accordance with the ‘protection action’ and other relevant provisions of this specification.

At the same time, the Farasis shall not take any responsibility for the damage in connection therewith.

Note: Clauses 2, 3, 5, and 6 above are warning clauses. Customers are reminded that when the battery reaches any of the indicators and parameters described in any of the above clauses, it may...

This means the battery has exceeded the usage conditions specified in this technical agreement, and the customer must take protective measures for the battery in accordance with the "Protective Actions" and other relevant provisions of this technical agreement.

Farasis Energy also declares that it assumes no responsibility for the quality of batteries under the aforementioned usage conditions, and will not be liable for any losses incurred by customers or third parties as a result.

No compensation will be provided.

6.2 A reasonable number of thermal sensors shall be installed by the Client in proximity to each Product in use to sense and measure Cell Temperature. The Client shall use this sensor to monitor and record Cell Temperature throughout the entire service life of such cell. Cell Temperature is a critical parameter for determining whether the Client is entitled to Farasis's warranties under the Contract.

Users should use this sensor to monitor and record battery temperature throughout the battery's lifespan. Battery temperature is a key factor determining whether a customer is entitled to receive [battery temperature] under the agreement/contract.

Key parameters for Farasis Energy's quality assurance.

6.3 The Client shall procure that each Product be used under the strict monitoring, control and protection of the Battery Management System to be incorporated by the Client.

6.4 The Client shall provide Farasis with detailed information about the BMS, including but not limited to its design, features, settings, and data file format, for design review and record keeping.

Information such as system features, framework, system data, and format is provided to Farasis Energy for design evaluation of the system and to establish battery management files.

Machine Translated by Google

6.5 Once the detailed information of the BMS has been reviewed and agreed by Farasis, Client shall not modify or change the design, features, setting or data file format of the BMS without the prior written agreement by Client. ÿÿÿÿÿÿÿ

It is important to note that customers must not modify or alter the design and framework of the battery management system without authorization, so as not to affect the performance of the battery.

6.6 Client shall keep complete records of the BMS monitoring data throughout the entire service life of each Product, including keeping record of number of occurrence of Rush Charge, which will be used in the determination and judgment of any product warranty and liability claim entitlement. No warranty or liability claim will be considered without a completeset

Customers should retain complete battery operation monitoring records capturing the entire service life of the relevant product.

According to the data, this information is used as a reference for determining product quality liability. Farasis Energy will not assume responsibility for product quality if it lacks complete monitoring data for the entire service life of the battery system.

Liability for proof.

6.7 When the Products are intended to be stored for a prolonged period of time (more than one month), reduce SOC to around 50%. After three months of 50% SOC storage, should be charged and discharged once, reduce SOC to 50%. 50% SOC storage lasts for more than 6 months, irreversible capacity loss will be about 5% without charge-discharge maintenance. If 50% SOC storage exceeds 9 months without charge and discharge maintenance, Farasis will not be responsible for quality protection due to capacity loss or other defects.Method of storage maintenance to 50%SOC:

Discharge at the rated current or power to the minimum cut-off voltage specified by the system manufacturer.

Charge at the rated current or power to the maximum cut-off voltage specified by the system manufacturer.

Discharge to 50% of the rated capacity of the system with the rated current or power specified by the system manufacturer.

If the battery is expected to be stored for more than 30 days, the SOC should be adjusted to around 50%. If the SOC is below 50%, a charge-discharge adjustment should be performed after three months of storage.

The State of Charge (SOC) reaches 50%. Storage at 50% SOC for more than 6 months without any charge/discharge maintenance will suffer an irreversible capacity loss of approximately 5%. Storage at 50% SOC for more than...

Farasis Energy will not be liable for any capacity loss or other defects caused to the battery due to failure to perform charge/discharge maintenance for 9 months.

Methods to adjust storage conditions to below 50% SOC:

The battery system discharges at a certain rate of current or power to the lower cut-off voltage specified in the datasheet.

The battery system is charged at a certain rate of current or power to the upper limit cutoff voltage specified in the datasheet.

The battery system discharges 50% of its rated capacity at a certain rate of current or power.

6.8 Prevent charging the Products at a temperature which is not allowed under the specification hereunder (including standard charge, optional fast charge, emergency charge and regeneration), otherwise unnecessary degradation of the capacity of the Products may occur. Follow the specification on minimum charging and regeneration temperature and use the BMS to control it. Charging at temperature lower than the specification hereunder shall render Farasis's warranties under the Contract inapplicable, thereby releasing Farasis from any liability in connection therewith.

Avoid charging the battery in low-temperature conditions prohibited by this specification (including standard charging, fast charging, emergency charging, and regenerative charging), otherwise accidents may occur.

This will cause a decrease in capacity. The battery management system should control the charging and recharge processes according to the minimum required temperatures. Temperatures below those specified in this specification are prohibited.

If the battery is not charged, Farasis Energy will not assume any responsibility for quality assurance.

6.9 The heat dissipation of the products should be fully considered in the design of the battery system. Farasis will not be responsible for any overheating damage to the products caused by the heat dissipation design of the battery system.

Farasis Energy assumes no responsibility for quality assurance.

6.10 The problem of waterproof and dust-proof of the battery system should be fully considered. The battery system must meet the waterproof and dust-proof grades stipulated by the relevant national standards. Farasis are not responsible for quality assurance due to damages (such as corrosion, rust, etc.) of Products caused by waterproof and dust-proof problems. ÿÿÿ

The design of the battery system should fully consider the waterproof and dustproof aspects of the battery cells, and the battery system must meet the waterproof and dustproof ratings specified in relevant national standards. Due to waterproofing,

Farasis Energy assumes no responsibility for quality assurance regarding damage to battery cells or batteries caused by dust issues (such as corrosion, rust, etc.).

Machine Translated by Google

6.11 It is forbidden to mix different P/N products in the same battery system (or vehicle); otherwise, Farasis will not be responsible for quality protection.

Responsibility for quantity protection.

6.12 When the cells are assembled into modules, the initial preloading force is required: 400N~500N, and long-term

Unrestrained use is prohibited; simultaneously, the modules should be insulated. Initial preload is required when assembling battery cells into modules.

400N~500N, long-term unrestrained use is prohibited, and the module must be properly insulated.

7. **Product End of Life** Management

This cell is designed to service with a finite life time. Client shall develop and implement an active tracking system to monitor and record impedance of each Product in its entire service life. Client and/or its customer shall stop using any of the Products when its impendence exceeds 180% or capacity less than 70% (25 ÿ) of the value when it was fresh. Failure to comply with this requirement shall render Farasis's warranties under the Contract inapplicable, thereby releasing Farasis from any liability

in connection therewith.

Batteries have a limited lifespan. Customers should establish an effective tracking system to monitor and record the battery's internal resistance (internal resistance measurement methods) for each period of use.

(The calculation method requires joint discussion and agreement between the customer and Farasis Energy.) When the internal resistance of a battery in use exceeds 180% of its initial internal resistance...

The battery should be discontinued when its capacity is less than 70% (25°C). Failure to comply with this requirement will result in Farasis Energy being exempt from liability under the product sales agreement and this specification.

The product quality assurance responsibilities that should be borne.

8 **Safety usage** specification

8.1 Do not immerse cells in water.

8.2 Do not drop cells into fire or expose them to any high-temperature environment exceeding the operating temperature specified in this specification; otherwise, fire hazards may occur. At all times, the cell temperature should not exceed 60°C. If this occurs, shut down the system by the BMS.

This could cause a fire. Under any normal use and storage conditions, the cell temperature must not exceed 60°C. If the cell temperature exceeds 60°C, the battery...

The management system needs to turn off the battery and stop its operation.

8.3 Do not short-circuit cell terminals; otherwise, the high current and temperature may cause personal injury or fire hazards. Metallic cell terminals are exposed from plastic packaging, and all safety precautions should be implemented to avoid short-circuiting them during system integration or connections. Short-circuiting the battery's positive and negative terminals is strictly prohibited; otherwise, the high current and temperature may cause personal injury or fire hazards.

To prevent fires. Since the positive and negative terminals of the battery are exposed within the plastic protective sleeve, adequate safety protection should be provided during battery system assembly and connection to avoid short circuits.

8.4 Always connect cell terminals according to its label(s) in right polarity. Reverse charging is strictly prohibited.ÿÿÿÿ

Instructions for connecting the battery to the positive and negative terminals are as follows: reverse charging is prohibited.

8.5 Overcharging a cell is extremely dangerous and may cause overheating and fire hazards. Multiple levels of fail-safe overcharge protection should be implemented in a battery management system (BMS).

During battery installation and use, multiple overcharge failure safety protections must be implemented in both hardware and software.

8.6 Normal charging should finish within a charging time out limit as set out in paragraph 2.2. When charging continues longer than charging time out limit, it tends to overheat the cells which may cause overheating and fire hazards. A timer should be implemented in the charger circuit and set up properly. In case charging does not terminate normally within charging time out limit, ensure that the timer will intervene and stop the charging. ÿÿÿÿÿÿÿ 2.2 ÿÿÿÿÿÿÿÿÿÿÿ

Electricity. If continuous charging exceeds a reasonable time limit, the battery may overheat, potentially leading to thermal runaway and fire. A timer should be installed.

To protect against overcharging, if the charging current reaches an overcharge level and cannot be stopped, the timer will activate to terminate the charging process.

Machine Translated by Google

8.7 Products should be securely fixed to a solid platform, and power cables should be securely attached by fasteners to avoid intermittent contact, which may cause arcing and sparks. Customers should securely fix the batteries to a solid surface and securely fasten the power cables.

It should be secured in a suitable position to avoid friction that could cause electric arcs and sparks.

8.8 Do not service cells or make electrical connections within the plastic package of the cell. Improper electrical connection within a cell may cause overheating during service.

Overheating occurred during the use of the pool.

8.9 In the event of electrolyte leakage, avoid contacting electrolyte with skin or eyes. In case come into contact, wash affected area with large amount of water and seek medical help. Do not swallow any parts or substances within a cell.ÿÿÿÿÿÿ

Avoid skin and eye contact with the electrolyte. If contact occurs, rinse the affected area thoroughly with plenty of water and seek medical attention. Do not use any...

Humans or animals may ingest any part of the battery or any substance contained in the battery.

8.10 Protect cells from mechanical shock, impact, and pressure. Internal electrical circuitry may short-circuit, generating high temperatures and fire hazards.

Mild fire.

8.11 When cells charging is terminated improperly for reasons such as exceeding allowable charging time, cut-off due to exceeding charging voltage or cut-off due to exceeding charging current, all these events are defined as ‘improper charge termination’. Such event may indicate that there is current leaking within a cell system or some components have started to malfunction and subsequent charging of such cell system without finding and fixing root cause of problem may cause potential overheat or fire hazards. When such event occurs, the BMS should lock itself up to prevent subsequent charging and notice should be given to the user to return the vehicle to dealer for servicing. Subsequent charging should only be resumed after the system has been thoroughly checked by qualified technician who can identify and fix root cause attributed to the ‘improper charge termination’.ÿÿÿÿÿÿ

Machine Translated by Google

According to the degree of influence on Farasis, the product demanding company is required to provide compensation to Farasis. If the product demanding company fails to use it in accordance with the specifications in this manual, causing social impact and affecting Farasis's reputation,

Farasis Energy will pursue the responsibility of the customers who requested the products. Depending on the extent of the impact on Farasis Energy, the customers will be required to provide compensation to Farasis Energy.

9.2 Farasis reserves the right to modify the product specifications and performance parameters. The buyer needs to confirm the latest status of Farasis products in advance before ordering them.

The right to modify parameters. Before ordering Farasis Energy products, the buyer needs to confirm the latest product status with Farasis Energy in advance.

9.3 English specifications are for reference only. Please refer to the technical specifications of the Chinese version.ÿÿÿÿ

The interpretations are for reference only; please refer to the Chinese version of the technical specifications.

10 Accessories: Cell Drawings

