

## CONFIGURE WI-FI

1. On the terminal's main screen, touch the Settings app.
2. Enter password: pax9876@@ and press OK.
3. In the Wireless & Networks section, select Wi-Fi and make sure it's enabled.
4. From the list of available networks, touch the name of the network you want to connect to.
5. Enter the password for the selected network and touch CONNECT.
6. Once connected touch the Back icon to return to the Settings screen.
7. Touch the Back icon again to return to the main screen.

## CHANGE DATE/TIME

1. On the terminal's main screen, touch the Settings icon.
2. On the Settings screen, touch the Please Input Password field.
3. Enter password: pax9876@@ and press OK.
4. Scroll down the System section.
5. Select Date & Time
6. Select Time Zone
7. Select Region
8. Enter your region, example: United States
9. Select your Time Zone, example: New York.

## SET UP STATIC IP ADDRESS

1. From the main screen where all the apps are displayed select the Settings application.
2. You will be prompted for a password, it will either be pax9876@@ or 9876.
3. Select Network & Internet
4. Choose either WiFi or Ethernet
5. Select Ethernet Configuration
6. Select DHCP and it should have a drop down with an option Static
7. Enter the Local IP, Netmask, Gateway IP, DNS1 and DNS2.
8. Select Save

## CHANGE ECR COMM TYPE

1. Inside the processing app (Sierra, Rapid Connect, Omaha, BroadPOS) go to the settings by tapping the corner of the screen clockwise, start with the top right corner > bottom right corner > bottom left corner > top left corner.
2. You will be prompted a password (294687)
3. Select ECR Comm Settings
4. There you will see Host Port and Protocol Type

## **CHANGE BATCH SEQUENCE NUMBER**

1. Inside the processing app (Sierra, Rapid Connect, Omaha, BroadPOS) go to the settings by tapping the corner of the screen clockwise, start with the top right corner > bottom right corner > bottom left corner > top left corner.
2. You will be prompted a password (294687)
3. Select Host Settings
4. Select Batch Number and increase the current number by 1. (Ex: if the current number is 8 change it to 9) or call our office to find out the correct batch number.

## **MANUALLY CLOSE BATCH**

1. Inside the processing app (Sierra, Rapid Connect, Omaha, BroadPOS) go to the settings by tapping the corner of the screen clockwise, start with the top right corner > bottom right corner > bottom left corner > top left corner.
2. You will be prompted a password (294687)
3. Select Host Settings
4. Select Batch Close