# A Vision-Based Dual-Mode Hand Gesture Interface for Simultaneous GUI Interaction and Teleoperation of a Four-Wheel Omnidirectional Mobile Robot

Tai Nguyen Anh
[Department, Institution]
[City, Country]
[email address]

***Abstract*—Hand-gesture teleoperation of mobile robots is usually limited to motion commands, so the operator still returns to a mouse or keyboard to change mode, set speed or press the emergency stop. We present a low-cost system in which one laptop webcam serves both purposes at once: the dominant hand drives a virtual cursor over a web dashboard, and the non-dominant hand commands the three planar degrees of freedom $(v_x, v_y, \omega)$ of a four-wheel X-configuration omnidirectional robot. On the laptop, a geometric pipeline on top of MediaPipe hand landmarks assigns hand roles with online correction of the mirrored handedness label and smooths the cursor with a One-Euro filter. On the ESP32 robot controller, four independent $100\,\mathrm{Hz}$ loops combine per-wheel dead-zone feed-forward with a PI controller whose integrator is frozen during acceleration and saturation. We evaluate the system on $13{,}080$ logged control cycles ($2{,}026\,\mathrm{s}$) from three floor runs. The vision loop ran at $29.9$ fps with $18.5\,\mathrm{ms}$ mean hand-landmark inference; the UDP round trip over the robot's own Wi-Fi access point had a median of $6.6$–$8.1\,\mathrm{ms}$ (95th percentile $16$–$26\,\mathrm{ms}$); the mean wheel-speed error under load was $1.5$–$3.2\,\%$ of full scale; and the body motion reconstructed from the encoders deviated from the command by $0.1$–$2.5\,\%$. Two cursor mechanisms that looked effective on a simulated hand, the One-Euro filter and a click-point anchor, gave little or no benefit on a real hand (jitter $-5\,\%$; click shift not reduced; reported as negative results). All results come from one robot and one operator, and no user study was performed.***

***Index Terms*—omnidirectional mobile robot, hand gesture interface, human–robot interaction, teleoperation, One-Euro filter, feed-forward control, ESP32**

## I. Introduction

Omnidirectional mobile robots (OMRs) with omni or mecanum wheels move holonomically: they translate forward, sideways, or diagonally and rotate in place with three independent velocities $(v_x, v_y, \omega)$ [1]. This freedom makes teleoperation harder, because the operator must command three coupled quantities while also supervising the robot through a graphical interface.

Contactless interfaces based on a camera and a hand-landmark detector such as MediaPipe Hands [2] are attractive because they need no wearable hardware. A common design maps one hand to a small set of discrete motion commands. In such a design, tasks that belong to the supervisory interface (switching control mode, adjusting a speed slider, pressing an emergency stop) typically still require a physical mouse or keyboard. Using the index fingertip as a mouse pointer brings its own problems: high-frequency tremor when the hand is held still, and a displacement of the index fingertip when a second finger is extended to click. Both turned out to be small in our real-hand measurements (Section IV-B).

On the actuation side, a low-cost ESP32 with L298N bipolar H-bridges has a large dead zone and unequal motors. In our robot the static-friction threshold differed between wheels by a factor of $2.7$ ($5.5\,\%$ to $14.8\,\%$ duty), so equal open-loop duty drives the four wheels at different speeds and the robot yaws when commanded straight.

This paper describes a system that addresses both sides with one camera and one microcontroller. Our contributions are:

1) A dual-hand interface in which the dominant hand controls the whole GUI and the non-dominant hand drives the robot from the same camera stream, including a role assigner that corrects the mirrored handedness label online.
2) A host–edge architecture over the robot's own Wi-Fi access point using UDP, with a single-owner lock, two-sided watchdogs and acceleration limiting.
3) A per-wheel feed-forward plus PI controller with conditional anti-windup on the ESP32, identified from measured wheel characteristics.

We evaluate the link and the controller on logged real runs, and we also report a negative real-hand result for two cursor mechanisms.

## II. System Architecture and Kinematics

### A. Host–Edge Architecture

Fig. 1 shows the system. The laptop (host) captures MJPG $640 \times 480$ video at 30 fps in a separate thread that keeps only the newest frame, and runs a two-hand MediaPipe HandLandmarker on the CPU. A role assigner splits the detected hands into a UI hand and a drive hand. The UI hand updates a cursor that is sent over WebSocket to the browser; the drive hand is classified into a motion gesture. A $20\,\mathrm{Hz}$ control loop selects the command from the active mode (manual or gesture), limits its acceleration, and sends it by UDP to the robot.

The robot (edge) is an ESP32 that creates a Wi-Fi access point (`omni-robot`, 192.168.4.1, UDP port $4210$) with modem sleep disabled. Every $10\,\mathrm{ms}$ it reads the latest command,

applies inverse kinematics, runs four wheel controllers, and drives two L298N modules. Each command is acknowledged with a message carrying, for every wheel, the target speed, the measured speed and the duty. The laptop logs these at $20\,\mathrm{Hz}$ to a CSV file.

Two safety mechanisms bound the effect of a lost link. The ESP32 returns a zero command if no packet arrives within $300\,\mathrm{ms}$, and accepts packets from only one owner address until it has been silent for that time. On the laptop, a command older than $0.4\,\mathrm{s}$ is replaced by zero.

### B. Kinematic Model

Body velocity follows the ROS convention (Fig. 2): $+x$ forward, $+y$ left, $+\omega$ counter-clockwise. Let $\mathbf{u} = [v_x, v_y, \omega]^\top \in [-1,1]^3$ be the normalized body command and $\mathbf{r} = [r_{FL}, r_{FR}, r_{RL}, r_{RR}]^\top$ the wheel speeds, where $1.0$ corresponds to $4300$ encoder counts per second. For the $45^\circ$ X-configuration the firmware uses

$$\mathbf{r}' = \begin{bmatrix} 1 & -1 & -1 \\ 1 & 1 & 1 \\ 1 & 1 & -1 \\ 1 & -1 & 1 \end{bmatrix} \mathbf{u}, \qquad r_i = \frac{r'_i}{\max\bigl(1, \max_j |r'_j|\bigr)}. \quad (1)$$

The common divisor keeps the direction of motion when one wheel would exceed its limit, which independent clipping would distort. The columns of the matrix in (1) are orthogonal with squared norm $4$, so its pseudo-inverse is the transpose divided by four [4] and the body velocity is recovered from the measured wheel speeds $\mathbf{m}$ by

$$\begin{bmatrix} v_x \\ v_y \\ \omega \end{bmatrix}_{\text{odo}} = \frac{1}{4} \begin{bmatrix} 1 & 1 & 1 & 1 \\ -1 & 1 & 1 & -1 \\ -1 & 1 & -1 & 1 \end{bmatrix} \mathbf{m}. \quad (2)$$

The robot uses four GM25-370 motors with a $1{:}78$ gearbox and Hall encoders. Counting both edges of both channels gives $8112$ counts per wheel revolution. The pulse-counter peripheral (PCNT) of the ESP32 decodes them in hardware with a $12.5\,\mu\mathrm{s}$ glitch filter [6].

## III. Gesture Interface and Wheel Control

### A. Finger State and Pointing Direction

For each hand the 21 landmarks $p_k$ are used. A finger $f$ is extended when its fingertip is farther from the wrist than its proximal interphalangeal joint by a ratio that does not depend on the hand's distance to the camera or its in-plane rotation:

$$S(f) = \begin{cases} 1, & \dfrac{\|p_{\mathrm{tip}(f)} - p_0\|_2}{\|p_{\mathrm{pip}(f)} - p_0\|_2} > 1.15, \\ 0, & \text{otherwise.} \end{cases} \quad (3)$$

If only the index finger is extended, the pointing angle is measured from the index base $p_5$ to the tip $p_8$ in the image plane and quantized to eight $45^\circ$ sectors, giving forward, backward, left, right and four diagonals. Index and middle fingers together pointing left or right command rotation. A fist or an open palm stops the robot. A `GestureFilter` requires $4$ consecutive frames to start a motion command and $6$ frames to stop.

### B. Hand Roles

Because the displayed image is mirrored, the handedness label of MediaPipe is inverted from the user's point of view. The role assigner works in three cases. With two hands, roles follow the horizontal order of the wrists, and the disagreement between this order and the (flipped) labels updates a score $c_k = 0.95\,c_{k-1} \pm 0.05$; when $c_k < -0.6$ the flip convention is toggled. With one hand, the label is voted over the last $10$ frames. If a second hand has just disappeared and the remaining wrist moved by less than $150\,\mathrm{px}$, the previous role is kept. In manual mode the drive branch is disabled and any single hand is the UI hand, so the whole dashboard can be used with one hand.

### C. Cursor, Click Anchor and Slider Grab

The index fingertip position is smoothed with a One-Euro filter [3] with $f_{\min} = 1\,\mathrm{Hz}$ and $\beta = 8$ in normalized image units: the cut-off $f_c = f_{\min} + \beta|\dot{x}|$ is low when the hand is still and rises with speed. The UI hand has three poses: *point* (index only; the cursor moves and a dwell of $0.8\,\mathrm{s}$ clicks), *click* (index and middle; a click or a drag) and *idle*. A pose must persist for 3 frames.

Extending the middle finger can pull the index fingertip away from the intended target (Section IV-B measures how much). When the pose changes from point to click at time $t$, the filtered point history $H$ gives the anchor

$$(x_a, y_a) = \bigl(x_j, y_j\bigr) \text{ with } j = \arg\max\{t_j :\ t - t_j \geq 0.2\,\mathrm{s}\},$$
$$(\Delta x, \Delta y) = (x_a - x(t),\ y_a - y(t)), \quad (4)$$

and the action point used to hit the DOM element is $(a_x, a_y) = \mathrm{clamp}\bigl(x + \Delta x,\ y + \Delta y\bigr)$ while the click lasts. The displayed cursor still follows the fingertip, so dragging moves normally; after release the offset decays exponentially with a time constant of $0.15\,\mathrm{s}$. Sliders are grabbed by holding still on them, then moved relative to the finger motion, and released by holding still again.

### D. Per-Wheel Speed Control

Two limiters guard against slip and supply sag. On the host, the body command ramps with at most $2.0\,\mathrm{s}^{-1}$ acceleration and $4.0\,\mathrm{s}^{-1}$ deceleration, and passes through zero before changing sign. On the ESP32 every wheel target moves toward its goal at most $4.0\,\mathrm{s}^{-1}$.

At every $10\,\mathrm{ms}$ step $k$, wheel $i$ has the filtered measured speed $\omega_i(k) = 0.7\,\omega_i(k-1) + 0.3\,c_i(k)/4300$, with $c_i$ the counts per second. The control law, a feed-forward term plus a PI term with conditional anti-windup [5], is

$$u_i^{\mathrm{ff}} = \mathrm{sgn}(r_i)\bigl(a_i + b_i|r_i|\bigr), \quad e_i = r_i - \omega_i,$$
$$I_i \leftarrow I_i + K_i e_i\,\Delta t \ \text{ only if not ramping and not saturated},$$
$$u_i = \mathrm{clamp}\bigl(u_i^{\mathrm{ff}} + K_p e_i + I_i,\ -1,\ 1\bigr), \quad (5)$$

with $K_p = 0.8$, $K_i = 6.0$. The constants $a_i$ and $b_i$ are least-squares fits of the steady-state duty versus speed measured





Fig. 1. Host–edge architecture. Solid red: UDP command; dashed green: acknowledgement with wheel telemetry.





Fig. 2. X-configuration geometry. Arrows give the thrust direction of each wheel for positive wheel speed.

TABLE I
IDENTIFIED FEED-FORWARD PARAMETERS (WHEELS LIFTED) AND MEAN STEADY TRACKING ERROR ON THE FLOOR.

| Wheel | $a_i$ (duty) | $b_i$ | Mean error (%) v1 gest. | v2 two-hand |
|---|---|---|---|---|
| FL | 0.076 | 0.470 | 1.9 | 2.5 |
| FR | 0.148 | 0.594 | 2.5 | 2.6 |
| RL | 0.055 | 0.453 | 1.6 | 2.3 |
| RR | 0.060 | 0.464 | 1.7 | 2.5 |

with the wheels lifted (Table I). A wheel whose duty is at least 0.95 while its speed stays below 0.05 for 0.7 s is switched off to protect against a jam.

TABLE II
LOGGED RUNS. RTT IS THE UDP ROUND-TRIP TIME: MEDIAN / 95TH PERCENTILE / MAXIMUM.

| Run | Rows | Time (s) | RTT (ms) |
|---|---|---|---|
| Manual (v1) | 3240 | 1512 | 7.8 / 22.5 / 97 |
| Gesture (v1) | 4820 | 247 | 8.1 / 26.1 / 101 |
| Two-hand (v2) | 5020 | 266 | 6.6 / 16.1 / 909 |
| Total | 13080 | 2026[a] | – |

[a]Sum of the unrounded durations.

## IV. EXPERIMENTS

### A. Setup

The host is a laptop with an Intel Core i5-13420H (12 threads, 15 GB RAM) running Linux, Python 3.12, MediaPipe 1.2.0 (CPU) and OpenCV 5.0. The robot is an ESP32 DevKit V1 with two L298N modules, four GM25-370 motors and a 12 V supply. Three runs on a floor were logged at 20 Hz (Table II); the first two use the single-hand version (v1) and the third the dual-hand version (v2). In the manual run, 389 of the logged rows belong to gesture mode. Rows recorded while the motor supply was off (53 rows in the manual run) are excluded. Only one operator and one robot were used. The dashboard is described in the accompanying technical report.

### B. Vision Pipeline

Camera and inference speed were measured on 359 consecutive frames with the full capture-and-detect loop and no hand in view: 29.9 fps, with a hand-landmark inference time of 18.5 ms (mean), 18.2 ms (median), 27.1 ms (95th percentile). Cost with hands present was not measured separately. Setting the driver buffer to one frame instead of two halved the stream

from 28.9 to 14.5 fps in an earlier benchmark with MJPG, because the camera dropped frames while the application held the only buffer.

The geometric logic is covered by 46 automatic checks on synthetic hands (gestures, pose, role assignment including inverted labels, cursor) and 49 checks of the dashboard's cursor handling in a browser (headless Chrome, $1280 \times 900$ window) (dwell click, two-finger click, relative slider grab, pad drag, hold buttons, release on lost hand); all passed on 12 November 2026.

In the two real gesture runs the filtered gesture changed 120 and 76 times; 7 (5.8 %) and 5 (6.6 %) of these lasted less than 0.3 s, i.e., 94.2 % and 93.4 % of gesture segments were stable by this criterion. Whether the short segments were unintended was not annotated.

*Cursor: a negative result.* A simulated hand suggested large benefits: with 2 px Gaussian noise (200 seeded runs) the filter cut the horizontal standard deviation of the cursor by 65.5 %, and the click anchor cut the action-point shift by 83.6 % for a 29.2 px fingertip jump.

On a real hand (script `tests/real_hand_eval.py`, one operator, $640 \times 480$ frames) neither effect was reproduced. With the index finger held still for 8 s (209 frames) the standard deviation of the raw fingertip was 2.26 px and that of the filtered cursor 2.14 px (−5 %); real tremor is probably slow and correlated, which a low-pass filter tuned for responsiveness does not remove (not tested). For the click shift, the operator held the fingertip still (within 3 px for 1 s, drifting trials rejected) and raised the middle finger 12 times. The fingertip moved by a median of only 1.65 px (1.1–5.7), against 29.2 px in the simulation, and the action point with the anchor moved by a median of 4.15 px (2.0–12.0), more than the fingertip in 11 of 12 trials (Fig. 3), so the 0.2 s look-back added about 2.5 px instead of removing a shift. An earlier run in which the operator did not keep the finger still is not used. With 12 clicks from one operator and no click hit-rate measurement, this is indicative only; the dwell radius (30 px) and the button sizes exceed these shifts, so the practical effect on clicking is probably small but untested.

### C. Link Latency

The round-trip time is measured per command from the sequence number of the UDP command to that of its acknowledgement. Table II and Fig. 5(a) show medians of 6.6–8.1 ms and a heavy tail; the worst single value, 909 ms in the two-hand run, is far above the 300 ms robot watchdog and so a stop would have occurred. This is round-trip network latency only; it excludes camera capture, inference and gesture filtering.

For 38 (26) confirmed motion gestures in the v1 gesture (v2) run, the time from the logged gesture to the moment the most loaded wheel reached 50 % of its new target was 260 ms median (204–359 ms) and 257 ms median (203–309 ms). This includes the deliberate acceleration limits of Section III-D, so it is not the minimum achievable latency, and it does not include the 4 frames ($\approx 133$ ms) needed to confirm a gesture.





Fig. 3. Real hand, 12 trials with the finger held still: displacement of the action point against that of the raw fingertip when the middle finger is raised. Points above the dashed line mean the action point moved more than the fingertip.

### D. Wheel Tracking and Body Motion

We evaluate wheel tracking only when the command has been constant for 0.3 s and at least 0.1 in magnitude. Table I and Fig. 4 give mean errors of 1.5–3.2 % of full scale over the three runs. The 95th percentile of the error is higher, 4.4–4.8 % in the v1 gesture run and 6.1–7.4 % in the v2 run, so the 5 % mark is met by the mean but not by the tail in the latter. The front-right wheel, which has the largest dead zone, needs the highest mean duty (0.48–0.49 against 0.36–0.44). We did not compare against a plain PID or against open loop on the same trajectories, so the benefit of the proposed controller over those is not quantified here.

Table III compares the commanded and the encoder-derived body velocity from (2) over segments with a constant primitive. The error in the main axis is below 0.6 % for translations and about 2.4–2.5 % for rotations, and the unintended motion in the other axes stays at or below 0.004. These are velocities from the wheel encoders and do not include wheel slip on the floor, so they are not ground-truth position errors.

## V. Limitations

The results come from one robot on one floor with one operator. There is no user study, so the claim that the interface is more convenient than a mouse is untested. The real-hand cursor measurements (jitter, click shift) come from one operator and 12 clicks, and the click hit rate was not measured. The comparison of the controller with a baseline is missing, and the gesture stability criterion does not tell intended from unintended transitions. Latency from camera capture to wheel motion was not measured end to end. The system has no obstacle sensing: the operator is the only safeguard.

TABLE III

COMMANDED VS. ENCODER-DERIVED BODY VELOCITY (NORMALIZED UNITS). THE FIRST SIX PRIMITIVES ARE FROM THE V1 GESTURE RUN; THE DIAGONALS ARE FROM THE V2 RUN.

| Primitive | Samples | Command $(v_x, v_y, \omega)$ | From encoders $(v_x, v_y, \omega)$ | Main-axis error | Max other axis |
|---|---|---|---|---|---|
| Forward | 543 | (+0.472, 0.000, 0.000) | (+0.474, +0.001, +0.002) | +0.6 % | 0.002 |
| Backward | 360 | (-0.510, 0.000, 0.000) | (-0.510, -0.001, -0.001) | -0.1 % | 0.001 |
| Left | 96 | (0.000, +0.480, 0.000) | (+0.004, +0.482, +0.002) | +0.4 % | 0.004 |
| Right | 73 | (0.000, -0.480, 0.000) | (-0.003, -0.479, 0.000) | -0.2 % | 0.003 |
| Rotate left | 238 | (0.000, 0.000, +0.435) | (+0.003, +0.001, +0.446) | +2.5 % | 0.003 |
| Rotate right | 230 | (0.000, 0.000, -0.442) | (-0.001, 0.000, -0.453) | +2.4 % | 0.001 |
| Forward-left (v2) | 98 | (+0.308, +0.245, 0.000) | (+0.316, +0.256, +0.001) | – | – |
| Forward-right (v2) | 71 | (+0.313, -0.237, 0.000) | (+0.316, -0.243, -0.002) | – | – |





Fig. 4. Wheel-speed control in the two-hand run. (a),(b) Set-point and measured speed for two wheels over a 50 s window. (c) Identified feed-forward lines. (d) Distribution of the steady-state tracking error (whiskers: 5th–95th percentile; diamond: mean); the dashed line marks 5 %.

## VI. CONCLUSION

A single webcam and a single ESP32 sufficed to operate a four-wheel omnidirectional robot and its dashboard at the same time: one hand for the interface and the other for driving. On the logged runs the link round trip was a few milliseconds at the median, the mean wheel-speed error was 1.5–3.2 % of full scale, and the encoder-derived body motion agreed with the commands within 2.5 %. The click anchor and the filter parameters need revisiting given the real-hand measurements. Planned work is a user study with real hands, a comparison with baseline controllers, a heading sensor, and obstacle sensing.

## REFERENCES


[1] R. Siegwart, I. R. Nourbakhsh, and D. Scaramuzza, *Introduction to Autonomous Mobile Robots*, 2nd ed. Cambridge, MA, USA: MIT Press, 2011.

[2] F. Zhang *et al.*, "MediaPipe Hands: On-device real-time hand tracking," arXiv:2006.10214, 2020 (CVPR Workshop on Computer Vision for AR/VR).

[3] G. Casiez, N. Roussel, and D. Vogel, "1€ filter: A simple speed-based low-pass filter for noisy input in interactive systems," in *Proc. ACM CHI*, Austin, TX, USA, 2012, pp. 2527–2530.

[4] K. M. Lynch and F. C. Park, *Modern Robotics: Mechanics, Planning, and Control*. Cambridge, U.K.: Cambridge Univ. Press, 2017.

[5] K. J. Åström and T. Hägglund, *Advanced PID Control*. Research Triangle Park, NC, USA: ISA, 2006.

[6] Espressif Systems, "ESP32 Technical Reference Manual," (pulse counter and LED PWM controller chapters).





Fig. 5. (a) Distribution of the UDP round-trip time for the three runs (log scale; values above 60 ms fall into the last bin). (b) Magnitude of the commanded and the encoder-derived velocity for the six primitives.