SMART-ASHA (AROGYA AI) • SYSTEMS ARCHITECTURE ANALYSIS

Evaluating the Migration from ESP32-S3 to STM32H533RE (Nucleo-H533RE)

Application ID: VK26-AU-FD-0006 • **Theme:** Frontier Diagnostics: The Next Vital Signs • **Author/Team:** Gauri Gupta, Anmol Nandwani, Vansh Sharma (VIPS-TC)

🔬 MCU ARCHITECTURE TRADE-OFF & FEASIBILITY ANALYSIS

Evaluating the Migration from ESP32-S3 to STM32H533RE (Nucleo-H533RE)

- **Project Title:** Smart-ASHA (Arogya AI) — Edge-AI Multimodal Cardiopulmonary & Biochemical Triage Workstation
- **Document Version:** v1.0
- **Target Platforms Compared:**
- **Baseline (Current):** Espressif ESP32-S3 (7Semi ESP32-S3 EC200U 4G LTE Workstation)
- **Candidate (Proposed):** STMicroelectronics STM32H533RE (Nucleo-H533RE Development Board)
- **Firmware Baseline:** `Arduino/final_eval_v2/final_eval_v2.ino`
- **Hardware Architecture Reference:** `docs/architecture.md` & `hardware/assembly_guide.md`

1. Executive Summary & Engineering Verdict

> [!CAUTION]
> **Definitive Systems Verdict: NET FUNCTIONAL DOWNGRADE for Smart-ASHA.**
>
> Replacing the **ESP32-S3** with the **STM32H533RE** is technically possible, but it represents a **substantial net regression** for the Smart-ASHA clinical workstation in terms of wireless integration, multiprocessing capability, memory headroom, BOM economics, and mechanical form factor.
>
> While the STM32H533RE provides superior raw ADC linearity and formal medical security certification (TrustZone / SESIP-3), it **completely lacks on-chip wireless silicon (No BLE, No Wi-Fi)**. Because Smart-ASHA's core clinical value proposition relies on **100% offline BLE 5.0 telemetry to an ASHA worker's smartphone**, moving to STM32 forces the addition of a secondary wireless co-processor (ironically an ESP32 or nRF chip), doubling hardware failure points and inflating unit costs.

EXECUTIVE VERDICT SUMMARY		
Dimension	ESP32-S3 (Current)	STM32H533RE (Proposed)
Field Usability & BLE Link	WINNER (Native BLE 5.0)	REGRESSION (Requires extra chip)
Real-Time Multitasking	WINNER (Dual-Core 240 MHz)	REGRESSION (Single-Core 250 MHz)
Memory Headroom	WINNER (16 MB Flash/512 KB)	REGRESSION (512 KB Flash/272 KB)
Analog Signal Precision (ECG)	ACCEPTABLE (eFuse cal)	WINNER (Low-noise, 16-bit oversample)
Mechanical Fit in IP54 Sleeve	WINNER (Fits CAD sleeve)	REGRESSION (Nucleo board too bulky)
Bill of Materials (BOM) Target	WINNER (< ₹8,000 target)	REGRESSION (> ₹10,500 with shields)
OVERALL VERDICT	OPTIMAL WORKSTATION MCU	FEASIBLE BUT IMPRACTICAL DOWNGRADE

2. Comprehensive Specification Comparison

Architectural Parameter	ESP32-S3 (Current Baseline)	STM32H533RE (Nucleo-64)	Architectural Impact on Smart-ASHA
CPU Architecture	Dual-Core Xtensa® 32-bit LX7	Single-Core Arm® Cortex®-M33	**Downgrade:** Loss of hardware core isolation between AI & sensing.
Max Clock Frequency	240 MHz	250 MHz	**Comparable:** 10 MHz advantage on STM32 is offset by single-core bottleneck.
DSP / Vector Acceleration	PIE (Processor Instruction Ext.)	Arm Helium / DSP + FPU	**Comparable:** Both accelerate quantized neural network ops.
SRAM	512 KB SRAM + up to 8 MB PSRAM	272 KB SRAM	**Downgrade:** 47% reduction in internal working memory.
Flash Memory	8 MB / 16 MB QSPI/OPI Flash	512 KB Embedded Flash	**Critical Downgrade:** 96% reduction in code/asset storage space.
Integrated Wireless	**BLE 5.0 (2 Mbps/Long-Range) + Wi-Fi**	**NONE** (Zero RF on silicon)	**Critical Downgrade:** Breaks offline Flutter app synchronization.
I²C Controllers	2 Hardware Buses (`Wire`, `Wire1`)	4 Hardware Buses (I2C1–I2C4)	**Slight Upgrade:** STM32 has more native I²C ports.
Analog ADC	12-bit SAR ADC (eFuse calibrated)	2× 12-bit SAR ADC (16-bit oversample)	**Upgrade:** STM32 provides lower noise for AD8232 Lead-I ECG.
Cellular Telemetry	7Semi board integrates Quectel EC200U	Requires external modem breakout	**Downgrade:** Requires external high-current wiring and buffers.
Flash Persistence	Built-in NVS (`Preferences.h`)	Internal Flash Sector Emulation	**Downgrade:** Requires custom EEPROM emulation driver.
Form Factor	Compact Carrier Board (48 × 38 mm)	Nucleo-64 Board (70 × 82 mm)	**Downgrade:** Exceeds CAD internal bay volume.
Unit Subsystem Cost	~₹2,500 (MCU + Modem + BLE)	~₹5,800 (Nucleo + BLE + Modem + Shield)	**Downgrade:** Increases device BOM by ₹3,300+.

3. Subsystem-by-Subsystem Technical Analysis

3.1 Wireless Telemetry & Offline Companion App (`smart_asha_mobile`)

- **Current ESP32-S3 Architecture:**
- Runs a native Bluetooth Low Energy (BLE 5.0) GATT server (`BLE_DEVICE_NAME: "Smart-ASHA-Pro"`).
- Streams 60 FPS real-time dual-channel PPG and ECG waveforms alongside the 24×32 Ironbow facial thermal matrix directly to the mobile app in **100% Airplane Mode**.
- **STM32H533RE Reality:**
- **The chip has zero wireless capability.**
- *Required Workaround:* You must purchase, wire, and write firmware for an external BLE co-processor (e.g. ESP32-C3, nRF52840, or HM-10) over UART (`USART3`).
- *Result:* You introduce a secondary microcontroller just to restore the wireless capability that the ESP32-S3 natively contains.

3.2 Edge-AI Thermal Inference vs. Multimodal Polling (Compute Pipeline)

- **Current ESP32-S3 Architecture (Asymmetric Dual-Core FreeRTOS):**

> **Core 0:** Edge Impulse 2D-CNN Inference (768-pixel thermopile array)

> **Core 1:** 400 kHz Optical Polling (MAX30105), Digital Filtering (SDNN/RMSSD), OLED, BLE

Because AI inference executes strictly on Core 0, the continuous optical peak detection on Core 1 never drops samples. * **STM32H533RE Reality (Single-Core Cortex-M33):** * Both the neural network and the 400 kHz optical pulse acquisition must share a single execution core. * Running inference on a 24×32 thermal frame takes approximately 80 ms – 140 ms using CMSIS-NN. During this window, the CPU cannot perform normal polling loops. * *Required Workaround:* You must re-architect the firmware around **Direct Memory Access (DMA)** circular buffers for `I2C2` (MAX30105) and configure preemptive FreeRTOS task prioritization to prevent hemodynamic peak-jitter.

ESP32-S3 Dual-Core Pipeline (Parallel)

Core 0: Asynchronous AI Inference (110 ms) → Triage Output

`|| (Concurrent Execution)`

Core 1: 400 kHz Optical Polling + ECG Filters + 60 FPS BLE → **Mobile App (Zero Jitter)**

Zero Optical Sample Loss

STM32H533RE Single-Core Pipeline (Time-Sliced)

Single Cortex-M33 (250 MHz): Task 1: AI Inference (Active)

`↓ (Blocks CPU / Requires DMA)`

Shared Core: Task 2: Sensor Sampling → **Risk of Sample Drops**

Requires Complex DMA Buffering

3.3 Memory Budget: Flash & SRAM Allocations

- **Current ESP32-S3:**
- **Flash:** 8 MB to 16 MB. The Edge Impulse model C++ library (~1.2 MB compiled with full tensor kernels), U8g2 multilingual Devanagari font glyphs, and NVS storage have ample margin.
- **SRAM:** 512 KB internal + optional 2 MB/8 MB PSRAM.
- **STM32H533RE:**
- **Flash: 512 KB total.**
- *Constraint:* Fitting the FreeRTOS kernel, Adafruit drivers, U8g2 graphical fonts, multilingual string tables (Hindi/English), and the Edge Impulse model within 512 KB is exceptionally tight. The model must be strictly INT8 quantized and font glyph tables aggressively stripped.
- **SRAM:** 272 KB total. Adequate for runtime buffers (3 KB thermal array, 2 KB PPG circular buffer), but leaves little room for future multimodal models.

3.4 Dual Physical I²C Bus Architecture

- **Current ESP32-S3:**
- `Wire` @ 50 kHz (`GPIO 8` , `GPIO 18`) -> TCA9548A multiplexer (MLX90640, AS7343, MPU6050, SH1106 OLED).
- `Wire1` @ 400 kHz (`GPIO 16` , `GPIO 17`) -> MAX30105 directly.
- **STM32H533RE:**
- **Direct Compatibility:** The STM32H533RE has up to 4 hardware I²C peripherals (`I2C1` , `I2C2` , `I2C3` , `I2C4`).
- `I2C1` (`PB8` , `PB9`) easily handles the TCA9548A multiplexer at 50 kHz.
- `I2C2` (`PB10` , `PB11`) handles the MAX30105 at 400 kHz.
- *Verdict:* **100% Compatible.**

3.5 Analog Front-End (ECG & Gas Sensor)

- **Current ESP32-S3:**
- 12-bit SAR ADC (`GPIO 4` for AD8232 ECG, `GPIO 6` for MQ-135 Gas).
- Requires software eFuse non-linear calibration (`analogReadMilliVolts()`) due to ESP32 ADC non-linearity.
- **STM32H533RE:**
- 2× 12-bit SAR ADCs with hardware oversampling up to 16 bits.
- Effective Number of Bits (ENOB) is ~10.8 bits compared to ESP32's ~9.2 bits.
- *Verdict:* **Clear Upgrade.** STM32 ADC delivers substantially cleaner biopotential waveforms for Lead-I ECG with less RF switching hash.

3.6 4G LTE Telemetry & High-Current Inrush Transients

- **Current ESP32-S3 (7Semi):**
- The Quectel EC200U-CN 4G LTE module is soldered directly onto the same carrier PCB, sharing power planes and internal UART pins.
- Low-ESR buffer capacitors (1000 µF) absorb 2.0 A RF power amplifier transmit bursts.
- **STM32H533RE:**
- The Nucleo-H533RE has no cellular module.
- You must connect an external EC200U breakout board via loose jumper cables to `USART2` (`PA2` / `PA3`).
- *Hurdle:* Running 2.0 A cellular burst currents over DuPont jumper wires induces inductive ground bounce ($V = L \cdot \frac{di}{dt}$), causing spontaneous MCU brownouts unless a dedicated carrier power distribution board is fabricated.

3.7 Industrial CAD Enclosure & Ergonomics

- **Current ESP32-S3:**
- Board footprint (48 × 38 mm) fits neatly into the internal electronics bay of the 210 × 125 × 45 mm IP54 "Stethoscope Sleeve" enclosure, leaving adequate thermal isolation volume for the MLX90640.
- **STM32H533RE (Nucleo-64):**
- Physical dimensions are 70 × 82 × 18 mm with a non-removable ST-LINK/V3E debugger section.
- **It will NOT fit** inside the fabricated 3D CAD enclosure. The enclosure would have to be completely redesigned, increasing its thickness and weight beyond the 450 g ergonomic target for ASHA workers.

4. Hardware Pinout Migration Mapping

If a hardware migration or bench prototype test on Nucleo-H533RE is required, use this exact pin mapping:

```
                          STM32H533RE (Nucleo-64) Pinout
                                  ┌──────────────────┐
[TCA9548A SCL]  PB8  ─┤ 10          9 ├─  PB9   [TCA9548A SDA]
[MAX30105 SCL]  PB10 ─┤ 11          8 ├─  PB11  [MAX30105 SDA]
[AD8232 ECG]    PA0  ─┤ A0        D13 ├─  PA5   [Green Status LED]
[MQ-135 Gas]    PA1  ─┤ A1         D1 ├─  PA2   [EC200U UART TX]
[BLE Module TX] PC4  ─┤ D2         D0 ├─  PA3   [EC200U UART RX]
[BLE Module RX] PC5  ─┤ D3        GND ├─  GND   [Common Star Ground]
                                  └──────────────────┘
```

Signal / Sensor Function	ESP32-S3 Pin	STM32H533RE Pin	Peripheral Instance	Operating Speed / Mode
Primary I²C SDA (Mux)	`GPIO 8`	`PB9`	`I2C1_SDA`	50 kHz Open-Drain, 4.7kΩ Pull-Up
Primary I²C SCL (Mux)	`GPIO 18`	`PB8`	`I2C1_SCL`	50 kHz Open-Drain, 4.7kΩ Pull-Up
Secondary I²C SDA (PPG)	`GPIO 16`	`PB11`	`I2C2_SDA`	400 kHz Fast-Mode, Isolated Bus
Secondary I²C SCL (PPG)	`GPIO 17`	`PB10`	`I2C2_SCL`	400 kHz Fast-Mode, Isolated Bus
AD8232 ECG Biopotential	`GPIO 4`	`PA0`	`ADC1_INP1`	12-bit Analog, Low-Pass Filtered
MQ-135 Gas Output	`GPIO 6`	`PA1`	`ADC1_INP2`	12-bit Analog Voltage
Quectel EC200U TX	Dedicated UART	`PA2`	`USART2_TX`	115200 Baud AT Commands
Quectel EC200U RX	Dedicated UART	`PA3`	`USART2_RX`	115200 Baud AT Commands
External BLE Module TX	N/A (Internal)	`PC4`	`USART3_TX`	115200 / 921600 Baud Telemetry
External BLE Module RX	N/A (Internal)	`PC5`	`USART3_RX`	115200 / 921600 Baud Telemetry
Tri-Color Green LED	`GPIO 40`	`PA5`	`GPIO_Output`	Digital Out (Push-Pull)

5. Firmware Refactoring Checklist (`final_eval_v2.ino`)

Migrating the firmware requires changes to approximately 35% of the codebase:

1. **Board Core Transition:**
2. Switch PlatformIO / Arduino IDE board target to `STMicroelectronics:stm32:Nucleo_H533RE`.
3. **Purge ESP32-Specific Libraries:** `cpp // REMOVE: #include <Preferences.h> #include <BLEDevice.h> #include <BLEServer.h> #include <BLEUtils.h> #include <BLE2902.h> #include <esp_task_wdt.h>`
4. **Replace BLE Engine:**
5. Replace the entire `BLEServerCallbacks` and `BLECharacteristic` GATT server code with a serial packet serializer that pushes data out over `Serial3` to the external BLE co-processor.
6. **Replace NVS Flash Vault:**
7. Replace `Preferences.h` (`prefs.putBytes("records", ...)`) with an STM32 internal Flash EEPROM emulation library (or write records to an external I^2C EEPROM like the AT24C256).
8. **Refactor FreeRTOS Multitasking:**
9. Remove `xTaskCreatePinnedToCore(...)` calls.
10. Implement single-core FreeRTOS task scheduling with DMA: ```cpp // OLD ESP32-S3 (Dual-Core): xTaskCreatePinnedToCore(aiTask, "AI_Inference", 8192, NULL, 1, &aiHandle, 0);

    // NEW STM32H533RE (Single-Core): xTaskCreate(aiTask, "AI_Inference", 2048, NULL, 1, &aiHandle); // Note: Must ensure MAX30105 I2C sampling uses DMA interrupts to avoid starving! ``` 6. **Recompile Edge-AI Model:** * Re-export the Edge Impulse model from the Edge Impulse Studio using the **Cortex-M33 CMSIS-NN** deployment target instead of the ESP32-S3 ESP-NN target.

6. Economic & Bill of Materials (BOM) Impact

Component / Subsystem	ESP32-S3 Architecture	STM32H533RE Architecture	Cost Variance
Processing Subsystem	ESP32-S3 Dev Module: **₹650**	Nucleo-H533RE: **₹2,200**	+ ₹1,550
Wireless Telemetry (BLE 5.0)	Integrated on Silicon: **₹0**	External ESP32-C3 / nRF BLE Module: **₹450**	+ ₹450
Cellular Modem Subsystem	7Semi Integrated EC200U: **₹2,100**	External EC200U Breakout + Shield: **₹2,800**	+ ₹700
PCB & Carrier Board	Single 4-Layer Rigid-Flex: **₹1,800**	Nucleo Stacking Shield + Carrier: **₹2,400**	+ ₹600
Enclosure Modification	Existing Molded CAD Sleeve: **₹850**	Enlarged Custom CAD Enclosure: **₹1,150**	+ ₹300
Total Core Electronics BOM	**~₹5,400**	**~₹9,000**	**+ ₹3,600 (+66%)**

WARNING

At production scale, the **₹3,600 cost penalty** violates the core Vishwakarma and rural healthcare mandate: maintaining the total BOM under ₹8,000 to remain 15× cheaper than commercial kiosks (e.g. HealthCube at ₹1,50,000+).

7. Strategic Defense for Reviewers & Technical Juries

If an academic evaluator, jury member, or competition reviewer asks:
"Why didn't you use an industrial ARM Cortex-M controller like the STM32H533RE instead of an IoT chip like the ESP32-S3?"

Use this formal technical justification:

> *"While the STM32H533RE (Cortex-M33) provides outstanding ADC SNR and hardware TrustZone, it is fundamentally an isolated microcontroller without wireless silicon.

Smart-ASHA is an **edge-AI clinical triage workstation designed for frontline rural healthcare**, where two architectural constraints are paramount: 1. **Offline Telemetry in Airplane Mode:** We stream 60 FPS uncompressed optical waveforms and 24×32 thermal heatmaps to the ASHA worker's smartphone over **BLE 5.0**. Using an STM32 would force us to add an external BLE radio co-processor—adding cost, size, and failure points. 2. **Asymmetric Multiprocessing:** The ESP32-S3's dual 240 MHz cores allow us to dedicate **Core 0 exclusively to our 2D-CNN thermal model**, while **Core 1 handles continuous 400 kHz optical pulse oximetry and ECG digital filtering** without CPU starvation or sample dropping.

By utilizing the ESP32-S3, we consolidate compute, BLE 5.0, Wi-Fi, and 4G LTE into a single integrated carrier board that fits within our handheld IP54 enclosure and keeps our Bill of Materials under ₹8,000."*

8. Summary Conclusion

- **Can you replace it? Yes.** The sensors and cellular communications can be made to work.
- **Is it recommended? No.** It is a net regression for the Smart-ASHA system.
- **When should you do it?** Only if a competition rule, sponsor grant (e.g., STMicroelectronics), or university department explicitly mandates an STM32 board.
- **Path Forward: Retain the ESP32-S3 architecture** as the primary production design for Smart-ASHA.