

Features: 1. Features the highly integrated TPS63802 chip, supporting multiple input voltages 2. Reduces energy loss and heat generation, effectively extending lithium battery runtime 3. Offers two selectable output voltages (3.3V/5V) for compatibility with diverse devices 4. Supports 1A/2A current output, reliably driving high-power modules 5. Easily integrates into various DIY projects, handheld devices, or power banks

Parameter: 3.3V Input Voltage: DC 1.8-5.5V Output Voltage: 3.3V
Output Current: 2A Quiescent Current: 20uA@3.7V Ripple 75mv
3.7V@3.3V 0A 34mv 3.7V@3.3V 2A
5V Input Voltage: DC 1.8-5.5V Output Voltage: 5V Output Current: 1A
Quiescent Current: 30uA@3.7V Ripple 90mv 3.7V@5V 0A 18mv
3.7V@5V 1A
PCB dimensions: 10.4 × 7.9 mm

Tps63802 Chip

Features the highly integrated TP63802 chip,
accommodating a wide range of input voltages

Buck-Boost Power Module

Easily integrated into various DIY projects,
handheld devices, or power banks

The board requires the following parameters for operation

Model	HL802A-3.3V	HL802A-5V
Input Voltage	(1.3v)1.8-5.5V	(1.3v)1.8-5.5V
Output Voltage	3.3V	5V
Output Current	2A	1A
Quiescent Current (Off)	20uA @3.7V	30uA @3.7V
Ripple	75mv 3.7V@3.3V 0A 34mv 3.7V@3.3V 2A	90mv 3.7V@5V 0A 18mv 3.7V@5V 1A

How to Adjust the Output Voltage:

The output voltage can only be adjusted between 3.3V and 5V. This is controlled via the solder joint below:

Open the solder joint to set the output voltage to 5V.

Short the solder joint to set the output voltage to 3.3V.

A silkscreen on the reverse side provides selection guidance.

Installation Dimensions:







