

# **AOS-CX Event Log Message Reference Guide 10.08**

**4100i, 6xxx, 8xxx Switch Series**



## **Copyright Information**

© Copyright 2021 Hewlett Packard Enterprise Development LP.

## **Open Source Code**

This product includes code licensed under the GNU General Public License, the GNU Lesser General Public License, and/or certain other open source licenses. A complete machine-readable copy of the source code corresponding to such code is available upon request. This offer is valid to anyone in receipt of this information and shall expire three years following the date of the final distribution of this product version by Hewlett Packard Enterprise Company. To obtain such source code, send a check or money order in the amount of US \$10.00 to:

Hewlett Packard Enterprise Company  
6280 America Center Drive  
San Jose, CA 95002  
USA

## **Notices**

The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein. Confidential computer software. Valid license from Hewlett Packard Enterprise required for possession, use, or copying. Consistent with FAR 12.211 and 12.212, Commercial Computer Software, Computer Software Documentation, and Technical Data for Commercial Items are licensed to the U.S. Government under vendor's standard commercial license.

Links to third-party websites take you outside the Hewlett Packard Enterprise website. Hewlett Packard Enterprise has no control over and is not responsible for information outside the Hewlett Packard Enterprise website.

---

|                                                   |           |
|---------------------------------------------------|-----------|
| <b>Contents</b>                                   | <b>3</b>  |
| <b>About this document</b>                        | <b>8</b>  |
| Applicable products                               | 8         |
| Latest version available online                   | 8         |
| Command syntax notation conventions               | 8         |
| About the examples                                | 9         |
| Identifying switch ports and interfaces           | 10        |
| Identifying modular switch components             | 11        |
| <b>AAA events</b>                                 | <b>12</b> |
| <b>ACLs events</b>                                | <b>14</b> |
| <b>Alarm events</b>                               | <b>15</b> |
| <b>ARP security events</b>                        | <b>18</b> |
| <b>ASIC table full error for L3PD events</b>      | <b>19</b> |
| <b>BFD events</b>                                 | <b>21</b> |
| <b>BGP events</b>                                 | <b>26</b> |
| <b>Bluetooth Management events</b>                | <b>31</b> |
| <b>CDP events</b>                                 | <b>33</b> |
| <b>Certificate management events</b>              | <b>35</b> |
| <b>Config Management events</b>                   | <b>40</b> |
| <b>Connectivity Fault Management (CFM) events</b> | <b>42</b> |
| <b>Container manager events</b>                   | <b>43</b> |
| <b>CoPP events</b>                                | <b>44</b> |
| <b>CPU_RX events</b>                              | <b>47</b> |
| <b>Credential Manager events</b>                  | <b>48</b> |
| <b>Device fingerprinting events</b>               | <b>50</b> |
| <b>DHCP Relay events</b>                          | <b>51</b> |

---

---

|                                                       |     |
|-------------------------------------------------------|-----|
| DHCP server events .....                              | 52  |
| DHCPv4 snooping events .....                          | 55  |
| DHCPv6 Relay events .....                             | 59  |
| DHCPv6 snooping events .....                          | 60  |
| Discovery and Capability Exchange (DCBx) events ..... | 64  |
| DNS client events .....                               | 66  |
| DPSE events .....                                     | 67  |
| ECMP events .....                                     | 69  |
| ERPS events .....                                     | 71  |
| EVPN events .....                                     | 75  |
| External Storage events .....                         | 79  |
| Fan events .....                                      | 81  |
| Fault monitor events .....                            | 86  |
| Firmware Update events .....                          | 88  |
| Hardware Health Monitor events .....                  | 90  |
| HTTPS Server events .....                             | 93  |
| In-System Programming events .....                    | 95  |
| Interface events .....                                | 98  |
| Internal storage events .....                         | 100 |
| IP source lockdown events .....                       | 101 |
| IP tunnels events .....                               | 103 |
| IP-SLA events .....                                   | 107 |
| IPv6 Router Advertisement events .....                | 109 |
| IRDP events .....                                     | 113 |
| Job scheduler events .....                            | 114 |
| L3 Encap capacity events .....                        | 115 |
| L3 Resource Manager events .....                      | 116 |

---

|                                                     |            |
|-----------------------------------------------------|------------|
| <b>LACP events .....</b>                            | <b>117</b> |
| <b>LAG events .....</b>                             | <b>123</b> |
| <b>Layer 3 Interface events .....</b>               | <b>126</b> |
| <b>LED events .....</b>                             | <b>133</b> |
| <b>LLDP events .....</b>                            | <b>134</b> |
| <b>Loop Protect events .....</b>                    | <b>137</b> |
| <b>Loopback events .....</b>                        | <b>139</b> |
| <b>MAC Address mode configuration events .....</b>  | <b>140</b> |
| <b>MAC Learning events .....</b>                    | <b>141</b> |
| <b>MACsec events .....</b>                          | <b>143</b> |
| <b>Management events .....</b>                      | <b>144</b> |
| <b>MDNS events .....</b>                            | <b>145</b> |
| <b>MGMD events .....</b>                            | <b>146</b> |
| <b>Mirroring events .....</b>                       | <b>151</b> |
| <b>Module events .....</b>                          | <b>153</b> |
| <b>MSDP events .....</b>                            | <b>161</b> |
| <b>Multicast Traffic Manager events .....</b>       | <b>163</b> |
| <b>Multiple spanning tree protocol events .....</b> | <b>164</b> |
| <b>MVRP events .....</b>                            | <b>168</b> |
| <b>NAE Agents events .....</b>                      | <b>170</b> |
| <b>NAE events .....</b>                             | <b>171</b> |
| <b>NAE Scripts events .....</b>                     | <b>174</b> |
| <b>ND snooping events .....</b>                     | <b>177</b> |
| <b>NDM events .....</b>                             | <b>179</b> |
| <b>NTP events .....</b>                             | <b>186</b> |
| <b>OSPFv2 events .....</b>                          | <b>188</b> |
| <b>OSPFv3 events .....</b>                          | <b>190</b> |

---

|                                                           |            |
|-----------------------------------------------------------|------------|
| <b>Password Reset events .....</b>                        | <b>192</b> |
| <b>PIM events .....</b>                                   | <b>193</b> |
| <b>Policies events .....</b>                              | <b>200</b> |
| <b>Port access events .....</b>                           | <b>201</b> |
| <b>Port access roles events .....</b>                     | <b>204</b> |
| <b>Port events .....</b>                                  | <b>205</b> |
| <b>Port security events .....</b>                         | <b>207</b> |
| <b>Port Statistics events .....</b>                       | <b>208</b> |
| <b>Port access group based policy events .....</b>        | <b>209</b> |
| <b>Power events .....</b>                                 | <b>211</b> |
| <b>Power over Ethernet events .....</b>                   | <b>216</b> |
| <b>PTP events .....</b>                                   | <b>225</b> |
| <b>QoS ASIC Provider events .....</b>                     | <b>228</b> |
| <b>Quality of Service events .....</b>                    | <b>230</b> |
| <b>Rapid per VLAN Spanning Tree Protocol events .....</b> | <b>231</b> |
| <b>RBAC events .....</b>                                  | <b>234</b> |
| <b>Redundant Management events .....</b>                  | <b>235</b> |
| <b>Replication Manager events .....</b>                   | <b>237</b> |
| <b>REST events .....</b>                                  | <b>238</b> |
| <b>Self Test events .....</b>                             | <b>249</b> |
| <b>sFlow events .....</b>                                 | <b>250</b> |
| <b>SFTP Client events .....</b>                           | <b>257</b> |
| <b>Smartlink events .....</b>                             | <b>258</b> |
| <b>SNMP events .....</b>                                  | <b>259</b> |
| <b>SSH client events .....</b>                            | <b>262</b> |
| <b>SSH server events .....</b>                            | <b>263</b> |
| <b>Supportability events .....</b>                        | <b>265</b> |

---

|                                                 |            |
|-------------------------------------------------|------------|
| <b>SYS events</b>                               | <b>272</b> |
| <b>SYSMON events</b>                            | <b>274</b> |
| <b>TCAM events</b>                              | <b>276</b> |
| <b>Temperature events</b>                       | <b>280</b> |
| <b>Time management events</b>                   | <b>283</b> |
| <b>Transceiver events</b>                       | <b>284</b> |
| <b>UDLD events</b>                              | <b>287</b> |
| <b>UDP Broadcast Forwarder events</b>           | <b>289</b> |
| <b>UFD events</b>                               | <b>290</b> |
| <b>User management events</b>                   | <b>291</b> |
| <b>User-based tunnels events</b>                | <b>293</b> |
| <b>Virtual Switching Extension (VSX) events</b> | <b>300</b> |
| <b>Virtual Switching Framework (VSF) events</b> | <b>308</b> |
| <b>VLAN events</b>                              | <b>318</b> |
| <b>VLAN Interface events</b>                    | <b>322</b> |
| <b>VRF events</b>                               | <b>323</b> |
| <b>VRF Manager events</b>                       | <b>324</b> |
| <b>VRRP events</b>                              | <b>325</b> |
| <b>VSX Sync events</b>                          | <b>331</b> |
| <b>VXLAN agent events</b>                       | <b>332</b> |
| <b>VXLAN events</b>                             | <b>333</b> |
| <b>Zero touch provisioning events</b>           | <b>337</b> |
| <b>Support and other resources</b>              | <b>343</b> |
| Accessing Aruba Support                         | 343        |
| Accessing Updates                               | 343        |
| Aruba Support Portal                            | 343        |
| My Networking                                   | 344        |
| Warranty information                            | 344        |
| Regulatory Information                          | 344        |
| Documentation feedback                          | 344        |

This document describes features of the AOS-CX network operating system. It is intended for administrators responsible for installing, configuring, and managing Aruba switches on a network.

## Applicable products

This document applies to the following products:

- Aruba 4100i Switch Series (JL817A, JL818A)
- Aruba 6100 Switch Series (JL675A, JL676A, JL677A, JL678A, JL679A)
- Aruba 6200 Switch Series (JL724A, JL725A, JL726A, JL727A, JL728A)
- Aruba 6300 Switch Series (JL658A, JL659A, JL660A, JL661A, JL662A, JL663A, JL664A, JL665A, JL666A, JL667A, JL668A, JL762A)
- Aruba 6400 Switch Series (JL741A, R0X26A, R0X27A, R0X29A, R0X30A)
- Aruba 8320 Switch Series (JL479A, JL579A, JL581A)
- Aruba 8325 Switch Series (JL624A, JL625A, JL626A, JL627A)
- Aruba 8360 Switch Series (JL700A, JL701A, JL702A, JL703A, JL706A, JL707A, JL708A, JL709A, JL710A, JL711A)
- Aruba 8400 Switch Series (JL375A, JL376A)

## Latest version available online

Updates to this document can occur after initial publication. For the latest versions of product documentation, see the links provided in [Support and Other Resources](#).

## Command syntax notation conventions

| Convention                                                                                                                                                                                                        | Usage                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <code>example-text</code>                                                                                                                                                                                         | Identifies commands and their options and operands, code examples, filenames, pathnames, and output displayed in a command window. Items that appear like the example text in the previous column are to be entered exactly as shown and are required unless enclosed in brackets ( [ ] ).                                                                                                                                                                            |
| <b>example-text</b>                                                                                                                                                                                               | In code and screen examples, indicates text entered by a user.                                                                                                                                                                                                                                                                                                                                                                                                        |
| Any of the following: <ul style="list-style-type: none"><li>■ <code>&lt;example-text&gt;</code></li><li>■ <code>&lt;example-text&gt;</code></li><li>■ <i>example-text</i></li><li>■ <i>example-text</i></li></ul> | Identifies a placeholder—such as a parameter or a variable—that you must substitute with an actual value in a command or in code: <ul style="list-style-type: none"><li>■ For output formats where italic text cannot be displayed, variables are enclosed in angle brackets (&lt; &gt;). Substitute the text—including the enclosing angle brackets—with an actual value.</li><li>■ For output formats where italic text can be displayed, variables might</li></ul> |



| Convention    | Usage                                                                                                                                                                                                                                                                                                                                                                |
|---------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|               | or might not be enclosed in angle brackets. Substitute the text including the enclosing angle brackets, if any, with an actual value.                                                                                                                                                                                                                                |
|               | Vertical bar. A logical OR that separates multiple items from which you can choose only one.<br>Any spaces that are on either side of the vertical bar are included for readability and are not a required part of the command syntax.                                                                                                                               |
| { }           | Braces. Indicates that at least one of the enclosed items is required.                                                                                                                                                                                                                                                                                               |
| [ ]           | Brackets. Indicates that the enclosed item or items are optional.                                                                                                                                                                                                                                                                                                    |
| ... or<br>... | Ellipsis: <ul style="list-style-type: none"> <li>■ In code and screen examples, a vertical or horizontal ellipsis indicates an omission of information.</li> <li>■ In syntax using brackets and braces, an ellipsis indicates items that can be repeated. When an item followed by ellipses is enclosed in brackets, zero or more items can be specified.</li> </ul> |

## About the examples

Examples in this document are representative and might not match your particular switch or environment. The slot and port numbers in this document are for illustration only and might be unavailable on your switch.

### Understanding the CLI prompts

When illustrating the prompts in the command line interface (CLI), this document uses the generic term `switch`, instead of the host name of the switch. For example:

```
switch>
```

The CLI prompt indicates the current command context. For example:

```
switch>
```

Indicates the operator command context.

```
switch#
```

Indicates the manager command context.

```
switch (CONTEXT-NAME)#
```

Indicates the configuration context for a feature. For example:

```
switch (config-if) #
```

Identifies the `interface` context.

### Variable information in CLI prompts

In certain configuration contexts, the prompt may include variable information. For example, when in the VLAN configuration context, a VLAN number appears in the prompt:

```
switch (config-vlan-100) #
```

When referring to this context, this document uses the syntax:

```
switch (config-vlan-<VLAN-ID>) #
```

Where `<VLAN-ID>` is a variable representing the VLAN number.

## Identifying switch ports and interfaces

Physical ports on the switch and their corresponding logical software interfaces are identified using the format:

*member/slot/port*

### On the 4100i Switch Series

- *member*: Always 1. VSF is not supported on this switch.
- *slot*: Always 1. This is not a modular switch, so there are no slots.
- *port*: Physical number of a port on the switch.

For example, the logical interface 1/1/4 in software is associated with physical port 4 on the switch.

### On the 6100 Switch Series

- *member*: Always 1. VSF is not supported on this switch.
- *slot*: Always 1. This is not a modular switch, so there are no slots.
- *port*: Physical number of a port on the switch.

For example, the logical interface 1/1/4 in software is associated with physical port 4 on the switch.

### On the 6200 Switch Series

- *member*: Member number of the switch in a Virtual Switching Framework (VSF) stack. Range: 1 to 8. The primary switch is always member 1. If the switch is not a member of a VSF stack, then member is 1.
- *slot*: Always 1. This is not a modular switch, so there are no slots.
- *port*: Physical number of a port on the switch.

For example, the logical interface 1/1/4 in software is associated with physical port 4 in slot 1 on member 1.

### On the 6300 Switch Series

- *member*: Member number of the switch in a Virtual Switching Framework (VSF) stack. Range: 1 to 10. The primary switch is always member 1. If the switch is not a member of a VSF stack, then member is 1.
- *slot*: Always 1. This is not a modular switch, so there are no slots.
- *port*: Physical number of a port on the switch.

For example, the logical interface 1/1/4 in software is associated with physical port 4 on member 1.

### On the 6400 Switch Series

- *member*: Always 1. VSF is not supported on this switch.
- *slot*: Specifies physical location of a module in the switch chassis.
  - Management modules are on the front of the switch in slots 1/1 and 1/2.
  - Line modules are on the front of the switch starting in slot 1/3.
- *port*: Physical number of a port on a line module.

For example, the logical interface 1/3/4 in software is associated with physical port 4 in slot 3 on member 1.

### On the 83xx Switch Series

- *member*: Always 1. VSF is not supported on this switch.
- *slot*: Always 1. This is not a modular switch, so there are no slots.
- *port*: Physical number of a port on the switch.

For example, the logical interface 1/1/4 in software is associated with physical port 4 on the switch.



---

If using breakout cables, the port designation changes to x:y, where x is the physical port and y is the lane when split to 4 x 10G or 4 x 25G. For example, the logical interface 1/1/4:2 in software is associated with lane 2 on physical port 4 in slot 1 on member 1.

---

## On the 8400 Switch Series

- *member*: Always 1. VSF is not supported on this switch.
- *slot*: Specifies physical location of a module in the switch chassis.
  - Management modules are on the front of the switch in slots 1/5 and 1/6.
  - Line modules are on the front of the switch in slots 1/1 through 1/4, and 1/7 through 1/10.
- *port*: Physical number of a port on a line module

For example, the logical interface 1/1/4 in software is associated with physical port 4 in slot 1 on member 1.

## Identifying modular switch components

- Power supplies are on the front of the switch behind the bezel above the management modules. Power supplies are labeled in software in the format: *member/power supply*:
  - *member*: 1.
  - *power supply*: 1 to 4.
- Fans are on the rear of the switch and are labeled in software as: *member/tray/fan*:
  - *member*: 1.
  - *tray*: 1 to 4.
  - *fan*: 1 to 4.
- Fabric modules are not labeled on the switch but are labeled in software in the format: *member/module*:
  - *member*: 1.
  - *member*: 1 or 2.
- The display module on the rear of the switch is not labeled with a member or slot number.

The following are the events related to AAA.

#### Event ID: 2301

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | AAA <aaa_config_type> update: <aaa_config_event>              |
| Category    | AAA                                                           |
| Severity    | Information                                                   |
| Description | Logs AAA Authentication/Authorization/Accounting/fail-through |

#### Event ID: 2302

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | TACACS <tacacs_type> <tacacs_action>: <tacacs_event>                      |
| Category    | AAA                                                                       |
| Severity    | Information                                                               |
| Description | Logs TACACS+ server update, server group update and global default update |

#### Event ID: 2303

|             |                                                                          |
|-------------|--------------------------------------------------------------------------|
| Message     | RADIUS <radius_type> <radius_action>: <radius_event>                     |
| Category    | AAA                                                                      |
| Severity    | Information                                                              |
| Description | Logs RADIUS server update, server group update and global default update |

#### Event ID: 2304

|             |                                                                                                              |
|-------------|--------------------------------------------------------------------------------------------------------------|
| Message     | RADIUS Server with Address:<server_address>, Authport:<server_authport>, VRF_ID:<server_vrfid> is "<status>" |
| Category    | AAA                                                                                                          |
| Severity    | Information                                                                                                  |
| Description | Logs changes in RADIUS server reachability status                                                            |

#### Event ID: 2305

|             |                                                                                  |
|-------------|----------------------------------------------------------------------------------|
| Message     | TACACS server host <server_address> port <server_port> vrf <server_vrf> <status> |
| Category    | AAA                                                                              |
| Severity    | Information                                                                      |
| Description | Logs changes in TACACS server reachability status                                |

### Event ID: 2306

|             |                                                                                        |
|-------------|----------------------------------------------------------------------------------------|
| Message     | RADIUS Server route with Address:<server_address>, VRF_ID:<server_vrfid> is "<status>" |
| Category    | AAA                                                                                    |
| Severity    | Information                                                                            |
| Description | Logs changes in RADIUS server route reachability status                                |

The following are the events related to ACLs.

#### Event ID: 10001

|             |                          |
|-------------|--------------------------|
| Message     | <code>&lt;log&gt;</code> |
| Category    | ACLs                     |
| Severity    | Information              |
| Description | ACL log                  |

#### Event ID: 10002

|             |                                                                                                                   |
|-------------|-------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;acl_name&gt; on &lt;interface_name&gt; (&lt;direction&gt;): &lt;hit_delta&gt; &lt;ace_string&gt;</code> |
| Category    | ACLs                                                                                                              |
| Severity    | Information                                                                                                       |
| Description | ACL log statistics                                                                                                |

#### Event ID: 10003

|             |                                                                                           |
|-------------|-------------------------------------------------------------------------------------------|
| Message     | <code>ACL &lt;acl_type&gt; &lt;acl_name&gt; failed to apply on &lt;application&gt;</code> |
| Category    | ACLs                                                                                      |
| Severity    | Error                                                                                     |
| Description | ACL application failure                                                                   |

The following are the events related to alarm.

#### Event ID: 11701

|             |                                                                                                                |
|-------------|----------------------------------------------------------------------------------------------------------------|
| Message     | Input alarm <id> config change: name: <name>, relay: <relay>, log_and_trap: <log_and_trap>, trigger: <trigger> |
| Category    | Alarm                                                                                                          |
| Severity    | Information                                                                                                    |
| Description | Event reported when there is a change in input alarm configuration.                                            |

#### Event ID: 11702

|             |                                                                                   |
|-------------|-----------------------------------------------------------------------------------|
| Message     | System alarm (<type>) config change: relay: <relay>, log_and_trap: <log_and_trap> |
| Category    | Alarm                                                                             |
| Severity    | Information                                                                       |
| Description | Event reported when there is a change in system alarm configuration.              |

#### Event ID: 11703

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | System alarm <name> has activated through log-and-trap': yes |
| Category    | Alarm                                                        |
| Severity    | Information                                                  |
| Description | Event reported when system alarm has activated               |

#### Event ID: 11704

|             |                                                                                     |
|-------------|-------------------------------------------------------------------------------------|
| Message     | Input alarm <name> has activated through log-and-trap, triggered at <trigger>': yes |
| Category    | Alarm                                                                               |
| Severity    | Information                                                                         |
| Description | Event reported when input alarm has activated                                       |

#### Event ID: 11705

|             |                                                                         |
|-------------|-------------------------------------------------------------------------|
| Message     | Snooze alarm activated, disabling relay function for <length> min': yes |
| Category    | Alarm                                                                   |
| Severity    | Information                                                             |
| Description | Event reported when alarm snooze timer has activated                    |

#### Event ID: 11706

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | Snooze alarm has expired': yes                     |
| Category    | Alarm                                              |
| Severity    | Information                                        |
| Description | Event reported when alarm snooze timer has expired |

#### Event ID: 11707

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | Alarm relay function is re-enabled': yes               |
| Category    | Alarm                                                  |
| Severity    | Information                                            |
| Description | Event reported when alarm relay function is re-enabled |

#### Event ID: 11708

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | Snooze alarm repeats, disabling relay function for <length> min': yes |
| Category    | Alarm                                                                 |
| Severity    | Information                                                           |
| Description | Event reported when alarm snooze timer repeats                        |

#### Event ID: 11709

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | System alarm <name> has activated through relay              |
| Category    | Alarm                                                        |
| Severity    | Information                                                  |
| Description | Event reported when system alarm has activated through relay |

#### Event ID: 11710

|         |                                                                        |
|---------|------------------------------------------------------------------------|
| Message | Input alarm <name> has activated through relay, triggered at <trigger> |
|---------|------------------------------------------------------------------------|



|             |                                                             |
|-------------|-------------------------------------------------------------|
| Category    | Alarm                                                       |
| Severity    | Information                                                 |
| Description | Event reported when input alarm has activated through relay |

The following are the events related to ARP security.

#### Event ID: 10401

|             |                                            |
|-------------|--------------------------------------------|
| Message     | ARP inspection <status> on vlan <vlan_id>. |
| Category    | ARP security                               |
| Severity    | Information                                |
| Description | ARP inspection configuration on VLAN       |

#### Event ID: 10402

|             |                                              |
|-------------|----------------------------------------------|
| Message     | ARP inspection <status> on port <port_name>. |
| Category    | ARP security                                 |
| Severity    | Information                                  |
| Description | ARP inspection port mode configuration       |

The following are the events related to ASIC table full error for L3PD.

### Event ID: 10801

|             |                                                                               |
|-------------|-------------------------------------------------------------------------------|
| Message     | Neighbor add failure due to neighbor hardware full.' throttle_count: 1        |
| Category    | ASIC table full error for L3PD                                                |
| Severity    | Error                                                                         |
| Description | Hardware table for NEIGHBOR entries are full, no new neighbors will be added. |

### Event ID: 10802

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | Route add failure due to route hardware full' throttle_count: 1        |
| Category    | ASIC table full error for L3PD                                         |
| Severity    | Error                                                                  |
| Description | Hardware table for ROUTE entries are full, no new route will be added. |

### Event ID: 10803

|             |                                                                          |
|-------------|--------------------------------------------------------------------------|
| Message     | Self IP add failure due to self ip hardware full                         |
| Category    | ASIC table full error for L3PD                                           |
| Severity    | Error                                                                    |
| Description | Hardware table for SELFIP entries are full, no new selfip will be added. |

### Event ID: 10804

|             |                                                                   |
|-------------|-------------------------------------------------------------------|
| Message     | Custom route prefix tables configured from customer_override.yaml |
| Category    | ASIC table full error for L3PD                                    |
| Severity    | Information                                                       |
| Description | Custom route prefix tables configured from customer_override.yaml |

### Event ID: 10805 (Severity: Warning)

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | Error parsing LIST_ROUTE_IPV4_PREFIX in customer_override.yaml file |
| Category    | ASIC table full error for L3PD                                      |
| Severity    | Warning                                                             |
| Description | Error parsing LIST_ROUTE_IPV4_PREFIX in customer_override.yaml file |

#### Event ID: 10806 (Severity: Warning)

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | Error parsing LIST_ROUTE_IPV6_PREFIX in customer_override.yaml file |
| Category    | ASIC table full error for L3PD                                      |
| Severity    | Warning                                                             |
| Description | Error parsing LIST_ROUTE_IPV6_PREFIX in customer_override.yaml file |

The following are the events related to BFD.

#### Event ID: 7301

|             |                                           |
|-------------|-------------------------------------------|
| Message     | BFD was enabled                           |
| Category    | BFD                                       |
| Severity    | Information                               |
| Description | Event raised when BFD is enabled globally |

#### Event ID: 7302

|             |                                            |
|-------------|--------------------------------------------|
| Message     | BFD was disabled                           |
| Category    | BFD                                        |
| Severity    | Information                                |
| Description | Event raised when BFD is disabled globally |

#### Event ID: 7303

|             |                                                |
|-------------|------------------------------------------------|
| Message     | BFD echo was enabled                           |
| Category    | BFD                                            |
| Severity    | Information                                    |
| Description | Event raised when BFD echo is enabled globally |

#### Event ID: 7304

|             |                                            |
|-------------|--------------------------------------------|
| Message     | BFD echo was disabled                      |
| Category    | BFD                                        |
| Severity    | Information                                |
| Description | Event raised when BFD is disabled globally |

#### Event ID: 7305

|             |                                                       |
|-------------|-------------------------------------------------------|
| Message     | BFD echo was enabled on interface <intf>              |
| Category    | BFD                                                   |
| Severity    | Information                                           |
| Description | Event raised when BFD echo is enabled on an interface |

#### Event ID: 7306

|             |                                                   |
|-------------|---------------------------------------------------|
| Message     | BFD echo was disabled on interface <intf>         |
| Category    | BFD                                               |
| Severity    | Information                                       |
| Description | Event raised when BFD is disabled on an interface |

#### Event ID: 7307

|             |                                                                                                                                                                                                                              |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | BFD session is up. session_id=<session_id>, vrf=<vrf>, op_mode=<op_mode>, src_port=<src_port>, dest_ip=<dest_ip>, local_state=<local_state>, local_diag=<local_diag>, remote_state=<remote_state>, remote_diag=<remote_diag> |
| Category    | BFD                                                                                                                                                                                                                          |
| Severity    | Information                                                                                                                                                                                                                  |
| Description | Event raised when a BFD session state becomes up                                                                                                                                                                             |

#### Event ID: 7308

|             |                                                                                                                                                                                                                                |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | BFD session is down. session_id=<session_id>, vrf=<vrf>, op_mode=<op_mode>, src_port=<src_port>, dest_ip=<dest_ip>, local_state=<local_state>, local_diag=<local_diag>, remote_state=<remote_state>, remote_diag=<remote_diag> |
| Category    | BFD                                                                                                                                                                                                                            |
| Severity    | Information                                                                                                                                                                                                                    |
| Description | Event raised when a BFD session state becomes down                                                                                                                                                                             |

#### Event ID: 7309

|          |                                                                                                                                                                                                                                                 |
|----------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message  | BFD session is administratively down. session_id=<session_id>, vrf=<vrf>, op_mode=<op_mode>, src_port=<src_port>, dest_ip=<dest_ip>, local_state=<local_state>, local_diag=<local_diag>, remote_state=<remote_state>, remote_diag=<remote_diag> |
| Category | BFD                                                                                                                                                                                                                                             |

|             |                                                          |
|-------------|----------------------------------------------------------|
| Severity    | Information                                              |
| Description | Event raised when a BFD session is administratively down |

#### Event ID: 7310

|             |                                                                  |
|-------------|------------------------------------------------------------------|
| Message     | BFD session was created without a source port                    |
| Category    | BFD                                                              |
| Severity    | Information                                                      |
| Description | Event raised when a BFD session is created without a source port |

#### Event ID: 7311

|             |                                                                  |
|-------------|------------------------------------------------------------------|
| Message     | Port <name> can forward BFD traffic                              |
| Category    | BFD                                                              |
| Severity    | Information                                                      |
| Description | Event raised when a port used by BFD session can forward traffic |

#### Event ID: 7312

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | Port <name> can not forward BFD traffic                              |
| Category    | BFD                                                                  |
| Severity    | Information                                                          |
| Description | Event raised when a port used by BFD session can not forward traffic |

#### Event ID: 7313

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | BFD sessions maximum active capacity reached                           |
| Category    | BFD                                                                    |
| Severity    | Information                                                            |
| Description | Event raised when the maximum number of active BFD sessions is reached |

#### Event ID: 7314 (Severity: Warning)

|          |                                                                                                                               |
|----------|-------------------------------------------------------------------------------------------------------------------------------|
| Message  | The echo function for the BFD session <session_id> will not become active until a global echo source IP address is configured |
| Category | BFD                                                                                                                           |

|             |                                                                                                |
|-------------|------------------------------------------------------------------------------------------------|
| Severity    | Warning                                                                                        |
| Description | Event raised when an Echo session is created without a valid echo_source IP address configured |

### Event ID: 7315

|             |                                                                                                                                                                                                                                          |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | BFD session is unidirectional. session_id=<session_id>, vrf=<vrf>, op_mode=<op_mode>, src_port=<src_port>, dest_ip=<dest_ip>, local_state=<local_state>, local_diag=<local_diag>, remote_state=<remote_state>, remote_diag=<remote_diag> |
| Category    | BFD                                                                                                                                                                                                                                      |
| Severity    | Error                                                                                                                                                                                                                                    |
| Description | Event raised when a BFD session state becomes unidirectional                                                                                                                                                                             |

### Event ID: 7316 (Severity: Warning)

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | BFD echo cannot be enabled on tunnels. interface=<intf>     |
| Category    | BFD                                                         |
| Severity    | Warning                                                     |
| Description | Event raised when BFD echo is enabled on a Tunnel interface |

### Event ID: 7317 (Severity: Warning)

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | BFD echo is not supported on IPv6 sessions                     |
| Category    | BFD                                                            |
| Severity    | Warning                                                        |
| Description | Event raised when BFD echo is enabled for a session using IPv6 |

### Event ID: 7318

|             |                                                                                                                                                                                                                                                                                                          |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | IP Version mismatch for BFD. session_id=<session_id>, vrf=<vrf>, op_mode=<op_mode>, src_port=<src_port>, dest_ip=<dest_ip>, local_state=<local_state>, local_diag=<local_diag>, remote_state=<remote_state>, remote_diag=<remote_diag>, from=<from>, ip_version=<ip_version>, Invalid IP address: <addr> |
| Category    | BFD                                                                                                                                                                                                                                                                                                      |
| Severity    | Error                                                                                                                                                                                                                                                                                                    |
| Description | "Event raised when SRC or DST IP Version doesn't match the session's IP Version"                                                                                                                                                                                                                         |

### Event ID: 7319 (Severity: Warning)



|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | BFD single-hop is not supported on interface <i>&lt;intf&gt;</i>       |
| Category    | BFD                                                                    |
| Severity    | Warning                                                                |
| Description | "Event raised when a BFD single-hop session source port is a loopback" |

#### Event ID: 7320 (Severity: Warning)

|             |                                                                                                       |
|-------------|-------------------------------------------------------------------------------------------------------|
| Message     | BFD session interval override not supported for protocol <i>&lt;from&gt;</i>                          |
| Category    | BFD                                                                                                   |
| Severity    | Warning                                                                                               |
| Description | "Event raised when a BFD session specifies an interval for a protocol that does not support override" |

#### Event ID: 7321 (Severity: Warning)

|             |                                                                                                                                                                                                     |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | BFD session <i>&lt;direction&gt;</i> interval override of <i>&lt;requested_interval&gt;</i> ms is out of bounds for protocol <i>&lt;from&gt;</i> , using <i>&lt;applied_interval&gt;</i> ms instead |
| Category    | BFD                                                                                                                                                                                                 |
| Severity    | Warning                                                                                                                                                                                             |
| Description | "Event raised when a BFD session specifies an interval outside the specified bounds"                                                                                                                |

The following are the events related to BGP.

#### Event ID: 2901

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | <code>&lt;remote-addr&gt;: Peer up. vrf-name: &lt;vrf-name&gt;</code> |
| Category    | BGP                                                                   |
| Severity    | Information                                                           |
| Description | Logs the changes in BGP connection state.                             |

#### Event ID: 2902

|             |                                                                                                                                                |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;remote-addr&gt;: Peer down. error-code: &lt;error-code&gt;, error-sub-code: &lt;error-subcode&gt;. vrf-name: &lt;vrf-name&gt;</code> |
| Category    | BGP                                                                                                                                            |
| Severity    | Information                                                                                                                                    |
| Description | Logs the failure in BGP connection state changes.                                                                                              |

#### Event ID: 2903

|             |                                                                                                                                 |
|-------------|---------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;remote-addr&gt;: Peer has received prefix equal to Maximum Prefix value configured. vrf-name: &lt;vrf-name&gt;</code> |
| Category    | BGP                                                                                                                             |
| Severity    | Information                                                                                                                     |
| Description | Trap when the number of received prefix reaches the maximum prefix value.                                                       |

#### Event ID: 2904

|             |                                                                                                                            |
|-------------|----------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;remote-addr&gt;: Peer has received prefix equal to Threshold value configured. vrf-name: &lt;vrf-name&gt;</code> |
| Category    | BGP                                                                                                                        |
| Severity    | Information                                                                                                                |
| Description | Trap when the number of received prefix reached the threshold value.                                                       |

#### Event ID: 2905

|             |                                                                                           |
|-------------|-------------------------------------------------------------------------------------------|
| Message     | BGP AS <code>&lt;as_number&gt;</code> configured. vrf-name: <code>&lt;vrf-name&gt;</code> |
| Category    | BGP                                                                                       |
| Severity    | Information                                                                               |
| Description | Logs BGP enable event.                                                                    |

#### Event ID: 2906

|             |                                                                                             |
|-------------|---------------------------------------------------------------------------------------------|
| Message     | BGP AS <code>&lt;as_number&gt;</code> unconfigured. vrf-name: <code>&lt;vrf-name&gt;</code> |
| Category    | BGP                                                                                         |
| Severity    | Information                                                                                 |
| Description | Logs BGP disable event.                                                                     |

#### Event ID: 2907

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | BGP router-id changed. vrf-name: <code>&lt;vrf-name&gt;</code> |
| Category    | BGP                                                            |
| Severity    | Information                                                    |
| Description | Logs BGP router-id change.                                     |

#### Event ID: 2908

|             |                                                                                                                                 |
|-------------|---------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;remote_addr&gt;</code> : Peer configured, AS <code>&lt;remote_as&gt;</code> . vrf-name: <code>&lt;vrf-name&gt;</code> |
| Category    | BGP                                                                                                                             |
| Severity    | Information                                                                                                                     |
| Description | Logs creation of BGP peer.                                                                                                      |

#### Event ID: 2909

|             |                                                                                                |
|-------------|------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;remote_addr&gt;</code> : User reset request. vrf-name: <code>&lt;vrf-name&gt;</code> |
| Category    | BGP                                                                                            |
| Severity    | Information                                                                                    |
| Description | Logs BGP peer session reset event.                                                             |

#### Event ID: 2910

|         |                                                                                                   |
|---------|---------------------------------------------------------------------------------------------------|
| Message | <code>&lt;remote_addr&gt;</code> : Peer password changed. vrf-name: <code>&lt;vrf-name&gt;</code> |
|---------|---------------------------------------------------------------------------------------------------|

|             |                                      |
|-------------|--------------------------------------|
| Category    | BGP                                  |
| Severity    | Information                          |
| Description | Logs BGP peer password change event. |

#### Event ID: 2911

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | <code>&lt;remote_addr&gt;: Peer deleted. vrf-name: &lt;vrf-name&gt;</code> |
| Category    | BGP                                                                        |
| Severity    | Information                                                                |
| Description | Logs deletion of BGP peer.                                                 |

#### Event ID: 2912

|             |                                                                                   |
|-------------|-----------------------------------------------------------------------------------|
| Message     | <code>&lt;remote_addr&gt;: Peer admin disabled. vrf-name: &lt;vrf-name&gt;</code> |
| Category    | BGP                                                                               |
| Severity    | Information                                                                       |
| Description | Logs BGP peer admin disable event                                                 |

#### Event ID: 2913

|             |                                                                                  |
|-------------|----------------------------------------------------------------------------------|
| Message     | <code>&lt;remote_addr&gt;: Peer admin enabled. vrf-name: &lt;vrf-name&gt;</code> |
| Category    | BGP                                                                              |
| Severity    | Information                                                                      |
| Description | Logs BGP peer admin enable event.                                                |

#### Event ID: 2914

|             |                                                                                                           |
|-------------|-----------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;remote_addr&gt;: Peer remote-as changed to &lt;remote_as&gt;. vrf-name: &lt;vrf-name&gt;</code> |
| Category    | BGP                                                                                                       |
| Severity    | Information                                                                                               |
| Description | Logs BGP peer remote-as change event.                                                                     |

#### Event ID: 2915

|         |                                                                                                         |
|---------|---------------------------------------------------------------------------------------------------------|
| Message | <code>&lt;remote_addr&gt;: Peer local-as changed to &lt;local_as&gt;. vrf-name: &lt;vrf-name&gt;</code> |
|---------|---------------------------------------------------------------------------------------------------------|

|             |                                 |
|-------------|---------------------------------|
| Category    | BGP                             |
| Severity    | Information                     |
| Description | BGP peer local-as change event. |

#### Event ID: 2916

|             |                                                                                                                 |
|-------------|-----------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;remote_addr&gt;: Peer source-address changed to &lt;src_ipaddr&gt;. vrf-name: &lt;vrf-name&gt;</code> |
| Category    | BGP                                                                                                             |
| Severity    | Information                                                                                                     |
| Description | Logs peer source address change event.                                                                          |

#### Event ID: 2917

|             |                                                                                                            |
|-------------|------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;remote_addr&gt;: Peer remove-private-as configuration changed. vrf-name: &lt;vrf-name&gt;</code> |
| Category    | BGP                                                                                                        |
| Severity    | Information                                                                                                |
| Description | Logs configuration of peer remove-private-as.                                                              |

#### Event ID: 2918

|             |                                                                                                                                                        |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;bgp_id&gt;: BGP identifier sent by Peer &lt;remote_addr&gt; matches ours. BGP session may not established. vrf-name: &lt;vrf-name&gt;</code> |
| Category    | BGP                                                                                                                                                    |
| Severity    | Information                                                                                                                                            |
| Description | Logs peer identifier has been matched with local identifier.                                                                                           |

#### Event ID: 2919 (Severity: Critical)

|             |                                                                                                                    |
|-------------|--------------------------------------------------------------------------------------------------------------------|
| Message     | <code>The BGP RIB has reached the threshold limit of &lt;threshold_limit&gt; for VRF &lt;vrf-name&gt;': yes</code> |
| Category    | BGP                                                                                                                |
| Severity    | Critical                                                                                                           |
| Description | Trap when the rib size reaches the threshold value.                                                                |

#### Event ID: 2920

|             |                                                                                                                  |
|-------------|------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;pg_name&gt;: Peer-group configured with remote-as &lt;remote_as&gt;. vrf-name: &lt;vrf-name&gt;</code> |
| Category    | BGP                                                                                                              |
| Severity    | Information                                                                                                      |
| Description | Logs BGP peer-group remote-as configuration event.                                                               |

The following are the events related to Bluetooth management.

### Event ID: 8001

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | Bluetooth has been <code>&lt;enabled_disabled&gt;</code> |
| Category    | Bluetooth Management                                     |
| Severity    | Information                                              |
| Description | Event raised when Bluetooth is enabled or disabled       |

### Event ID: 8002 (Severity: Warning)

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | Bluetooth unable to trust pairing device                      |
| Category    | Bluetooth Management                                          |
| Severity    | Warning                                                       |
| Description | Event raised when Bluetooth is unable to trust pairing device |

### Event ID: 8003

|             |                                                                   |
|-------------|-------------------------------------------------------------------|
| Message     | Bluetooth adapter <code>&lt;inserted_removed&gt;</code>           |
| Category    | Bluetooth Management                                              |
| Severity    | Information                                                       |
| Description | Event raised when btd receives signal for Bluetooth adapter event |

### Event ID: 8004

|             |                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------|
| Message     | Bluetooth device <code>&lt;connected_disconnected&gt;</code> : <code>&lt;mac_address&gt;</code> |
| Category    | Bluetooth Management                                                                            |
| Severity    | Information                                                                                     |
| Description | Event raised when btd receives signal for Bluetooth device event                                |

### Event ID: 8005 (Severity: Warning)

|             |                                                                                                     |
|-------------|-----------------------------------------------------------------------------------------------------|
| Message     | Bluetooth device rejected because another device is already connected                               |
| Category    | Bluetooth Management                                                                                |
| Severity    | Warning                                                                                             |
| Description | Event raised when btd disconnects a newly paired device because another device is already connected |



The following are the events related to CDP.

#### Event ID: 8901

|             |                  |
|-------------|------------------|
| Message     | CDP Enabled      |
| Category    | CDP              |
| Severity    | Information      |
| Description | Logs CDP enabled |

#### Event ID: 8902

|             |                   |
|-------------|-------------------|
| Message     | CDP Disabled      |
| Category    | CDP               |
| Severity    | Information       |
| Description | Logs CDP disabled |

#### Event ID: 8903

|             |                                            |
|-------------|--------------------------------------------|
| Message     | CDP neighbor <mac> is added on <interface> |
| Category    | CDP                                        |
| Severity    | Information                                |
| Description | Log to indicate CDP neighbor addition      |

#### Event ID: 8904

|             |                                                                   |
|-------------|-------------------------------------------------------------------|
| Message     | CDP neighbor <mac> is updated on <interface>' throttle_count: 100 |
| Category    | CDP                                                               |
| Severity    | Information                                                       |
| Description | Log to indicate CDP neighbour modification                        |

#### Event ID: 8905

|             |                                              |
|-------------|----------------------------------------------|
| Message     | CDP neighbor <mac> is deleted on <interface> |
| Category    | CDP                                          |
| Severity    | Information                                  |
| Description | Log to indicate CDP neighbor deletion        |

### Event ID: 8906

|             |                                                  |
|-------------|--------------------------------------------------|
| Message     | All CDP neighbor info cleared                    |
| Category    | CDP                                              |
| Severity    | Information                                      |
| Description | Log to indicate all CDP neighbor info is cleared |

The following are the events related to certificate management.

### Event ID: 7701

|             |                                           |
|-------------|-------------------------------------------|
| Message     | TA Profile <name> created                 |
| Category    | Certificate management                    |
| Severity    | Information                               |
| Description | Event raised when a ta profile is created |

### Event ID: 7702

|             |                                           |
|-------------|-------------------------------------------|
| Message     | TA Profile <name> deleted                 |
| Category    | Certificate management                    |
| Severity    | Information                               |
| Description | Event raised when a ta profile is removed |

### Event ID: 7703

|             |                                                  |
|-------------|--------------------------------------------------|
| Message     | Leaf certificate <name> imported                 |
| Category    | Certificate management                           |
| Severity    | Information                                      |
| Description | Event raised when a leaf certificate is imported |

### Event ID: 7704

|             |                                                 |
|-------------|-------------------------------------------------|
| Message     | Leaf certificate <name> deleted                 |
| Category    | Certificate management                          |
| Severity    | Information                                     |
| Description | Event raised when a leaf certificate is deleted |

### Event ID: 7705 (Severity: Warning)

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | Certificate <name> will expire within <days> days                     |
| Category    | Certificate management                                                |
| Severity    | Warning                                                               |
| Description | Event raised when an installed certifiante will expire within 60 days |

#### Event ID: 7706 (Severity: Warning)

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | Certificate <name> has not yet reached its start date                     |
| Category    | Certificate management                                                    |
| Severity    | Warning                                                                   |
| Description | Event raised when an installed certifiante is not yet past its start date |

#### Event ID: 7707 (Severity: Warning)

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | Certificate <name> has expired and can no longer be used |
| Category    | Certificate management                                   |
| Severity    | Warning                                                  |
| Description | Event raised when an installed certifiante has expired   |

#### Event ID: 7708

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | Certificate <name> verified and accepted' throttle_count: 100 |
| Category    | Certificate management                                        |
| Severity    | Information                                                   |
| Description | Event raised when a certificate chain is verified             |

#### Event ID: 7709 (Severity: Warning)

|             |                                                                                        |
|-------------|----------------------------------------------------------------------------------------|
| Message     | Certificate <name> rejected due to verification failure (<error>)' throttle_count: 100 |
| Category    | Certificate management                                                                 |
| Severity    | Warning                                                                                |
| Description | Event raised when a certificate chain is rejected                                      |

#### Event ID: 7710

|             |                                                                          |
|-------------|--------------------------------------------------------------------------|
| Message     | Certificate signing request <name> created                               |
| Category    | Certificate management                                                   |
| Severity    | Information                                                              |
| Description | Event raised when a certificate signing request is created on the switch |

#### Event ID: 7711

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | Self-signed certificate <name> created                               |
| Category    | Certificate management                                               |
| Severity    | Information                                                          |
| Description | Event raised when a self-signed certificate is created on the switch |

#### Event ID: 7712

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | Application association with the <name> certificate is not permitted |
| Category    | Certificate management                                               |
| Severity    | Error                                                                |
| Description | Event raised when an invalid certificate association is made         |

#### Event ID: 7713 (Severity: Warning)

|             |                                                                                                                                            |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Certificate <name> failed OCSP verification (<status>), but was accepted because OCSP enforcement is set to optional.' throttle_count: 100 |
| Category    | Certificate management                                                                                                                     |
| Severity    | Warning                                                                                                                                    |
| Description | Event raised when a certificate is verified due to optional OCSP enforcement                                                               |

#### Event ID: 7714

|             |                                                                                   |
|-------------|-----------------------------------------------------------------------------------|
| Message     | CA certificates successfully downloaded from EST server <name>                    |
| Category    | Certificate management                                                            |
| Severity    | Information                                                                       |
| Description | Event raised when CA certificates were successfully downloaded from an EST server |

#### Event ID: 7715

|             |                                                                              |
|-------------|------------------------------------------------------------------------------|
| Message     | Failed to download CA certificates from EST server <name>                    |
| Category    | Certificate management                                                       |
| Severity    | Error                                                                        |
| Description | Event raised when CA certificates could not be downloaded from an EST server |

#### Event ID: 7716

|             |                                                                   |
|-------------|-------------------------------------------------------------------|
| Message     | Certificate <name> successfully enrolled by EST server <est_name> |
| Category    | Certificate management                                            |
| Severity    | Information                                                       |
| Description | Event raised when a certificate is successfully enrolled with EST |

#### Event ID: 7717

|             |                                                                   |
|-------------|-------------------------------------------------------------------|
| Message     | Failed to enroll certificate <name> with EST server <est_name>    |
| Category    | Certificate management                                            |
| Severity    | Error                                                             |
| Description | Event raised when certificate enrollment with an EST server fails |

#### Event ID: 7718

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | Certificate <name> successfully reenrolled by EST server <est_name> |
| Category    | Certificate management                                              |
| Severity    | Information                                                         |
| Description | Event raised when a certificate is successfully reenrolled with EST |

#### Event ID: 7719

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | Failed to reenroll certificate <name> with EST server <est_name>    |
| Category    | Certificate management                                              |
| Severity    | Error                                                               |
| Description | Event raised when certificate reenrollment with an EST server fails |

#### Event ID: 7720 (Severity: Warning)

|         |                                                   |
|---------|---------------------------------------------------|
| Message | Certificate <name> is not set for signing purpose |
|---------|---------------------------------------------------|

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Category    | Certificate management                                        |
| Severity    | Warning                                                       |
| Description | Event raised when a signer certificate is not set for signing |

### Event ID: 7721 (Severity: Warning)

|             |                                                                    |
|-------------|--------------------------------------------------------------------|
| Message     | Certificate <name> is invalid or malformed                         |
| Category    | Certificate management                                             |
| Severity    | Warning                                                            |
| Description | Event raised when an installed certificate is invalid or malformed |

The following are the events related to config management.

### Event ID: 6801

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | Copying configs from: <from> to: <to>                          |
| Category    | Config Management                                              |
| Severity    | Information                                                    |
| Description | Logs a message when configs copying from one format to another |

### Event ID: 6802

|             |                                                   |
|-------------|---------------------------------------------------|
| Message     | Error while copying configs. Error: <error>       |
| Category    | Config Management                                 |
| Severity    | Error                                             |
| Description | Logs a message when copying config has some error |

### Event ID: 6803

|             |                                                                                                              |
|-------------|--------------------------------------------------------------------------------------------------------------|
| Message     | <type>:<value>                                                                                               |
| Category    | Config Management                                                                                            |
| Severity    | Information                                                                                                  |
| Description | Logs a message when config validation prunes tables/columns in startup-config or when errors are encountered |

### Event ID: 6804

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | Error while copying configs. Error: <error>                   |
| Category    | Config Management                                             |
| Severity    | Error                                                         |
| Description | Logs a message when copying config to shadowdb has some error |

### Event ID: 6805



|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | Information while copying configs. Info: <i>&lt;info&gt;</i> |
| Category    | Config Management                                            |
| Severity    | Information                                                  |
| Description | Logs a message when copying config has some information      |

## Chapter 13

# Connectivity Fault Management (CFM) events

The following are the events related to Connectivity Fault Management (CFM).

### Event ID: 11601

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | Connection lost for Maintenance Endpoint <id> on <interface>.       |
| Category    | Connectivity Fault Management (CFM)                                 |
| Severity    | Error                                                               |
| Description | Event reported when connection is lost on the Maintenance Endpoint. |

### Event ID: 11602

|             |                                                                         |
|-------------|-------------------------------------------------------------------------|
| Message     | Connection restored for Maintenance Endpoint <id> on <interface>.       |
| Category    | Connectivity Fault Management (CFM)                                     |
| Severity    | Information                                                             |
| Description | Event reported when connection is restored on the Maintenance Endpoint. |

The following are the events related to container manager.

### Event ID: 11801

|             |                                          |
|-------------|------------------------------------------|
| Message     | Container <i>&lt;name&gt;</i> is created |
| Category    | Container manager                        |
| Severity    | Information                              |
| Description | Event reported when container is created |

### Event ID: 11802

|             |                                          |
|-------------|------------------------------------------|
| Message     | Container <i>&lt;name&gt;</i> is removed |
| Category    | Container manager                        |
| Severity    | Information                              |
| Description | Event reported when container is removed |

### Event ID: 11803

|             |                                              |
|-------------|----------------------------------------------|
| Message     | Container <i>&lt;name&gt;</i> is operational |
| Category    | Container manager                            |
| Severity    | Information                                  |
| Description | Event reported when container is operational |

The following are the events related to control plane policing.

#### Event ID: 1501

|             |                                         |
|-------------|-----------------------------------------|
| Message     | <code>COPP initialization failed</code> |
| Category    | CoPP                                    |
| Severity    | Error                                   |
| Description | Logs COPP initialization failure.       |

#### Event ID: 1502

|             |                                             |
|-------------|---------------------------------------------|
| Message     | <code>COPP initialization successful</code> |
| Category    | CoPP                                        |
| Severity    | Information                                 |
| Description | Logs COPP initialization success.           |

#### Event ID: 1503

|             |                                                      |
|-------------|------------------------------------------------------|
| Message     | <code>Ingress FP Group create failed</code>          |
| Category    | CoPP                                                 |
| Severity    | Error                                                |
| Description | Logs ingress field processor group creation failure. |

#### Event ID: 1504

|             |                                                     |
|-------------|-----------------------------------------------------|
| Message     | <code>Egress FP Group create failed</code>          |
| Category    | CoPP                                                |
| Severity    | Error                                               |
| Description | Logs egress field processor group creation failure. |

#### Event ID: 1505

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | Programming defaults failed                        |
| Category    | CoPP                                               |
| Severity    | Error                                              |
| Description | Logs failure for initialization of default values. |

#### Event ID: 1506

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | Packet class programming failed for <class>                |
| Category    | CoPP                                                       |
| Severity    | Error                                                      |
| Description | Logs failure of programming queue for a CoPP packet class. |

#### Event ID: 1507

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | Failed to program ingress field processor rule for <class>            |
| Category    | CoPP                                                                  |
| Severity    | Error                                                                 |
| Description | Logs failure of programming ingress field processor for a CoPP class. |

#### Event ID: 1508

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | Failed to program egress rule for <class>                            |
| Category    | CoPP                                                                 |
| Severity    | Error                                                                |
| Description | Logs failure of programming egress field processor for a CoPP class. |

#### Event ID: 1509

|             |                                                     |
|-------------|-----------------------------------------------------|
| Message     | CoPP initial initialization failed on slot <slot>   |
| Category    | CoPP                                                |
| Severity    | Error                                               |
| Description | Logs CoPP initial initialization failure on a slot. |

#### Event ID: 1510

|         |                                                 |
|---------|-------------------------------------------------|
| Message | CoPP final initialization failed on slot <slot> |
|---------|-------------------------------------------------|

|             |                                                   |
|-------------|---------------------------------------------------|
| Category    | CoPP                                              |
| Severity    | Error                                             |
| Description | Logs CoPP final initialization failure on a slot. |

### Event ID: 1511

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | CoPP deinitialization failed on slot <code>&lt;slot&gt;</code> |
| Category    | CoPP                                                           |
| Severity    | Error                                                          |
| Description | Logs CoPP deinitialization failure on a slot.                  |

### Event ID: 1512

|             |                                                                                                          |
|-------------|----------------------------------------------------------------------------------------------------------|
| Message     | Failed to configure hardware for CoPP on slot <code>&lt;slot&gt;</code> class <code>&lt;class&gt;</code> |
| Category    | CoPP                                                                                                     |
| Severity    | Error                                                                                                    |
| Description | Logs failure while configuring hardware on a slot for a CoPP class.                                      |

### Event ID: 1513

|             |                                                                                                         |
|-------------|---------------------------------------------------------------------------------------------------------|
| Message     | Failed to retrieve CoPP statistics from slot <code>&lt;slot&gt;</code> class <code>&lt;class&gt;</code> |
| Category    | CoPP                                                                                                    |
| Severity    | Error                                                                                                   |
| Description | Logs failure while retrieving statistics on a slot for a CoPP class.                                    |

The following are the events related to CPU\_RX.

#### Event ID: 7501

|             |                                                                         |
|-------------|-------------------------------------------------------------------------|
| Message     | Kernel filter "<action>" failed on unit <unit> for <filter_description> |
| Category    | CPU_RX                                                                  |
| Severity    | Information                                                             |
| Description | Event raised when a kernel filter cannot be created or deleted          |

#### Event ID: 7502

|             |                                                                                                                                                            |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Cannot create kernel filter on unit <unit> for <filter_description>. All filters are in use. Configuring fewer per-port features can help with this issue. |
| Category    | CPU_RX                                                                                                                                                     |
| Severity    | Error                                                                                                                                                      |
| Description | Event raised when a kernel filter cannot be created because all filters are in use                                                                         |

The following are the events related to credential manager.

### Event ID: 6501 (Severity: Warning)

|             |                                                                                                            |
|-------------|------------------------------------------------------------------------------------------------------------|
| Message     | An internal error occurred while reading the export password and default export password was used instead. |
| Category    | Credential Manager                                                                                         |
| Severity    | Warning                                                                                                    |
| Description | Warns the user that export password file was corrupted and default passwd was used instead.                |

### Event ID: 6502 (Severity: Warning)

|             |                                                                                                                                                                                      |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | A critical system file has been corrupted. Please configure your export password to the one used by your most recent configuration export and import your most recent configuration. |
| Category    | Credential Manager                                                                                                                                                                   |
| Severity    | Warning                                                                                                                                                                              |
| Description | Warns the user that the chassis secret has been corrupted.                                                                                                                           |

### Event ID: 6504

|             |                                                                    |
|-------------|--------------------------------------------------------------------|
| Message     | Self-signed certificate successfully created for the https-server. |
| Category    | Credential Manager                                                 |
| Severity    | Information                                                        |
| Description | Logs a message when the self-signed cert is created by credmgr.    |

### Event ID: 6505

|             |                                                                  |
|-------------|------------------------------------------------------------------|
| Message     | User admin password changed from ServiceOS                       |
| Category    | Credential Manager                                               |
| Severity    | Information                                                      |
| Description | Logs a message when a user changes admin password from ServiceOS |

### Event ID: 6506



|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | SSH authorized keys were added for user <user>               |
| Category    | Credential Manager                                           |
| Severity    | Information                                                  |
| Description | Logs a message when SSH authorized keys are added for a user |

#### Event ID: 6507

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | Failed to write SSH authorized keys for user <user>                    |
| Category    | Credential Manager                                                     |
| Severity    | Error                                                                  |
| Description | Logs a message after a failure to write SSH authorized keys for a user |

#### Event ID: 6508

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | SSH authorized keys deleted for user <user>                 |
| Category    | Credential Manager                                          |
| Severity    | Information                                                 |
| Description | Logs a message afte deleting SSH authorized keys for a user |

#### Event ID: 6509

|             |                                                                                       |
|-------------|---------------------------------------------------------------------------------------|
| Message     | User <user> has configured an invalid SSH authorized key with key identifier <key-id> |
| Category    | Credential Manager                                                                    |
| Severity    | Error                                                                                 |
| Description | Logs a message when SSH authorized key fails validation chack                         |

The following are the events related to device fingerprinting.

### Event ID: 12401 (Severity: Warning)

|             |                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------|
| Message     | Reached the maximum number of clients limit on the switch for device fingerprinting.            |
| Category    | Device fingerprinting                                                                           |
| Severity    | Warning                                                                                         |
| Description | Log the event when the maximum client limit for device fingerprinting is reached on the switch. |

### Event ID: 12402 (Severity: Warning)

|             |                                                                                                                                                   |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Reached the maximum clients limit of <code>&lt;client_limit&gt;</code> on the interface <code>&lt;interface&gt;</code> for device fingerprinting. |
| Category    | Device fingerprinting                                                                                                                             |
| Severity    | Warning                                                                                                                                           |
| Description | Log the event when the per port clients limit for device fingerprinting is reached.                                                               |

The following are the events related to DHCP relay.

#### Event ID: 3401

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | DHCP Relay Enabled                                         |
| Category    | DHCP Relay                                                 |
| Severity    | Information                                                |
| Description | This command enables the DHCP Relay feature in the device. |

#### Event ID: 3402

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | DHCP Relay Disabled                                         |
| Category    | DHCP Relay                                                  |
| Severity    | Information                                                 |
| Description | This command disables the DHCP Relay feature in the device. |

The following are the events related to DHCP server.

#### Event ID: 1901

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | DHCP Lease added <expiry_time> <mac> <ip> <host> <client_id> |
| Category    | DHCP server                                                  |
| Severity    | Information                                                  |
| Description | Logs DHCP lease addition                                     |

#### Event ID: 1902

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | DHCP Lease deleted <expiry_time> <mac> <ip> <host> <client_id> |
| Category    | DHCP server                                                    |
| Severity    | Information                                                    |
| Description | Logs DHCP lease deletion                                       |

#### Event ID: 1903

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | DHCP Lease updated <expiry_time> <mac> <ip> <host> <client_id> |
| Category    | DHCP server                                                    |
| Severity    | Information                                                    |
| Description | Logs DHCP lease updation                                       |

#### Event ID: 1904

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | DHCP Lease addition failed <expiry_time> <mac> <ip> <host> <client_id> |
| Category    | DHCP server                                                            |
| Severity    | Error                                                                  |
| Description | Logs failure in DHCP lease addition                                    |

#### Event ID: 1905

|             |                                                                                                                   |
|-------------|-------------------------------------------------------------------------------------------------------------------|
| Message     | DHCP Lease deletion failed <code>&lt;expiry_time&gt; &lt;mac&gt; &lt;ip&gt; &lt;host&gt; &lt;client_id&gt;</code> |
| Category    | DHCP server                                                                                                       |
| Severity    | Error                                                                                                             |
| Description | Logs failure in DHCP lease deletion                                                                               |

#### Event ID: 1906

|             |                                                                                                                 |
|-------------|-----------------------------------------------------------------------------------------------------------------|
| Message     | DHCP Lease update failed <code>&lt;expiry_time&gt; &lt;mac&gt; &lt;ip&gt; &lt;host&gt; &lt;client_id&gt;</code> |
| Category    | DHCP server                                                                                                     |
| Severity    | Error                                                                                                           |
| Description | Logs failure in DHCP lease updation                                                                             |

#### Event ID: 1907

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | DHCP server enabled on VRF <code>&lt;vrf_name&gt;</code> |
| Category    | DHCP server                                              |
| Severity    | Information                                              |
| Description | Event raised when DHCP server gets enabled on the VRF    |

#### Event ID: 1908

|             |                                                           |
|-------------|-----------------------------------------------------------|
| Message     | DHCP server disabled on VRF <code>&lt;vrf_name&gt;</code> |
| Category    | DHCP server                                               |
| Severity    | Information                                               |
| Description | Event raised when DHCP server gets disabled on the VRF    |

#### Event ID: 1909

|             |                                                                                                                                                               |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Invalid DHCP configuration: <code>&lt;config&gt;</code> provided on DHCP Server instance running on VRF <code>&lt;vrf_name&gt;</code> . Ignoring this config. |
| Category    | DHCP server                                                                                                                                                   |
| Severity    | Error                                                                                                                                                         |
| Description | Event raised when user configures an invalid DHCP configuration                                                                                               |

#### Event ID: 1910

|             |                                                           |
|-------------|-----------------------------------------------------------|
| Message     | DHCP Server Lease cleared on vrf <vrf>.                   |
| Category    | DHCP server                                               |
| Severity    | Information                                               |
| Description | Event raised when DHCP Server Lease on the VRF is cleared |

### Event ID: 1911

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | DHCPv6 Server Lease cleared on vrf <vrf>.                   |
| Category    | DHCP server                                                 |
| Severity    | Information                                                 |
| Description | Event raised when DHCPv6 Server Lease on the VRF is cleared |

The following are the events related to DHCPv4 snooping.

### Event ID: 8201 (Severity: Warning)

|             |                                                                                                             |
|-------------|-------------------------------------------------------------------------------------------------------------|
| Message     | Server <code>&lt;ip_address&gt;</code> packet received on untrusted port <code>&lt;port&gt;</code> dropped. |
| Category    | DHCPv4 snooping                                                                                             |
| Severity    | Warning                                                                                                     |
| Description | Log event when packet dropped while server packet received on untrusted port.                               |

### Event ID: 8202 (Severity: Warning)

|             |                                                                               |
|-------------|-------------------------------------------------------------------------------|
| Message     | Client packet destined to untrusted port <code>&lt;port&gt;</code> dropped.   |
| Category    | DHCPv4 snooping                                                               |
| Severity    | Warning                                                                       |
| Description | Log event when client packet dropped while packet destined to untrusted port. |

### Event ID: 8203 (Severity: Warning)

|             |                                                                                                              |
|-------------|--------------------------------------------------------------------------------------------------------------|
| Message     | Packet received from unauthorized server <code>&lt;ip_address&gt;</code> on port <code>&lt;port&gt;</code> . |
| Category    | DHCPv4 snooping                                                                                              |
| Severity    | Warning                                                                                                      |
| Description | Log event when packet dropped while packet received from unauthorized server.                                |

### Event ID: 8204 (Severity: Warning)

|             |                                                                                                        |
|-------------|--------------------------------------------------------------------------------------------------------|
| Message     | Received untrusted relay info from client <code>&lt;mac&gt;</code> on port <code>&lt;port&gt;</code> . |
| Category    | DHCPv4 snooping                                                                                        |
| Severity    | Warning                                                                                                |
| Description | Log event when client packet received with untrusted relay info.                                       |

### Event ID: 8205 (Severity: Warning)

|             |                                                                                                                                                     |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Client address <code>&lt;client_mac&gt;</code> not equal to source MAC <code>&lt;source_mac&gt;</code> detected on port <code>&lt;port&gt;</code> . |
| Category    | DHCPv4 snooping                                                                                                                                     |
| Severity    | Warning                                                                                                                                             |
| Description | Log event when client address not equal to source MAC.                                                                                              |

#### Event ID: 8206 (Severity: Warning)

|             |                                                                                                                                                                                                  |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Binding for <code>&lt;ip_address&gt;:&lt;mac&gt;</code> exists on port <code>&lt;existing_port&gt;</code> . Dropping release request received for the binding on <code>&lt;new_port&gt;</code> . |
| Category    | DHCPv4 snooping                                                                                                                                                                                  |
| Severity    | Warning                                                                                                                                                                                          |
| Description | Log event when release packet received on incorrect port.                                                                                                                                        |

#### Event ID: 8207 (Severity: Warning)

|             |                                                                                                                        |
|-------------|------------------------------------------------------------------------------------------------------------------------|
| Message     | The dynamic binding for <code>&lt;mac&gt;</code> on port <code>&lt;port&gt;</code> was replaced with a manual binding. |
| Category    | DHCPv4 snooping                                                                                                        |
| Severity    | Warning                                                                                                                |
| Description | Log event when dynamic binding for a port was replaced with a manual binding.                                          |

#### Event ID: 8208 (Severity: Warning)

|             |                                                                                                           |
|-------------|-----------------------------------------------------------------------------------------------------------|
| Message     | Drop request from <code>&lt;mac&gt;</code> for already assigned address <code>&lt;ip_address&gt;</code> . |
| Category    | DHCPv4 snooping                                                                                           |
| Severity    | Warning                                                                                                   |
| Description | Log event when drop client request for already assigned ip.                                               |

#### Event ID: 8209 (Severity: Warning)

|             |                                                                                                                                                        |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Drop offer from <code>&lt;server_ip_address&gt;</code> of already assigned address <code>&lt;lease_ip_address&gt;</code> to <code>&lt;mac&gt;</code> . |
| Category    | DHCPv4 snooping                                                                                                                                        |
| Severity    | Warning                                                                                                                                                |
| Description | Log event when drop server offer for already assigned ip.                                                                                              |

#### Event ID: 8210 (Severity: Warning)



|             |                                                                                                                     |
|-------------|---------------------------------------------------------------------------------------------------------------------|
| Message     | Drop offer from <code>&lt;server_ip_address&gt;</code> of <code>&lt;lease_ip_address&gt;</code> address is illegal. |
| Category    | DHCPv4 snooping                                                                                                     |
| Severity    | Warning                                                                                                             |
| Description | Log event when drop server offer for illegal ip.                                                                    |

#### Event ID: 8211 (Severity: Warning)

|             |                                                                                                                     |
|-------------|---------------------------------------------------------------------------------------------------------------------|
| Message     | Maximum bindings limit reached on port <code>&lt;port&gt;</code> , dropping request from <code>&lt;mac&gt;</code> . |
| Category    | DHCPv4 snooping                                                                                                     |
| Severity    | Warning                                                                                                             |
| Description | Log event when binding limit reached on port.                                                                       |

#### Event ID: 8212

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | All the dynamic binding entries were cleared.           |
| Category    | DHCPv4 snooping                                         |
| Severity    | Information                                             |
| Description | Log event when all dynamic binding entries are cleared. |

#### Event ID: 8213

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | Dynamic binding entries on the port <code>&lt;port&gt;</code> were cleared. |
| Category    | DHCPv4 snooping                                                             |
| Severity    | Information                                                                 |
| Description | Log event when all dynamic binding entries on a port are cleared.           |

#### Event ID: 8214

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | Dynamic binding entries on the VLAN <code>&lt;vid&gt;</code> were cleared. |
| Category    | DHCPv4 snooping                                                            |
| Severity    | Information                                                                |
| Description | Log event when all dynamic binding entries on a vlan are cleared.          |

#### Event ID: 8215

|             |                                                                                                         |
|-------------|---------------------------------------------------------------------------------------------------------|
| Message     | Dynamic binding entry with ip <code>&lt;ip&gt;</code> on the VLAN <code>&lt;vid&gt;</code> was cleared. |
| Category    | DHCPv4 snooping                                                                                         |
| Severity    | Information                                                                                             |
| Description | Log event when a specific dynamic binding entry on a vlan is cleared.                                   |

#### Event ID: 8216

|             |                                                                                                                                                             |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Failed to import dynamic ip binding entries from external storage.<br>volume: <code>&lt;volume_name&gt;</code> , filename: <code>&lt;file_name&gt;</code> . |
| Category    | DHCPv4 snooping                                                                                                                                             |
| Severity    | Error                                                                                                                                                       |
| Description | Log event when failed to import dynamic ip binding entries from external storage.                                                                           |

#### Event ID: 8217

|             |                                                                                                               |
|-------------|---------------------------------------------------------------------------------------------------------------|
| Message     | Failed to import dynamic ip binding entries from local storage.<br>filepath: <code>&lt;file_path&gt;</code> . |
| Category    | DHCPv4 snooping                                                                                               |
| Severity    | Error                                                                                                         |
| Description | Log event when failed to import dynamic ip binding entries from local storage.                                |

#### Event ID: 8218 (Severity: Warning)

|             |                                                                                     |
|-------------|-------------------------------------------------------------------------------------|
| Message     | Flash-storage is active for DHCPv4-Snooping.                                        |
| Category    | DHCPv4 snooping                                                                     |
| Severity    | Warning                                                                             |
| Description | Log event when flash-storage becomes active after external-storage unconfiguration. |

The following are the events related to DHCPv6 relay.

#### Event ID: 3301

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | DHCPv6 Relay Enabled                                         |
| Category    | DHCPv6 Relay                                                 |
| Severity    | Information                                                  |
| Description | This command enables the DHCPv6 Relay feature in the device. |

#### Event ID: 3302

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | DHCPv6 Relay Disabled                                         |
| Category    | DHCPv6 Relay                                                  |
| Severity    | Information                                                   |
| Description | This command disables the DHCPv6 Relay feature in the device. |

The following are the events related to DHCPv6 snooping.

### Event ID: 8301 (Severity: Warning)

|             |                                                                                                               |
|-------------|---------------------------------------------------------------------------------------------------------------|
| Message     | Server <code>&lt;ipv6_address&gt;</code> packet received on untrusted port <code>&lt;port&gt;</code> dropped. |
| Category    | DHCPv6 snooping                                                                                               |
| Severity    | Warning                                                                                                       |
| Description | Log event when packet dropped while server packet received on untrusted port.                                 |

### Event ID: 8302 (Severity: Warning)

|             |                                                                               |
|-------------|-------------------------------------------------------------------------------|
| Message     | Client packet destined to untrusted port <code>&lt;port&gt;</code> dropped.   |
| Category    | DHCPv6 snooping                                                               |
| Severity    | Warning                                                                       |
| Description | Log event when client packet dropped while packet destined to untrusted port. |

### Event ID: 8303 (Severity: Warning)

|             |                                                                                                                |
|-------------|----------------------------------------------------------------------------------------------------------------|
| Message     | Packet received from unauthorized server <code>&lt;ipv6_address&gt;</code> on port <code>&lt;port&gt;</code> . |
| Category    | DHCPv6 snooping                                                                                                |
| Severity    | Warning                                                                                                        |
| Description | Log event when packet dropped while packet received from unauthorized server.                                  |

### Event ID: 8304 (Severity: Warning)

|             |                                                                                                        |
|-------------|--------------------------------------------------------------------------------------------------------|
| Message     | Received untrusted relay info from client <code>&lt;mac&gt;</code> on port <code>&lt;port&gt;</code> . |
| Category    | DHCPv6 snooping                                                                                        |
| Severity    | Warning                                                                                                |
| Description | Log event when client packet received with untrusted relay info.                                       |

### Event ID: 8305 (Severity: Warning)

|             |                                                                                                                                   |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------|
| Message     | Binding for <ipv6_address>:<mac> exists on port <existing_port>. Dropping release request received for the binding on <new_port>. |
| Category    | DHCPv6 snooping                                                                                                                   |
| Severity    | Warning                                                                                                                           |
| Description | Log event when release packet received on incorrect port.                                                                         |

#### Event ID: 8306 (Severity: Warning)

|             |                                                                                  |
|-------------|----------------------------------------------------------------------------------|
| Message     | The dynamic binding for <mac> on port <port> was replaced with a manual binding. |
| Category    | DHCPv6 snooping                                                                  |
| Severity    | Warning                                                                          |
| Description | Log event when dynamic binding for a port was replaced with a manual binding.    |

#### Event ID: 8307 (Severity: Warning)

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | Drop request from <mac> for already assigned address <ipv6_address>. |
| Category    | DHCPv6 snooping                                                      |
| Severity    | Warning                                                              |
| Description | Log event when drop client request for already assigned ip.          |

#### Event ID: 8308 (Severity: Warning)

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | Maximum bindings limit reached on port <port>, dropping request from <mac>. |
| Category    | DHCPv6 snooping                                                             |
| Severity    | Warning                                                                     |
| Description | Log event when binding limit reached on port.                               |

#### Event ID: 8309

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | All the dynamic binding entries were cleared.           |
| Category    | DHCPv6 snooping                                         |
| Severity    | Information                                             |
| Description | Log event when all dynamic binding entries are cleared. |

#### Event ID: 8310

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | Dynamic binding entries on the port <code>&lt;port&gt;</code> were cleared. |
| Category    | DHCPv6 snooping                                                             |
| Severity    | Information                                                                 |
| Description | Log event when all dynamic binding entries on a port are cleared.           |

#### Event ID: 8311

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | Dynamic binding entries on the VLAN <code>&lt;vid&gt;</code> were cleared. |
| Category    | DHCPv6 snooping                                                            |
| Severity    | Information                                                                |
| Description | Log event when all dynamic binding entries on a vlan are cleared.          |

#### Event ID: 8312

|             |                                                                                                         |
|-------------|---------------------------------------------------------------------------------------------------------|
| Message     | Dynamic binding entry with ip <code>&lt;ip&gt;</code> on the VLAN <code>&lt;vid&gt;</code> was cleared. |
| Category    | DHCPv6 snooping                                                                                         |
| Severity    | Information                                                                                             |
| Description | Log event when a specific dynamic binding entry on a vlan is cleared.                                   |

#### Event ID: 8313

|             |                                                                                                                                                               |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Failed to import dynamic ip binding entries from external storage.<br>volume:" <code>&lt;volume_name&gt;</code> , filename:" <code>&lt;file_name&gt;</code> . |
| Category    | DHCPv6 snooping                                                                                                                                               |
| Severity    | Error                                                                                                                                                         |
| Description | Log event when import of dynamic binding entries from external storage is failed.                                                                             |

#### Event ID: 8314

|             |                                                                                                                |
|-------------|----------------------------------------------------------------------------------------------------------------|
| Message     | Failed to import dynamic ip binding entries from local storage.<br>filepath:" <code>&lt;file_path&gt;</code> . |
| Category    | DHCPv6 snooping                                                                                                |
| Severity    | Error                                                                                                          |
| Description | Log event when import of dynamic binding entries from local storage is failed.                                 |

#### Event ID: 8315 (Severity: Warning)

|             |                                                                                     |
|-------------|-------------------------------------------------------------------------------------|
| Message     | Flash-storage is active for DHCPv6-Snooping.                                        |
| Category    | DHCPv6 snooping                                                                     |
| Severity    | Warning                                                                             |
| Description | Log event when flash-storage becomes active after external-storage unconfiguration. |

The following are the events related to DCBx.

### Event ID: 9201

|             |                                          |
|-------------|------------------------------------------|
| Message     | DCBX Enabled                             |
| Category    | Discovery and Capability Exchange (DCBx) |
| Severity    | Information                              |
| Description | Logs event when DCBX is globally enabled |

### Event ID: 9202

|             |                                          |
|-------------|------------------------------------------|
| Message     | DCBX Disabled                            |
| Category    | Discovery and Capability Exchange (DCBx) |
| Severity    | Information                              |
| Description | Log event when DCBX is globally disabled |

### Event ID: 9203

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | DCBX is enabled on interface <code>&lt;intf_name&gt;</code> |
| Category    | Discovery and Capability Exchange (DCBx)                    |
| Severity    | Information                                                 |
| Description | Log event when DCBX is enabled on the interface             |

### Event ID: 9204

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | DCBX is disabled on interface <code>&lt;intf_name&gt;</code> |
| Category    | Discovery and Capability Exchange (DCBx)                     |
| Severity    | Information                                                  |
| Description | Log event when DCBX is disabled on the interface             |

### Event ID: 9205



|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | DCBX status active on interface <code>&lt;intf_name&gt;</code> |
| Category    | Discovery and Capability Exchange (DCBx)                       |
| Severity    | Information                                                    |
| Description | Log event when DCBX oper status is active on an interface      |

#### Event ID: 9206

|             |                                                                  |
|-------------|------------------------------------------------------------------|
| Message     | DCBX status inactive on interface <code>&lt;intf_name&gt;</code> |
| Category    | Discovery and Capability Exchange (DCBx)                         |
| Severity    | Information                                                      |
| Description | Log event when DCBX oper status is inactive on an interface      |

#### Event ID: 9207

|             |                                                                   |
|-------------|-------------------------------------------------------------------|
| Message     | PFC TLV status active on interface <code>&lt;intf_name&gt;</code> |
| Category    | Discovery and Capability Exchange (DCBx)                          |
| Severity    | Information                                                       |
| Description | Log event when PFC TLVs are active on an interface                |

#### Event ID: 9208

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | PFC TLV status inactive on interface <code>&lt;intf_name&gt;</code> |
| Category    | Discovery and Capability Exchange (DCBx)                            |
| Severity    | Information                                                         |
| Description | Log event when PFC TLVs are inactive on an interface                |

#### Event ID: 9209 (Severity: Warning)

|             |                                                                              |
|-------------|------------------------------------------------------------------------------|
| Message     | PFC TLV status priority mismatch on interface <code>&lt;intf_name&gt;</code> |
| Category    | Discovery and Capability Exchange (DCBx)                                     |
| Severity    | Warning                                                                      |
| Description | Log event when there is PFC TLV priority mismatch on an interface            |

The following are the events related to DNS client.

#### Event ID: 11901

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | <code>&lt;type&gt; event for VRF &lt;vrf_name&gt;</code> |
| Category    | DNS client                                               |
| Severity    | Information                                              |
| Description | Event reported when DNS event triggered                  |

The following are the events related to DPSE.

#### Event ID: 10901 (Severity: Critical)

|             |                                                                                           |
|-------------|-------------------------------------------------------------------------------------------|
| Message     | Line card module <code>&lt;linecard_name&gt;</code> triggered backplane sequence recovery |
| Category    | DPSE                                                                                      |
| Severity    | Critical                                                                                  |
| Description | A line card hit a backplane sequence error that triggered a recovery operation            |

#### Event ID: 10902

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | HA event triggered backplane sequence recovery              |
| Category    | DPSE                                                        |
| Severity    | Information                                                 |
| Description | A backplane sequence reset was triggered due to an HA event |

#### Event ID: 10903

|             |                                                                          |
|-------------|--------------------------------------------------------------------------|
| Message     | HA event completed backplane sequence recovery                           |
| Category    | DPSE                                                                     |
| Severity    | Information                                                              |
| Description | The system completed a backplane sequence reset triggered by an HA event |

#### Event ID: 10904 (Severity: Critical)

|             |                                                                                           |
|-------------|-------------------------------------------------------------------------------------------|
| Message     | Line card module <code>&lt;linecard_name&gt;</code> completed backplane sequence recovery |
| Category    | DPSE                                                                                      |
| Severity    | Critical                                                                                  |
| Description | The system completed backplane sequence recovery triggered by line card error             |

#### Event ID: 10905

|             |                                                     |
|-------------|-----------------------------------------------------|
| Message     | No active modules have been detected in the system. |
| Category    | DPSE                                                |
| Severity    | Information                                         |
| Description | No active modules have been detected in the system. |

### Event ID: 10906 (Severity: Critical)

|             |                                                                               |
|-------------|-------------------------------------------------------------------------------|
| Message     | Control Plane (<operation_name>) failure during (<plugin_name>) configuration |
| Category    | DPSE                                                                          |
| Severity    | Critical                                                                      |
| Description | An ops-switchd plugin failed executing an operation                           |

The following are the events related to ECMP.

#### Event ID: 1801

|             |                                                                                                     |
|-------------|-----------------------------------------------------------------------------------------------------|
| Message     | Failed to update ecmp object for route <code>&lt;route&gt;</code> , error: <code>&lt;err&gt;</code> |
| Category    | ECMP                                                                                                |
| Severity    | Error                                                                                               |
| Description | logs errors while creating ecmp group.                                                              |

#### Event ID: 1802

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | Update ecmp object for route <code>&lt;route&gt;</code> |
| Category    | ECMP                                                    |
| Severity    | Information                                             |
| Description | logs while creating ecmp group.                         |

#### Event ID: 1803

|             |                                                                                                     |
|-------------|-----------------------------------------------------------------------------------------------------|
| Message     | Failed to delete ecmp egress object <code>&lt;egressid&gt;</code> , error: <code>&lt;err&gt;</code> |
| Category    | ECMP                                                                                                |
| Severity    | Error                                                                                               |
| Description | logs errors while deleting ecmp group.                                                              |

#### Event ID: 1804

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | Delete ecmp egress object <code>&lt;egressid&gt;</code> |
| Category    | ECMP                                                    |
| Severity    | Information                                             |
| Description | logs while deleting ecmp group.                         |

#### Event ID: 1805

|             |                             |
|-------------|-----------------------------|
| Message     | ECMP error: <err>           |
| Category    | ECMP                        |
| Severity    | Error                       |
| Description | logs for ECMP setup errors. |

The following are the events related to ERPS.

### Event ID: 8501 (Severity: Warning)

|             |                                                                                           |
|-------------|-------------------------------------------------------------------------------------------|
| Message     | Expected R-APS packets not received on <ifID> in ring <ringID> with control VLAN <ccvlan> |
| Category    | ERPS                                                                                      |
| Severity    | Warning                                                                                   |
| Description | Log event when RAPS messages are not received for a certain time interval                 |

### Event ID: 8502 (Severity: Warning)

|             |                                                                                                                                                   |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Misconfiguration detected on ring <ringID> with control VLAN <ccvlan>. Another node in the ring with mac <node> is also operating as an RPL owner |
| Category    | ERPS                                                                                                                                              |
| Severity    | Warning                                                                                                                                           |
| Description | Log event when a ring misconfiguration happens                                                                                                    |

### Event ID: 8503

|             |                                                                                  |
|-------------|----------------------------------------------------------------------------------|
| Message     | Operational state of the ring <ringID>, instance <instanceID> changed to <state> |
| Category    | ERPS                                                                             |
| Severity    | Information                                                                      |
| Description | Log state transition of ring instance                                            |

### Event ID: 8504

|             |                                                      |
|-------------|------------------------------------------------------|
| Message     | <interfaceName> is not an L2 port                    |
| Category    | ERPS                                                 |
| Severity    | Information                                          |
| Description | Log event when ring is configured with a non-L2 port |

**Event ID: 8505**

|             |                                                                                                                     |
|-------------|---------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;interfaceName&gt; is already associated with &lt;portName&gt; of ERPS ring &lt;ringID&gt;</code>          |
| Category    | ERPS                                                                                                                |
| Severity    | Information                                                                                                         |
| Description | Log event when an interface which is already associated to a ring port is getting mapped to other ring port as well |

**Event ID: 8506**

|             |                                                                                                                                           |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>Configured control-channel VLAN &lt;ccVlan&gt; is already protected by ERPS ring &lt;ringID&gt;, instance &lt;instanceID&gt;</code> |
| Category    | ERPS                                                                                                                                      |
| Severity    | Information                                                                                                                               |
| Description | Log event when control-channel VLAN is part of the protected-vlans                                                                        |

**Event ID: 8507**

|             |                                                                                                                                  |
|-------------|----------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>VLAN &lt;ccVlan&gt; is already configured as control-channel for instance &lt;instanceID&gt; of ring &lt;ringID&gt;</code> |
| Category    | ERPS                                                                                                                             |
| Severity    | Information                                                                                                                      |
| Description | Log event when control-channel VLAN overlaps with another control-channel of same ring                                           |

**Event ID: 8508**

|             |                                                                                                                                 |
|-------------|---------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>Vlan &lt;dataVlan&gt; is already part of the protected VLAN set of ring &lt;ringID&gt; instance &lt;instanceID&gt;</code> |
| Category    | ERPS                                                                                                                            |
| Severity    | Information                                                                                                                     |
| Description | Log event when protected-vlan(s) overlap                                                                                        |

**Event ID: 8509**

|             |                                                                                    |
|-------------|------------------------------------------------------------------------------------|
| Message     | <code>Control VLAN must not be same on parent and sub rings</code>                 |
| Category    | ERPS                                                                               |
| Severity    | Information                                                                        |
| Description | Log event when same control-channel VLAN is configured on both major and sub-rings |



**Event ID: 8510**

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | Parent-ring <ringID> is same as sub-ring                               |
| Category    | ERPS                                                                   |
| Severity    | Information                                                            |
| Description | Log event when parent-ring id is configured to be the same as sub-ring |

**Event ID: 8511**

|             |                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------|
| Message     | VLAN <vlanID> in the protected VLANs list is also configured as the control-channel             |
| Category    | ERPS                                                                                            |
| Severity    | Information                                                                                     |
| Description | Log event when VLAN from the protected-vlans list is already configured as control-channel VLAN |

**Event ID: 8512**

|             |                                                                                      |
|-------------|--------------------------------------------------------------------------------------|
| Message     | <portName> is already configured as RPL port for instance <instanceID>               |
| Category    | ERPS                                                                                 |
| Severity    | Information                                                                          |
| Description | Log event if the same ring port is configured as RPL port for more than one instance |

**Event ID: 8513**

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | RPL configuration is not allowed on ISL port <interfaceName>           |
| Category    | ERPS                                                                   |
| Severity    | Information                                                            |
| Description | Log event if ring port which is also an ISL is being configured as RPL |

**Event ID: 8514**

|             |                                                                                           |
|-------------|-------------------------------------------------------------------------------------------|
| Message     | Protected VLAN set of instance in sub-ring should map to same instance in the parent ring |
| Category    | ERPS                                                                                      |
| Severity    | Information                                                                               |
| Description | Log event if protected-vlan set of sub-ring is not a subset of the major-ring             |

**Event ID: 8515**

|             |                                                                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Operational state of the ring <i>&lt;ringID&gt;</i> , instance <i>&lt;instanceID&gt;</i> changed to Initializing with reason <i>&lt;reason&gt;</i> |
| Category    | ERPS                                                                                                                                               |
| Severity    | Information                                                                                                                                        |
| Description | Log transition of state of ring instance to initializing and the reason for it                                                                     |

The following are the events related to EVPN.

#### Event ID: 9501

|             |                             |
|-------------|-----------------------------|
| Message     | EVPN EVI: <evi> created     |
| Category    | EVPN                        |
| Severity    | Information                 |
| Description | Logs EVPN EVI create event. |

#### Event ID: 9502

|             |                             |
|-------------|-----------------------------|
| Message     | EVPN EVI: <evi> deleted     |
| Category    | EVPN                        |
| Severity    | Information                 |
| Description | Logs EVPN EVI delete event. |

#### Event ID: 9503

|             |                                       |
|-------------|---------------------------------------|
| Message     | EVPN RD: <rd> updated for EVI: <evi>  |
| Category    | EVPN                                  |
| Severity    | Information                           |
| Description | Logs EVPN RD update event for an EVI. |

#### Event ID: 9504

|             |                                       |
|-------------|---------------------------------------|
| Message     | EVPN RD deleted for EVI: <evi>        |
| Category    | EVPN                                  |
| Severity    | Information                           |
| Description | Logs EVPN RD delete event for an EVI. |

#### Event ID: 9505

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | EVPN RT: <code>&lt;rt&gt;</code> created for EVI: <code>&lt;evi&gt;</code> |
| Category    | EVPN                                                                       |
| Severity    | Information                                                                |
| Description | Logs EVPN RT create event for an EVI.                                      |

#### Event ID: 9506

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | EVPN RT: <code>&lt;rt&gt;</code> deleted for EVI: <code>&lt;evi&gt;</code> |
| Category    | EVPN                                                                       |
| Severity    | Information                                                                |
| Description | Logs EVPN RT delete event for an EVI.                                      |

#### Event ID: 9507

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | EVPN RT: <code>&lt;rt&gt;</code> updated for EVI: <code>&lt;evi&gt;</code> |
| Category    | EVPN                                                                       |
| Severity    | Information                                                                |
| Description | Logs EVPN RT update event for an EVI.                                      |

#### Event ID: 9508

|             |                                                                                         |
|-------------|-----------------------------------------------------------------------------------------|
| Message     | VNI: <code>&lt;vni&gt;</code> is added for EVPN Peer VTEP: <code>&lt;vtep_ip&gt;</code> |
| Category    | EVPN                                                                                    |
| Severity    | Information                                                                             |
| Description | Logs EVPN VTEP VNI add event.                                                           |

#### Event ID: 9509

|             |                                                                                           |
|-------------|-------------------------------------------------------------------------------------------|
| Message     | VNI: <code>&lt;vni&gt;</code> is deleted for EVPN Peer VTEP: <code>&lt;vtep_ip&gt;</code> |
| Category    | EVPN                                                                                      |
| Severity    | Information                                                                               |
| Description | Logs EVPN VTEP VNI delete event.                                                          |

#### Event ID: 9510

|         |                                                                                                                                                                           |
|---------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message | EVPN static MAC conflict <code>&lt;action&gt;</code> , MAC: <code>&lt;mac_addr&gt;</code> , IP address: <code>&lt;ip_addr&gt;</code> , VTEP: <code>&lt;vtep_ip&gt;</code> |
|---------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------|

|             |                                      |
|-------------|--------------------------------------|
| Category    | EVPN                                 |
| Severity    | Error                                |
| Description | Logs EVPN static MAC conflict event. |

#### Event ID: 9511

|             |                                                                               |
|-------------|-------------------------------------------------------------------------------|
| Message     | EVPN static MAC conflict <i>&lt;action&gt;</i> , MAC: <i>&lt;mac_addr&gt;</i> |
| Category    | EVPN                                                                          |
| Severity    | Error                                                                         |
| Description | Logs EVPN static MAC conflict event.                                          |

#### Event ID: 9512

|             |                                                                                   |
|-------------|-----------------------------------------------------------------------------------|
| Message     | EVPN duplicate MAC dampening <i>&lt;action&gt;</i> , MAC: <i>&lt;mac_addr&gt;</i> |
| Category    | EVPN                                                                              |
| Severity    | Error                                                                             |
| Description | Logs EVPN duplicate MAC dampening event.                                          |

#### Event ID: 9513

|             |                                      |
|-------------|--------------------------------------|
| Message     | EVPN VRF: <i>&lt;vrf&gt;</i> created |
| Category    | EVPN                                 |
| Severity    | Information                          |
| Description | Logs EVPN VRF create event.          |

#### Event ID: 9514

|             |                                      |
|-------------|--------------------------------------|
| Message     | EVPN VRF: <i>&lt;vrf&gt;</i> deleted |
| Category    | EVPN                                 |
| Severity    | Information                          |
| Description | Logs EVPN VRF delete event.          |

#### Event ID: 9515

|          |                                                                |
|----------|----------------------------------------------------------------|
| Message  | EVPN RD: <i>&lt;rd&gt;</i> updated for VRF: <i>&lt;vrf&gt;</i> |
| Category | EVPN                                                           |

|             |                                |
|-------------|--------------------------------|
| Severity    | Information                    |
| Description | Logs EVPN VRF RD update event. |

#### Event ID: 9516

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | EVPN RT: <code>&lt;rt&gt;</code> created for VRF: <code>&lt;vrf&gt;</code> |
| Category    | EVPN                                                                       |
| Severity    | Information                                                                |
| Description | Logs EVPN VRF RT create event.                                             |

#### Event ID: 9517

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | EVPN RT: <code>&lt;rt&gt;</code> deleted for VRF: <code>&lt;vrf&gt;</code> |
| Category    | EVPN                                                                       |
| Severity    | Information                                                                |
| Description | Logs EVPN VRF RT delete event.                                             |

#### Event ID: 9518

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | EVPN RT: <code>&lt;rt&gt;</code> updated for VRF: <code>&lt;vrf&gt;</code> |
| Category    | EVPN                                                                       |
| Severity    | Information                                                                |
| Description | Logs EVPN VRF RT update event.                                             |

The following are the events related to external storage.

#### Event ID: 7801

|             |                                                |
|-------------|------------------------------------------------|
| Message     | Share <name> mount failure' throttle_count: 10 |
| Category    | External Storage                               |
| Severity    | Error                                          |
| Description | Event raised when a share fails to mount       |

#### Event ID: 7802

|             |                                             |
|-------------|---------------------------------------------|
| Message     | Share <name> dismount failure               |
| Category    | External Storage                            |
| Severity    | Error                                       |
| Description | Event raised when a share fails to dismount |

#### Event ID: 7803

|             |                                  |
|-------------|----------------------------------|
| Message     | Share <name> is mounted          |
| Category    | External Storage                 |
| Severity    | Information                      |
| Description | Event raised when a share mounts |

#### Event ID: 7804

|             |                                     |
|-------------|-------------------------------------|
| Message     | Share <name> is dismounted          |
| Category    | External Storage                    |
| Severity    | Information                         |
| Description | Event raised when a share dismounts |

#### Event ID: 7805

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | Share <name> mount is aborted                                        |
| Category    | External Storage                                                     |
| Severity    | Error                                                                |
| Description | Event raised when a mount times out or aborts due to a config change |

### Event ID: 7806

|             |                                  |
|-------------|----------------------------------|
| Message     | USB device <status>.             |
| Category    | External Storage                 |
| Severity    | Information                      |
| Description | USB device mounted or unmounted. |



The following are the events related to fan.

#### Event ID: 201

|             |                                                                                               |
|-------------|-----------------------------------------------------------------------------------------------|
| Message     | There are <code>&lt;count&gt;</code> total fans in subsystem <code>&lt;subsystem&gt;</code> . |
| Category    | Fan                                                                                           |
| Severity    | Information                                                                                   |
| Description | Log the total number of fans in the subsystem                                                 |

#### Event ID: 202

|             |                                                                                                                                             |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Subsystem <code>&lt;subsystem&gt;</code> setting fan speed control register to <code>&lt;speedval&gt;</code> : <code>&lt;value&gt;</code> . |
| Category    | Fan                                                                                                                                         |
| Severity    | Information                                                                                                                                 |
| Description | Log the fan speed set                                                                                                                       |

#### Event ID: 203

|             |                                                  |
|-------------|--------------------------------------------------|
| Message     | Air flow direction: <code>&lt;value&gt;</code> . |
| Category    | Fan                                              |
| Severity    | Information                                      |
| Description | Log the air flow direction                       |

#### Event ID: 204 (Severity: Warning)

|             |                                                       |
|-------------|-------------------------------------------------------|
| Message     | Fan tray <code>&lt;FT_Num&gt;</code> was removed.     |
| Category    | Fan                                                   |
| Severity    | Warning                                               |
| Description | Log event when a fan tray is removed from the chassis |

#### Event ID: 205

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | Fan tray <FT_Num> was inserted.                        |
| Category    | Fan                                                    |
| Severity    | Information                                            |
| Description | Log event when a fan tray is inserted into the chassis |

#### Event ID: 206

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | Fan module <FMod_Num> in fan tray <FT_Num> was removed. |
| Category    | Fan                                                     |
| Severity    | Information                                             |
| Description | Log event when a fan module is removed from a fan tray  |

#### Event ID: 207

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | Fan module <FMod_Num> in fan tray <FT_Num> was inserted. |
| Category    | Fan                                                      |
| Severity    | Information                                              |
| Description | Log event when a fan module is inserted into a fan tray  |

#### Event ID: 208

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | Unsupported fan tray <FT_Num> detected. Please insert a standard fan tray. |
| Category    | Fan                                                                        |
| Severity    | Error                                                                      |
| Description | Log event when an unsupported fan tray is inserted                         |

#### Event ID: 209

|             |                                                                                                                       |
|-------------|-----------------------------------------------------------------------------------------------------------------------|
| Message     | Shutting down system now because <num_of_failure> <failure_type> <compare_mode> limit of <num_of_failure_limit>': yes |
| Category    | Fan                                                                                                                   |
| Severity    | Error                                                                                                                 |
| Description | Log error when system shutdown is initiated due to critical fan faults                                                |

#### Event ID: 211 (Severity: Warning)

|             |                                                                                                                                  |
|-------------|----------------------------------------------------------------------------------------------------------------------------------|
| Message     | Shutting down system in <seconds> seconds because <num_of_failure> <failure_type> <compare_mode> limit of <num_of_failure_limit> |
| Category    | Fan                                                                                                                              |
| Severity    | Warning                                                                                                                          |
| Description | Log error when the number of failures exceed the allowable limit                                                                 |

### Event ID: 212 (Severity: Warning)

|             |                                                |
|-------------|------------------------------------------------|
| Message     | System shutdown timer is cancelled.': yes      |
| Category    | Fan                                            |
| Severity    | Warning                                        |
| Description | Log event when the shutdown timer is cancelled |

### Event ID: 213

|             |                                                      |
|-------------|------------------------------------------------------|
| Message     | <num_of_failure> <failure_type> in the system.': yes |
| Category    | Fan                                                  |
| Severity    | Error                                                |
| Description | Log error when there are fan faults                  |

### Event ID: 214

|             |                                                                                         |
|-------------|-----------------------------------------------------------------------------------------|
| Message     | <function>: Fan fault in tray <tray_index>, module <fan_index>, reason: <reason>.': yes |
| Category    | Fan                                                                                     |
| Severity    | Error                                                                                   |
| Description | List out the faulty or missing fan names                                                |

### Event ID: 215

|             |                               |
|-------------|-------------------------------|
| Message     | <FanName> fan is <FanStatus>. |
| Category    | Fan                           |
| Severity    | Information                   |
| Description | Log the fan status            |

### Event ID: 216

|             |                                                                                                |
|-------------|------------------------------------------------------------------------------------------------|
| Message     | Status of fan <FanModuleIdx> in tray <FanTrayIdx> has changed from <OldStatus> to <NewStatus>. |
| Category    | Fan                                                                                            |
| Severity    | Information                                                                                    |
| Description | Log the change in fan status                                                                   |

### Event ID: 217 (Severity: Warning)

|             |                                                                                                |
|-------------|------------------------------------------------------------------------------------------------|
| Message     | Operational fan count below minimum. <FanCount> fans operating, but <FanMinimum> are required. |
| Category    | Fan                                                                                            |
| Severity    | Warning                                                                                        |
| Description | Log when minimum number of fans are not present.                                               |

### Event ID: 218

|             |                                                                                    |
|-------------|------------------------------------------------------------------------------------|
| Message     | Fan speed index for thermal zone <ZoneIdx> is <FanSpdIdxStatus>.                   |
| Category    | Fan                                                                                |
| Severity    | Information                                                                        |
| Description | Log when the fan speed index changes to and from the maximum for each thermal zone |

### Event ID: 219

|             |                                                |
|-------------|------------------------------------------------|
| Message     | Fan tray <FT_Num> powered <Status>.            |
| Category    | Fan                                            |
| Severity    | Information                                    |
| Description | Log event when a fan tray is powered on or off |

### Event ID: 220

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | Fan tray <FT_Num> airflow is <FT_Dir>.                                 |
| Category    | Fan                                                                    |
| Severity    | Information                                                            |
| Description | Log event when a fan tray is inserted specifying its airflow direction |

### Event ID: 221 (Severity: Warning)

|             |                                                                                                                                |
|-------------|--------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;FT_air_curr&gt; airflow fan tray &lt;FT_Num&gt; unsupported; this system requires &lt;FT_air_req&gt; airflow.</code> |
| Category    | Fan                                                                                                                            |
| Severity    | Warning                                                                                                                        |
| Description | Log event when a fan tray airflow is not matching with system airflow                                                          |

### Event ID: 222

|             |                                                                                                                           |
|-------------|---------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;num_of_failure&gt; &lt;failure_type&gt; &lt;compare_mode&gt; limit of &lt;num_of_failure_limit&gt;': yes</code> |
| Category    | Fan                                                                                                                       |
| Severity    | Error                                                                                                                     |
| Description | Log error when number of faulty/supported fans does not meet the allowable limit                                          |

### Event ID: 223 (Severity: Warning)

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | <code>Fan tray &lt;FT_Num&gt; FRU EPPROM is incorrectly programmed.</code> |
| Category    | Fan                                                                        |
| Severity    | Warning                                                                    |
| Description | Log when fan tray SKU ID in FRU is mismatched                              |

### Event ID: 224 (Severity: Warning)

|             |                                                                                                                             |
|-------------|-----------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;FT_air_curr&gt; airflow fan tray &lt;FT_Num&gt; disabled; this system requires &lt;FT_air_req&gt; airflow.</code> |
| Category    | Fan                                                                                                                         |
| Severity    | Warning                                                                                                                     |
| Description | Log event when a fan tray airflow is not matching with system airflow and is disabled                                       |

### Event ID: 225 (Severity: Warning)

|             |                                                                                            |
|-------------|--------------------------------------------------------------------------------------------|
| Message     | <code>fan tray &lt;FT_Num&gt; misconfigured; this fan tray has been &lt;En_Dis&gt;.</code> |
| Category    | Fan                                                                                        |
| Severity    | Warning                                                                                    |
| Description | Log event when a misconfigured fan tray is enabled or disabled                             |

The following are the events related to fault monitor.

#### Event ID: 11101 (Severity: Warning)

|             |                                                      |
|-------------|------------------------------------------------------|
| Message     | Interface <interface>: <fault> fault detected': yes  |
| Category    | Fault monitor                                        |
| Severity    | Warning                                              |
| Description | Logs event when a fault is detected on an interface. |

#### Event ID: 11102 (Severity: Warning)

|             |                                                                                 |
|-------------|---------------------------------------------------------------------------------|
| Message     | Interface <interface>: <fault> fault detected and port disabled': yes           |
| Category    | Fault monitor                                                                   |
| Severity    | Warning                                                                         |
| Description | Logs event and shutdown the interface when a fault is detected on an interface. |

#### Event ID: 11103

|             |                                                                                 |
|-------------|---------------------------------------------------------------------------------|
| Message     | Interface <interface>: <fault> fault re-enable time expired, port enabled': yes |
| Category    | Fault monitor                                                                   |
| Severity    | Information                                                                     |
| Description | Interface is auto-enabled on timer expiry.                                      |

#### Event ID: 11104

|             |                                                                                          |
|-------------|------------------------------------------------------------------------------------------|
| Message     | Interface <interface>: <fault> fault disable cancelled due to configuration change': yes |
| Category    | Fault monitor                                                                            |
| Severity    | Information                                                                              |
| Description | Interface is auto-enabled on profile configuration change.                               |

#### Event ID: 11105

|             |                                                                                   |
|-------------|-----------------------------------------------------------------------------------|
| Message     | Admin state changed and interface: <i>&lt;interface&gt;</i> is auto-enabled': yes |
| Category    | Fault monitor                                                                     |
| Severity    | Information                                                                       |
| Description | Interface is auto-enabled on admin state change.                                  |

### Event ID: 11106 (Severity: Warning)

|             |                                                                                                                            |
|-------------|----------------------------------------------------------------------------------------------------------------------------|
| Message     | Interface <i>&lt;interface&gt;</i> : <i>&lt;fault&gt;</i> fault detected, port is already disabled by another fault.': yes |
| Category    | Fault monitor                                                                                                              |
| Severity    | Warning                                                                                                                    |
| Description | Logs event when disabling of a faulty interface failed.                                                                    |

### Event ID: 11107

|             |                                                                                                           |
|-------------|-----------------------------------------------------------------------------------------------------------|
| Message     | MAC Lockout packet drop detected for <i>&lt;mac&gt;</i> as source address: <i>&lt;sa_diff_count&gt;</i> . |
| Category    | Fault monitor                                                                                             |
| Severity    | Information                                                                                               |
| Description | Logs event when a packet drop is detected for MAC Lockout MAC as source address.                          |

### Event ID: 11108

|             |                                                                                                                |
|-------------|----------------------------------------------------------------------------------------------------------------|
| Message     | MAC Lockout packet drop detected for <i>&lt;mac&gt;</i> as destination address: <i>&lt;da_diff_count&gt;</i> . |
| Category    | Fault monitor                                                                                                  |
| Severity    | Information                                                                                                    |
| Description | Logs event when a packet drop is detected for MAC Lockout MAC as destination address.                          |

### Event ID: 11109

|             |                                                                                                                                                        |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | MAC Lockout packet drop detected for <i>&lt;mac&gt;</i> as source: <i>&lt;sa_diff_count&gt;</i> and destination: <i>&lt;da_diff_count&gt;</i> address. |
| Category    | Fault monitor                                                                                                                                          |
| Severity    | Information                                                                                                                                            |
| Description | Logs event when a packet drop is detected for MAC Lockout.                                                                                             |

The following are the events related to firmware update.

### Event ID: 4401

|             |                                                                                                                                         |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------|
| Message     | User <user>: <image_profile> image updated via <dnld_type> from <host>. Firmware version, Before Update: <before> After Update: <after> |
| Category    | Firmware Update                                                                                                                         |
| Severity    | Information                                                                                                                             |
| Description | Indicates that the switch firmware was succesfully updated from a remote source                                                         |

### Event ID: 4402

|             |                                                                                                                             |
|-------------|-----------------------------------------------------------------------------------------------------------------------------|
| Message     | User <user>: <image_profile> image updated via <dnld_type>. Firmware version, Before Update: <before> After Update: <after> |
| Category    | Firmware Update                                                                                                             |
| Severity    | Information                                                                                                                 |
| Description | Indicates that the switch firmware was succesfully updated from a local source                                              |

### Event ID: 4403

|             |                                                                              |
|-------------|------------------------------------------------------------------------------|
| Message     | User <user>: <image_profile> image update failed via <dnld_type> from <host> |
| Category    | Firmware Update                                                              |
| Severity    | Error                                                                        |
| Description | Indicates that a switch firmware update failed from a remote source          |

### Event ID: 4404

|             |                                                                    |
|-------------|--------------------------------------------------------------------|
| Message     | User <user>: <image_profile> image update failed via <dnld_type>   |
| Category    | Firmware Update                                                    |
| Severity    | Error                                                              |
| Description | Indicates that a switch firmware update failed from a local source |

### Event ID: 4405



|             |                                                                                        |
|-------------|----------------------------------------------------------------------------------------|
| Message     | Firmware image signature not valid                                                     |
| Category    | Firmware Update                                                                        |
| Severity    | Error                                                                                  |
| Description | Indicates that a the signature verification check during switch firmware update failed |

#### Event ID: 4406

|             |                                                                                     |
|-------------|-------------------------------------------------------------------------------------|
| Message     | Firmware image is not compatible with hardware                                      |
| Category    | Firmware Update                                                                     |
| Severity    | Error                                                                               |
| Description | Indicates that firmware image downloaded for update is not compatible with hardware |

#### Event ID: 4407

|             |                                                                  |
|-------------|------------------------------------------------------------------|
| Message     | Firmware image is invalid                                        |
| Category    | Firmware Update                                                  |
| Severity    | Error                                                            |
| Description | Indicates that image downloaded for update is not a switch image |

The following are the events related to hardware health monitor.

### Event ID: 3001

|             |                                                                                                                                                       |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Diagnostic <code>&lt;test_name&gt;</code> failed with error code <code>&lt;error_code&gt;</code> on management module <code>&lt;slot&gt;</code> : yes |
| Category    | Hardware Health Monitor                                                                                                                               |
| Severity    | Error                                                                                                                                                 |
| Description | Event raised when hardware diagnostics detects error in management module                                                                             |

### Event ID: 3002

|             |                                                                                                                                               |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Diagnostic <code>&lt;test_name&gt;</code> failed with error code <code>&lt;error_code&gt;</code> on line card <code>&lt;slot&gt;</code> : yes |
| Category    | Hardware Health Monitor                                                                                                                       |
| Severity    | Error                                                                                                                                         |
| Description | Event raised when hardware diagnostics detects error in line card                                                                             |

### Event ID: 3003

|             |                                                                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Diagnostic <code>&lt;test_name&gt;</code> failed with error code <code>&lt;error_code&gt;</code> on fabric card <code>&lt;slot&gt;</code> : yes |
| Category    | Hardware Health Monitor                                                                                                                         |
| Severity    | Error                                                                                                                                           |
| Description | Event raised when hardware diagnostics detects error in fabric card                                                                             |

### Event ID: 3004

|             |                                                                                                                                              |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Diagnostic <code>&lt;test_name&gt;</code> failed with error code <code>&lt;error_code&gt;</code> on fan tray <code>&lt;slot&gt;</code> : yes |
| Category    | Hardware Health Monitor                                                                                                                      |
| Severity    | Error                                                                                                                                        |
| Description | Event raised when hardware diagnostics detects error in fan tray                                                                             |

**Event ID: 3005**

|             |                                                                                              |
|-------------|----------------------------------------------------------------------------------------------|
| Message     | Diagnostic <test_name> failed with error code <error_code> on rear display card <slot>': yes |
| Category    | Hardware Health Monitor                                                                      |
| Severity    | Error                                                                                        |
| Description | Event raised when hardware diagnostics detects error in rear display card                    |

**Event ID: 3006**

|             |                                                                                 |
|-------------|---------------------------------------------------------------------------------|
| Message     | Diagnostic <test_name> failed with error code <error_code> for the system': yes |
| Category    | Hardware Health Monitor                                                         |
| Severity    | Error                                                                           |
| Description | Event raised when hardware diagnostics detects error in the system              |

**Event ID: 3007 (Severity: Warning)**

|             |                                                  |
|-------------|--------------------------------------------------|
| Message     | There are <origin> happening on <location>': yes |
| Category    | Hardware Health Monitor                          |
| Severity    | Warning                                          |
| Description | Logs MCE BUS error                               |

**Event ID: 3008 (Severity: Warning)**

|             |                                                                              |
|-------------|------------------------------------------------------------------------------|
| Message     | There are IO errors on <location> from <seg>:<bus>:<device>:<function>': yes |
| Category    | Hardware Health Monitor                                                      |
| Severity    | Warning                                                                      |
| Description | Logs MCE IO error                                                            |

**Event ID: 3009**

|             |                                                                                            |
|-------------|--------------------------------------------------------------------------------------------|
| Message     | There are unknown errors on <location> from <status>:<addr>:<misc>:<mcgstatus>:<cap>': yes |
| Category    | Hardware Health Monitor                                                                    |
| Severity    | Information                                                                                |
| Description | Logs MCE unknown error                                                                     |

**Event ID: 3010 (Severity: Warning)**

|             |                                                                                  |
|-------------|----------------------------------------------------------------------------------|
| Message     | CPUs <cpus> L<level> <type> cache error detected. CPUs <offlined> offlined': yes |
| Category    | Hardware Health Monitor                                                          |
| Severity    | Warning                                                                          |
| Description | Logs CPU cache error                                                             |

**Event ID: 3011 (Severity: Warning)**

|             |                                                                                               |
|-------------|-----------------------------------------------------------------------------------------------|
| Message     | Socket <socket> correctable memory error count <cecount> exceeded threshold <threshold>': yes |
| Category    | Hardware Health Monitor                                                                       |
| Severity    | Warning                                                                                       |
| Description | Log when socket correctable memory error count is exceeded threshold                          |

**Event ID: 3012 (Severity: Warning)**

|             |                                                                                                |
|-------------|------------------------------------------------------------------------------------------------|
| Message     | Module <channel> correctable memory error count <cecount> exceeded threshold <threshold>': yes |
| Category    | Hardware Health Monitor                                                                        |
| Severity    | Warning                                                                                        |
| Description | Log when module correctable memory error count is exceeded threshold                           |

**Event ID: 3013 (Severity: Warning)**

|             |                                                                                                          |
|-------------|----------------------------------------------------------------------------------------------------------|
| Message     | Page <page> correctable memory error count <cecount> exceeded threshold <threshold> and <offlined>': yes |
| Category    | Hardware Health Monitor                                                                                  |
| Severity    | Warning                                                                                                  |
| Description | Log when page correctable memory error count is exceeded threshold                                       |

The following are the events related to HTTPS server.

### Event ID: 5601

|             |                                                                                    |
|-------------|------------------------------------------------------------------------------------|
| Message     | User <code>&lt;user&gt;</code> has enabled <code>&lt;mode&gt;</code> for REST mode |
| Category    | HTTPS Server                                                                       |
| Severity    | Information                                                                        |
| Description | Logs a message when a user changes the status of the REST mode                     |

### Event ID: 5602

|             |                                                                                                             |
|-------------|-------------------------------------------------------------------------------------------------------------|
| Message     | User <code>&lt;user&gt;</code> has <code>&lt;status&gt;</code> HTTPS Server on VRF <code>&lt;vrf&gt;</code> |
| Category    | HTTPS Server                                                                                                |
| Severity    | Information                                                                                                 |
| Description | Logs a message when a user enables/disables the https-server VRF configuration                              |

### Event ID: 5603

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | User <code>&lt;user&gt;</code> closed all HTTPS sessions |
| Category    | HTTPS Server                                             |
| Severity    | Information                                              |
| Description | Logs a message when a user closes all HTTPS sessions     |

### Event ID: 5604

|             |                                                                                                                   |
|-------------|-------------------------------------------------------------------------------------------------------------------|
| Message     | User <code>&lt;user&gt;</code> changed the HTTPS Server max user sessions amount to <code>&lt;sessions&gt;</code> |
| Category    | HTTPS Server                                                                                                      |
| Severity    | Information                                                                                                       |
| Description | Logs a message when a user changes the maximum amount of sessions per user                                        |

### Event ID: 5605

|             |                                                                          |
|-------------|--------------------------------------------------------------------------|
| Message     | User <user> changed the HTTPS Server idle timeout to <timeout>           |
| Category    | HTTPS Server                                                             |
| Severity    | Information                                                              |
| Description | Logs a message when a user changes the value of the session idle timeout |

The following are the events related to in-system programming.

### Event ID: 7200

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | Internal fatal error at <code>&lt;file&gt;:&lt;line&gt;</code> |
| Category    | In-System Programming                                          |
| Severity    | Error                                                          |
| Description | ISP internal fatal error                                       |

### Event ID: 7210

|             |                                                                                                                        |
|-------------|------------------------------------------------------------------------------------------------------------------------|
| Message     | Non-failsafe update needed for <code>&lt;devspec&gt;</code> . Please run the <code>allow-unsafe-updates</code> command |
| Category    | In-System Programming                                                                                                  |
| Severity    | Error                                                                                                                  |
| Description | A non-failsafe device update is needed, but the <code>allow-unsafe-updates</code> command has not yet been run         |

### Event ID: 7211

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | Do not interrupt non-failsafe update for <code>&lt;devspec&gt;</code>  |
| Category    | In-System Programming                                                  |
| Severity    | Error                                                                  |
| Description | A non-failsafe device update is about to start, so do not interrupt it |

### Event ID: 7212

|             |                                                                                                                                  |
|-------------|----------------------------------------------------------------------------------------------------------------------------------|
| Message     | Starting update for <code>&lt;devspec&gt;</code> from version <code>&lt;fromver&gt;</code> to version <code>&lt;tover&gt;</code> |
| Category    | In-System Programming                                                                                                            |
| Severity    | Information                                                                                                                      |
| Description | A device update is about to start                                                                                                |

### Event ID: 7213

|             |                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------|
| Message     | Update successful for <devspec> from version <fromver> to version <tover>                       |
| Category    | In-System Programming                                                                           |
| Severity    | Information                                                                                     |
| Description | A device update was successful or in some cases was successfully arranged to be performed later |

#### Event ID: 7214 (Severity: Critical)

|             |                             |
|-------------|-----------------------------|
| Message     | Update failed for <devspec> |
| Category    | In-System Programming       |
| Severity    | Critical                    |
| Description | A device update failed      |

#### Event ID: 7215

|             |                                                                                 |
|-------------|---------------------------------------------------------------------------------|
| Message     | Deferred update for <devspec> will be performed after an automatic module reset |
| Category    | In-System Programming                                                           |
| Severity    | Information                                                                     |
| Description | A device update was postponed until after an automatic reset of its module      |

#### Event ID: 7216

|             |                                                                                     |
|-------------|-------------------------------------------------------------------------------------|
| Message     | Approximately <time> minute(s) remaining to update <numdevs> device(s) on <modspec> |
| Category    | In-System Programming                                                               |
| Severity    | Information                                                                         |
| Description | Indicates the approximate remaining update time for a module                        |

#### Event ID: 7217

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | Insufficient redundant power is available to update <devspec> |
| Category    | In-System Programming                                         |
| Severity    | Information                                                   |
| Description | Unable to update non-redundant power supply                   |

#### Event ID: 7218



|             |                                                                                                                                                                   |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Programmable device updates are pending that require a power cycle. Wait for all fabric and line modules to be ready, then power the system off and back on again |
| Category    | In-System Programming                                                                                                                                             |
| Severity    | Information                                                                                                                                                       |
| Description | ISP needs the chassis power-cycled manually when it cannot be done automatically                                                                                  |

### Event ID: 7219 (Severity: Critical)

|             |                                                 |
|-------------|-------------------------------------------------|
| Message     | Failed to write-protect <devspec> (pass <pass>) |
| Category    | In-System Programming                           |
| Severity    | Critical                                        |
| Description | Failed to write-protect a module or device      |

The following are the events related to interface.

### Event ID: 401

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | Interface port_admin set to up for <interface> interface |
| Category    | Interface                                                |
| Severity    | Information                                              |
| Description | Log when interface port_admin set to up                  |

### Event ID: 402

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | Interface port_admin set to down for <interface> interface |
| Category    | Interface                                                  |
| Severity    | Information                                                |
| Description | Log when interface port_admin set to down                  |

### Event ID: 403

|             |                                                   |
|-------------|---------------------------------------------------|
| Message     | Link status for interface <interface> is up': yes |
| Category    | Interface                                         |
| Severity    | Information                                       |
| Description | Log when interface link status is up              |

### Event ID: 404

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | Link status for interface <interface> is <state>': yes |
| Category    | Interface                                              |
| Severity    | Information                                            |
| Description | Log when interface link status is down                 |

### Event ID: 405

|          |                         |
|----------|-------------------------|
| Message  | Reserved for future use |
| Category | Interface               |
| Severity | Error                   |

### Event ID: 406

|             |                                                                                                |
|-------------|------------------------------------------------------------------------------------------------|
| Message     | Interface <code>&lt;interface&gt;</code> encountered a hardware error that caused a link reset |
| Category    | Interface                                                                                      |
| Severity    | Information                                                                                    |
| Description | Log when interface encountered an error that requires user intervention                        |

### Event ID: 407

|             |                                                                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Interface <code>&lt;interface&gt;</code> downshifted to speed <code>&lt;port_speed&gt;</code> Mbps because link attempt failed at higher speed. |
| Category    | Interface                                                                                                                                       |
| Severity    | Information                                                                                                                                     |
| Description | Log when interface encountered a downshift                                                                                                      |

### Event ID: 408 (Severity: Warning)

|             |                                                                                                          |
|-------------|----------------------------------------------------------------------------------------------------------|
| Message     | Interface <code>&lt;interface&gt;</code> is down because MACsec and PFC features are mutually exclusive. |
| Category    | Interface                                                                                                |
| Severity    | Warning                                                                                                  |
| Description | Log when interface is down due to incompatible MACsec and PFC configuration                              |

The following are the events related to internal storage.

### Event ID: 9101

|             |                                                                                       |
|-------------|---------------------------------------------------------------------------------------|
| Message     | Failed to report storage <name> details for module <module_num>. Error: <error>': yes |
| Category    | Internal storage                                                                      |
| Severity    | Error                                                                                 |
| Description | Event raised when there is a storage reporting failure                                |

### Event ID: 9102

|             |                                                                                             |
|-------------|---------------------------------------------------------------------------------------------|
| Message     | Storage <name> health alert. Endurance utilization at <usage>% in module <module_num>': yes |
| Category    | Internal storage                                                                            |
| Severity    | Information                                                                                 |
| Description | Event raised when the storage health deteriorates                                           |

### Event ID: 9103

|             |                                                                               |
|-------------|-------------------------------------------------------------------------------|
| Message     | Storage <name> endurance utilization at <usage>% in module <module_num>': yes |
| Category    | Internal storage                                                              |
| Severity    | Information                                                                   |
| Description | Event raised when there is a change in storage endurance                      |

### Event ID: 9104

|             |                                                                                                                                      |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Storage <name> health alert. Endurance utilization at <usage>% in module <module_num>. Failure is imminent. Please backup data': yes |
| Category    | Internal storage                                                                                                                     |
| Severity    | Error                                                                                                                                |
| Description | Event raised when storage failure is imminent                                                                                        |

The following are the events related to IP source lockdown.

### Event ID: 9801 (Severity: Warning)

|             |                                                                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | IP_SOURCE_LOCKDOWN resource utilization has reached 80 percent of the supported limit of <code>&lt;max_supported_limit&gt;</code> on the system |
| Category    | IP source lockdown                                                                                                                              |
| Severity    | Warning                                                                                                                                         |
| Description | This log event informs the user that IP_SOURCE_LOCKDOWN resource utilization has reached 80 percent of the supported limits                     |

### Event ID: 9802 (Severity: Critical)

|             |                                                                                                                                                                                                        |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | IP_SOURCE_LOCKDOWN resource utilization has exceeded maximum supported limit of <code>&lt;max_supported_limit&gt;</code> on the system. IP source-lockdown functionality will not work for new entries |
| Category    | IP source lockdown                                                                                                                                                                                     |
| Severity    | Critical                                                                                                                                                                                               |
| Description | This log event informs the user that IP_SOURCE_LOCKDOWN resource utilization has exceeded the supported limits                                                                                         |

### Event ID: 9803

|             |                                                                                                                                                       |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | IP_SOURCE_LOCKDOWN resource utilization has reduced below 80 percent of the supported limit of <code>&lt;max_supported_limit&gt;</code> on the system |
| Category    | IP source lockdown                                                                                                                                    |
| Severity    | Information                                                                                                                                           |
| Description | This log event informs the user that IP_SOURCE_LOCKDOWN resource utilization has reduced below 80 percent of the supported limits                     |

### Event ID: 9804

|          |                                                                             |
|----------|-----------------------------------------------------------------------------|
| Message  | IPV4_SOURCE_LOCKDOWN is enabled on interface <code>&lt;interface&gt;</code> |
| Category | IP source lockdown                                                          |

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Severity    | Information                                                    |
| Description | Log event when IPV4_SOURCE_LOCKDOWN is enabled on an interface |

### Event ID: 9805

|             |                                                                 |
|-------------|-----------------------------------------------------------------|
| Message     | IPV4_SOURCE_LOCKDOWN is disabled on interface <interface>       |
| Category    | IP source lockdown                                              |
| Severity    | Information                                                     |
| Description | Log event when IPV4_SOURCE_LOCKDOWN is disabled on an interface |

### Event ID: 9806

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | IPV6_SOURCE_LOCKDOWN is enabled on interface <interface>       |
| Category    | IP source lockdown                                             |
| Severity    | Information                                                    |
| Description | Log event when IPV6_SOURCE_LOCKDOWN is enabled on an interface |

### Event ID: 9807

|             |                                                                 |
|-------------|-----------------------------------------------------------------|
| Message     | IPV6_SOURCE_LOCKDOWN is disabled on interface <interface>       |
| Category    | IP source lockdown                                              |
| Severity    | Information                                                     |
| Description | Log event when IPV6_SOURCE_LOCKDOWN is disabled on an interface |

The following are the events related to IP tunnels.

### Event ID: 9601

|             |                                                                                                                  |
|-------------|------------------------------------------------------------------------------------------------------------------|
| Message     | Tunnel Creation Failed - Name (<tunnel_name>) Type (<type>) VRF (<vrf>) Local IP (<src_ip>) Remote IP (<dst_ip>) |
| Category    | IP tunnels                                                                                                       |
| Severity    | Error                                                                                                            |
| Description | Event raised when tunnel creation fails                                                                          |

### Event ID: 9602

|             |                                                                                                          |
|-------------|----------------------------------------------------------------------------------------------------------|
| Message     | Tunnel Created - Name (<tunnel_name>) Type (<type>) VRF (<vrf>) Local IP (<src_ip>) Remote IP (<dst_ip>) |
| Category    | IP tunnels                                                                                               |
| Severity    | Information                                                                                              |
| Description | Event raised when tunnel created                                                                         |

### Event ID: 9603

|             |                                                                                                                  |
|-------------|------------------------------------------------------------------------------------------------------------------|
| Message     | Tunnel Deletion Failed - Name (<tunnel_name>) Type (<type>) VRF (<vrf>) Local IP (<src_ip>) Remote IP (<dst_ip>) |
| Category    | IP tunnels                                                                                                       |
| Severity    | Error                                                                                                            |
| Description | Event raised when tunnel deletion failed                                                                         |

### Event ID: 9604

|             |                                                                                                          |
|-------------|----------------------------------------------------------------------------------------------------------|
| Message     | Tunnel Deleted - Name (<tunnel_name>) Type (<type>) VRF (<vrf>) Local IP (<src_ip>) Remote IP (<dst_ip>) |
| Category    | IP tunnels                                                                                               |
| Severity    | Information                                                                                              |
| Description | Event raised when tunnel deleted                                                                         |

**Event ID: 9605**

|             |                                                                                                                                  |
|-------------|----------------------------------------------------------------------------------------------------------------------------------|
| Message     | Tunnel Modification Failed - Name (<tunnel_name>) Type (<type>) VRF (<vrf>) Local IP (<src_ip>) Remote IP (<dst_ip>) TTL (<ttl>) |
| Category    | IP tunnels                                                                                                                       |
| Severity    | Error                                                                                                                            |
| Description | Event raised when tunnel modification failed                                                                                     |

**Event ID: 9606**

|             |                                                                                                                     |
|-------------|---------------------------------------------------------------------------------------------------------------------|
| Message     | Tunnel Source IP Modified - Name (<tunnel_name>) Type (<type>) VRF (<vrf>) Local IP (<src_ip>) Remote IP (<dst_ip>) |
| Category    | IP tunnels                                                                                                          |
| Severity    | Information                                                                                                         |
| Description | Event raised when tunnel source ip modified                                                                         |

**Event ID: 9607**

|             |                                                                                                                          |
|-------------|--------------------------------------------------------------------------------------------------------------------------|
| Message     | Tunnel Destination IP Modified - Name (<tunnel_name>) Type (<type>) VRF (<vrf>) Local IP (<src_ip>) Remote IP (<dst_ip>) |
| Category    | IP tunnels                                                                                                               |
| Severity    | Information                                                                                                              |
| Description | Event raised when tunnel destination ip modified                                                                         |

**Event ID: 9608**

|             |                                                                                                                           |
|-------------|---------------------------------------------------------------------------------------------------------------------------|
| Message     | Tunnel TTL Modified - Name (<tunnel_name>) Type (<type>) VRF (<vrf>) Local IP (<src_ip>) Remote IP (<dst_ip>) TTL (<ttl>) |
| Category    | IP tunnels                                                                                                                |
| Severity    | Information                                                                                                               |
| Description | Event raised when tunnel TTL modified                                                                                     |

**Event ID: 9609**

|             |                                                                                                                                         |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Tunnel MTU Modification Failed - Name (<tunnel_name>) Type (<type>) VRF (<vrf>) Local IP (<src_ip>) Remote IP (<dst_ip>) MTU (<ip_mtu>) |
| Category    | IP tunnels                                                                                                                              |
| Severity    | Error                                                                                                                                   |
| Description | Event raised when tunnel mtu modification failed                                                                                        |



**Event ID: 9610**

|             |                                                                                                                              |
|-------------|------------------------------------------------------------------------------------------------------------------------------|
| Message     | Tunnel MTU Modified - Name (<tunnel_name>) Type (<type>) VRF (<vrf>) Local IP (<src_ip>) Remote IP (<dst_ip>) MTU (<ip_mtu>) |
| Category    | IP tunnels                                                                                                                   |
| Severity    | Information                                                                                                                  |
| Description | Event raised when tunnel mtu modified                                                                                        |

**Event ID: 9611**

|             |                                                                                                                     |
|-------------|---------------------------------------------------------------------------------------------------------------------|
| Message     | Tunnel Nexthop Add Failed - Name (<tunnel_name>) Type (<type>) VRF (<vrf>) Local IP (<src_ip>) Remote IP (<dst_ip>) |
| Category    | IP tunnels                                                                                                          |
| Severity    | Error                                                                                                               |
| Description | Event raised when tunnel nexthop add failed                                                                         |

**Event ID: 9612**

|             |                                                                                                                |
|-------------|----------------------------------------------------------------------------------------------------------------|
| Message     | Tunnel Nexthop Added - Name (<tunnel_name>) Type (<type>) VRF (<vrf>) Local IP (<src_ip>) Remote IP (<dst_ip>) |
| Category    | IP tunnels                                                                                                     |
| Severity    | Information                                                                                                    |
| Description | Event raised when tunnel nexthop gets added                                                                    |

**Event ID: 9613**

|             |                                                                                                                        |
|-------------|------------------------------------------------------------------------------------------------------------------------|
| Message     | Tunnel Nexthop Modify Failed - Name (<tunnel_name>) Type (<type>) VRF (<vrf>) Local IP (<src_ip>) Remote IP (<dst_ip>) |
| Category    | IP tunnels                                                                                                             |
| Severity    | Error                                                                                                                  |
| Description | Event raised when tunnel nexthop modify failed                                                                         |

**Event ID: 9614**

|             |                                                                                                                   |
|-------------|-------------------------------------------------------------------------------------------------------------------|
| Message     | Tunnel Nexthop Modified - Name (<tunnel_name>) Type (<type>) VRF (<vrf>) Local IP (<src_ip>) Remote IP (<dst_ip>) |
| Category    | IP tunnels                                                                                                        |
| Severity    | Information                                                                                                       |
| Description | Event raised when tunnel nexthop gets modified                                                                    |

**Event ID: 9615**

|             |                                                                                                                                  |
|-------------|----------------------------------------------------------------------------------------------------------------------------------|
| Message     | Tunnel Nexthop Delete Failed - Name (< tunnel_name >) Type (< type >) VRF (< vrf >) Local IP (< src_ip >) Remote IP (< dst_ip >) |
| Category    | IP tunnels                                                                                                                       |
| Severity    | Error                                                                                                                            |
| Description | Event raised when tunnel nexthop delete failed                                                                                   |

**Event ID: 9616**

|             |                                                                                                                            |
|-------------|----------------------------------------------------------------------------------------------------------------------------|
| Message     | Tunnel Nexthop Deleted - Name (< tunnel_name >) Type (< type >) VRF (< vrf >) Local IP (< src_ip >) Remote IP (< dst_ip >) |
| Category    | IP tunnels                                                                                                                 |
| Severity    | Information                                                                                                                |
| Description | Event raised when tunnel nexthop gets deleted                                                                              |

The following are the events related to IP-SLA.

### Event ID: 7401

|             |                                                                              |
|-------------|------------------------------------------------------------------------------|
| Message     | IP-SLA session:<name> state changed to failed <state> due to reason <reason> |
| Category    | IP-SLA                                                                       |
| Severity    | Error                                                                        |
| Description | Event raised when an IP-SLA session state is changed to any failed state     |

### Event ID: 7402

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | IP-SLA session:<name> state changed to <state> due to reason <reason>  |
| Category    | IP-SLA                                                                 |
| Severity    | Information                                                            |
| Description | Event raised when an IP-SLA session state is changed to any info state |

### Event ID: 7403

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | IP-SLA <name>: <operation>                              |
| Category    | IP-SLA                                                  |
| Severity    | Information                                             |
| Description | Event raised when an IP-SLA session is added or deleted |

### Event ID: 7404

|             |                                                      |
|-------------|------------------------------------------------------|
| Message     | IP-SLA session:<name> is incomplete to schedule      |
| Category    | IP-SLA                                               |
| Severity    | Error                                                |
| Description | Event raised when an IP-SLA incomple config is added |

### Event ID: 7405

|             |                                                                                   |
|-------------|-----------------------------------------------------------------------------------|
| Message     | IP-SLA session:<name> interface <interface> is not ready and SLA is disabled      |
| Category    | IP-SLA                                                                            |
| Severity    | Error                                                                             |
| Description | Event raised when an IP-SLA session stopped due to source IP or interface changes |

#### Event ID: 7406

|             |                                                                                   |
|-------------|-----------------------------------------------------------------------------------|
| Message     | IP-SLA session:<name> interface <interface> is ready and SLA is enabled           |
| Category    | IP-SLA                                                                            |
| Severity    | Error                                                                             |
| Description | Event raised when an IP-SLA session started due to source IP or interface changes |

#### Event ID: 7407

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | IP-SLA session:<name> failed to bind source, reason:<reason> |
| Category    | IP-SLA                                                       |
| Severity    | Error                                                        |
| Description | Event raised when an IP-SLA session failed to bind source    |

#### Event ID: 7408

|             |                                                                    |
|-------------|--------------------------------------------------------------------|
| Message     | IP-SLA session:<name> failed to initialize socket, reason:<reason> |
| Category    | IP-SLA                                                             |
| Severity    | Error                                                              |
| Description | Event raised when an IP-SLA session failed to initialize socket    |

The following are the events related to IPv6 router advertisement.

### Event ID: 3901

|             |                                                   |
|-------------|---------------------------------------------------|
| Message     | ipv6 ra enabled on interface: <i>&lt;intf&gt;</i> |
| Category    | IPv6 Router Advertisement                         |
| Severity    | Information                                       |
| Description | Event raised when ipv6 ra enabled                 |

### Event ID: 3902

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | ipv6 ra disabled on interface: <i>&lt;intf&gt;</i> |
| Category    | IPv6 Router Advertisement                          |
| Severity    | Information                                        |
| Description | Event raised when ipv6 ra disabled                 |

### Event ID: 3903

|             |                                                                              |
|-------------|------------------------------------------------------------------------------|
| Message     | Disabled sending MTU in Router-Advertisement messages on <i>&lt;intf&gt;</i> |
| Category    | IPv6 Router Advertisement                                                    |
| Severity    | Information                                                                  |
| Description | Event raised when ipv6 ra suppress mtu is configured                         |

### Event ID: 3904

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | Enabled sending MTU in Router-Advertisement messages on <i>&lt;intf&gt;</i> |
| Category    | IPv6 Router Advertisement                                                   |
| Severity    | Information                                                                 |
| Description | Event raised when ipv6 ra suppress mtu configured                           |

### Event ID: 3905

|             |                                                                                |
|-------------|--------------------------------------------------------------------------------|
| Message     | Disabled sending RDNSS in Router-Advertisement messages on <i>&lt;intf&gt;</i> |
| Category    | IPv6 Router Advertisement                                                      |
| Severity    | Information                                                                    |
| Description | Event raised when ipv6 ra suppress rdns is configured                          |

#### Event ID: 3906

|             |                                                                               |
|-------------|-------------------------------------------------------------------------------|
| Message     | Enabled sending RDNSS in Router-Advertisement messages on <i>&lt;intf&gt;</i> |
| Category    | IPv6 Router Advertisement                                                     |
| Severity    | Information                                                                   |
| Description | Event raised when ipv6 ra suppress rdns is removed                            |

#### Event ID: 3907

|             |                                                                                |
|-------------|--------------------------------------------------------------------------------|
| Message     | Disabled sending DNSSL in Router-Advertisement messages on <i>&lt;intf&gt;</i> |
| Category    | IPv6 Router Advertisement                                                      |
| Severity    | Information                                                                    |
| Description | Event raised when ipv6 ra suppress dnss is configured                          |

#### Event ID: 3908

|             |                                                                               |
|-------------|-------------------------------------------------------------------------------|
| Message     | Enabled sending DNSSL in Router-Advertisement messages on <i>&lt;intf&gt;</i> |
| Category    | IPv6 Router Advertisement                                                     |
| Severity    | Information                                                                   |
| Description | Event raised when ipv6 ra suppress dnss is removed                            |

#### Event ID: 3909

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | Interface: <i>&lt;intf&gt;</i> is added to router discovery |
| Category    | IPv6 Router Advertisement                                   |
| Severity    | Information                                                 |
| Description | Event raised when ipv6 ra interface is added                |

#### Event ID: 3910

|         |                                                                 |
|---------|-----------------------------------------------------------------|
| Message | Interface: <i>&lt;intf&gt;</i> is deleted from router discovery |
|---------|-----------------------------------------------------------------|

|             |                                                |
|-------------|------------------------------------------------|
| Category    | IPv6 Router Advertisement                      |
| Severity    | Information                                    |
| Description | Event raised when ipv6 ra interface is deleted |

#### Event ID: 3911

|             |                                                                                                             |
|-------------|-------------------------------------------------------------------------------------------------------------|
| Message     | Added ipv6 prefix: <code>&lt;ipv6_addr&gt;/&lt;prefixlen&gt;</code> on interface: <code>&lt;intf&gt;</code> |
| Category    | IPv6 Router Advertisement                                                                                   |
| Severity    | Information                                                                                                 |
| Description | Event raised when ipv6 address is added on interface                                                        |

#### Event ID: 3912

|             |                                                                                                                 |
|-------------|-----------------------------------------------------------------------------------------------------------------|
| Message     | Deleted ipv6 prefix: <code>&lt;ipv6_addr&gt;/&lt;prefixlen&gt;</code> from interface: <code>&lt;intf&gt;</code> |
| Category    | IPv6 Router Advertisement                                                                                       |
| Severity    | Information                                                                                                     |
| Description | Event raised when ipv6 address is deleted from interface                                                        |

#### Event ID: 3913

|             |                                                                                                     |
|-------------|-----------------------------------------------------------------------------------------------------|
| Message     | Added RA Prefix: <code>&lt;prefix&gt;</code> on interface: <code>&lt;intf&gt;</code> to prefix list |
| Category    | IPv6 Router Advertisement                                                                           |
| Severity    | Information                                                                                         |
| Description | Event raised when RA Prefix is added on interface                                                   |

#### Event ID: 3914

|             |                                                                                                         |
|-------------|---------------------------------------------------------------------------------------------------------|
| Message     | Deleted RA Prefix: <code>&lt;prefix&gt;</code> on interface: <code>&lt;intf&gt;</code> from prefix list |
| Category    | IPv6 Router Advertisement                                                                               |
| Severity    | Information                                                                                             |
| Description | Event raised when RA Prefix is deleted from interface                                                   |

#### Event ID: 3915

|          |                                                                     |
|----------|---------------------------------------------------------------------|
| Message  | default prefix is configured on interface <code>&lt;intf&gt;</code> |
| Category | IPv6 Router Advertisement                                           |

|             |                                                |
|-------------|------------------------------------------------|
| Severity    | Information                                    |
| Description | Event raised when default prefix is configured |

### Event ID: 3916

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | RDNSS is added on interface: <code>&lt;intf&gt;</code> |
| Category    | IPv6 Router Advertisement                              |
| Severity    | Information                                            |
| Description | Event raised when RDNSS is added                       |

### Event ID: 3917

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | RDNSS is deleted on interface: <code>&lt;intf&gt;</code> |
| Category    | IPv6 Router Advertisement                                |
| Severity    | Information                                              |
| Description | Event raised when RDNSS is deleted                       |

### Event ID: 3918

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | DNSSL is added on interface: <code>&lt;intf&gt;</code> |
| Category    | IPv6 Router Advertisement                              |
| Severity    | Information                                            |
| Description | Event raised when DNSSL is added                       |

### Event ID: 3919

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | DNSSL is deleted on interface: <code>&lt;intf&gt;</code> |
| Category    | IPv6 Router Advertisement                                |
| Severity    | Information                                              |
| Description | Event raised when DNSSL is deleted                       |



The following are the events related to IRDP.

#### Event ID: 3501

|             |                                                                                      |
|-------------|--------------------------------------------------------------------------------------|
| Message     | IRDP enabled on interface <i>&lt;interface&gt;</i>                                   |
| Category    | IRDP                                                                                 |
| Severity    | Information                                                                          |
| Description | This command enables the IRDP (ICMP Router Discovery Protocol) feature on interface. |

#### Event ID: 3502

|             |                                                                                       |
|-------------|---------------------------------------------------------------------------------------|
| Message     | IRDP disabled on interface <i>&lt;interface&gt;</i>                                   |
| Category    | IRDP                                                                                  |
| Severity    | Information                                                                           |
| Description | This command disables the IRDP (ICMP Router Discovery Protocol) feature on interface. |

The following are the events related to job scheduler.

#### Event ID: 12201

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | Creating schedule <name>, trigger time(s): <start_datetime><details> |
| Category    | Job scheduler                                                        |
| Severity    | Information                                                          |
| Description | Event reported when a schedule is created                            |

#### Event ID: 12202

|             |                                                           |
|-------------|-----------------------------------------------------------|
| Message     | Schedule <name> triggered, trigger_count: <trigger_count> |
| Category    | Job scheduler                                             |
| Severity    | Information                                               |
| Description | Event reported when a schedule triggers                   |

#### Event ID: 12203

|             |                                                                                           |
|-------------|-------------------------------------------------------------------------------------------|
| Message     | Timezone changed. Re-creating schedule <name>, trigger time(s): <start_datetime><details> |
| Category    | Job scheduler                                                                             |
| Severity    | Information                                                                               |
| Description | Event reported when the schedules are recreated due to timezone change.                   |

The following are the events related to L3 Encap capacity.

### Event ID: 10601 (Severity: Warning)

|             |                                                                                                                                                            |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | L3 resources critical for neighbor and route forwarding are low. Used: <code>&lt;encaps_allocated&gt;</code> , Available: <code>&lt;encaps_free&gt;</code> |
| Category    | L3 Encap capacity                                                                                                                                          |
| Severity    | Warning                                                                                                                                                    |
| Description | L3 resources needed for neighbor and route forwarding are running low. Large-scale neighbor moves could cause traffic loss.                                |

### Event ID: 10602

|             |                                                                                                                                                                       |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | L3 resources critical for neighbor and route forwarding are at safe levels. Used: <code>&lt;encaps_allocated&gt;</code> , Available: <code>&lt;encaps_free&gt;</code> |
| Category    | L3 Encap capacity                                                                                                                                                     |
| Severity    | Information                                                                                                                                                           |
| Description | L3 resources needed for neighbor and route forwarding are back to a safe level.                                                                                       |

### Event ID: 10603

|             |                                                                                                                                                           |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Out of L3 resources critical for neighbor and route forwarding. Used: <code>&lt;encaps_allocated&gt;</code> , Available: <code>&lt;encaps_free&gt;</code> |
| Category    | L3 Encap capacity                                                                                                                                         |
| Severity    | Error                                                                                                                                                     |
| Description | L3 resources needed for neighbor and route forwarding have run out. Traffic loss is imminent.                                                             |

The following are the events related to L3 Resource Manager.

#### Event ID: 11501 (Severity: Warning)

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | IPv6 route prefix <prefix> is not supported on this platform. |
| Category    | L3 Resource Manager                                           |
| Severity    | Warning                                                       |
| Description | logs warning for route addition attempt.                      |

#### Event ID: 11502

|             |                                                                                                                                  |
|-------------|----------------------------------------------------------------------------------------------------------------------------------|
| Message     | "Exceeded resource '<resource>' capacity adding <object>. Use 'show capacities-status' for more information." throttle_count: 40 |
| Category    | L3 Resource Manager                                                                                                              |
| Severity    | Error                                                                                                                            |
| Description | logs error for running out of resources.                                                                                         |

#### Event ID: 11503 (Severity: Warning)

|             |                                                                                                                                   |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------|
| Message     | "Resource '<resource>' usage is at <percent>% of capacity. Use 'show capacities-status' for more information." throttle_count: 40 |
| Category    | L3 Resource Manager                                                                                                               |
| Severity    | Warning                                                                                                                           |
| Description | logs warning for hitting certain capacity limits.                                                                                 |

The following are the events related to LACP.

#### Event ID: 1301

|             |                              |
|-------------|------------------------------|
| Message     | Dynamic LAG <lag_id> created |
| Category    | LACP                         |
| Severity    | Information                  |
| Description | Dynamic LAG has been created |

#### Event ID: 1302

|             |                              |
|-------------|------------------------------|
| Message     | Dynamic LAG <lag_id> deleted |
| Category    | LACP                         |
| Severity    | Information                  |
| Description | Dynamic LAG has been deleted |

#### Event ID: 1303

|             |                                                                                                           |
|-------------|-----------------------------------------------------------------------------------------------------------|
| Message     | Interface <intf_id> added to LAG <lag_id>. Existing configuration on interface <intf_id> will be removed. |
| Category    | LACP                                                                                                      |
| Severity    | Information                                                                                               |
| Description | Log when interface has been added to LAG                                                                  |

#### Event ID: 1304

|             |                                                                                                                 |
|-------------|-----------------------------------------------------------------------------------------------------------------|
| Message     | Interface <intf_id> removed from LAG <lag_id>. It will be set with default configuration with admin down state. |
| Category    | LACP                                                                                                            |
| Severity    | Information                                                                                                     |
| Description | Log when interface has been removed from LAG                                                                    |

#### Event ID: 1305

|             |                                                                  |
|-------------|------------------------------------------------------------------|
| Message     | LACP system priority set to <code>&lt;system_priority&gt;</code> |
| Category    | LACP                                                             |
| Severity    | Information                                                      |
| Description | Log when LACP system priority is set                             |

#### Event ID: 1306

|             |                                                                                     |
|-------------|-------------------------------------------------------------------------------------|
| Message     | LACP mode set to <code>&lt;lacp_mode&gt;</code> for LAG <code>&lt;lag_id&gt;</code> |
| Category    | LACP                                                                                |
| Severity    | Information                                                                         |
| Description | Log when LACP mode is set                                                           |

#### Event ID: 1307

|             |                                                      |
|-------------|------------------------------------------------------|
| Message     | LACP system ID set to <code>&lt;system_id&gt;</code> |
| Category    | LACP                                                 |
| Severity    | Information                                          |
| Description | Log when LACP system ID is set                       |

#### Event ID: 1308

|             |                                                                                     |
|-------------|-------------------------------------------------------------------------------------|
| Message     | LACP rate set to <code>&lt;lacp_rate&gt;</code> for LAG <code>&lt;lag_id&gt;</code> |
| Category    | LACP                                                                                |
| Severity    | Information                                                                         |
| Description | Log when LACP rate is set                                                           |

#### Event ID: 1309

|             |                                                                                                                                                                                                                                         |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Partner is detected for interface <code>&lt;intf_id&gt;</code> LAG <code>&lt;lag_id&gt;</code> : <code>&lt;partner_sys_id&gt;</code> . Actor state: <code>&lt;actor_state&gt;</code> , partner state <code>&lt;partner_state&gt;</code> |
| Category    | LACP                                                                                                                                                                                                                                    |
| Severity    | Information                                                                                                                                                                                                                             |
| Description | Log when LACP partner is detected                                                                                                                                                                                                       |

#### Event ID: 1310 (Severity: Warning)

|         |                                                                                                           |
|---------|-----------------------------------------------------------------------------------------------------------|
| Message | Partner is out of sync for interface <code>&lt;intf_id&gt;</code> LAG <code>&lt;lag_id&gt;</code> . Actor |
|---------|-----------------------------------------------------------------------------------------------------------|

|             |                                                                                            |
|-------------|--------------------------------------------------------------------------------------------|
|             | state: <code>&lt;actor_state&gt;</code> , partner state <code>&lt;partner_state&gt;</code> |
| Category    | LACP                                                                                       |
| Severity    | Warning                                                                                    |
| Description | Log when LACP parter is out of sync                                                        |

### Event ID: 1311 (Severity: Warning)

|             |                                                                                                                                                   |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Partner is lost (timed out) for interface <code>&lt;intf_id&gt;</code> LAG <code>&lt;lag_id&gt;</code> .<br>State: <code>&lt;fsm_state&gt;</code> |
| Category    | LACP                                                                                                                                              |
| Severity    | Warning                                                                                                                                           |
| Description | Log to indicate that LACP partner is lost                                                                                                         |

### Event ID: 1312

|             |                                                  |
|-------------|--------------------------------------------------|
| Message     | Failed to create LAG <code>&lt;lag_id&gt;</code> |
| Category    | LACP                                             |
| Severity    | Error                                            |
| Description | Log when LAG creation is failed                  |

### Event ID: 1313

|             |                                            |
|-------------|--------------------------------------------|
| Message     | LAG <code>&lt;lag_id&gt;</code> set as VSX |
| Category    | LACP                                       |
| Severity    | Information                                |
| Description | Log when VSX is created                    |

### Event ID: 1314

|             |                                                                                                                                            |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | LAG <code>&lt;lag_id&gt;</code> not sending LACPDUs through interface <code>&lt;intf_id&gt;</code> because VSX information is not complete |
| Category    | LACP                                                                                                                                       |
| Severity    | Information                                                                                                                                |
| Description | Log when LAG is not sending LACPDUs through interface because VSX information is incomplete                                                |

### Event ID: 1315

|             |                                                                                                       |
|-------------|-------------------------------------------------------------------------------------------------------|
| Message     | LACP fallback mode set to <code>&lt;lacp_fallback_mode&gt;</code> for lag <code>&lt;lag_id&gt;</code> |
| Category    | LACP                                                                                                  |
| Severity    | Error                                                                                                 |
| Description | Log when LACP fallback mode is set                                                                    |

#### Event ID: 1316

|             |                                                                                                             |
|-------------|-------------------------------------------------------------------------------------------------------------|
| Message     | LACP fallback timeout set to <code>&lt;lacp_fallback_timeout&gt;</code> for lag <code>&lt;lag_id&gt;</code> |
| Category    | LACP                                                                                                        |
| Severity    | Error                                                                                                       |
| Description | Log when LACP fallback timeout is set                                                                       |

#### Event ID: 1317

|             |                                                                                                              |
|-------------|--------------------------------------------------------------------------------------------------------------|
| Message     | LACP fallback timeout <code>&lt;lacp_fallback_timeout&gt;</code> expired for lag <code>&lt;lag_id&gt;</code> |
| Category    | LACP                                                                                                         |
| Severity    | Error                                                                                                        |
| Description | Log when LACP fallback timeout is expired                                                                    |

#### Event ID: 1318

|             |                                                                                                |
|-------------|------------------------------------------------------------------------------------------------|
| Message     | Interface <code>&lt;intf_id&gt;</code> enabled by fallback for lag <code>&lt;lag_id&gt;</code> |
| Category    | LACP                                                                                           |
| Severity    | Error                                                                                          |
| Description | Log when interface is enabled by fallback                                                      |

#### Event ID: 1319

|             |                                                                    |
|-------------|--------------------------------------------------------------------|
| Message     | LAG global load balancing mode is set to <code>&lt;mode&gt;</code> |
| Category    | LACP                                                               |
| Severity    | Information                                                        |
| Description | Logs to set global load balancing mode for LAG interfaces.         |

#### Event ID: 1320

|         |                                                                                                 |
|---------|-------------------------------------------------------------------------------------------------|
| Message | LAG load balancing mode is set to <code>&lt;mode&gt;</code> for lag <code>&lt;lag_id&gt;</code> |
|---------|-------------------------------------------------------------------------------------------------|



|             |                                                             |
|-------------|-------------------------------------------------------------|
| Category    | LACP                                                        |
| Severity    | Information                                                 |
| Description | Logs to set per port load balancing mode for LAG interface. |

#### Event ID: 1321

|             |                                                                                                                                                                                            |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | LAG <code>&lt;lag_id&gt;</code> State change for interface <code>&lt;intf_id&gt;</code> : Actor state: <code>&lt;actor_state&gt;</code> , Partner state <code>&lt;partner_state&gt;</code> |
| Category    | LACP                                                                                                                                                                                       |
| Severity    | Information                                                                                                                                                                                |
| Description | Logs that capture changes to LACP state for LAG interface.                                                                                                                                 |

#### Event ID: 1322

|             |                                                                                                                                                                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Interface <code>&lt;intf_name&gt;</code> cannot be part of Lag <code>&lt;lag_number&gt;</code> . Speed mismatched (Interface speed <code>&lt;port_speed&gt;</code> Mbps Lag base speed <code>&lt;lag_speed&gt;</code> Mbps). ' throttle_count: 100 |
| Category    | LACP                                                                                                                                                                                                                                               |
| Severity    | Information                                                                                                                                                                                                                                        |
| Description | Logs to capture if LACP protocol does not allow interface to be part of lag due to speed mismatch.                                                                                                                                                 |

#### Event ID: 1323

|             |                                                                               |
|-------------|-------------------------------------------------------------------------------|
| Message     | Fallback is <code>&lt;fallback&gt;</code> for LAG <code>&lt;lag_id&gt;</code> |
| Category    | LACP                                                                          |
| Severity    | Information                                                                   |
| Description | Logs to capture if fallback is changed for LAG interface                      |

#### Event ID: 1324

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | LACP Graceful Shut is initiated                        |
| Category    | LACP                                                   |
| Severity    | Information                                            |
| Description | Logs that capture LACP Graceful Shut for LAG interface |

#### Event ID: 1325

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | LACP Graceful Shut is completed                        |
| Category    | LACP                                                   |
| Severity    | Information                                            |
| Description | Logs that capture LACP Graceful Shut for LAG interface |

The following are the events related to LAG.

#### Event ID: 1401

|             |                                                                                      |
|-------------|--------------------------------------------------------------------------------------|
| Message     | Trunk set succeeds unit <code>&lt;unit&gt;</code> lag_id <code>&lt;lag_id&gt;</code> |
| Category    | LAG                                                                                  |
| Severity    | Debug                                                                                |
| Description | Logs the creation of trunk.                                                          |

#### Event ID: 1402

|             |                                                                                                                                                   |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Lag creation failed unit <code>&lt;unit&gt;</code> lag_id <code>&lt;lag_id&gt;</code> rc <code>&lt;rc&gt;</code> error <code>&lt;error&gt;</code> |
| Category    | LAG                                                                                                                                               |
| Severity    | Error                                                                                                                                             |
| Description | Logs the failure of trunk creation.                                                                                                               |

#### Event ID: 1403

|             |                                                                                                                                                     |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Destroy lag failed on unit <code>&lt;unit&gt;</code> lag_id <code>&lt;lag_id&gt;</code> rc <code>&lt;rc&gt;</code> error <code>&lt;error&gt;</code> |
| Category    | LAG                                                                                                                                                 |
| Severity    | Error                                                                                                                                               |
| Description | Logs the failure of trunk destroy.                                                                                                                  |

#### Event ID: 1404

|             |                                                                                                                                    |
|-------------|------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Trunk member add port succeeds on unit <code>&lt;unit&gt;</code> hw_port <code>&lt;hw_port&gt;</code> tid <code>&lt;tid&gt;</code> |
| Category    | LAG                                                                                                                                |
| Severity    | Debug                                                                                                                              |
| Description | Logs the addition of port to trunk.                                                                                                |

#### Event ID: 1405

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | Trunk port attach error on hw_port <hw_port> tid <tid> rc <rc> <error> |
| Category    | LAG                                                                    |
| Severity    | Error                                                                  |
| Description | Logs the failure of addition of port to trunk.                         |

#### Event ID: 1406

|             |                                                                                  |
|-------------|----------------------------------------------------------------------------------|
| Message     | Failed to set egress enable on hw_port <hw_port> tid <tid> rc <rc> error <error> |
| Category    | LAG                                                                              |
| Severity    | Error                                                                            |
| Description | Logs the failure to set egress enable.                                           |

#### Event ID: 1407

|             |                                                                         |
|-------------|-------------------------------------------------------------------------|
| Message     | Failed to delete hw_port <hw_port> from tid <tid> rc <rc> error <error> |
| Category    | LAG                                                                     |
| Severity    | Error                                                                   |
| Description | Logs the failure to delete a port.                                      |

#### Event ID: 1408

|             |                                                                                     |
|-------------|-------------------------------------------------------------------------------------|
| Message     | Trunk psc set failed on unit <unit> lag_id <lag_id> psc <psc> rc <rc> error <error> |
| Category    | LAG                                                                                 |
| Severity    | Error                                                                               |
| Description | Logs the failure to set port selection criteria.                                    |

#### Event ID: 1409

|             |                                                           |
|-------------|-----------------------------------------------------------|
| Message     | LAG <interface>, set to load balance mode to <mode>       |
| Category    | LAG                                                       |
| Severity    | Information                                               |
| Description | logs to set load balancing mode for LAG L2/L3 interfaces. |

#### Event ID: 1410

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | Add port <i>&lt;port&gt;</i> to LAG <i>&lt;interface&gt;</i> |
| Category    | LAG                                                          |
| Severity    | Information                                                  |
| Description | logs to add port to LAG.                                     |

#### Event ID: 1411

|             |                                                                   |
|-------------|-------------------------------------------------------------------|
| Message     | Remove port <i>&lt;port&gt;</i> from LAG <i>&lt;interface&gt;</i> |
| Category    | LAG                                                               |
| Severity    | Information                                                       |
| Description | logs to remove port from LAG.                                     |

#### Event ID: 1412

|             |                                                                                              |
|-------------|----------------------------------------------------------------------------------------------|
| Message     | Add port <i>&lt;port&gt;</i> to vlan <i>&lt;vlan&gt;</i> for L3 LAG <i>&lt;interface&gt;</i> |
| Category    | LAG                                                                                          |
| Severity    | Information                                                                                  |
| Description | logs to add port to L3 LAG.                                                                  |

#### Event ID: 1413

|             |                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------|
| Message     | Remove port <i>&lt;port&gt;</i> to vlan <i>&lt;vlan&gt;</i> for L3 LAG <i>&lt;interface&gt;</i> |
| Category    | LAG                                                                                             |
| Severity    | Information                                                                                     |
| Description | logs to remove port from LAG.                                                                   |

#### Event ID: 1414

|             |                                                   |
|-------------|---------------------------------------------------|
| Message     | Destroy L3 LAG interface <i>&lt;interface&gt;</i> |
| Category    | LAG                                               |
| Severity    | Information                                       |
| Description | logs to destroy L3 LAG.                           |

The following are the events related to layer 3 interface.

#### Event ID: 1701

|             |                                   |
|-------------|-----------------------------------|
| Message     | L3-Interface <interface>, created |
| Category    | Layer 3 Interface                 |
| Severity    | Information                       |
| Description | logs to create L3 interface.      |

#### Event ID: 1702

|             |                                   |
|-------------|-----------------------------------|
| Message     | L3-Interface <interface>, deleted |
| Category    | Layer 3 Interface                 |
| Severity    | Information                       |
| Description | logs to delete L3 interface.      |

#### Event ID: 1703

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | Interface <interface>, configured administratively <state> |
| Category    | Layer 3 Interface                                          |
| Severity    | Information                                                |
| Description | logs for admin state of L3 interface.                      |

#### Event ID: 1704

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | Failed to create <vlanid> for layer 3 interface <interface> |
| Category    | Layer 3 Interface                                           |
| Severity    | Error                                                       |
| Description | logs errors while creating vlan for layer 3 interfaces.     |

#### Event ID: 1705

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | Failed to destroy layer 3 interface <interface> vlan <vlanid>, error: <err> |
| Category    | Layer 3 Interface                                                           |
| Severity    | Error                                                                       |
| Description | logs errors while destroying vlan for layer 3 interfaces.                   |

#### Event ID: 1706

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | Failed to delete an l3 interface <interface>, error: <err> |
| Category    | Layer 3 Interface                                          |
| Severity    | Error                                                      |
| Description | logs errors while destroying layer 3 interface.            |

#### Event ID: 1707

|             |                                                                              |
|-------------|------------------------------------------------------------------------------|
| Message     | Failed to add L3 host entry for ip <ipaddr>, error: <err>' throttle_count: 1 |
| Category    | Layer 3 Interface                                                            |
| Severity    | Error                                                                        |
| Description | logs errors while adding l3 hosts.                                           |

#### Event ID: 1708

|             |                                     |
|-------------|-------------------------------------|
| Message     | Added L3 host entry for ip <ipaddr> |
| Category    | Layer 3 Interface                   |
| Severity    | Information                         |
| Description | logs while adding l3 hosts.         |

#### Event ID: 1709

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | Failed to delete L3 host entry for ip <ipaddr>, error: <err> |
| Category    | Layer 3 Interface                                            |
| Severity    | Error                                                        |
| Description | logs errors while deleting l3 hosts.                         |

#### Event ID: 1710

|             |                                       |
|-------------|---------------------------------------|
| Message     | Deleted L3 host entry for ip <ipaddr> |
| Category    | Layer 3 Interface                     |
| Severity    | Information                           |
| Description | logs while deleting l3 hosts.         |

#### Event ID: 1711

|             |                                                   |
|-------------|---------------------------------------------------|
| Message     | Failed to get L3 host hit for ip <ipaddr>         |
| Category    | Layer 3 Interface                                 |
| Severity    | Error                                             |
| Description | logs errors to get L3 host hit for a specific ip. |

#### Event ID: 1712

|             |                           |
|-------------|---------------------------|
| Message     | L3 interface error: <err> |
| Category    | Layer 3 Interface         |
| Severity    | Error                     |
| Description | logs for L3 setup errors. |

#### Event ID: 1713

|             |                                                                    |
|-------------|--------------------------------------------------------------------|
| Message     | Added Nexthop <nexthop>, egress_id <egress_id>, for route <prefix> |
| Category    | Layer 3 Interface                                                  |
| Severity    | Information                                                        |
| Description | logs for nexthop addition.                                         |

#### Event ID: 1714

|             |                                             |
|-------------|---------------------------------------------|
| Message     | Delete Nexthop <nexthop> for route <prefix> |
| Category    | Layer 3 Interface                           |
| Severity    | Information                                 |
| Description | logs for nexthop deletion.                  |

#### Event ID: 1715

|         |                      |
|---------|----------------------|
| Message | Added route <prefix> |
|---------|----------------------|



|             |                          |
|-------------|--------------------------|
| Category    | Layer 3 Interface        |
| Severity    | Information              |
| Description | logs for route addition. |

#### Event ID: 1716

|             |                                           |
|-------------|-------------------------------------------|
| Message     | Update: route state: <i>&lt;state&gt;</i> |
| Category    | Layer 3 Interface                         |
| Severity    | Information                               |
| Description | logs for route update.                    |

#### Event ID: 1717

|             |                                    |
|-------------|------------------------------------|
| Message     | Delete route <i>&lt;prefix&gt;</i> |
| Category    | Layer 3 Interface                  |
| Severity    | Information                        |
| Description | logs for route deletion.           |

#### Event ID: 1718

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | Delete route <i>&lt;prefix&gt;</i> , error: <i>&lt;err&gt;</i> |
| Category    | Layer 3 Interface                                              |
| Severity    | Error                                                          |
| Description | logs error for route deletion.                                 |

#### Event ID: 1719

|             |                                                                                 |
|-------------|---------------------------------------------------------------------------------|
| Message     | Add route <i>&lt;prefix&gt;</i> , error: <i>&lt;err&gt;</i> ' throttle_count: 1 |
| Category    | Layer 3 Interface                                                               |
| Severity    | Error                                                                           |
| Description | logs error for route addition.                                                  |

#### Event ID: 1720

|          |                                                                                       |
|----------|---------------------------------------------------------------------------------------|
| Message  | Error creating egress object for port <i>&lt;port&gt;</i> , error: <i>&lt;err&gt;</i> |
| Category | Layer 3 Interface                                                                     |

|             |                                         |
|-------------|-----------------------------------------|
| Severity    | Error                                   |
| Description | logs errors for egress object creation. |

#### Event ID: 1721

|             |                                                                                                                       |
|-------------|-----------------------------------------------------------------------------------------------------------------------|
| Message     | Created L3 egress ID <code>&lt;egress_id&gt;</code> for port <code>&lt;port&gt;</code> intf <code>&lt;intf&gt;</code> |
| Category    | Layer 3 Interface                                                                                                     |
| Severity    | Information                                                                                                           |
| Description | logs for egress object creation.                                                                                      |

#### Event ID: 1722

|             |                                                                                                   |
|-------------|---------------------------------------------------------------------------------------------------|
| Message     | Error deleting egress object for port <code>&lt;port&gt;</code> , error: <code>&lt;err&gt;</code> |
| Category    | Layer 3 Interface                                                                                 |
| Severity    | Error                                                                                             |
| Description | logs errors for egress object deletion.                                                           |

#### Event ID: 1723

|             |                                                                                        |
|-------------|----------------------------------------------------------------------------------------|
| Message     | Deleted L3 egress ID <code>&lt;egress_id&gt;</code> for port <code>&lt;port&gt;</code> |
| Category    | Layer 3 Interface                                                                      |
| Severity    | Information                                                                            |
| Description | logs for egress object deletion.                                                       |

#### Event ID: 1724

|             |                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------|
| Message     | Interface <code>&lt;interface&gt;</code> , configured with ipv4 address <code>&lt;value&gt;</code> |
| Category    | Layer 3 Interface                                                                                  |
| Severity    | Information                                                                                        |
| Description | logs for ipv4 address update on interface.                                                         |

#### Event ID: 1725

|             |                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------|
| Message     | Interface <code>&lt;interface&gt;</code> , configured with ipv6 address <code>&lt;value&gt;</code> |
| Category    | Layer 3 Interface                                                                                  |
| Severity    | Information                                                                                        |
| Description | logs for ipv6 address update on interface.                                                         |

**Event ID: 1726**

|             |                                                                                |
|-------------|--------------------------------------------------------------------------------|
| Message     | Interface <i>&lt;interface&gt;</i> , ipv4 address deleted <i>&lt;value&gt;</i> |
| Category    | Layer 3 Interface                                                              |
| Severity    | Information                                                                    |
| Description | logs for ipv4 address delete from interface.                                   |

**Event ID: 1727**

|             |                                                                                |
|-------------|--------------------------------------------------------------------------------|
| Message     | Interface <i>&lt;interface&gt;</i> , ipv6 address deleted <i>&lt;value&gt;</i> |
| Category    | Layer 3 Interface                                                              |
| Severity    | Information                                                                    |
| Description | logs for ipv6 address delete from interface.                                   |

**Event ID: 1728**

|             |                                                                                                                      |
|-------------|----------------------------------------------------------------------------------------------------------------------|
| Message     | IPv6 Address Status: Interface <i>&lt;intf&gt;</i> , address <i>&lt;addr&gt;</i> , status <i>&lt;addr_status&gt;</i> |
| Category    | Layer 3 Interface                                                                                                    |
| Severity    | Information                                                                                                          |
| Description | Event raised when ipv6 address status changes                                                                        |

**Event ID: 1729**

|             |                                                                                                  |
|-------------|--------------------------------------------------------------------------------------------------|
| Message     | Interface <i>&lt;interface&gt;</i> , configured with secondary ipv4 address <i>&lt;value&gt;</i> |
| Category    | Layer 3 Interface                                                                                |
| Severity    | Information                                                                                      |
| Description | logs for secondary ipv4 address update on interface.                                             |

**Event ID: 1730**

|             |                                                                                          |
|-------------|------------------------------------------------------------------------------------------|
| Message     | Interface <i>&lt;interface&gt;</i> , secondary ipv4 address deleted <i>&lt;value&gt;</i> |
| Category    | Layer 3 Interface                                                                        |
| Severity    | Information                                                                              |
| Description | logs for secondary ipv4 address delete from interface.                                   |

**Event ID: 1731**

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | IP MTU <mtu> not applied due to hardware resource limitation |
| Category    | Layer 3 Interface                                            |
| Severity    | Error                                                        |
| Description | Logs failure while configuring hardware for IPMTU.           |

The following are the events related to LED.

#### Event ID: 501

|             |                                                      |
|-------------|------------------------------------------------------|
| Message     | There are <count> LED types in subsystem <subsystem> |
| Category    | LED                                                  |
| Severity    | Information                                          |
| Description | Log about number of LED types in subsystem           |

#### Event ID: 502

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | There are <count> LED configs in subsystem <subsystem> |
| Category    | LED                                                    |
| Severity    | Information                                            |
| Description | Log about number of LED config in subsystem            |

The following are the events related to LLDP.

#### Event ID: : 101

|             |                                                                                        |
|-------------|----------------------------------------------------------------------------------------|
| Message     | LLDP Enabled                                                                           |
| Category    | LLDP                                                                                   |
| Severity    | Information                                                                            |
| Description | Logs event when LLDP (Link Layer Discovery Protocol) feature is enabled in the switch. |

#### Event ID: : 102

|             |                                                                                         |
|-------------|-----------------------------------------------------------------------------------------|
| Message     | LLDP Disabled                                                                           |
| Category    | LLDP                                                                                    |
| Severity    | Information                                                                             |
| Description | Logs event when LLDP (Link Layer Discovery Protocol) feature is disabled in the switch. |

#### Event ID: : 103

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | Configured LLDP tx-timer to <value>                                        |
| Category    | LLDP                                                                       |
| Severity    | Information                                                                |
| Description | Logs event when the LLDP status update interval is configured by the user. |

#### Event ID: 104

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | LLDP neighbor <chassisid> added on <interface>               |
| Category    | LLDP                                                         |
| Severity    | Information                                                  |
| Description | Logs event when a new neighbor entry is added to the switch. |

#### Event ID: 105

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | LLDP neighbor <chassisid> updated on <interface>' throttle_count: 100 |
| Category    | LLDP                                                                  |
| Severity    | Information                                                           |
| Description | Logs event when an existing neighbor entry is updated in the switch.  |

#### Event ID: 106

|             |                                                                    |
|-------------|--------------------------------------------------------------------|
| Message     | LLDP neighbor <chassisid> deleted on <interface>                   |
| Category    | LLDP                                                               |
| Severity    | Information                                                        |
| Description | Logs event when an existing neighbor entry is deleted from switch. |

#### Event ID: 107

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | Configured LLDP Management IP <value>                                  |
| Category    | LLDP                                                                   |
| Severity    | Information                                                            |
| Description | Logs event when a new management IP address is configured by the user. |

#### Event ID: 108

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | Configured LLDP tx-hold to <hold>                                         |
| Category    | LLDP                                                                      |
| Severity    | Information                                                               |
| Description | Logs event when LLDP transmit multiplier value is configured by the user. |

#### Event ID: 109

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | Configured LLDP tx-delay to <value>                                  |
| Category    | LLDP                                                                 |
| Severity    | Information                                                          |
| Description | Logs event when LLDP transmit delay value is configured by the user. |

#### Event ID: 110

|         |                                         |
|---------|-----------------------------------------|
| Message | Configured LLDP reinit-delay to <value> |
|---------|-----------------------------------------|

|             |                                                                                  |
|-------------|----------------------------------------------------------------------------------|
| Category    | LLDP                                                                             |
| Severity    | Information                                                                      |
| Description | Logs event when LLDP interface reinitialization value is configured by the user. |

### Event ID: 111

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | <code>LLDP statistics cleared</code>                         |
| Category    | LLDP                                                         |
| Severity    | Information                                                  |
| Description | Logs event when LLDP statistics are cleared from the switch. |

### Event ID: 112

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | <code>LLDP neighbor info cleared</code>                               |
| Category    | LLDP                                                                  |
| Severity    | Information                                                           |
| Description | Logs event when LLDP neighbor information is cleared from the switch. |

### Event ID: 113

|             |                                                                                                                                                   |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>PVID mismatch on &lt;interface&gt; pvid = &lt;pvid&gt;, Neighbor &lt;chassisid&gt; port_id = &lt;ninterface&gt; pvid = &lt;npvid&gt;</code> |
| Category    | LLDP                                                                                                                                              |
| Severity    | Information                                                                                                                                       |
| Description | Log event when the PVID mismatches between the switch and neighbor over an interface.                                                             |



The following are the events related to loop protect.

### Event ID: 2801 (Severity: Warning)

|             |                                                                                                                          |
|-------------|--------------------------------------------------------------------------------------------------------------------------|
| Message     | Port <code>&lt;portName&gt;</code> is disabled by Loop-protection after loop detection on VLAN <code>&lt;vlan&gt;</code> |
| Category    | Loop Protect                                                                                                             |
| Severity    | Warning                                                                                                                  |
| Description | Logs port disabled by Loop protect                                                                                       |

### Event ID: 2802 (Severity: Warning)

|             |                                                                                                                                                                     |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Ports TX <code>&lt;txportName&gt;</code> and RX <code>&lt;rxportName&gt;</code> are disabled by Loop-protect after loop detection on VLAN <code>&lt;vlan&gt;</code> |
| Category    | Loop Protect                                                                                                                                                        |
| Severity    | Warning                                                                                                                                                             |
| Description | Logs port disabled by Loop protect                                                                                                                                  |

### Event ID: 2803 (Severity: Warning)

|             |                                                                                       |
|-------------|---------------------------------------------------------------------------------------|
| Message     | Loop detected on port <code>&lt;portName&gt;</code> on VLAN <code>&lt;vlan&gt;</code> |
| Category    | Loop Protect                                                                          |
| Severity    | Warning                                                                               |
| Description | Logs port which receives PDU of its own                                               |

### Event ID: 2804

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | Port <code>&lt;portName&gt;</code> enabled after disable time expired |
| Category    | Loop Protect                                                          |
| Severity    | Information                                                           |
| Description | Logs port enabled after disabled time expired                         |

### Event ID: 2805

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | Port <code>&lt;portName&gt;</code> added for loop-protection |
| Category    | Loop Protect                                                 |
| Severity    | Information                                                  |
| Description | Logs port added                                              |

#### Event ID: 2806

|             |                                                                 |
|-------------|-----------------------------------------------------------------|
| Message     | Port <code>&lt;portName&gt;</code> deleted from loop-protection |
| Category    | Loop Protect                                                    |
| Severity    | Information                                                     |
| Description | Logs port deleted                                               |

#### Event ID: 2807

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | Loop-Protection stats cleared for port <code>&lt;portName&gt;</code> |
| Category    | Loop Protect                                                         |
| Severity    | Information                                                          |
| Description | Loop-Protection stats cleared for port                               |

#### Event ID: 2808

|             |                                                                                                                       |
|-------------|-----------------------------------------------------------------------------------------------------------------------|
| Message     | Ports TX <code>&lt;txportName&gt;</code> and RX <code>&lt;rxportName&gt;</code> are involved during TX port disabling |
| Category    | Loop Protect                                                                                                          |
| Severity    | Information                                                                                                           |
| Description | Logs TX and RX ports after TX disabled by Loop protect                                                                |

The following are the events related to loopback.

#### Event ID: 901

|             |                                         |
|-------------|-----------------------------------------|
| Message     | Loopback Interface <interface>, created |
| Category    | Loopback                                |
| Severity    | Information                             |
| Description | Log when loopback interface is created  |

#### Event ID: 902

|             |                                         |
|-------------|-----------------------------------------|
| Message     | Loopback Interface <interface>, deleted |
| Category    | Loopback                                |
| Severity    | Information                             |
| Description | Log when loopback interface is deleted  |

#### Event ID: 903

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | Loopback Interface <interface>, configured administratively <state> |
| Category    | Loopback                                                            |
| Severity    | Information                                                         |
| Description | Log about loopback interface admin state                            |

The following are the events related to MAC Address mode configuration.

#### Event ID: 11001

|             |                                                                                                             |
|-------------|-------------------------------------------------------------------------------------------------------------|
| Message     | The MAC Address configured mode changed from <code>&lt;old_mode&gt;</code> to <code>&lt;new_mode&gt;</code> |
| Category    | MAC Address mode configuration                                                                              |
| Severity    | Information                                                                                                 |
| Description | Log event when the MAC Address configured mode is changed                                                   |

#### Event ID: 11002

|             |                                                                                                              |
|-------------|--------------------------------------------------------------------------------------------------------------|
| Message     | The MAC Address operational mode changed from <code>&lt;old_mode&gt;</code> to <code>&lt;new_mode&gt;</code> |
| Category    | MAC Address mode configuration                                                                               |
| Severity    | Information                                                                                                  |
| Description | Log event when the MAC Address operational mode is changed                                                   |

#### Event ID: 11003

|             |                                                                                                             |
|-------------|-------------------------------------------------------------------------------------------------------------|
| Message     | Station MAC add failure due to hardware full, mac= <code>&lt;mac&gt;</code> vlan= <code>&lt;vlan&gt;</code> |
| Category    | MAC Address mode configuration                                                                              |
| Severity    | Error                                                                                                       |
| Description | Log event when a local station MAC address cannot be added because the table is full                        |

#### Event ID: 11004

|             |                                                                                                                                                                                                                 |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | The MAC Address operational mode changed from <code>&lt;old_mode&gt;</code> to <code>&lt;new_mode&gt;</code> due to reaching SVI threshold. Current= <code>&lt;current&gt;</code> Max= <code>&lt;max&gt;</code> |
| Category    | MAC Address mode configuration                                                                                                                                                                                  |
| Severity    | Error                                                                                                                                                                                                           |
| Description | Log event when the MAC Address operational mode is changed due to out of resources                                                                                                                              |

The following are the events related to MAC learning.

### Event ID: 4801

|             |                                                                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | MAC <code>&lt;mac&gt;</code> moved from port <code>&lt;from-intf&gt;</code> to port <code>&lt;to-intf&gt;</code> on VLAN <code>&lt;vlan&gt;</code> |
| Category    | MAC Learning                                                                                                                                       |
| Severity    | Information                                                                                                                                        |
| Description | Event raised when L2 mac move                                                                                                                      |

### Event ID: 4802

|             |                                                                                                          |
|-------------|----------------------------------------------------------------------------------------------------------|
| Message     | All dynamic MAC addresses on VLAN <code>&lt;vlan&gt;</code> were flushed                                 |
| Category    | MAC Learning                                                                                             |
| Severity    | Information                                                                                              |
| Description | Event raised when L2 MAC table is flushed with vlan delete event or clear mac-address command from vtysh |

### Event ID: 4803

|             |                                                                                                              |
|-------------|--------------------------------------------------------------------------------------------------------------|
| Message     | All dynamic MAC addresses on port <code>&lt;intf&gt;</code> were flushed                                     |
| Category    | MAC Learning                                                                                                 |
| Severity    | Information                                                                                                  |
| Description | Event raised when L2 MAC table is flushed with port move to L3 event or clear mac-address command from vtysh |

### Event ID: 4804

|             |                                                                                                        |
|-------------|--------------------------------------------------------------------------------------------------------|
| Message     | All dynamic MAC addresses on port <code>&lt;intf&gt;</code> were flushed                               |
| Category    | MAC Learning                                                                                           |
| Severity    | Information                                                                                            |
| Description | Event raised when L2 MAC table is flushed with port down event or clear mac-address command from vtysh |

### Event ID: 4805

|             |                                                                                                        |
|-------------|--------------------------------------------------------------------------------------------------------|
| Message     | All dynamic MAC addresses on VLAN <vlan> were flushed                                                  |
| Category    | MAC Learning                                                                                           |
| Severity    | Information                                                                                            |
| Description | Event raised when L2 MAC table is flushed with vlan down event or clear mac-address command from vtysh |

The following are the events related to MACsec.

#### Event ID: 11201

|             |                                                                              |
|-------------|------------------------------------------------------------------------------|
| Message     | MACsec session established on Rx Secure Channel <sci> on interface <ifname>. |
| Category    | MACsec                                                                       |
| Severity    | Information                                                                  |
| Description | A MACsec session established on an interface.                                |

#### Event ID: 11202

|             |                                                                               |
|-------------|-------------------------------------------------------------------------------|
| Message     | MKA session secured for Connectivity Association <ckn> on interface <ifname>. |
| Category    | MACsec                                                                        |
| Severity    | Information                                                                   |
| Description | A Connectivity Association was successfully established on an interface.      |

#### Event ID: 11203

|             |                                                                                                                                                              |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Secure Association key updated for Connectivity Association <ckn> on interface <ifname> - Latest AN/KN <latest_an>/<latest_kn>, Old AN/KN <old_an>/<old_kn>. |
| Category    | MACsec                                                                                                                                                       |
| Severity    | Information                                                                                                                                                  |
| Description | A new Secure Association key created for a Connectivity Association.                                                                                         |

#### Event ID: 11204

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | Possible replay attempt detected on the Secure Channel <sci>. |
| Category    | MACsec                                                        |
| Severity    | Information                                                   |
| Description | A possible replay attempt detected on a Secure Channel.       |

The following are the events related to management.

### Event ID: 4301

|             |                                                     |
|-------------|-----------------------------------------------------|
| Message     | MGMT_INTF: <mgmt_intf_config_param>                 |
| Category    | Management                                          |
| Severity    | Information                                         |
| Description | Logs related to management interface configurations |

### Event ID: 4302

|             |                                                           |
|-------------|-----------------------------------------------------------|
| Message     | MGMT_INTF: <mgmt_intf_config_err>                         |
| Category    | Management                                                |
| Severity    | Error                                                     |
| Description | Logs related to management interface configurations error |

### Event ID: 4303 (Severity: Critical)

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | MGMT_INTF: <mgmt_intf_config_crit>                           |
| Category    | Management                                                   |
| Severity    | Critical                                                     |
| Description | Logs related to management interface critical configurations |



The following are the events related to MDNS.

#### Event ID: 11401

|             |                                                           |
|-------------|-----------------------------------------------------------|
| Message     | mDNS-SD enabled                                           |
| Category    | MDNS                                                      |
| Severity    | Information                                               |
| Description | Logs event when mDNS-SD feature is enabled in the switch. |

#### Event ID: 11402

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | mDNS-SD disabled                                           |
| Category    | MDNS                                                       |
| Severity    | Information                                                |
| Description | Logs event when mDNS-SD feature is disabled in the switch. |

The following are the events related to MGMD.

#### Event ID: 2601 (Severity: Fatal)

|             |                                                                                           |
|-------------|-------------------------------------------------------------------------------------------|
| Message     | Failed to alloc a <code>&lt;pkt_type&gt;</code> pkt(interface <code>&lt;vlan&gt;</code> ) |
| Category    | MGMD                                                                                      |
| Severity    | Fatal                                                                                     |
| Description | This log event informs packet allocation failed in MGMD subsystem.                        |

#### Event ID: 2602

|             |                                                                                                      |
|-------------|------------------------------------------------------------------------------------------------------|
| Message     | Received IGMPv1 query from <code>&lt;ip_address&gt;</code> when the device is configured for IGMPv2. |
| Category    | MGMD                                                                                                 |
| Severity    | Information                                                                                          |
| Description | This log event used to log IGMP warning when IGMPv1 query is received.                               |

#### Event ID: 2603 (Severity: Fatal)

|             |                                                                                                   |
|-------------|---------------------------------------------------------------------------------------------------|
| Message     | Unable to alloc a buf of size <code>&lt;size_value&gt;</code> for <code>&lt;sub_system&gt;</code> |
| Category    | MGMD                                                                                              |
| Severity    | Fatal                                                                                             |
| Description | This log event informs the user that MGMD could not allocate memory.                              |

#### Event ID: 2604

|             |                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------|
| Message     | Interface <code>&lt;if_name&gt;</code> : Other Querier detected for <code>&lt;mgmd_type&gt;</code> |
| Category    | MGMD                                                                                               |
| Severity    | Information                                                                                        |
| Description | This log event informs the user that IGMP/MLD detected other querier.                              |

#### Event ID: 2605

|             |                                                                                                                              |
|-------------|------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;mgmd_type&gt; Querier Election in progress for interface &lt;if_name&gt; with IP address &lt;ip_address&gt;</code> |
| Category    | MGMD                                                                                                                         |
| Severity    | Information                                                                                                                  |
| Description | This log event informs the user that IGMP/MLD has started querier election on interface.                                     |

#### Event ID: 2606

|             |                                                                                |
|-------------|--------------------------------------------------------------------------------|
| Message     | <code>Interface &lt;if_name&gt;: End &lt;mgmd_type&gt; Querier role</code>     |
| Category    | MGMD                                                                           |
| Severity    | Information                                                                    |
| Description | This log event informs the user that IGMP/MLD ended querier role on interface. |

#### Event ID: 2607

|             |                                                                                                       |
|-------------|-------------------------------------------------------------------------------------------------------|
| Message     | <code>Interface &lt;if_name&gt;: Start &lt;mgmd_type&gt; Querier role addr: &lt;ip_address&gt;</code> |
| Category    | MGMD                                                                                                  |
| Severity    | Information                                                                                           |
| Description | This log event informs the user that MGMD started querier role on interface.                          |

#### Event ID: 2608 (Severity: Warning)

|             |                                                                                                       |
|-------------|-------------------------------------------------------------------------------------------------------|
| Message     | <code>Received packet from &lt;ip_address&gt;, type &lt;type&gt;, on invalid port &lt;port&gt;</code> |
| Category    | MGMD                                                                                                  |
| Severity    | Warning                                                                                               |
| Description | This log event informs the user that MGMD received packet on invalid port.                            |

#### Event ID: 2609

|             |                                                                                                                         |
|-------------|-------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>Received IGMPv1 query from &lt;ip_address&gt; when the device is configured for IGMPv3.' throttle_count: 1</code> |
| Category    | MGMD                                                                                                                    |
| Severity    | Information                                                                                                             |
| Description | This log event used to log IGMP warning when configured mode is IGMPv3 and IGMPv1 query is received.                    |

#### Event ID: 2610

|             |                                                                                                      |
|-------------|------------------------------------------------------------------------------------------------------|
| Message     | Received IGMPv2 query from <ip_address> when the device is configured for IGMPv3.' throttle_count: 1 |
| Category    | MGMD                                                                                                 |
| Severity    | Information                                                                                          |
| Description | This log event used to log IGMP warning when configured mode is IGMPv3 and IGMPv2 query is received. |

#### Event ID: 2611

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | <mgmd_type> snooping is <status> on VLAN <vlan>               |
| Category    | MGMD                                                          |
| Severity    | Information                                                   |
| Description | This log event informs the user that IGMP/MLD status on VLAN. |

#### Event ID: 2612

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | <mgmd_type> is <status> on Interface <if_name>                        |
| Category    | MGMD                                                                  |
| Severity    | Information                                                           |
| Description | This log event informs the user the IGMP/MLD status on the Interface. |

#### Event ID: 2613

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | Port <port> on vlan <vlan> is set to <status> mode for <mgmd_type>. |
| Category    | MGMD                                                                |
| Severity    | Information                                                         |
| Description | This log event informs the user that the port mode has changed.     |

#### Event ID: 2614

|             |                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------|
| Message     | <mgmd_type> is not operational on VLAN <vlan> due to resource unavailability                    |
| Category    | MGMD                                                                                            |
| Severity    | Error                                                                                           |
| Description | This log event informs the user that the IGMP/MLD is disabled on a VLAN due to internal errors. |

#### Event ID: 2615

|             |                                                                                                                           |
|-------------|---------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;mgmd_type&gt;</code> is not operational on interface <code>&lt;l3Port&gt;</code> due to resource unavailability |
| Category    | MGMD                                                                                                                      |
| Severity    | Error                                                                                                                     |
| Description | This log event informs the user that the IGMP/MLD is disabled on a L3 interface due to internal errors.                   |

#### Event ID: 2616

|             |                                                                                                                                       |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------|
| Message     | IGMP/MLD Resource utilization has exceeded the supported limits on the system. Membership reports for the new groups will be dropped. |
| Category    | MGMD                                                                                                                                  |
| Severity    | Information                                                                                                                           |
| Description | This log event informs the user that MGMD resource utilization has exceeded the supported limits                                      |

#### Event ID: 2617

|             |                                                                                                               |
|-------------|---------------------------------------------------------------------------------------------------------------|
| Message     | IGMP/MLD Resource utilization has reached 90 percent of the supported limits on the system.                   |
| Category    | MGMD                                                                                                          |
| Severity    | Information                                                                                                   |
| Description | This log event informs the user that MGMD resource utilization has reached 90 percent of the supported limits |

#### Event ID: 2618

|             |                                                                                                            |
|-------------|------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;mgmd_type&gt;</code> snooping is <code>&lt;status&gt;</code> on VLAN <code>&lt;vlan&gt;</code> . |
| Category    | MGMD                                                                                                       |
| Severity    | Information                                                                                                |
| Description | This log event informs the user that whether IGMP/MLD snooping is operational.                             |

#### Event ID: 2619

|             |                                                                                                                         |
|-------------|-------------------------------------------------------------------------------------------------------------------------|
| Message     | Received IGMPv3 query from <code>&lt;ip_address&gt;</code> when the device is configured for IGMPv2.' throttle_count: 1 |
| Category    | MGMD                                                                                                                    |
| Severity    | Information                                                                                                             |
| Description | This log event used to log IGMP warning when IGMPv2 query is received.                                                  |

**Event ID: 2620**

|             |                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------|
| Message     | Received MLDV1 query from <ip_address> when the device is configured for MLDV2.' throttle_count: 1 |
| Category    | MGMD                                                                                               |
| Severity    | Information                                                                                        |
| Description | This log event used to log MLD warning when configured mode is MLDV2 and MLDV1 query is received.  |

**Event ID: 2621**

|             |                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------|
| Message     | Received MLDV2 query from <ip_address> when the device is configured for MLDV1.' throttle_count: 1 |
| Category    | MGMD                                                                                               |
| Severity    | Information                                                                                        |
| Description | This log event used to log MLD warning when configured mode is MLDv2 and MLDv1 query is received.  |

**Event ID: 2622**

|             |                                                                                                                               |
|-------------|-------------------------------------------------------------------------------------------------------------------------------|
| Message     | Flood mode is temporarily activated on ERPS ports <port0> and <port1> as ring state for ring id <ring_id> changed to <state>. |
| Category    | MGMD                                                                                                                          |
| Severity    | Information                                                                                                                   |
| Description | This log event used to log if ERPS Ring state changed to idle or protection.                                                  |

The following are the events related to mirroring.

#### Event ID: 6701

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | Failed to create mirror session <number>                   |
| Category    | Mirroring                                                  |
| Severity    | Error                                                      |
| Description | Logs a message when the creation of a mirror session fails |

#### Event ID: 6702

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | Mirror session <number> created                               |
| Category    | Mirroring                                                     |
| Severity    | Information                                                   |
| Description | Logs a message when the creation of a mirror session succeeds |

#### Event ID: 6703

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | Failed to delete mirror session <number>                   |
| Category    | Mirroring                                                  |
| Severity    | Error                                                      |
| Description | Logs a message when the deletion of a mirror session fails |

#### Event ID: 6704

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | Mirror session <number> deleted                            |
| Category    | Mirroring                                                  |
| Severity    | Information                                                |
| Description | Logs a message when mirror session is successfully deleted |

#### Event ID: 6705

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | Failed to update mirror session <i>&lt;number&gt;</i>   |
| Category    | Mirroring                                               |
| Severity    | Error                                                   |
| Description | Logs a message when an update of a mirror session fails |

### Event ID: 6706

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | Mirror session <i>&lt;number&gt;</i> updated                |
| Category    | Mirroring                                                   |
| Severity    | Information                                                 |
| Description | Logs a message when the update of a mirror session succeeds |



The following are the events related to module.

### Event ID: 3201

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; inserted': yes</code> |
| Category    | Module                                                       |
| Severity    | Information                                                  |
| Description | Indicates that the module has been physically inserted       |

### Event ID: 3202 (Severity: Warning)

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; removed': yes</code> |
| Category    | Module                                                      |
| Severity    | Warning                                                     |
| Description | Indicates that the module has been physically removed       |

### Event ID: 3203

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | <code>Initiating &lt;type&gt; module &lt;name&gt; reboot': yes</code> |
| Category    | Module                                                                |
| Severity    | Information                                                           |
| Description | Indicates that the module is about to reboot                          |

### Event ID: 3204

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; is ready</code> |
| Category    | Module                                                 |
| Severity    | Information                                            |
| Description | Indicates that the module is initialized and ready     |

### Event ID: 3205

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; is down: &lt;reason&gt;</code> |
| Category    | Module                                                                |
| Severity    | Information                                                           |
| Description | Indicates that the module is down                                     |

#### Event ID: 3206

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; is in diagnostics mode</code> |
| Category    | Module                                                               |
| Severity    | Information                                                          |
| Description | Indicates that a module is in diagnostics mode                       |

#### Event ID: 3207

|             |                                                                                |
|-------------|--------------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; has failed: &lt;reason&gt;': yes</code> |
| Category    | Module                                                                         |
| Severity    | Error                                                                          |
| Description | Indicates that a module has failed                                             |

#### Event ID: 3208

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; admin state set to up</code> |
| Category    | Module                                                              |
| Severity    | Information                                                         |
| Description | Indicates that the module administrative state is set to up         |

#### Event ID: 3209

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; admin state set to down</code> |
| Category    | Module                                                                |
| Severity    | Information                                                           |
| Description | Indicates that the module administrative state is set to down         |

#### Event ID: 3210

|         |                                                                              |
|---------|------------------------------------------------------------------------------|
| Message | <code>&lt;type&gt; module &lt;name&gt; admin state set to diagnostics</code> |
|---------|------------------------------------------------------------------------------|

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Category    | Module                                                               |
| Severity    | Information                                                          |
| Description | Indicates that the module administrative state is set to diagnostics |

### Event ID: 3211

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; ISP passed</code> |
| Category    | Module                                                   |
| Severity    | Information                                              |
| Description | Indicates that ISP has passed for the module             |

### Event ID: 3212

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; ISP failed': yes</code> |
| Category    | Module                                                         |
| Severity    | Error                                                          |
| Description | Indicates that ISP has failed for the module                   |

### Event ID: 3213 (Severity: Warning)

|             |                                                           |
|-------------|-----------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; ISP skipped</code> |
| Category    | Module                                                    |
| Severity    | Warning                                                   |
| Description | Indicates that ISP has been skipped for the module        |

### Event ID: 3214

|             |                                                                         |
|-------------|-------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; has enabled standby power</code> |
| Category    | Module                                                                  |
| Severity    | Debug                                                                   |
| Description | Indicates that the module is in standby (low-power) mode                |

### Event ID: 3215

|          |                                                                                                        |
|----------|--------------------------------------------------------------------------------------------------------|
| Message  | <code>&lt;type&gt; module &lt;name&gt; is requesting to power on with priority &lt;priority&gt;</code> |
| Category | Module                                                                                                 |

|             |                                                     |
|-------------|-----------------------------------------------------|
| Severity    | Debug                                               |
| Description | Indicates that the module is requesting to power on |

### Event ID: 3216

|             |                                                                              |
|-------------|------------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; power request has been granted</code> |
| Category    | Module                                                                       |
| Severity    | Debug                                                                        |
| Description | Indicates that the power request for the module has been granted             |

### Event ID: 3217

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; power request has been denied</code> |
| Category    | Module                                                                      |
| Severity    | Error                                                                       |
| Description | Indicates that the power request for the module has been denied             |

### Event ID: 3218

|             |                                                                   |
|-------------|-------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; enabling main power</code> |
| Category    | Module                                                            |
| Severity    | Debug                                                             |
| Description | Indicates that main power for the module is being enabled         |

### Event ID: 3219

|             |                                                                  |
|-------------|------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; main power enabled</code> |
| Category    | Module                                                           |
| Severity    | Debug                                                            |
| Description | Indicates that main power for the module has been enabled        |

### Event ID: 3220

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; main power failed': yes</code> |
| Category    | Module                                                                |
| Severity    | Error                                                                 |
| Description | Indicates that main power for the module has failed                   |

**Event ID: 3221**

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; device initialization started</code> |
| Category    | Module                                                                      |
| Severity    | Debug                                                                       |
| Description | Indicates that device initialization for the module has started             |

**Event ID: 3222**

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; device initialization passed</code> |
| Category    | Module                                                                     |
| Severity    | Debug                                                                      |
| Description | Indicates that device initialization for the module has passed             |

**Event ID: 3223**

|             |                                                                                                  |
|-------------|--------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; device initialization failed: &lt;reason&gt;': yes</code> |
| Category    | Module                                                                                           |
| Severity    | Error                                                                                            |
| Description | Indicates that device initialization for the module has failed                                   |

**Event ID: 3224**

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; ASIC initialization started</code> |
| Category    | Module                                                                    |
| Severity    | Information                                                               |
| Description | Indicates that an ASIC for the module is being initialized                |

**Event ID: 3225**

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; ASIC initialization completed</code> |
| Category    | Module                                                                      |
| Severity    | Debug                                                                       |
| Description | Indicates that ASIC initialization for the module has completed             |

**Event ID: 3226**

|             |                                                                                                |
|-------------|------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; ASIC initialization failed: &lt;reason&gt;': yes</code> |
| Category    | Module                                                                                         |
| Severity    | Error                                                                                          |
| Description | Indicates that ASIC initialization for the module has failed                                   |

#### Event ID: 3227

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; ASIC deinitialization started</code> |
| Category    | Module                                                                      |
| Severity    | Debug                                                                       |
| Description | Indicates that an ASIC for the module is being deinitialized                |

#### Event ID: 3228

|             |                                                                               |
|-------------|-------------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; ASIC deinitialization completed</code> |
| Category    | Module                                                                        |
| Severity    | Debug                                                                         |
| Description | Indicates that ASIC deinitialization for the module has completed             |

#### Event ID: 3229

|             |                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; ASIC denitIALIZATION failed: &lt;reason&gt;': yes</code> |
| Category    | Module                                                                                          |
| Severity    | Error                                                                                           |
| Description | Indicates that ASIC deinitialization for the module has failed                                  |

#### Event ID: 3230

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | <code>&lt;name&gt; is starting zeroization': yes</code> |
| Category    | Module                                                  |
| Severity    | Information                                             |
| Description | Indicates that the module is about to start zeroization |

#### Event ID: 3231

|         |                                                  |
|---------|--------------------------------------------------|
| Message | <code>&lt;name&gt; zeroization completed.</code> |
|---------|--------------------------------------------------|

|             |                                                     |
|-------------|-----------------------------------------------------|
| Category    | Module                                              |
| Severity    | Information                                         |
| Description | Indicates that the module zeroization has completed |

#### Event ID: 3232

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | <code>&lt;name&gt; zeroization failed.': yes</code>      |
| Category    | Module                                                   |
| Severity    | Information                                              |
| Description | Indicates that the module zeroization failed to complete |

#### Event ID: 3233

|             |                                                                                                  |
|-------------|--------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; configured with product number &lt;part_number&gt;</code> |
| Category    | Module                                                                                           |
| Severity    | Information                                                                                      |
| Description | Indicates that the module has been configured                                                    |

#### Event ID: 3234

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; has been unconfigured</code> |
| Category    | Module                                                              |
| Severity    | Information                                                         |
| Description | Indicates that the module has been unconfigured                     |

#### Event ID: 3235

|             |                                                                   |
|-------------|-------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; initiating failover</code> |
| Category    | Module                                                            |
| Severity    | Information                                                       |
| Description | Indicates that the module has started failover                    |

#### Event ID: 3236

|          |                                                                  |
|----------|------------------------------------------------------------------|
| Message  | <code>&lt;type&gt; module &lt;name&gt; failover completed</code> |
| Category | Module                                                           |

|             |                                                  |
|-------------|--------------------------------------------------|
| Severity    | Information                                      |
| Description | Indicates that the module has completed failover |

#### Event ID: 3237

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; initiating ISP</code> |
| Category    | Module                                                       |
| Severity    | Information                                                  |
| Description | Indicates that ISP has started for the module                |

#### Event ID: 3238

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; enabling front-end power</code> |
| Category    | Module                                                                 |
| Severity    | Information                                                            |
| Description | Indicates that front-end power is being enabled                        |

#### Event ID: 3239 (Severity: Warning)

|             |                                                                                         |
|-------------|-----------------------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; disabling front-end power: &lt;reason&gt;</code> |
| Category    | Module                                                                                  |
| Severity    | Warning                                                                                 |
| Description | Indicates that front-end power is being disabled                                        |

#### Event ID: 3240

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; has persistent hardware error</code> |
| Category    | Module                                                                      |
| Severity    | Error                                                                       |
| Description | Indicates that persistent hardware error has occurred                       |



The following are the events related to MSDP.

#### Event ID: 8601

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | Router MSDP is <i>&lt;status&gt;</i> on VRF <i>&lt;vrf_name&gt;</i> |
| Category    | MSDP                                                                |
| Severity    | Information                                                         |
| Description | Router msdp configuration status                                    |

#### Event ID: 8602

|             |                                                                                               |
|-------------|-----------------------------------------------------------------------------------------------|
| Message     | Forwarding state of interface <i>&lt;if_name&gt;</i> has been changed to <i>&lt;state&gt;</i> |
| Category    | MSDP                                                                                          |
| Severity    | Information                                                                                   |
| Description | MSDP Source Interface operational status                                                      |

#### Event ID: 8603

|             |                                                                                                                                                     |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | MSDP Peer <i>&lt;peer_ip&gt;</i> ( <i>&lt;tcp_entity&gt;</i> ) with connection source <i>&lt;if_name&gt;</i> has entered <i>&lt;state&gt;</i> state |
| Category    | MSDP                                                                                                                                                |
| Severity    | Information                                                                                                                                         |
| Description | Logs the changes in MSDP Peer connection state.                                                                                                     |

#### Event ID: 8604

|             |                                                                                       |
|-------------|---------------------------------------------------------------------------------------|
| Message     | Port <i>&lt;port&gt;</i> is <i>&lt;status&gt;</i> to MSDP Peer <i>&lt;peer_ip&gt;</i> |
| Category    | MSDP                                                                                  |
| Severity    | Information                                                                           |
| Description | Log event when port is added or deleted for a peer.                                   |

#### Event ID: 8606

|             |                                                                                                                                                  |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | MSDP Peer <i>&lt;peer_ip&gt;</i> is <i>&lt;status&gt;</i> on VRF <i>&lt;vrf_name&gt;</i> . Interface <i>&lt;if_name&gt;</i> is added to the Peer |
| Category    | MSDP                                                                                                                                             |
| Severity    | Information                                                                                                                                      |
| Description | Log event when peer is enabled or disabled                                                                                                       |

#### Event ID: 8607

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | Start <i>&lt;tcp_entity&gt;</i> role for MSDP peer <i>&lt;peer_ip&gt;</i> |
| Category    | MSDP                                                                      |
| Severity    | Information                                                               |
| Description | Log event when client or server is elected                                |

#### Event ID: 8608

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | Finish packet was received on MSDP Peer <i>&lt;peer_ip&gt;</i> |
| Category    | MSDP                                                           |
| Severity    | Information                                                    |
| Description | Log event when TCP final packet is received.                   |

#### Event ID: 8609 (Severity: Warning)

|             |                                                                                                                                                                               |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Failed to add SA Cache entry: S= <i>&lt;src_ip&gt;</i> , G= <i>&lt;grp_ip&gt;</i> , R= <i>&lt;rp_ip&gt;</i> for Peer <i>&lt;peer_ip&gt;</i> as MSDP SA Cache Limit is reached |
| Category    | MSDP                                                                                                                                                                          |
| Severity    | Warning                                                                                                                                                                       |
| Description | Log event when MSDP SA cache limit is reached.                                                                                                                                |

The following are the events related to Multicast Traffic Manager.

### Event ID: 4001 (Severity: Warning)

|             |                                                                                                       |
|-------------|-------------------------------------------------------------------------------------------------------|
| Message     | The Multicast L3 Bridge Control Forwarding entries limit was reached:<br><limit>' throttle_count: 100 |
| Category    | Multicast Traffic Manager                                                                             |
| Severity    | Warning                                                                                               |
| Description | Event raised when the maximum number of multicast L3 Bridge Control Forwarding entries is reached     |

## Chapter 64

# Multiple spanning tree protocol events

The following are the events related to multiple spanning tree protocol.

### Event ID: 2001

|             |                                                                                        |
|-------------|----------------------------------------------------------------------------------------|
| Message     | MSTP Enabled                                                                           |
| Category    | Multiple spanning tree protocol                                                        |
| Severity    | Information                                                                            |
| Description | This command enables the MSTP (Multiple Spanning-tree Protocol) feature in the device. |

### Event ID: 2002

|             |                                                                                         |
|-------------|-----------------------------------------------------------------------------------------|
| Message     | MSTP Disabled                                                                           |
| Category    | Multiple spanning tree protocol                                                         |
| Severity    | Information                                                                             |
| Description | This command disables the MSTP (Multiple Spanning-tree Protocol) feature in the device. |

### Event ID: 2003 (Severity: Warning)

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | <code>&lt;config_parameter&gt; should be &lt;value&gt;</code>         |
| Category    | Multiple spanning tree protocol                                       |
| Severity    | Warning                                                               |
| Description | This log event informs the user that the MSTP config parameter is bad |

### Event ID: 2004 (Severity: Warning)

|             |                                                                                     |
|-------------|-------------------------------------------------------------------------------------|
| Message     | BPDU has <code>&lt;config_parameter&gt;</code> from port <code>&lt;value&gt;</code> |
| Category    | Multiple spanning tree protocol                                                     |
| Severity    | Warning                                                                             |
| Description | This log event informs the user that the Switch received a BPDU with a bad config   |

### Event ID: 2005 (Severity: Warning)

|             |                                                                         |
|-------------|-------------------------------------------------------------------------|
| Message     | Bad reconfiguration request: <code>&lt;reconfig_parameter&gt;</code>    |
| Category    | Multiple spanning tree protocol                                         |
| Severity    | Warning                                                                 |
| Description | This log event informs the user that the MSTP reconfig parameter is bad |

#### Event ID: 2006

|             |                                                                                                                                                                                     |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;proto&gt;</code> - Root changed from <code>&lt;old_priority&gt;</code> : <code>&lt;old_mac&gt;</code> to <code>&lt;new_priority&gt;</code> : <code>&lt;new_mac&gt;</code> |
| Category    | Multiple spanning tree protocol                                                                                                                                                     |
| Severity    | Information                                                                                                                                                                         |
| Description | This log event informs the user that the MSTP root has changed                                                                                                                      |

#### Event ID: 2007 (Severity: Warning)

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | Port <code>&lt;port&gt;</code> disabled - BPDU received on protected port |
| Category    | Multiple spanning tree protocol                                           |
| Severity    | Warning                                                                   |
| Description | This log event informs the user that BPDU was received on protected port  |

#### Event ID: 2008

|             |                                                                                                                                               |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;proto&gt;</code> starved for <code>&lt;pkt_type&gt;</code> on port <code>&lt;port&gt;</code> from <code>&lt;priority_mac&gt;</code> |
| Category    | Multiple spanning tree protocol                                                                                                               |
| Severity    | Information                                                                                                                                   |
| Description | This log event informs the user that the Rx queue is starved in the particular port                                                           |

#### Event ID: 2009

|             |                                                                                                      |
|-------------|------------------------------------------------------------------------------------------------------|
| Message     | BPDU loss- port <code>&lt;port&gt;</code> moved to inconsistent state for <code>&lt;proto&gt;</code> |
| Category    | Multiple spanning tree protocol                                                                      |
| Severity    | Information                                                                                          |
| Description | This log event informs the user that the port is in inconsistent state                               |

#### Event ID: 2010

|             |                                                                                               |
|-------------|-----------------------------------------------------------------------------------------------|
| Message     | Port <code>&lt;port&gt;</code> moved out of inconsistent state for <code>&lt;proto&gt;</code> |
| Category    | Multiple spanning tree protocol                                                               |
| Severity    | Information                                                                                   |
| Description | This log event informs the user that the MSTP is out of inconsistent state                    |

#### Event ID: 2011

|             |                                                                                                                                 |
|-------------|---------------------------------------------------------------------------------------------------------------------------------|
| Message     | Topology Change received on port <code>&lt;port&gt;</code> for <code>&lt;proto&gt;</code> from source: <code>&lt;mac&gt;</code> |
| Category    | Multiple spanning tree protocol                                                                                                 |
| Severity    | Information                                                                                                                     |
| Description | This log event informs the user that the MSTP topology change is received                                                       |

#### Event ID: 2012

|             |                                                                                                                                 |
|-------------|---------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;proto&gt;</code> - Topology Change generated on port <code>&lt;port&gt;</code> going in to <code>&lt;state&gt;</code> |
| Category    | Multiple spanning tree protocol                                                                                                 |
| Severity    | Information                                                                                                                     |
| Description | This log event informs the user that the MSTP topology change is generated                                                      |

#### Event ID: 2013

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | BPDU received on admin edge port <code>&lt;port&gt;</code>                  |
| Category    | Multiple spanning tree protocol                                             |
| Severity    | Information                                                                 |
| Description | This log event informs the user that a BPDU was received on admin edge port |

#### Event ID: 2014

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | Port <code>&lt;port&gt;</code> blocked on CIST                |
| Category    | Multiple spanning tree protocol                               |
| Severity    | Information                                                   |
| Description | This log event informs the user that the CIST port is blocked |

#### Event ID: 2015

|         |                                                  |
|---------|--------------------------------------------------|
| Message | Port <code>&lt;port&gt;</code> unblocked on CIST |
|---------|--------------------------------------------------|

|             |                                                                 |
|-------------|-----------------------------------------------------------------|
| Category    | Multiple spanning tree protocol                                 |
| Severity    | Information                                                     |
| Description | This log event informs the user that the CIST port is unblocked |

### Event ID: 2016

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | Port <code>&lt;port&gt;</code> blocked on MST <code>&lt;instance&gt;</code> |
| Category    | Multiple spanning tree protocol                                             |
| Severity    | Information                                                                 |
| Description | This log event informs the user that the MSTI port is blocked               |

### Event ID: 2017

|             |                                                                               |
|-------------|-------------------------------------------------------------------------------|
| Message     | Port <code>&lt;port&gt;</code> unblocked on MST <code>&lt;instance&gt;</code> |
| Category    | Multiple spanning tree protocol                                               |
| Severity    | Information                                                                   |
| Description | This log event informs the user that the MSTI port is unblocked               |

### Event ID: 2018

|             |                                                                                                                  |
|-------------|------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;proto&gt;</code> Root Port changed from <code>&lt;old_port&gt;</code> to <code>&lt;new_port&gt;</code> |
| Category    | Multiple spanning tree protocol                                                                                  |
| Severity    | Information                                                                                                      |
| Description | This log event informs the user that the root port is changed                                                    |

### Event ID: 2019

|             |                                                                                                                                    |
|-------------|------------------------------------------------------------------------------------------------------------------------------------|
| Message     | spanning tree mode changed from <code>&lt;old_mode&gt;</code> to <code>&lt;new_mode&gt;</code> , it will trigger the reconvergence |
| Category    | Multiple spanning tree protocol                                                                                                    |
| Severity    | Information                                                                                                                        |
| Description | This log event informs the user that the spanning tree mode is changed.                                                            |

The following are the events related to MVRP.

#### Event ID: 3101

|             |                                                                                           |
|-------------|-------------------------------------------------------------------------------------------|
| Message     | MVRP enabled on port <i>&lt;port&gt;</i>                                                  |
| Category    | MVRP                                                                                      |
| Severity    | Information                                                                               |
| Description | This command enables the MVRP (Multiple VLAN Registration Protocol) feature on interface. |

#### Event ID: 3102

|             |                                                                                            |
|-------------|--------------------------------------------------------------------------------------------|
| Message     | MVRP disabled on port <i>&lt;port&gt;</i>                                                  |
| Category    | MVRP                                                                                       |
| Severity    | Information                                                                                |
| Description | This command disables the MVRP (Multiple VLAN Registration Protocol) feature on interface. |

#### Event ID: 3103

|             |                                                                                                                             |
|-------------|-----------------------------------------------------------------------------------------------------------------------------|
| Message     | MVRP failed to create VLAN <i>&lt;vlan&gt;</i> . Maximum VLANs <i>&lt;max_vlan&gt;</i> already created' throttle_count: 100 |
| Category    | MVRP                                                                                                                        |
| Severity    | Information                                                                                                                 |
| Description | This log event informs user that the vlan create is failed.                                                                 |

#### Event ID: 3104

|             |                                                                         |
|-------------|-------------------------------------------------------------------------|
| Message     | MVRP statistics have been cleared for port <i>&lt;port&gt;</i>          |
| Category    | MVRP                                                                    |
| Severity    | Information                                                             |
| Description | This log event informs user that the mvrp statistics have been cleared. |

#### Event ID: 3105



|             |                                                                         |
|-------------|-------------------------------------------------------------------------|
| Message     | MVRP statistics have been cleared for <i>&lt;port&gt;</i> ports         |
| Category    | MVRP                                                                    |
| Severity    | Information                                                             |
| Description | This log event informs user that the mvrp statistics have been cleared. |

The following are the events related to NAE agents.

**Event ID: 6901**

|             |                                                      |
|-------------|------------------------------------------------------|
| Message     | An action has been triggered by the NAE agent <name> |
| Category    | NAE Agents                                           |
| Severity    | Information                                          |
| Description | Action has been triggered by an NAE agent            |

The following are the events related to Network Analytics Engine.

#### Event ID: 6001

|             |                                                                                                |
|-------------|------------------------------------------------------------------------------------------------|
| Message     | NAE agent <code>&lt;name&gt;</code> started to collect samples from <code>&lt;uri&gt;</code> . |
| Category    | NAE                                                                                            |
| Severity    | Information                                                                                    |
| Description | NAE agent started to collect samples.                                                          |

#### Event ID: 6002

|             |                                                                                                |
|-------------|------------------------------------------------------------------------------------------------|
| Message     | NAE agent <code>&lt;name&gt;</code> stopped to collect samples from <code>&lt;uri&gt;</code> . |
| Category    | NAE                                                                                            |
| Severity    | Information                                                                                    |
| Description | NAE agent stopped to collect samples.                                                          |

#### Event ID: 6003

|             |                                                                                                             |
|-------------|-------------------------------------------------------------------------------------------------------------|
| Message     | NAE agent <code>&lt;name&gt;</code> with URI <code>&lt;uri&gt;</code> has error and cannot collect samples. |
| Category    | NAE                                                                                                         |
| Severity    | Error                                                                                                       |
| Description | NAE agent with URI has error and cannot collect samples.                                                    |

#### Event ID: 6004

|             |                                                                                                |
|-------------|------------------------------------------------------------------------------------------------|
| Message     | NAE agent <code>&lt;name&gt;</code> is watching for condition <code>&lt;condition&gt;</code> . |
| Category    | NAE                                                                                            |
| Severity    | Information                                                                                    |
| Description | NAE agent is watching for condition.                                                           |

#### Event ID: 6005

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | NAE agent <name> stopped to watch for condition <condition>. |
| Category    | NAE                                                          |
| Severity    | Information                                                  |
| Description | NAE agent stopped to watch for condition.                    |

#### Event ID: 6006

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | NAE agent <name> with condition <condition> has error and is not watched. |
| Category    | NAE                                                                       |
| Severity    | Error                                                                     |
| Description | NAE agent with condition has error and is not watched.                    |

#### Event ID: 6007

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | NAE agent <name> generated an alert based on condition <condition>. |
| Category    | NAE                                                                 |
| Severity    | Information                                                         |
| Description | NAE agent generated an alert based on condition.                    |

#### Event ID: 6008 (Severity: Warning)

|             |                                                                                                                                                           |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | NAE experiencing a spike in data points to process for NAE monitor <monitorName>. NAE will temporarily stop monitoring new data points for <monitorName>. |
| Category    | NAE                                                                                                                                                       |
| Severity    | Warning                                                                                                                                                   |
| Description | NAE experiencing a spike in data points to process. Temporarily disabling processing updates from specific NAE monitor.                                   |

#### Event ID: 6009

|             |                                                                    |
|-------------|--------------------------------------------------------------------|
| Message     | NAE resuming to monitor data points from NAE monitor <monitorName> |
| Category    | NAE                                                                |
| Severity    | Information                                                        |
| Description | NAE resuming to monitor data points from specific NAE monitor.     |

#### Event ID: 6010

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | User <user> has cleard NAE time series database                |
| Category    | NAE                                                            |
| Severity    | Information                                                    |
| Description | Logs a message when a user clears the NAE time series database |

The following are the events related to Network Analytics Engine scripts.

#### Event ID: 5501

|             |                                       |
|-------------|---------------------------------------|
| Message     | NAE script <name> has been validated. |
| Category    | NAE Scripts                           |
| Severity    | Information                           |
| Description | NAE script has been validated.        |

#### Event ID: 5502

|             |                                   |
|-------------|-----------------------------------|
| Message     | Error found in NAE Script <name>. |
| Category    | NAE Scripts                       |
| Severity    | Error                             |
| Description | Error found in NAE Script.        |

#### Event ID: 5503

|             |                                  |
|-------------|----------------------------------|
| Message     | Error found in NAE Agent <name>. |
| Category    | NAE Scripts                      |
| Severity    | Error                            |
| Description | Error found in NAE Agent.        |

#### Event ID: 5504

|             |                                                                                                                     |
|-------------|---------------------------------------------------------------------------------------------------------------------|
| Message     | Error executing NAE action <action_type> belonging to condition <condition> and agent <agent> due to <description>. |
| Category    | NAE Scripts                                                                                                         |
| Severity    | Error                                                                                                               |
| Description | NAE Action error.                                                                                                   |

#### Event ID: 5505

|             |                                                   |
|-------------|---------------------------------------------------|
| Message     | NAE Script <name> has been created by the system. |
| Category    | NAE Scripts                                       |
| Severity    | Information                                       |
| Description | NAE Script has been created by the system.        |

#### Event ID: 5506

|             |                                                  |
|-------------|--------------------------------------------------|
| Message     | NAE Agent <name> has been created by the system. |
| Category    | NAE Scripts                                      |
| Severity    | Information                                      |
| Description | NAE Agent has been created by the system.        |

#### Event ID: 5507

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | <msg>                                              |
| Category    | NAE Scripts                                        |
| Severity    | Information                                        |
| Description | Log event when instantiated from active NAE agent. |

#### Event ID: 5508

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | <msg>                                              |
| Category    | NAE Scripts                                        |
| Severity    | Information                                        |
| Description | Log event when instantiated from active NAE agent. |

#### Event ID: 5509 (Severity: Critical)

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | <msg>                                              |
| Category    | NAE Scripts                                        |
| Severity    | Critical                                           |
| Description | Log event when instantiated from active NAE agent. |

#### Event ID: 5510

|         |       |
|---------|-------|
| Message | <msg> |
|---------|-------|

|             |                                                    |
|-------------|----------------------------------------------------|
| Category    | NAE Scripts                                        |
| Severity    | Error                                              |
| Description | Log event when instantiated from active NAE agent. |

### Event ID: 5511 (Severity: Warning)

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | <msg>                                              |
| Category    | NAE Scripts                                        |
| Severity    | Warning                                            |
| Description | Log event when instantiated from active NAE agent. |



The following are the events related to ND snooping.

### Event ID: 8401

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | All the dynamic binding entries were cleared.           |
| Category    | ND snooping                                             |
| Severity    | Information                                             |
| Description | Log event when all dynamic binding entries are cleared. |

### Event ID: 8402

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | Dynamic binding entries on the port <i>&lt;port&gt;</i> were cleared. |
| Category    | ND snooping                                                           |
| Severity    | Information                                                           |
| Description | Log event when all dynamic binding entries on a port are cleared.     |

### Event ID: 8403

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | Dynamic binding entries on the VLAN <i>&lt;vid&gt;</i> were cleared. |
| Category    | ND snooping                                                          |
| Severity    | Information                                                          |
| Description | Log event when all dynamic binding entries on a vlan are cleared.    |

### Event ID: 8404

|             |                                                                                             |
|-------------|---------------------------------------------------------------------------------------------|
| Message     | Dynamic binding entry with ip <i>&lt;ip&gt;</i> on the VLAN <i>&lt;vid&gt;</i> was cleared. |
| Category    | ND snooping                                                                                 |
| Severity    | Information                                                                                 |
| Description | Log event when a specific dynamic binding entry on a vlan is cleared.                       |

### Event ID: 8405

|             |                                                                                                                |
|-------------|----------------------------------------------------------------------------------------------------------------|
| Message     | ND packet of type=<type> received on port:<port> vlan:<vlan> with src_mac:<src_mac> is <status>. count=<count> |
| Category    | ND snooping                                                                                                    |
| Severity    | Information                                                                                                    |
| Description | Log event when ND packet received on port.                                                                     |

The following are the events related to NDM.

#### Event ID: 6101

|             |                                                                  |
|-------------|------------------------------------------------------------------|
| Message     | Static Neighbor <ip> created on Port <port>, VRF <vrf> mac <mac> |
| Category    | NDM                                                              |
| Severity    | Information                                                      |
| Description | Static neighbor created                                          |

#### Event ID: 6102

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | Static Neighbor <ip> deleted on Port <port>, VRF <vrf> and mac <mac> |
| Category    | NDM                                                                  |
| Severity    | Information                                                          |
| Description | Static neighbor deleted                                              |

#### Event ID: 6103

|             |                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------|
| Message     | Static Neighbor <ip> modified on Port <port> and VRF <vrf> from mac <old_mac> to new mac <new_mac> |
| Category    | NDM                                                                                                |
| Severity    | Information                                                                                        |
| Description | Static neighbor modified                                                                           |

#### Event ID: 6104

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | IPDB neighbor <ip> added in port <port>, VRF <vrf> |
| Category    | NDM                                                |
| Severity    | Information                                        |
| Description | IPDB neighbor added to the neighbor Table          |

#### Event ID: 6105

|             |                                               |
|-------------|-----------------------------------------------|
| Message     | IPDB Neighbor <ip> Deleted                    |
| Category    | NDM                                           |
| Severity    | Information                                   |
| Description | IPDB neighbor deleted from the neighbor Table |

#### Event ID: 6106

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | Clear all Arp entries requested on Port <port> and VRF <vrf> |
| Category    | NDM                                                          |
| Severity    | Information                                                  |
| Description | Clear all arp entries requested on Specific Port             |

#### Event ID: 6107

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | Clear all VSX Peer ARP entries requested on Port <port> and vrf <vrf> |
| Category    | NDM                                                                   |
| Severity    | Information                                                           |
| Description | Clear all VSX Peer ARP entries requested on Specific Port             |

#### Event ID: 6108

|             |                                                 |
|-------------|-------------------------------------------------|
| Message     | Clear all Arp entries requested on VRF <vrf>    |
| Category    | NDM                                             |
| Severity    | Information                                     |
| Description | Clear all arp entries requested on Specific VRF |

#### Event ID: 6109

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | Clear all VSX Peer Arp entries requested on VRF <vrf>    |
| Category    | NDM                                                      |
| Severity    | Information                                              |
| Description | Clear all VSX Peer arp entries requested on Specific VRF |

#### Event ID: 6110

|         |                                 |
|---------|---------------------------------|
| Message | Clear all Arp entries requested |
|---------|---------------------------------|

|             |                                 |
|-------------|---------------------------------|
| Category    | NDM                             |
| Severity    | Information                     |
| Description | Clear all arp entries requested |

#### Event ID: 6111

|             |                                          |
|-------------|------------------------------------------|
| Message     | Clear all VSX Peer Arp entries requested |
| Category    | NDM                                      |
| Severity    | Information                              |
| Description | Clear all VSX Peer arp entries requested |

#### Event ID: 6112

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | EVPN Virtual Tunnel EndPoint Neighbor <ip> added to Port<port> on VRF <vrf> |
| Category    | NDM                                                                         |
| Severity    | Information                                                                 |
| Description | EVPN Virtual Tunnel EndPoint Neighbor added to the neighbor table           |

#### Event ID: 6113

|             |                                                                                               |
|-------------|-----------------------------------------------------------------------------------------------|
| Message     | EVPN Virtual Tunnel EndPoint Neighbor <ip> updated on Port<port> and VRF <vrf> with mac <mac> |
| Category    | NDM                                                                                           |
| Severity    | Information                                                                                   |
| Description | EVPN Virtual Tunnel EndPoint Neighbor Updated in the neighbor table                           |

#### Event ID: 6114

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | EVPN VTEP Neighbor <ip> deleted from Port<port> and VRF <vrf> |
| Category    | NDM                                                           |
| Severity    | Information                                                   |
| Description | EVPN VTEP Neighbor deleted from the neighbor table            |

#### Event ID: 6115

|         |                               |
|---------|-------------------------------|
| Message | Management Role set to <role> |
|---------|-------------------------------|

|             |                                  |
|-------------|----------------------------------|
| Category    | NDM                              |
| Severity    | Information                      |
| Description | Processing Redundancy management |

#### Event ID: 6116

|             |                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------|
| Message     | Management role changed from old <code>&lt;role1&gt;</code> to new role <code>&lt;role2&gt;</code> |
| Category    | NDM                                                                                                |
| Severity    | Information                                                                                        |
| Description | Management role changed to new role                                                                |

#### Event ID: 6117

|             |                                                                                                          |
|-------------|----------------------------------------------------------------------------------------------------------|
| Message     | IPv4 neighbor ageout time changed to <code>&lt;time&gt;</code> seconds on port <code>&lt;port&gt;</code> |
| Category    | NDM                                                                                                      |
| Severity    | Information                                                                                              |
| Description | IPv4 neighbor ageout time changed to new value                                                           |

#### Event ID: 6118

|             |                                                                                                          |
|-------------|----------------------------------------------------------------------------------------------------------|
| Message     | IPv6 neighbor ageout time changed to <code>&lt;time&gt;</code> seconds on port <code>&lt;port&gt;</code> |
| Category    | NDM                                                                                                      |
| Severity    | Information                                                                                              |
| Description | IPv6 neighbor ageout time changed to new value                                                           |

#### Event ID: 6119

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | VSX neighbor datapath init sync status is enabled for peer neighbors sync |
| Category    | NDM                                                                       |
| Severity    | Information                                                               |
| Description | VSX neighbor datapath init sync status is enabled                         |

#### Event ID: 6120

|         |                                                                                             |
|---------|---------------------------------------------------------------------------------------------|
| Message | VSX neighbor datapath init sync status is disabled, Peer Neighbors sync cannot be performed |
|---------|---------------------------------------------------------------------------------------------|

|             |                                                    |
|-------------|----------------------------------------------------|
| Category    | NDM                                                |
| Severity    | Information                                        |
| Description | VSX neighbor datapath init sync status is disabled |

#### Event ID: 6121

|             |                                                      |
|-------------|------------------------------------------------------|
| Message     | static neighbor <ip> add failed, Subnet match failed |
| Category    | NDM                                                  |
| Severity    | Error                                                |
| Description | Static Neighbor add failed, subnet not matched       |

#### Event ID: 6122

|             |                                               |
|-------------|-----------------------------------------------|
| Message     | static neighbor <ip> add failed, it is own ip |
| Category    | NDM                                           |
| Severity    | Error                                         |
| Description | Static Neighbor add failed, it is own ip      |

#### Event ID: 6123

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | static neighbor <ip> Subnet match add failed, port is down |
| Category    | NDM                                                        |
| Severity    | Error                                                      |
| Description | Static Neighbor add failed, port is down                   |

#### Event ID: 6124

|             |                                                  |
|-------------|--------------------------------------------------|
| Message     | Neighbor table VSX peer DB connection terminated |
| Category    | NDM                                              |
| Severity    | Information                                      |
| Description | Neighbor table VSX peer DB connection terminated |

#### Event ID: 6125

|          |                                                   |
|----------|---------------------------------------------------|
| Message  | Neighbor table VSX peer DB connection established |
| Category | NDM                                               |

|             |                                                   |
|-------------|---------------------------------------------------|
| Severity    | Information                                       |
| Description | Neighbor table VSX peer DB connection established |

#### Event ID: 6126

|             |                                                      |
|-------------|------------------------------------------------------|
| Message     | VSX Peer IP <ip> added the port <port> and VRF <vrf> |
| Category    | NDM                                                  |
| Severity    | Information                                          |
| Description | VSX Peer IP added in port vsxPeerIpCache             |

#### Event ID: 6127

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | VSX Peer IP <ip> deleted from the port <port> and VRF <vrf> |
| Category    | NDM                                                         |
| Severity    | Information                                                 |
| Description | VSX Peer IP deleted in port vsxPeerIpCache                  |

#### Event ID: 6128

|             |                                           |
|-------------|-------------------------------------------|
| Message     | Proxy arp enabled for the port <port>     |
| Category    | NDM                                       |
| Severity    | Information                               |
| Description | Proxy arp enabled for the given interface |

#### Event ID: 6129

|             |                                            |
|-------------|--------------------------------------------|
| Message     | Proxy arp disabled for the port <port>     |
| Category    | NDM                                        |
| Severity    | Information                                |
| Description | Proxy arp disabled for the given interface |

#### Event ID: 6130

|          |                                                                                             |
|----------|---------------------------------------------------------------------------------------------|
| Message  | Neighbor <ip> modified on Port <port> and VRF <vrf> from mac <old_mac> to new mac <new_mac> |
| Category | NDM                                                                                         |



|             |                   |
|-------------|-------------------|
| Severity    | Information       |
| Description | Neighbor modified |

#### Event ID: 6131

|             |                                   |
|-------------|-----------------------------------|
| Message     | Neighbor Discovery daemon started |
| Category    | NDM                               |
| Severity    | Information                       |
| Description | Neighbor Discovery daemon started |

#### Event ID: 6132

|             |                                                                                                        |
|-------------|--------------------------------------------------------------------------------------------------------|
| Message     | Duplicate IPv4 address <ip> is detected on port <port> with a MAC address of <mac>' throttle_count: 40 |
| Category    | NDM                                                                                                    |
| Severity    | Error                                                                                                  |
| Description | Duplicate IP detected from ARP reply                                                                   |

#### Event ID: 6133

|             |                                                                                    |
|-------------|------------------------------------------------------------------------------------|
| Message     | Duplicate IPv6 address <ip> is detected on port <port> with a MAC address of <mac> |
| Category    | NDM                                                                                |
| Severity    | Error                                                                              |
| Description | Duplicate IPv6 address detected from Neighbour advertisement                       |

#### Event ID: 6134

|             |                                                                                                        |
|-------------|--------------------------------------------------------------------------------------------------------|
| Message     | Duplicate IPv4 address <ip> is detected on port <port> with a MAC address of <mac>' throttle_count: 40 |
| Category    | NDM                                                                                                    |
| Severity    | Error                                                                                                  |
| Description | Duplicate IP detected from ARP request                                                                 |

The following are the events related to NTP.

#### Event ID: 1101

|             |                                                                                                           |
|-------------|-----------------------------------------------------------------------------------------------------------|
| Message     | NTP Association <code>&lt;event&gt;</code> : <code>&lt;server&gt;</code> <code>&lt;server_info&gt;</code> |
| Category    | NTP                                                                                                       |
| Severity    | Information                                                                                               |
| Description | Logs NTP Association configuration changes                                                                |

#### Event ID: 1102

|             |                                                                                                           |
|-------------|-----------------------------------------------------------------------------------------------------------|
| Message     | NTP Trusted keys <code>&lt;trusted_keys&gt;</code> and Untrusted keys <code>&lt;untrusted_keys&gt;</code> |
| Category    | NTP                                                                                                       |
| Severity    | Information                                                                                               |
| Description | Logs NTP Trusted and Untrusted authentication-keys                                                        |

#### Event ID: 1103

|             |                                                                                       |
|-------------|---------------------------------------------------------------------------------------|
| Message     | NTP Authentication state change: <code>&lt;old&gt;</code> -> <code>&lt;new&gt;</code> |
| Category    | NTP                                                                                   |
| Severity    | Information                                                                           |
| Description | Logs NTP Authentication state changes                                                 |

#### Event ID: 1104

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | NTP VRF state change: <code>&lt;old&gt;</code> -> <code>&lt;new&gt;</code> |
| Category    | NTP                                                                        |
| Severity    | Information                                                                |
| Description | Logs NTP VRF configuration state changes                                   |

#### Event ID: 1105

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | NTP primary server connection established to <server>       |
| Category    | NTP                                                         |
| Severity    | Information                                                 |
| Description | Logs NTP primary server connection established state change |

#### Event ID: 1106

|             |                                                      |
|-------------|------------------------------------------------------|
| Message     | NTP primary server connection lost to <server>       |
| Category    | NTP                                                  |
| Severity    | Information                                          |
| Description | Logs NTP primary server connection lost state change |

#### Event ID: 1107

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | NTP enable state change: <old> -> <new>                 |
| Category    | NTP                                                     |
| Severity    | Information                                             |
| Description | Event raised when NTP is changed to enabled or disabled |

The following are the events related to OSPFv2.

#### Event ID: 2401

|             |                                                                                 |
|-------------|---------------------------------------------------------------------------------|
| Message     | AdjChg: Nbr <router-id> on <ospf-interface>(<area>): <old_state> -> <new_state> |
| Category    | OSPFv2                                                                          |
| Severity    | Information                                                                     |
| Description | Logs the changes in OSPFv2 neighbour state machine.                             |

#### Event ID: 2402

|             |                                                                                       |
|-------------|---------------------------------------------------------------------------------------|
| Message     | Interface <interface>(<area>) changed from <old_state> to <new_state>, input: <input> |
| Category    | OSPFv2                                                                                |
| Severity    | Information                                                                           |
| Description | Logs the changes in the interface FSM state.                                          |

#### Event ID: 2403

|             |                                       |
|-------------|---------------------------------------|
| Message     | <event> with <destination> <nexthops> |
| Category    | OSPFv2                                |
| Severity    | Information                           |
| Description | Logs OSPFv2 route add and delete.     |

#### Event ID: 2404

|             |                                                                                |
|-------------|--------------------------------------------------------------------------------|
| Message     | AdjChg: Nbr <router-id> on <ospf-interface>: <state> -> <next_state> (<event>) |
| Category    | OSPFv2                                                                         |
| Severity    | Information                                                                    |
| Description | Logs the changes in OSPFv2 neighbour state machine.                            |

#### Event ID: 2405

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | Router-id updated from <code>&lt;old&gt;</code> to <code>&lt;new&gt;</code> |
| Category    | OSPFv2                                                                      |
| Severity    | Information                                                                 |
| Description | Logs the changes in the router-id.                                          |

#### Event ID: 2406

|             |                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------|
| Message     | Failed to <code>&lt;action&gt;</code> <code>&lt;rule&gt;</code> error: <code>&lt;err&gt;</code> |
| Category    | OSPFv2                                                                                          |
| Severity    | Error                                                                                           |
| Description | Logs errors for OSPFv2 FP creation/installation.                                                |

#### Event ID: 2407

|             |                                                                                                                                                      |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | OSPF all routers field entry added: <code>group_id=&lt;group_id&gt;</code> <code>fp_id=&lt;fp_id&gt;</code><br><code>stat_id=&lt;stats_id&gt;</code> |
| Category    | OSPFv2                                                                                                                                               |
| Severity    | Information                                                                                                                                          |
| Description | Logs for OSPFv2 FP creation/installation.                                                                                                            |

#### Event ID: 2408

|             |                                                                                                                                                          |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | OSPF designated routers field entry added: <code>group_id=&lt;group_id&gt;</code> <code>fp_id=&lt;fp_id&gt;</code> <code>stat_id=&lt;stats_id&gt;</code> |
| Category    | OSPFv2                                                                                                                                                   |
| Severity    | Information                                                                                                                                              |
| Description | Logs for OSPFv2 DR FP creation/installation.                                                                                                             |

#### Event ID: 2410

|             |                                                                                                        |
|-------------|--------------------------------------------------------------------------------------------------------|
| Message     | Duplicate router-id for <code>&lt;ospf-interface&gt;</code> from source <code>&lt;source-ip&gt;</code> |
| Category    | OSPFv2                                                                                                 |
| Severity    | Error                                                                                                  |
| Description | Logs when router-id is duplicate.                                                                      |

The following are the events related to OSPFv3.

#### Event ID: 4901

|             |                                                  |
|-------------|--------------------------------------------------|
| Message     | Failed to <action> <rule> error: <err>           |
| Category    | OSPFv3                                           |
| Severity    | Error                                            |
| Description | Logs errors for OSPFv3 FP creation/installation. |

#### Event ID: 4902

|             |                                                                                           |
|-------------|-------------------------------------------------------------------------------------------|
| Message     | OSPF3 all routers field entry added: group_id=<group_id> fp_id=<fp_id> stat_id=<stats_id> |
| Category    | OSPFv3                                                                                    |
| Severity    | Information                                                                               |
| Description | Logs for OSPFv3 FP creation/installation.                                                 |

#### Event ID: 4903

|             |                                                                                                  |
|-------------|--------------------------------------------------------------------------------------------------|
| Message     | OSPF3 designated routers field entry added: group_id=<group_id> fp_id=<fp_id> stat_id=<stats_id> |
| Category    | OSPFv3                                                                                           |
| Severity    | Information                                                                                      |
| Description | Logs for OSPFv3 DR FP creation/installation.                                                     |

#### Event ID: 4904

|             |                                                                                                      |
|-------------|------------------------------------------------------------------------------------------------------|
| Message     | AdjChg: Nbr<router-id> on interface <link-local> on <interface> (<area>): <old_state> -> <new_state> |
| Category    | OSPFv3                                                                                               |
| Severity    | Information                                                                                          |
| Description | Logs the changes in OSPFv3 neighbour state machine.                                                  |

#### Event ID: 4905

|             |                                                                                                                                                                                                             |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Interface <code>&lt;link-local&gt;</code> on <code>&lt;interface&gt;(&lt;area&gt;)</code> changed from <code>&lt;old_state&gt;</code> to <code>&lt;new_state&gt;</code> , input: <code>&lt;input&gt;</code> |
| Category    | OSPFv3                                                                                                                                                                                                      |
| Severity    | Information                                                                                                                                                                                                 |
| Description | Logs the changes in the interface FSM state.                                                                                                                                                                |

### Event ID: 4907

|             |                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------|
| Message     | Duplicate router-id for <code>&lt;link-local&gt;</code> from source <code>&lt;source-ip&gt;</code> |
| Category    | OSPFv3                                                                                             |
| Severity    | Error                                                                                              |
| Description | Logs when router-id is duplicate.                                                                  |

The following are the events related to password reset.

#### Event ID: 5901

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | Password reset succeeded for admin user.                 |
| Category    | Password Reset                                           |
| Severity    | Information                                              |
| Description | Log message when admin user password reset is successful |

#### Event ID: 5902

|             |                                                  |
|-------------|--------------------------------------------------|
| Message     | Password reset failed for admin user.            |
| Category    | Password Reset                                   |
| Severity    | Information                                      |
| Description | Log message when admin user password reset fails |



The following are the events related to PIM.

### Event ID: 5101

|             |                                                                                    |
|-------------|------------------------------------------------------------------------------------|
| Message     | Failed to send <pkt_type> packet on Interface <InterfaceName>' throttle_count: 100 |
| Category    | PIM                                                                                |
| Severity    | Error                                                                              |
| Description | Send error packet                                                                  |

### Event ID: 5102

|             |                                                                  |
|-------------|------------------------------------------------------------------|
| Message     | PIM interface <InterfaceName> is configured with IP <ip_address> |
| Category    | PIM                                                              |
| Severity    | Information                                                      |
| Description | Pim IP config                                                    |

### Event ID: 5103

|             |                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------|
| Message     | Packet dropped from <ip_address> on interface <InterfaceName> <error> <value>' throttle_count: 100 |
| Category    | PIM                                                                                                |
| Severity    | Error                                                                                              |
| Description | Packet dropped                                                                                     |

### Event ID: 5104

|             |                                                                                          |
|-------------|------------------------------------------------------------------------------------------|
| Message     | Received packet from router <ip_address>, unkwn pkt type <pkt_type>' throttle_count: 100 |
| Category    | PIM                                                                                      |
| Severity    | Error                                                                                    |
| Description | Received packet from router                                                              |

### Event ID: 5105

|             |                                                                                                                                                  |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Failed to add flow <dip0>.<dip1>.<dip2>.<dip3>,<br><sip0>.<sip1>.<sip2>.<sip3> (<status> <srcport> <srcvid> <totalvid><br><flowtype> <callerid>) |
| Category    | PIM                                                                                                                                              |
| Severity    | Error                                                                                                                                            |
| Description | Failed to add flow                                                                                                                               |

#### Event ID: 5106

|             |                                                                                                                                               |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Failed to remove flow g <dip0>.<dip1>.<dip2>.<dip3>, s <sip0>,<br><sip1>.<sip2>.<sip3> (<status> <srcport> <srcvid> <flowtype><br><callerid>) |
| Category    | PIM                                                                                                                                           |
| Severity    | Error                                                                                                                                         |
| Description | Failed to remove flow for Hardware                                                                                                            |

#### Event ID: 5107 (Severity: Warning)

|             |                                                                                                                                                       |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Failed to add a mroute for s=<source>, g=<group> on interface<br><interfaceName> as the configured mroute limits are reached' throttle_<br>count: 100 |
| Category    | PIM                                                                                                                                                   |
| Severity    | Warning                                                                                                                                               |
| Description | Failed to program mroute as the limits are reached                                                                                                    |

#### Event ID: 5108 (Severity: Warning)

|             |                                                                                                                                                               |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Failed to add a mroute for s=<source>, g=<group> on interface<br><interfaceName> as the configured sources per group limit is reached'<br>throttle_count: 100 |
| Category    | PIM                                                                                                                                                           |
| Severity    | Warning                                                                                                                                                       |
| Description | Failed to program mroute as the sources per group limit is reached                                                                                            |

#### Event ID: 5109

|          |                                                                              |
|----------|------------------------------------------------------------------------------|
| Message  | This router is elected as the <ip_version> <state> for interface<br><ifname> |
| Category | PIM                                                                          |

|             |                     |
|-------------|---------------------|
| Severity    | Information         |
| Description | PIM DR election log |

#### Event ID: 5110

|             |                                                                                                                           |
|-------------|---------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; &lt;reason&gt; failed with Fd: &lt;fd&gt; on Port: &lt;port&gt;. Error description: &lt;err&gt;</code> |
| Category    | PIM                                                                                                                       |
| Severity    | Error                                                                                                                     |
| Description | Multicast socket creation error                                                                                           |

#### Event ID: 5111

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | OVSDDB operation failed with <code>&lt;err&gt;'</code> throttle_count: 100 |
| Category    | PIM                                                                        |
| Severity    | Error                                                                      |
| Description | DB Operation failed                                                        |

#### Event ID: 5112

|             |                                                                                                                                   |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------|
| Message     | New Elected BSR for VRF <code>&lt;vrf_name&gt;</code> is <code>&lt;ebsr_ip&gt;</code> with priority <code>&lt;priority&gt;</code> |
| Category    | PIM                                                                                                                               |
| Severity    | Information                                                                                                                       |
| Description | Elected BSR                                                                                                                       |

#### Event ID: 5113

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | Elected BSR removed on VRF <code>&lt;vrf_name&gt;</code> |
| Category    | PIM                                                      |
| Severity    | Information                                              |
| Description | Elected BSR removed                                      |

#### Event ID: 5114

|         |                                                                                                                                                                   |
|---------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message | Candidate BSR <code>&lt;ip_address&gt;</code> with priority <code>&lt;priority&gt;</code> is <code>&lt;status&gt;</code> on interface <code>&lt;ifname&gt;</code> |
|---------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------|

|             |                          |
|-------------|--------------------------|
| Category    | PIM                      |
| Severity    | Information              |
| Description | Configured candidate BSR |

### Event ID: 5115

|             |                                                                                                                      |
|-------------|----------------------------------------------------------------------------------------------------------------------|
| Message     | PIM Neighbor <code>&lt;neighbor_ip&gt;</code> is <code>&lt;event&gt;</code> on interface <code>&lt;ifname&gt;</code> |
| Category    | PIM                                                                                                                  |
| Severity    | Information                                                                                                          |
| Description | Neighbor status                                                                                                      |

### Event ID: 5116 (Severity: Warning)

|             |                                                                                                                                                      |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;pkt&gt;</code> packet is discarded on interface <code>&lt;ifname&gt;</code> . Reason: <code>&lt;reason&gt;</code> '<br>throttle_count: 100 |
| Category    | PIM                                                                                                                                                  |
| Severity    | Warning                                                                                                                                              |
| Description | Packet drop                                                                                                                                          |

### Event ID: 5117

|             |                                                                                                                                             |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Forwarding state has changed to <code>&lt;state&gt;</code> on <code>&lt;ip_version&gt;</code> enabled interface <code>&lt;ifname&gt;</code> |
| Category    | PIM                                                                                                                                         |
| Severity    | Information                                                                                                                                 |
| Description | Interface operational status                                                                                                                |

### Event ID: 5118

|             |                                                                                                                                         |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;pim_version&gt;</code> <code>&lt;mode&gt;</code> mode is <code>&lt;status&gt;</code> on interface <code>&lt;ifname&gt;</code> |
| Category    | PIM                                                                                                                                     |
| Severity    | Information                                                                                                                             |
| Description | Interface PIM mode                                                                                                                      |

### Event ID: 5119

|         |                                                                                                          |
|---------|----------------------------------------------------------------------------------------------------------|
| Message | Router <code>&lt;pim_version&gt;</code> is <code>&lt;mode&gt;</code> on VRF <code>&lt;vrfname&gt;</code> |
|---------|----------------------------------------------------------------------------------------------------------|

|             |                                 |
|-------------|---------------------------------|
| Category    | PIM                             |
| Severity    | Information                     |
| Description | Router pim configuration status |

### Event ID: 5120

|             |                                                                                                                 |
|-------------|-----------------------------------------------------------------------------------------------------------------|
| Message     | Candidate RP <code>&lt;ip_address&gt;</code> is <code>&lt;event&gt;</code> on VRF <code>&lt;vrf_name&gt;</code> |
| Category    | PIM                                                                                                             |
| Severity    | Information                                                                                                     |
| Description | Learnt or removed candidate RP                                                                                  |

### Event ID: 5121

|             |                                                                                                                                           |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Software Packet Queue <code>&lt;limit&gt;</code> threshold value <code>&lt;val&gt;</code> reached. Queue size: <code>&lt;qsize&gt;</code> |
| Category    | PIM                                                                                                                                       |
| Severity    | Information                                                                                                                               |
| Description | Software Packet Queue reaches threshold                                                                                                   |

### Event ID: 5122

|             |                                                                                                                                        |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------|
| Message     | This router is elected as the <code>&lt;ip_version&gt;</code> VSX <code>&lt;state&gt;</code> for interface <code>&lt;ifname&gt;</code> |
| Category    | PIM                                                                                                                                    |
| Severity    | Information                                                                                                                            |
| Description | PIM VSX DR Election log                                                                                                                |

### Event ID: 5123

|             |                                                           |
|-------------|-----------------------------------------------------------|
| Message     | VSX ISL Status changed to <code>&lt;isl_status&gt;</code> |
| Category    | PIM                                                       |
| Severity    | Information                                               |
| Description | VSX ISL Status update log                                 |

### Event ID: 5124

|         |                                                                                                     |
|---------|-----------------------------------------------------------------------------------------------------|
| Message | Candidate RP <code>&lt;ip_address&gt;</code> is configured on interface <code>&lt;ifname&gt;</code> |
|---------|-----------------------------------------------------------------------------------------------------|

|             |                         |
|-------------|-------------------------|
| Category    | PIM                     |
| Severity    | Information             |
| Description | Configured candidate RP |

#### Event ID: 5125

|             |                                                                                                           |
|-------------|-----------------------------------------------------------------------------------------------------------|
| Message     | BFD Session created for neighbor <code>&lt;ip_address&gt;</code> on interface <code>&lt;ifname&gt;</code> |
| Category    | PIM                                                                                                       |
| Severity    | Information                                                                                               |
| Description | BFD Session created                                                                                       |

#### Event ID: 5126

|             |                                                                                                           |
|-------------|-----------------------------------------------------------------------------------------------------------|
| Message     | BFD Session deleted for neighbor <code>&lt;ip_address&gt;</code> on interface <code>&lt;ifname&gt;</code> |
| Category    | PIM                                                                                                       |
| Severity    | Information                                                                                               |
| Description | BFD Session deleted                                                                                       |

#### Event ID: 5127

|             |                                                                                                                         |
|-------------|-------------------------------------------------------------------------------------------------------------------------|
| Message     | PIM Resource utilization of <code>&lt;capacity_type&gt;</code> has reached/exceeded the supported limits on the system. |
| Category    | PIM                                                                                                                     |
| Severity    | Information                                                                                                             |
| Description | This log event informs the user that PIM resource utilization has exceeded the supported limits                         |

#### Event ID: 5128

|             |                                                                                                                              |
|-------------|------------------------------------------------------------------------------------------------------------------------------|
| Message     | PIM Resource utilization of <code>&lt;capacity_type&gt;</code> has reached 90 percent of the supported limits on the system. |
| Category    | PIM                                                                                                                          |
| Severity    | Information                                                                                                                  |
| Description | This log event informs the user that PIM resource utilization has reached 90 percent of the supported limits                 |

#### Event ID: 5129

|             |                                                                                                                 |
|-------------|-----------------------------------------------------------------------------------------------------------------|
| Message     | PIM Resource utilization of <capacity_type> has dropped below 90 percent of the supported limits on the system. |
| Category    | PIM                                                                                                             |
| Severity    | Information                                                                                                     |
| Description | This log event informs the user that PIM resource utilization drops below 90 percent of the supported limits    |

The following are the events related to policies.

#### Event ID: 10101

|             |                                                                                 |
|-------------|---------------------------------------------------------------------------------|
| Message     | Policy <i>&lt;policy_name&gt;</i> failed to apply on <i>&lt;application&gt;</i> |
| Category    | Policies                                                                        |
| Severity    | Error                                                                           |
| Description | Policy application failure                                                      |



The following are the events related to port access.

#### Event ID: 10501

|             |                                                                                                        |
|-------------|--------------------------------------------------------------------------------------------------------|
| Message     | Client <code>&lt;mac_address&gt;</code> was logged-off administratively through command-line interface |
| Category    | Port access                                                                                            |
| Severity    | Information                                                                                            |
| Description | Client was logged-off administratively through command-line interface                                  |

#### Event ID: 10502

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | Port <code>&lt;port&gt;</code> is blocked by port-access |
| Category    | Port access                                              |
| Severity    | Information                                              |
| Description | The port is blocked by port-access daemon                |

#### Event ID: 10503

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | Port <code>&lt;port&gt;</code> is unblocked by port-access |
| Category    | Port access                                                |
| Severity    | Information                                                |
| Description | The port is unblocked by port-access daemon                |

#### Event ID: 10504

|             |                                                                                                                                                                          |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Clients were logged-off on the port <code>&lt;port&gt;</code> due to a change in authentication mode from <code>&lt;old_mode&gt;</code> to <code>&lt;new_mode&gt;</code> |
| Category    | Port access                                                                                                                                                              |
| Severity    | Information                                                                                                                                                              |
| Description | The authentication mode associated with the port is changed                                                                                                              |

#### Event ID: 10505

|             |                                                                                                                                                                     |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Clients were logged-off on the port <code>&lt;port&gt;</code> due to a change in client limit from <code>&lt;old_limit&gt;</code> to <code>&lt;new_limit&gt;</code> |
| Category    | Port access                                                                                                                                                         |
| Severity    | Information                                                                                                                                                         |
| Description | The client limit associated with the port is changed                                                                                                                |

#### Event ID: 10506

|             |                                                                                                                                        |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------|
| Message     | The name associated with VLAN <code>&lt;vlan_id&gt;</code> changed from <code>&lt;old_name&gt;</code> to <code>&lt;new_name&gt;</code> |
| Category    | Port access                                                                                                                            |
| Severity    | Information                                                                                                                            |
| Description | The name associated with a VLAN in use by port-access daemon changed                                                                   |

#### Event ID: 10507

|             |                                                                                                                   |
|-------------|-------------------------------------------------------------------------------------------------------------------|
| Message     | Clients using policy <code>&lt;policy_name&gt;</code> were logged-off due to a configuration change in the policy |
| Category    | Port access                                                                                                       |
| Severity    | Information                                                                                                       |
| Description | The policy configuration is updated by the user                                                                   |

#### Event ID: 10508

|             |                                                                                                                   |
|-------------|-------------------------------------------------------------------------------------------------------------------|
| Message     | VLAN conflict detected on port <code>&lt;port&gt;</code>                                                          |
| Category    | Port access                                                                                                       |
| Severity    | Error                                                                                                             |
| Description | VLAN is configured as Trunk for some clients and access for others. This could potentially result in traffic loss |

#### Event ID: 10509

|             |                                                                                                                                   |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------|
| Message     | Client limit exceeded on port <code>&lt;port&gt;</code> , caused by an unauthenticated client <code>&lt;mac_addr&gt;': yes</code> |
| Category    | Port access                                                                                                                       |
| Severity    | Information                                                                                                                       |
| Description | Log event when an intruder is detected on the port                                                                                |

#### Event ID: 10510

|             |                                                                                                                                                                                                                                      |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | All clients except client with MAC address <code>&lt;mac_addr&gt;</code> logged-off on the port <code>&lt;port&gt;</code> due to a change in authentication mode from <code>&lt;old_mode&gt;</code> to <code>&lt;new_mode&gt;</code> |
| Category    | Port access                                                                                                                                                                                                                          |
| Severity    | Information                                                                                                                                                                                                                          |
| Description | The authentication mode associated with the port is changed                                                                                                                                                                          |

The following are the events related to port access roles.

#### Event ID: 9301

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | Failed to apply ClearPass role - <code>&lt;cprole_error_string&gt;</code> |
| Category    | Port access roles                                                         |
| Severity    | Error                                                                     |
| Description | Logs an event if there are errors when applying a ClearPass role          |

#### Event ID: 9302

|             |                                                                                                            |
|-------------|------------------------------------------------------------------------------------------------------------|
| Message     | Failed to create the role - <code>&lt;role_name&gt;</code> , maximum limit reached'<br>throttle_count: 100 |
| Category    | Port access roles                                                                                          |
| Severity    | Error                                                                                                      |
| Description | Logs an event if the maximum limit is reached while creating a Port Access Role                            |

The following are the events related to port.

#### Event ID: 601

|             |                                         |
|-------------|-----------------------------------------|
| Message     | Netlink socket creation failed <error>  |
| Category    | Port                                    |
| Severity    | Information                             |
| Description | Log when netlink socket creation failed |

#### Event ID: 602

|             |                                     |
|-------------|-------------------------------------|
| Message     | Netlink socket bind failed <error>  |
| Category    | Port                                |
| Severity    | Information                         |
| Description | Log when netlink socket bind failed |

#### Event ID: 603

|             |                                                           |
|-------------|-----------------------------------------------------------|
| Message     | Netlink failed to set mtu <mtu> for interface <interface> |
| Category    | Port                                                      |
| Severity    | Information                                               |
| Description | Log when netlink failed to set mtu for interface          |

#### Event ID: 604

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | Netlink failed to bring <status> the interface <interface> |
| Category    | Port                                                       |
| Severity    | Information                                                |
| Description | Log when netlink failed to change the interface status     |

#### Event ID: 605

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | Unknown internal vlan policy <i>&lt;policy&gt;</i> |
| Category    | Port                                               |
| Severity    | Information                                        |
| Description | Unknown internal vlan policy                       |

#### Event ID: 606

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | Error allocating internal vlan for port <i>&lt;vlan&gt;</i> |
| Category    | Port                                                        |
| Severity    | Information                                                 |
| Description | Log when allocation failed for internal vlan for port       |

#### Event ID: 607

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | Overlapping networks observed for <i>&lt;ip_address&gt;</i> |
| Category    | Port                                                        |
| Severity    | Error                                                       |
| Description | Log when a duplicate address is received on a port          |

The following are the events related to port security.

#### Event ID: 9401

|             |                                                                                            |
|-------------|--------------------------------------------------------------------------------------------|
| Message     | Client limit exceeded on port <if_name>, caused by an unauthorized client <mac_addr>': yes |
| Category    | Port security                                                                              |
| Severity    | Information                                                                                |
| Description | Log event when an intruder is detected on the port                                         |

#### Event ID: 9402

|             |                                                                                                                     |
|-------------|---------------------------------------------------------------------------------------------------------------------|
| Message     | Port security sticky client move violation triggered on port <port> for client with MAC address <mac_addr>.'.': yes |
| Category    | Port security                                                                                                       |
| Severity    | Information                                                                                                         |
| Description | Log event when sticky mac is moved to other port                                                                    |

The following are the events related to port statistics.

#### Event ID: 6601

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | Failed to create layer 3 IPv4 RX statistic for port:<name>          |
| Category    | Port Statistics                                                     |
| Severity    | Error                                                               |
| Description | Logs a message when the creation of a Layer 3 IPv4 RX counter fails |

#### Event ID: 6602

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | Failed to create layer 3 IPv6 RX statistic for port:<name>          |
| Category    | Port Statistics                                                     |
| Severity    | Error                                                               |
| Description | Logs a message when the creation of a Layer 3 IPv6 RX counter fails |

#### Event ID: 6603

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | Failed to create layer 3 IPv4 TX statistic for port:<name>          |
| Category    | Port Statistics                                                     |
| Severity    | Error                                                               |
| Description | Logs a message when the creation of a Layer 3 IPv4 TX counter fails |

#### Event ID: 6604

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | Failed to create layer 3 IPv6 TX statistic for port:<name>          |
| Category    | Port Statistics                                                     |
| Severity    | Error                                                               |
| Description | Logs a message when the creation of a Layer 3 IPv6 TX counter fails |



The following are the events related to port access group based policy.

### Event ID: 12601

|             |                                                                                                     |
|-------------|-----------------------------------------------------------------------------------------------------|
| Message     | Configuration change in the policy <code>&lt;pac_gbp_name&gt;</code> <code>&lt;operation&gt;</code> |
| Category    | Port access group based policy                                                                      |
| Severity    | Information                                                                                         |
| Description | The group based policy configuration is updated by the user                                         |

### Event ID: 12602

|             |                                                                                                                         |
|-------------|-------------------------------------------------------------------------------------------------------------------------|
| Message     | Configuration update in the policy due to class change <code>&lt;pac_gbp_name&gt;</code> <code>&lt;operation&gt;</code> |
| Category    | Port access group based policy                                                                                          |
| Severity    | Information                                                                                                             |
| Description | The group based policy class configuration is updated by the user                                                       |

### Event ID: 12603

|             |                                                                                                                                      |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Trigger received to <code>&lt;operation&gt;</code> policy: <code>&lt;pac_gbp_name&gt;</code> for client: <code>&lt;client&gt;</code> |
| Category    | Port access group based policy                                                                                                       |
| Severity    | Information                                                                                                                          |
| Description | The group based policy applying/unapplying for client                                                                                |

### Event ID: 12604

|             |                                                                                                                                                                     |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Trigger received to <code>&lt;operation&gt;</code> policy: <code>&lt;pac_gbp_name&gt;</code> for client: <code>&lt;client&gt;</code> is <code>&lt;result&gt;</code> |
| Category    | Port access group based policy                                                                                                                                      |
| Severity    | Information                                                                                                                                                         |
| Description | The group based policy apply/unapply for client result                                                                                                              |

### Event ID: 12605

|             |                                                                                              |
|-------------|----------------------------------------------------------------------------------------------|
| Message     | Trigger received on <operation> of line_card: <line_card> to <action> policy: <pac_gbp_name> |
| Category    | Port access group based policy                                                               |
| Severity    | Information                                                                                  |
| Description | The group based policy apply/unapply on new linecard                                         |

#### Event ID: 12606

|             |                                                                                                          |
|-------------|----------------------------------------------------------------------------------------------------------|
| Message     | Trigger received on <operation> of line_card: <line_card> to <action> policy: <pac_gbp_name> is <result> |
| Category    | Port access group based policy                                                                           |
| Severity    | Information                                                                                              |
| Description | The group based policy apply/unapply on new linecard result                                              |

The following are the events related to power.

#### Event ID: 301

|             |                                     |
|-------------|-------------------------------------|
| Message     | PSU <name> changed state to <state> |
| Category    | Power                               |
| Severity    | Information                         |
| Description | Log the change in PSU status.       |

#### Event ID: 302 (Severity: Warning)

|             |                                                                                   |
|-------------|-----------------------------------------------------------------------------------|
| Message     | PSUs inserted in the system are of <Type> types. This is <Support> configuration. |
| Category    | Power                                                                             |
| Severity    | Warning                                                                           |
| Description | Log the identification of mixed PSU types                                         |

#### Event ID: 303

|             |                                                                   |
|-------------|-------------------------------------------------------------------|
| Message     | PSU <name> encountered a warning. Total warning count: <warnings> |
| Category    | Power                                                             |
| Severity    | Error                                                             |
| Description | Log the warnings encountered by the PSU                           |

#### Event ID: 304

|             |                                                   |
|-------------|---------------------------------------------------|
| Message     | PSU <name> faulted. Total fault count: <failures> |
| Category    | Power                                             |
| Severity    | Error                                             |
| Description | Log the failures encountered by the PSU           |

#### Event ID: 305 (Severity: Warning)

|             |                                             |
|-------------|---------------------------------------------|
| Message     | PSU <name>: Internal communication <status> |
| Category    | Power                                       |
| Severity    | Warning                                     |
| Description | Log PSU internal communication failure      |

#### Event ID: 306 (Severity: Warning)

|             |                                   |
|-------------|-----------------------------------|
| Message     | PSU <name>: Fan-<fanidx> <status> |
| Category    | Power                             |
| Severity    | Warning                           |
| Description | Log PSU fan fault                 |

#### Event ID: 307 (Severity: Warning)

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | PSU <name>: <sensorid> sensor <status> threshold limit |
| Category    | Power                                                  |
| Severity    | Warning                                                |
| Description | Log when PSU temperature sensor exceeded threshold     |

#### Event ID: 308

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | PSU <name> has shutdown due to over temperature in <sensorid> sensor |
| Category    | Power                                                                |
| Severity    | Error                                                                |
| Description | Log when PSU temperature sensor triggered PSU shutdown               |

#### Event ID: 309 (Severity: Warning)

|             |                                                     |
|-------------|-----------------------------------------------------|
| Message     | PSU <name>: Output current <status> threshold limit |
| Category    | Power                                               |
| Severity    | Warning                                             |
| Description | Log when PSU output current exceeds threshold       |

#### Event ID: 310

|         |                                                   |
|---------|---------------------------------------------------|
| Message | PSU <name> has shutdown due to output overcurrent |
|---------|---------------------------------------------------|

|             |                                                    |
|-------------|----------------------------------------------------|
| Category    | Power                                              |
| Severity    | Error                                              |
| Description | Log when PSU output current triggered PSU shutdown |

### Event ID: 311

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | PSU <code>&lt;name&gt;</code> has shutdown due to output overvoltage |
| Category    | Power                                                                |
| Severity    | Error                                                                |
| Description | Log when PSU output voltage triggered PSU shutdown                   |

### Event ID: 312

|             |                                                       |
|-------------|-------------------------------------------------------|
| Message     | PSU Redundancy set to <code>&lt;redund&gt;</code>     |
| Category    | Power                                                 |
| Severity    | Information                                           |
| Description | Log a change in the PSU redundancy user configuration |

### Event ID: 313

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | PSU Redundancy operating at <code>&lt;redund&gt;</code> |
| Category    | Power                                                   |
| Severity    | Information                                             |
| Description | Log a change in the PSU redundancy operational state    |

### Event ID: 314 (Severity: Warning)

|             |                                                                                   |
|-------------|-----------------------------------------------------------------------------------|
| Message     | PSU <code>&lt;name&gt;</code> disabled: PSU airflow does not match system-airflow |
| Category    | Power                                                                             |
| Severity    | Warning                                                                           |
| Description | Log when PSU is disabled due to airflow direction mismatch                        |

### Event ID: 315

|          |                                                                 |
|----------|-----------------------------------------------------------------|
| Message  | PSU <code>&lt;name&gt;</code> disabled: PSU communication error |
| Category | Power                                                           |

|             |                                                     |
|-------------|-----------------------------------------------------|
| Severity    | Error                                               |
| Description | Log when PSU is disabled due to communication error |

### Event ID: 316 (Severity: Warning)

|             |                                                                                                                                                                   |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; module &lt;name&gt; denied power due to insufficient power. Configured PoE power can be deconfigured to allow card to be granted power.</code> |
| Category    | Power                                                                                                                                                             |
| Severity    | Warning                                                                                                                                                           |
| Description | There is insufficient power to power a card. Power can be removed from configured PoE PDs to be able to power the card.                                           |

### Event ID: 317 (Severity: Warning)

|             |                                                                                     |
|-------------|-------------------------------------------------------------------------------------|
| Message     | <code>PSU &lt;name&gt; disabled: PSU inserted is not supported by the system</code> |
| Category    | Power                                                                               |
| Severity    | Warning                                                                             |
| Description | Log when PSU is disabled due to an unsupported PSU                                  |

### Event ID: 318

|             |                                                     |
|-------------|-----------------------------------------------------|
| Message     | <code>Power over Ethernet status has faulted</code> |
| Category    | Power                                               |
| Severity    | Error                                               |
| Description | Log 54V Power over Ethernet status fault            |

### Event ID: 319

|             |                                                 |
|-------------|-------------------------------------------------|
| Message     | <code>Power over Ethernet status is good</code> |
| Category    | Power                                           |
| Severity    | Information                                     |
| Description | Log 54V Power over Ethernet status is good      |

### Event ID: 320

|          |                                                      |
|----------|------------------------------------------------------|
| Message  | <code>PSU &lt;name&gt; &lt;alert&gt; occurred</code> |
| Category | Power                                                |

|             |                                   |
|-------------|-----------------------------------|
| Severity    | Error                             |
| Description | Log when PSU voltage alert occurs |

#### Event ID: 321

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | PSU <i>&lt;name&gt;</i> <i>&lt;alert&gt;</i> recovered |
| Category    | Power                                                  |
| Severity    | Information                                            |
| Description | Log when PSU voltage alert recovers                    |

#### Event ID: 322 (Severity: Warning)

|             |                                                                  |
|-------------|------------------------------------------------------------------|
| Message     | Invalid PoE power configuration, using default maximum PoE power |
| Category    | Power                                                            |
| Severity    | Warning                                                          |
| Description | Log when configured PoE power is invalid                         |

The following are the events related to power over Ethernet.

### Event ID: 7901

|             |                                                                                                                                                      |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Detected powered device on interface <code>&lt;interface_name&gt;</code> . Type: <code>&lt;pd_type&gt;</code> , Class: <code>&lt;pd_class&gt;</code> |
| Category    | Power over Ethernet                                                                                                                                  |
| Severity    | Information                                                                                                                                          |
| Description | Detected powered device on interface. Type, Class.                                                                                                   |

### Event ID: 7902

|             |                                                                                |
|-------------|--------------------------------------------------------------------------------|
| Message     | Powered device power delivery on interface <code>&lt;interface_name&gt;</code> |
| Category    | Power over Ethernet                                                            |
| Severity    | Information                                                                    |
| Description | Powered device power delivery on interface.                                    |

### Event ID: 7903 (Severity: Warning)

|             |                                                                              |
|-------------|------------------------------------------------------------------------------|
| Message     | Powered device power denied on interface <code>&lt;interface_name&gt;</code> |
| Category    | Power over Ethernet                                                          |
| Severity    | Warning                                                                      |
| Description | Powered device power denied on interface.                                    |

### Event ID: 7904 (Severity: Warning)

|             |                                                                                                                    |
|-------------|--------------------------------------------------------------------------------------------------------------------|
| Message     | Powered device fault on interface <code>&lt;interface_name&gt;</code> . Fault type <code>&lt;fault_type&gt;</code> |
| Category    | Power over Ethernet                                                                                                |
| Severity    | Warning                                                                                                            |
| Description | Powered device fault on interface. Fault type.                                                                     |

### Event ID: 7905



|             |                                                                              |
|-------------|------------------------------------------------------------------------------|
| Message     | Powered device disconnected on interface <code>&lt;interface_name&gt;</code> |
| Category    | Power over Ethernet                                                          |
| Severity    | Information                                                                  |
| Description | Powered device disconnected on interface.                                    |

#### Event ID: 7906

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | PoE disabled on interface <code>&lt;interface_name&gt;</code> |
| Category    | Power over Ethernet                                           |
| Severity    | Information                                                   |
| Description | PoE disabled on interface                                     |

#### Event ID: 7907

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | Powered device mps absent on interface <code>&lt;interface_name&gt;</code> |
| Category    | Power over Ethernet                                                        |
| Severity    | Information                                                                |
| Description | Powered device mps absent on interface                                     |

#### Event ID: 7908

|             |                                                                                                                                                                                                                       |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Detected dual signature powered device on interface <code>&lt;interface_name&gt;</code> .<br>Type: <code>&lt;pd_type&gt;</code> , ClassA: <code>&lt;paira_class&gt;</code> , ClassB: <code>&lt;pairb_class&gt;</code> |
| Category    | Power over Ethernet                                                                                                                                                                                                   |
| Severity    | Information                                                                                                                                                                                                           |
| Description | Detected dual signature powered device on interface. Type, ClassA, ClassB                                                                                                                                             |

#### Event ID: 7909

|             |                                                                                               |
|-------------|-----------------------------------------------------------------------------------------------|
| Message     | Dual signature powered device power delivery on interface <code>&lt;interface_name&gt;</code> |
| Category    | Power over Ethernet                                                                           |
| Severity    | Information                                                                                   |
| Description | Dual signature powered device power delivery on interface.                                    |

#### Event ID: 7910 (Severity: Warning)

|             |                                                                                                        |
|-------------|--------------------------------------------------------------------------------------------------------|
| Message     | Dual signature powered device fault on interface <interface_name> pair <pair>. Fault type <fault_type> |
| Category    | Power over Ethernet                                                                                    |
| Severity    | Warning                                                                                                |
| Description | Dual signature powered device fault on interface. Fault type.                                          |

#### Event ID: 7911

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | Dual signature powered device mps absent on interface <interface_name> |
| Category    | Power over Ethernet                                                    |
| Severity    | Information                                                            |
| Description | Dual signature powered device mps absent on interface                  |

#### Event ID: 7912

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | Powered device FET bad fault recovered on interface <interface_name> |
| Category    | Power over Ethernet                                                  |
| Severity    | Information                                                          |
| Description | Powered device FET bad fault recovered on interface                  |

#### Event ID: 7913

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | Powered device FET bad fault recovery failed on interface <interface_name> |
| Category    | Power over Ethernet                                                        |
| Severity    | Information                                                                |
| Description | Powered device FET bad fault recovery failed on interface                  |

#### Event ID: 7914

|             |                                                                                                                             |
|-------------|-----------------------------------------------------------------------------------------------------------------------------|
| Message     | Powered device got class demoted on interface <interface_name>. Requested_class <req_class> Assigned_class <assigned_class> |
| Category    | Power over Ethernet                                                                                                         |
| Severity    | Information                                                                                                                 |
| Description | Powered device got class demoted on interface                                                                               |

#### Event ID: 7915

|             |                                                                                                                                                                                                                                                                                                                    |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Dual signature powered device got class demoted on interface <code>&lt;interface_name&gt;</code> . Requested_classA <code>&lt;req_class_A&gt;</code> Requested_classB <code>&lt;req_class_B&gt;</code> Assigned_classA <code>&lt;assigned_class_A&gt;</code> Assigned_classB <code>&lt;assigned_class_B&gt;</code> |
| Category    | Power over Ethernet                                                                                                                                                                                                                                                                                                |
| Severity    | Information                                                                                                                                                                                                                                                                                                        |
| Description | Dual signature powered device got class demoted on interface                                                                                                                                                                                                                                                       |

#### Event ID: 7916

|             |                                                                                        |
|-------------|----------------------------------------------------------------------------------------|
| Message     | Powered device pre std detect enabled on interface <code>&lt;interface_name&gt;</code> |
| Category    | Power over Ethernet                                                                    |
| Severity    | Information                                                                            |
| Description | Powered device pre std detect enabled on interface                                     |

#### Event ID: 7917

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | PoE usage exceeded threshold limit of <code>&lt;threshold_limit&gt;</code> |
| Category    | Power over Ethernet                                                        |
| Severity    | Information                                                                |
| Description | PoE usage exceeded threshold limit                                         |

#### Event ID: 7918

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | PoE controller <code>&lt;cntrl_name&gt;</code> got into fault |
| Category    | Power over Ethernet                                           |
| Severity    | Information                                                   |
| Description | PoE controller got into fault                                 |

#### Event ID: 7919

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | PoE controller <code>&lt;cntrl_name&gt;</code> got reset |
| Category    | Power over Ethernet                                      |
| Severity    | Information                                              |
| Description | PoE controller got reset                                 |

#### Event ID: 7920

|             |                                                                                                                             |
|-------------|-----------------------------------------------------------------------------------------------------------------------------|
| Message     | Powered device got class promoted on interface <interface_name>.Requested_class <req_class> Assigned_class <assigned_class> |
| Category    | Power over Ethernet                                                                                                         |
| Severity    | Information                                                                                                                 |
| Description | Powered device got class promoted                                                                                           |

#### Event ID: 7921

|             |                                                                                                                                                                                                                    |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Dual signature powered device got class promoted on interface <interface_name>.Requested_classA <req_class_A> Requested_classB <req_class_B> Assigned_classA <assigned_class_A> Assigned_classB <assigned_class_B> |
| Category    | Power over Ethernet                                                                                                                                                                                                |
| Severity    | Information                                                                                                                                                                                                        |
| Description | Dual signature powered device got class promoted                                                                                                                                                                   |

#### Event ID: 7922

|             |                                                                                                                                                                                                                                                                       |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Powered device is drawing power more than its class on interface <interface_name>, type:<pd_type> class:<pd_class> power:<power> is exceeding the max average power of the PD class. Check the PD max power draw, cabling type and length to improve interoperability |
| Category    | Power over Ethernet                                                                                                                                                                                                                                                   |
| Severity    | Information                                                                                                                                                                                                                                                           |
| Description | Powered device is drawing power more than its class                                                                                                                                                                                                                   |

#### Event ID: 7923

|             |                                                                                                           |
|-------------|-----------------------------------------------------------------------------------------------------------|
| Message     | Powered device UVLO fault on interface <interface_name>, will attempt to recover itself by toggling power |
| Category    | Power over Ethernet                                                                                       |
| Severity    | Information                                                                                               |
| Description | Powered device UVLO fault on interface                                                                    |

#### Event ID: 7924

|          |                                                            |
|----------|------------------------------------------------------------|
| Message  | Powered device FET BAD fault on interface <interface_name> |
| Category | Power over Ethernet                                        |

|             |                              |
|-------------|------------------------------|
| Severity    | Information                  |
| Description | Powered device FET BAD fault |

#### Event ID: 7925

|             |                                                                                                                                                                                                                                                                              |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Dual signature powered device is drawing power more than its class on interface <code>&lt;interface_name&gt;</code> , type: <code>&lt;pd_type&gt;</code> classA: <code>&lt;paira_class&gt;</code> classB: <code>&lt;pairb_class&gt;</code> power: <code>&lt;power&gt;</code> |
| Category    | Power over Ethernet                                                                                                                                                                                                                                                          |
| Severity    | Information                                                                                                                                                                                                                                                                  |
| Description | Dual signature powered device is drawing power more than its class                                                                                                                                                                                                           |

#### Event ID: 7926

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | PoE usage is below threshold of <code>&lt;threshold_limit&gt;</code> |
| Category    | Power over Ethernet                                                  |
| Severity    | Information                                                          |
| Description | PoE usage is below threshold                                         |

#### Event ID: 7927 (Severity: Warning)

|             |                                                                                                                                                                                                                                           |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Total power drawn: <code>&lt;power_drawn&gt;</code> W by powered device is exceeding the total available PoE power: <code>&lt;power_available&gt;</code> W. Check the PD max power draw, cabling type and length to avoid system crowbar. |
| Category    | Power over Ethernet                                                                                                                                                                                                                       |
| Severity    | Warning                                                                                                                                                                                                                                   |
| Description | PoE drawn power is more than available PoE power                                                                                                                                                                                          |

#### Event ID: 7928 (Severity: Warning)

|             |                                                                                                |
|-------------|------------------------------------------------------------------------------------------------|
| Message     | Powered device invalid signature indication on interface <code>&lt;interface_name&gt;</code> . |
| Category    | Power over Ethernet                                                                            |
| Severity    | Warning                                                                                        |
| Description | Powered device invalid signature indication                                                    |

#### Event ID: 7929

|             |                                    |
|-------------|------------------------------------|
| Message     | PoE hardware access daemon exiting |
| Category    | Power over Ethernet                |
| Severity    | Information                        |
| Description | PoE hardware access daemon exiting |

#### Event ID: 7930

|             |                          |
|-------------|--------------------------|
| Message     | POE proto daemon exiting |
| Category    | Power over Ethernet      |
| Severity    | Information              |
| Description | POE proto daemon exiting |

#### Event ID: 7931

|             |                                                                                                        |
|-------------|--------------------------------------------------------------------------------------------------------|
| Message     | Always-on PoE detected a powered device on interface <i>&lt;interface_name&gt;</i> and delivered power |
| Category    | Power over Ethernet                                                                                    |
| Severity    | Information                                                                                            |
| Description | Always-on PoE detected a powered device on interface                                                   |

#### Event ID: 7932

|             |                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------|
| Message     | Powered device disconnected on interface <i>&lt;interface_name&gt;</i> due to LLDP dot3 disable |
| Category    | Power over Ethernet                                                                             |
| Severity    | Information                                                                                     |
| Description | Powered device disconnected on interface due to LLDP dot3 disable                               |

#### Event ID: 7933

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | Subsystem <i>&lt;subsys_name&gt;</i> came up with quick PoE |
| Category    | Power over Ethernet                                         |
| Severity    | Information                                                 |
| Description | Subsystem came up with quick PoE                            |

#### Event ID: 7934

|             |                                                                                                          |
|-------------|----------------------------------------------------------------------------------------------------------|
| Message     | Quick PoE detected a powered device on interface <code>&lt;interface_name&gt;</code> and delivered power |
| Category    | Power over Ethernet                                                                                      |
| Severity    | Information                                                                                              |
| Description | Quick PoE detected a powered device on interface                                                         |

#### Event ID: 7935 (Severity: Warning)

|             |                                                                                                                                                         |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Powered device denied on interface <code>&lt;interface_name&gt;</code> of line module with Quick PoE enabled. Remove device to avoid crowbar on reboot. |
| Category    | Power over Ethernet                                                                                                                                     |
| Severity    | Warning                                                                                                                                                 |
| Description | Powered device denied on interface of line module with Quick PoE enabled.                                                                               |

#### Event ID: 7936 (Severity: Warning)

|             |                                                                                                                                                          |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Powered device demoted on interface <code>&lt;interface_name&gt;</code> of line module with Quick PoE enabled. Remove device to avoid crowbar on reboot. |
| Category    | Power over Ethernet                                                                                                                                      |
| Severity    | Warning                                                                                                                                                  |
| Description | Powered device demoted on interface of line module with Quick PoE enabled                                                                                |

#### Event ID: 7937 (Severity: Warning)

|             |                                                                                                   |
|-------------|---------------------------------------------------------------------------------------------------|
| Message     | PoE disable ignored on interface <code>&lt;interface_name&gt;</code> because Quick PoE is enabled |
| Category    | Power over Ethernet                                                                               |
| Severity    | Warning                                                                                           |
| Description | PoE disable ignored on interface because Quick PoE is enabled                                     |

#### Event ID: 7938 (Severity: Warning)

|             |                                                                                                                           |
|-------------|---------------------------------------------------------------------------------------------------------------------------|
| Message     | PoE assigned class configuration is ignored on interface <code>&lt;interface_name&gt;</code> because Quick PoE is enabled |
| Category    | Power over Ethernet                                                                                                       |
| Severity    | Warning                                                                                                                   |
| Description | PoE assigned class configuration is ignored on interface because Quick PoE is enabled                                     |

#### Event ID: 7939

|             |                                                                                 |
|-------------|---------------------------------------------------------------------------------|
| Message     | Powered device requested power down on interface <interface_name><br><duration> |
| Category    | Power over Ethernet                                                             |
| Severity    | Information                                                                     |
| Description | Powered device requested power down on interface.                               |

### Event ID: 7940

|             |                                                                                                  |
|-------------|--------------------------------------------------------------------------------------------------|
| Message     | Powered device disconnected on interface <interface_name> due to pd-class-override config change |
| Category    | Power over Ethernet                                                                              |
| Severity    | Information                                                                                      |
| Description | Powered device disconnected on interface due to pd-class-override config change                  |



The following are the events related to PTP.

#### Event ID: 12101

|             |                                                                                                                              |
|-------------|------------------------------------------------------------------------------------------------------------------------------|
| Message     | PTP <code>&lt;type&gt;</code> <code>&lt;delay_mechanism&gt;</code> clock started with profile <code>&lt;profile&gt;</code> . |
| Category    | PTP                                                                                                                          |
| Severity    | Information                                                                                                                  |
| Description | Event reported when PTP clock is started.                                                                                    |

#### Event ID: 12102

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | PTP clock stopped. Reason: <code>&lt;reason&gt;</code> |
| Category    | PTP                                                    |
| Severity    | Information                                            |
| Description | Event reported when PTP clock is stopped.              |

#### Event ID: 12103

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | Interface <code>&lt;name&gt;</code> enabled for PTP exchange. |
| Category    | PTP                                                           |
| Severity    | Information                                                   |
| Description | Event reported when PTP port is enabled for tx and rx.        |

#### Event ID: 12104

|             |                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------|
| Message     | Interface <code>&lt;name&gt;</code> disabled for PTP exchange. Reason: <code>&lt;reason&gt;</code> |
| Category    | PTP                                                                                                |
| Severity    | Information                                                                                        |
| Description | Event reported when PTP enabled port is disabled.                                                  |

#### Event ID: 12105

|             |                                                  |
|-------------|--------------------------------------------------|
| Message     | PTP clock is in <code>&lt;state&gt;</code> state |
| Category    | PTP                                              |
| Severity    | Information                                      |
| Description | Event reported for different PTP clock state.    |

#### Event ID: 12106

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | Interface <code>&lt;name&gt;</code> is in <code>&lt;state&gt;</code> state |
| Category    | PTP                                                                        |
| Severity    | Information                                                                |
| Description | Event reported for different PTP port state.                               |

#### Event ID: 12107

|             |                                                                                                                                                                                                                                                         |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | New GrandSource/Parent is selected: Parent: <code>&lt;parent&gt;</code> , GrandSource: <code>&lt;grandsource&gt;</code> , Quality: <code>&lt;quality&gt;</code> , Priority1: <code>&lt;priority1&gt;</code> , Priority2: <code>&lt;priority2&gt;</code> |
| Category    | PTP                                                                                                                                                                                                                                                     |
| Severity    | Information                                                                                                                                                                                                                                             |
| Description | Event reported when PTP parent is updated/modified.                                                                                                                                                                                                     |

#### Event ID: 12108

|             |                                                                                                                                                                |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | PTP operational log_announce_interval is changed to <code>&lt;value&gt;</code> on interface <code>&lt;name&gt;</code> for profile <code>&lt;profile&gt;</code> |
| Category    | PTP                                                                                                                                                            |
| Severity    | Information                                                                                                                                                    |
| Description | Event reported when PTP log announce interval is modified.                                                                                                     |

#### Event ID: 12109

|             |                                                                                                                                                                          |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | PTP operational log_min_pdelay_request_interval is changed to <code>&lt;value&gt;</code> on interface <code>&lt;name&gt;</code> for profile <code>&lt;profile&gt;</code> |
| Category    | PTP                                                                                                                                                                      |
| Severity    | Information                                                                                                                                                              |
| Description | Event reported when PTP log min pdelay request interval is modified.                                                                                                     |

#### Event ID: 12110

|             |                                                                                                                |
|-------------|----------------------------------------------------------------------------------------------------------------|
| Message     | PTP operational log_min_delay_request_interval is changed to <value> on interface <name> for profile <profile> |
| Category    | PTP                                                                                                            |
| Severity    | Information                                                                                                    |
| Description | Event reported when PTP log min delay request interval is modified.                                            |

#### Event ID: 12111

|             |                                                                                                      |
|-------------|------------------------------------------------------------------------------------------------------|
| Message     | PTP operational sync_request_timeout is changed to <value> on interface <name> for profile <profile> |
| Category    | PTP                                                                                                  |
| Severity    | Information                                                                                          |
| Description | Event reported when PTP sync request timeout is modified.                                            |

#### Event ID: 12112

|             |                                                                                               |
|-------------|-----------------------------------------------------------------------------------------------|
| Message     | PTP operational sync_interval is changed to <value> on interface <name> for profile <profile> |
| Category    | PTP                                                                                           |
| Severity    | Information                                                                                   |
| Description | Event reported when PTP sync interval is modified.                                            |

#### Event ID: 12113

|             |                                                                                                          |
|-------------|----------------------------------------------------------------------------------------------------------|
| Message     | PTP operational announce_request_timeout is changed to <value> on interface <name> for profile <profile> |
| Category    | PTP                                                                                                      |
| Severity    | Information                                                                                              |
| Description | Event reported when PTP announce request timeout is modified.                                            |

#### Event ID: 12114

|             |                                                 |
|-------------|-------------------------------------------------|
| Message     | PTP config invalid. Reason: <reason>            |
| Category    | PTP                                             |
| Severity    | Information                                     |
| Description | Event reported if PTP configuration is invalid. |

The following are the events related to quality of service ASIC provider.

#### Event ID: 5801 (Severity: Warning)

|             |                                                                                                                |
|-------------|----------------------------------------------------------------------------------------------------------------|
| Message     | QoS failed initial initialization for slot <code>&lt;local_slot&gt;</code> . Error: <code>&lt;error&gt;</code> |
| Category    | QoS ASIC Provider                                                                                              |
| Severity    | Warning                                                                                                        |
| Description | QoS initial initialization failed                                                                              |

#### Event ID: 5802 (Severity: Critical)

|             |                                                                                                                            |
|-------------|----------------------------------------------------------------------------------------------------------------------------|
| Message     | QoS failed final initialization on new slot <code>&lt;new_slot&gt;</code> for peer slot <code>&lt;existing_slot&gt;</code> |
| Category    | QoS ASIC Provider                                                                                                          |
| Severity    | Critical                                                                                                                   |
| Description | QoS final initialization failed for new slot                                                                               |

#### Event ID: 5803

|             |                                                                  |
|-------------|------------------------------------------------------------------|
| Message     | QoS error after card removal from slot <code>&lt;slot&gt;</code> |
| Category    | QoS ASIC Provider                                                |
| Severity    | Error                                                            |
| Description | QoS error after card removal                                     |

#### Event ID: 5804

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | Error during QoS feature configuration: <code>&lt;error_string&gt;</code> |
| Category    | QoS ASIC Provider                                                         |
| Severity    | Error                                                                     |
| Description | Error while attempting QoS feature configuration                          |

#### Event ID: 5805

|             |                                                                                        |
|-------------|----------------------------------------------------------------------------------------|
| Message     | Error during QoS HW configuration: <code>&lt;error_string&gt; error &lt;val&gt;</code> |
| Category    | QoS ASIC Provider                                                                      |
| Severity    | Error                                                                                  |
| Description | Error while attempting QoS HW configuration                                            |

### Event ID: 5806 (Severity: Warning)

|             |                                                                                                                                                                               |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Port: <code>&lt;port_name&gt;</code> PFC priority <code>&lt;pri&gt;</code> using queue <code>&lt;queue&gt;</code> should not be sharing the queue with other local-priorities |
| Category    | QoS ASIC Provider                                                                                                                                                             |
| Severity    | Warning                                                                                                                                                                       |
| Description | Warning PFC priority sharing a queue                                                                                                                                          |

The following are the events related to quality of service.

### Event ID: 5701

|             |                                                                               |
|-------------|-------------------------------------------------------------------------------|
| Message     | QoS failed to retrieve default information. Error: <code>&lt;error&gt;</code> |
| Category    | Quality of Service                                                            |
| Severity    | Information                                                                   |
| Description | QoS failed to retrieve default configuration                                  |

### Event ID: 5702

|             |                                              |
|-------------|----------------------------------------------|
| Message     | QoS error: <code>&lt;error_string&gt;</code> |
| Category    | Quality of Service                           |
| Severity    | Error                                        |
| Description | QoS error occurred                           |

### Event ID: 5703 (Severity: Warning)

|             |                                                                                                                                                                |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | The PFC configuration for interface <code>&lt;ifname&gt;</code> exceeds the system limit of <code>&lt;limit&gt;</code> unique combinations and was not applied |
| Category    | Quality of Service                                                                                                                                             |
| Severity    | Warning                                                                                                                                                        |
| Description | Logged when there are more unique combinations of flow controlled priorities than the system allows.                                                           |

## Chapter 88

# Rapid per VLAN Spanning Tree Protocol events

The following are the events related to rapid per VLAN spanning tree protocol.

### Event ID: 5001

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | RPVST Enabled                                                       |
| Category    | Rapid per VLAN Spanning Tree Protocol                               |
| Severity    | Information                                                         |
| Description | This log event indicates that RPVST has been enabled on the switch. |

### Event ID: 5002

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | RPVST Disabled                                                       |
| Category    | Rapid per VLAN Spanning Tree Protocol                                |
| Severity    | Information                                                          |
| Description | This log event indicates that RPVST has been disabled on the switch. |

### Event ID: 5003

|             |                                                                                                                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | RPVST - Root changed from <code>&lt;old_priority&gt;</code> : <code>&lt;old_mac&gt;</code> to <code>&lt;new_priority&gt;</code> : <code>&lt;new_mac&gt;</code> on VLAN <code>&lt;vlan&gt;</code> . |
| Category    | Rapid per VLAN Spanning Tree Protocol                                                                                                                                                              |
| Severity    | Information                                                                                                                                                                                        |
| Description | This log event indicates that RPVST root on a VLAN has changed                                                                                                                                     |

### Event ID: 5004 (Severity: Warning)

|             |                                                                                                               |
|-------------|---------------------------------------------------------------------------------------------------------------|
| Message     | Port <code>&lt;port&gt;</code> disabled - BPDU received on protected port on VLAN <code>&lt;vlan&gt;</code> . |
| Category    | Rapid per VLAN Spanning Tree Protocol                                                                         |
| Severity    | Warning                                                                                                       |
| Description | This log event informs the user BPDU received on protected port                                               |

### Event ID: 5005

|             |                                                                                                                              |
|-------------|------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;proto&gt; starved for &lt;pkt_type&gt; on port &lt;port&gt; from &lt;priority_mac&gt; on VLAN &lt;vlan&gt;.</code> |
| Category    | Rapid per VLAN Spanning Tree Protocol                                                                                        |
| Severity    | Information                                                                                                                  |
| Description | This log event informs the user that the Rx is starved in particular port                                                    |

#### Event ID: 5006

|             |                                                                                                           |
|-------------|-----------------------------------------------------------------------------------------------------------|
| Message     | <code>Topology change received on port &lt;port&gt; from source: &lt;mac&gt; on VLAN &lt;vlan&gt;.</code> |
| Category    | Rapid per VLAN Spanning Tree Protocol                                                                     |
| Severity    | Information                                                                                               |
| Description | This log event informs the user that the RPVST topology change is received                                |

#### Event ID: 5007

|             |                                                                                   |
|-------------|-----------------------------------------------------------------------------------|
| Message     | <code>Topology change generated on port &lt;port&gt; on VLAN &lt;vlan&gt;.</code> |
| Category    | Rapid per VLAN Spanning Tree Protocol                                             |
| Severity    | Information                                                                       |
| Description | This log event informs the user that the RPVST topology change is generated       |

#### Event ID: 5008 (Severity: Warning)

|             |                                                                          |
|-------------|--------------------------------------------------------------------------|
| Message     | <code>Port &lt;port&gt; blocked on RPVST &lt;instance&gt;</code>         |
| Category    | Rapid per VLAN Spanning Tree Protocol                                    |
| Severity    | Warning                                                                  |
| Description | This log event informs the user that the port is blocked on the instance |

#### Event ID: 5009 (Severity: Warning)

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | <code>Port &lt;port&gt; unblocked on RPVST &lt;instance&gt;</code>         |
| Category    | Rapid per VLAN Spanning Tree Protocol                                      |
| Severity    | Warning                                                                    |
| Description | This log event informs the user that the port is unblocked on the instance |

#### Event ID: 5010



|             |                                                                                                                           |
|-------------|---------------------------------------------------------------------------------------------------------------------------|
| Message     | Root port changed from <code>&lt;old_port&gt;</code> to <code>&lt;new_port&gt;</code> on VLAN <code>&lt;vlan&gt;</code> . |
| Category    | Rapid per VLAN Spanning Tree Protocol                                                                                     |
| Severity    | Information                                                                                                               |
| Description | This log event informs the user that the root port is changed                                                             |

#### Event ID: 5011

|             |                                                                                                                                                                   |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | PVID mismatch detected on <code>&lt;interface&gt;</code> with pvid = <code>&lt;pvid&gt;</code> , Neighbor pvid = <code>&lt;npvid&gt;</code> ' throttle_count: 100 |
| Category    | Rapid per VLAN Spanning Tree Protocol                                                                                                                             |
| Severity    | Information                                                                                                                                                       |
| Description | Log event when the PVID mismatches between the switch and neighbor over an interface                                                                              |

#### Event ID: 5012

|             |                                                                                                                                    |
|-------------|------------------------------------------------------------------------------------------------------------------------------------|
| Message     | spanning tree mode changed from <code>&lt;old_mode&gt;</code> to <code>&lt;new_mode&gt;</code> , it will trigger the reconvergence |
| Category    | Rapid per VLAN Spanning Tree Protocol                                                                                              |
| Severity    | Information                                                                                                                        |
| Description | This log event informs the user that the spanning tree mode is changed.                                                            |

#### Event ID: 5013

|             |                                                                                                                                             |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Current Virtual Ports <code>&lt;Current_Virtual_Ports&gt;</code> exceeds the max supported limit <code>&lt;Maximum_Virtual_Ports&gt;</code> |
| Category    | Rapid per VLAN Spanning Tree Protocol                                                                                                       |
| Severity    | Information                                                                                                                                 |
| Description | Log event when the current virtual port count crosses the maximum allowed value                                                             |

The following are the events related to RBAC.

#### Event ID: 10301

|             |                                                       |
|-------------|-------------------------------------------------------|
| Message     | Local authorization has been <tac_status>d            |
| Category    | RBAC                                                  |
| Severity    | Information                                           |
| Description | Log event when local tac_plus server has been started |

#### Event ID: 10302

|             |                                                      |
|-------------|------------------------------------------------------|
| Message     | Failed to <tac_status> local authorization           |
| Category    | RBAC                                                 |
| Severity    | Error                                                |
| Description | Log event when local tac_plus server failed to start |

The following are the events related to redundant management.

### Event ID: 2201

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | Failover detected: Reason <i>&lt;reason&gt;</i>        |
| Category    | Redundant Management                                   |
| Severity    | Information                                            |
| Description | This log event informs that failover event is detected |

### Event ID: 2202

|             |                                                                                   |
|-------------|-----------------------------------------------------------------------------------|
| Message     | Lost <i>&lt;mgmt_module&gt;</i> as Standby Management Module, redundancy disabled |
| Category    | Redundant Management                                                              |
| Severity    | Information                                                                       |
| Description | This log event informs that standby mgmt module has been removed                  |

### Event ID: 2203

|             |                                                                  |
|-------------|------------------------------------------------------------------|
| Message     | Detected the removal of the Standby Management Module            |
| Category    | Redundant Management                                             |
| Severity    | Information                                                      |
| Description | This log event informs that standby mgmt module has been removed |

### Event ID: 2204

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | <i>&lt;mgmt_module&gt;</i> is Active                          |
| Category    | Redundant Management                                          |
| Severity    | Information                                                   |
| Description | This log event informs about the status of Active mgmt module |

### Event ID: 2205

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | <code>&lt;mgmt_module&gt; is Standby</code>                    |
| Category    | Redundant Management                                           |
| Severity    | Information                                                    |
| Description | This log event informs about the status of Standby mgmt module |

### Event ID: 2206

|             |                                                                                            |
|-------------|--------------------------------------------------------------------------------------------|
| Message     | <code>Detected &lt;mgmt_module&gt; as Standby Management Module, redundancy enabled</code> |
| Category    | Redundant Management                                                                       |
| Severity    | Information                                                                                |
| Description | This log event informs that standby mgmt module is added to the system                     |

### Event ID: 2207

|             |                                                                                        |
|-------------|----------------------------------------------------------------------------------------|
| Message     | <code>Remote Standby Management module recover detected. Reason: Heartbeat loss</code> |
| Category    | Redundant Management                                                                   |
| Severity    | Information                                                                            |
| Description | This log event informs the user that Active mgmt module has detected heartbeat loss    |

### Event ID: 2208

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | <code>&lt;mgmt_module&gt; is waiting for filesync</code>     |
| Category    | Redundant Management                                         |
| Severity    | Information                                                  |
| Description | This log event informs the user that filesync is in progress |

### Event ID: 2209

|             |                                                                  |
|-------------|------------------------------------------------------------------|
| Message     | <code>&lt;mgmt_module&gt; is starting ISSU operation</code>      |
| Category    | Redundant Management                                             |
| Severity    | Information                                                      |
| Description | This log event informs the user that an ISSU operation has begun |

The following are the events related to replication manager.

### Event ID: 2701 (Severity: Warning)

|             |                                                 |
|-------------|-------------------------------------------------|
| Message     | All bitmaps have been allocated                 |
| Category    | Replication Manager                             |
| Severity    | Warning                                         |
| Description | Log to indicate all bitmaps have been allocated |

### Event ID: 2702 (Severity: Warning)

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | Over 80 percent of bitmaps have been allocated                 |
| Category    | Replication Manager                                            |
| Severity    | Warning                                                        |
| Description | Log to indicate over 80 percent of bitmaps have been allocated |

### Event ID: 2705 (Severity: Warning)

|             |                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------|
| Message     | Multicast L3 Bridge Control Forwarding entry with uuid <uuid_str> has no reference to a VLAN    |
| Category    | Replication Manager                                                                             |
| Severity    | Warning                                                                                         |
| Description | Log indicates Mutlicast L3 Bridge Control Forwarding entry with uuid has no reference to a VLAN |

The following are the events related to REST.

#### Event ID: 4601

|             |                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------|
| Message     | Authentication failed for user <code>&lt;user&gt;</code> in session <code>&lt;sessionid&gt;</code> |
| Category    | REST                                                                                               |
| Severity    | Error                                                                                              |
| Description | logs a failed authentication attempt of a user via REST                                            |

#### Event ID: 4602

|             |                                                                                                       |
|-------------|-------------------------------------------------------------------------------------------------------|
| Message     | Authentication succeeded for user <code>&lt;user&gt;</code> in session <code>&lt;sessionid&gt;</code> |
| Category    | REST                                                                                                  |
| Severity    | Information                                                                                           |
| Description | logs a successful authentication attempt of a user via REST                                           |

#### Event ID: 4603 (Severity: Critical)

|             |                                                                                                                                                                                                                 |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Conflict in authorization configuration. Existing config::URL( <code>&lt;match&gt;</code> ), type( <code>&lt;value&gt;</code> ) New config::( <code>&lt;url&gt;</code> ), type( <code>&lt;autztype&gt;</code> ) |
| Category    | REST                                                                                                                                                                                                            |
| Severity    | Critical                                                                                                                                                                                                        |
| Description | logs an authorization configuration conflict                                                                                                                                                                    |

#### Event ID: 4604

|             |                                                                                             |
|-------------|---------------------------------------------------------------------------------------------|
| Message     | Session started for user <code>&lt;user&gt;</code> , session <code>&lt;sessionid&gt;</code> |
| Category    | REST                                                                                        |
| Severity    | Information                                                                                 |
| Description | logs the start of a REST user session                                                       |

#### Event ID: 4605

|             |                                                                                           |
|-------------|-------------------------------------------------------------------------------------------|
| Message     | Session ended for user <code>&lt;user&gt;</code> , session <code>&lt;sessionid&gt;</code> |
| Category    | REST                                                                                      |
| Severity    | Information                                                                               |
| Description | logs the end of a REST user session                                                       |

#### Event ID: 4606

|             |                                                                                                                                                |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Authorization failed for user <code>&lt;user&gt;</code> , for resource <code>&lt;resource&gt;</code> , with action <code>&lt;action&gt;</code> |
| Category    | REST                                                                                                                                           |
| Severity    | Error                                                                                                                                          |
| Description | logs a failed authorization attempt of a user via REST                                                                                         |

#### Event ID: 4607

|             |                                                                                                                                                   |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Authorization succeeded for user <code>&lt;user&gt;</code> , for resource <code>&lt;resource&gt;</code> , with action <code>&lt;action&gt;</code> |
| Category    | REST                                                                                                                                              |
| Severity    | Information                                                                                                                                       |
| Description | logs a successful authorization attempt of a user via REST                                                                                        |

#### Event ID: 4608

|             |                                                                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Authorization allowed for user <code>&lt;user&gt;</code> , for resource <code>&lt;resource&gt;</code> , with action <code>&lt;action&gt;</code> |
| Category    | REST                                                                                                                                            |
| Severity    | Information                                                                                                                                     |
| Description | logs an allowed authorization attempt of a user via REST                                                                                        |

#### Event ID: 4609

|             |                                                                                                                     |
|-------------|---------------------------------------------------------------------------------------------------------------------|
| Message     | User <code>&lt;user&gt;</code> added <code>&lt;added_user&gt;</code> with role <code>&lt;added_user_role&gt;</code> |
| Category    | REST                                                                                                                |
| Severity    | Information                                                                                                         |
| Description | logs a successful add of a user via REST                                                                            |

#### Event ID: 4610

|             |                                               |
|-------------|-----------------------------------------------|
| Message     | User <user> deleted <deleted_user>            |
| Category    | REST                                          |
| Severity    | Information                                   |
| Description | logs a successful deletion of a user via REST |

#### Event ID: 4611

|             |                                                       |
|-------------|-------------------------------------------------------|
| Message     | User <user> successfully changed password             |
| Category    | REST                                                  |
| Severity    | Information                                           |
| Description | logs a successful password change for a user via REST |

#### Event ID: 4612 (Severity: Warning)

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | User <user> password change failed                       |
| Category    | REST                                                     |
| Severity    | Warning                                                  |
| Description | logs an unsuccessful password change for a user via REST |

#### Event ID: 4613

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | <user> has written a new switch configuration to <config_name> |
| Category    | REST                                                           |
| Severity    | Information                                                    |
| Description | logs a success config write operation                          |

#### Event ID: 4614

|             |                                                                 |
|-------------|-----------------------------------------------------------------|
| Message     | <user> has copied switch configuration <from_name> to <to_name> |
| Category    | REST                                                            |
| Severity    | Information                                                     |
| Description | logs a success copy of saved                                    |

#### Event ID: 4615

|         |                                                                |
|---------|----------------------------------------------------------------|
| Message | <user> has configured <dns_nameserver> DNS nameserver to <dns> |
|---------|----------------------------------------------------------------|



|             |                                                         |
|-------------|---------------------------------------------------------|
| Category    | REST                                                    |
| Severity    | Information                                             |
| Description | logs a success when the nameserver is written to ovssdb |

### Event ID: 4616

|             |                                                           |
|-------------|-----------------------------------------------------------|
| Message     | <code>&lt;user&gt; has deleted all DNS nameservers</code> |
| Category    | REST                                                      |
| Severity    | Information                                               |
| Description | logs a success when the nameserver is deleted from ovssdb |

### Event ID: 4617

|             |                                                           |
|-------------|-----------------------------------------------------------|
| Message     | <code>&lt;user&gt; created &lt;uri&gt;</code>             |
| Category    | REST                                                      |
| Severity    | Information                                               |
| Description | A user has successfully created a new resource in OVSSDB. |

### Event ID: 4618

|             |                                                       |
|-------------|-------------------------------------------------------|
| Message     | <code>&lt;user&gt; deleted &lt;uri&gt;</code>         |
| Category    | REST                                                  |
| Severity    | Information                                           |
| Description | A user has successfully deleted a resource in OVSSDB. |

### Event ID: 4619

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | <code>&lt;user&gt; modified &lt;uri&gt;</code>         |
| Category    | REST                                                   |
| Severity    | Information                                            |
| Description | A user has successfully modified a resource in OVSSDB. |

### Event ID: 4620

|          |                                                                       |
|----------|-----------------------------------------------------------------------|
| Message  | <code>User: &lt;user&gt; added subscriber: &lt;subscriber&gt;.</code> |
| Category | REST                                                                  |

|             |                                               |
|-------------|-----------------------------------------------|
| Severity    | Information                                   |
| Description | A user has added new notification subscriber. |

#### Event ID: 4621

|             |                                                |
|-------------|------------------------------------------------|
| Message     | User: <user> removed subscriber: <subscriber>. |
| Category    | REST                                           |
| Severity    | Information                                    |
| Description | A user has removed notification subscriber.    |

#### Event ID: 4622

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | Subscriber: <subscriber> added subscription: <subscription>. |
| Category    | REST                                                         |
| Severity    | Information                                                  |
| Description | A subscriber has added new subscription.                     |

#### Event ID: 4623

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | Subscriber: <subscriber> removed subscription: <subscription>. |
| Category    | REST                                                           |
| Severity    | Information                                                    |
| Description | A subscriber has removed subscription.                         |

#### Event ID: 4624 (Severity: Warning)

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | Unable to add new subscriber. Max number of subscribers has been reached. |
| Category    | REST                                                                      |
| Severity    | Warning                                                                   |
| Description | Unable to add new subscriber as max number reached.                       |

#### Event ID: 4625 (Severity: Warning)

|          |                                                                                                |
|----------|------------------------------------------------------------------------------------------------|
| Message  | Unable to add new subscription. Max number of subscriptions for <subscriber> has been reached. |
| Category | REST                                                                                           |

|             |                                                                                    |
|-------------|------------------------------------------------------------------------------------|
| Severity    | Warning                                                                            |
| Description | Unable to add new subscription as max number reached for the specified subscriber. |

#### Event ID: 4626

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | NAE Script <name> has been created by user <user>. |
| Category    | REST                                               |
| Severity    | Information                                        |
| Description | NAE Script has been created successfully.          |

#### Event ID: 4627

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | NAE Script <name> has been deleted by user <user>. |
| Category    | REST                                               |
| Severity    | Information                                        |
| Description | NAE Script has been deleted successfully.          |

#### Event ID: 4628

|             |                                                   |
|-------------|---------------------------------------------------|
| Message     | NAE Agent <name> has been created by user <user>. |
| Category    | REST                                              |
| Severity    | Information                                       |
| Description | NAE Agent has been created successfully.          |

#### Event ID: 4629

|             |                                                   |
|-------------|---------------------------------------------------|
| Message     | NAE Agent <name> has been updated by user <user>. |
| Category    | REST                                              |
| Severity    | Information                                       |
| Description | NAE Agent has been updated successfully.          |

#### Event ID: 4630

|             |                                                   |
|-------------|---------------------------------------------------|
| Message     | NAE Agent <name> has been deleted by user <user>. |
| Category    | REST                                              |
| Severity    | Information                                       |
| Description | NAE Agent has been deleted successfully.          |

**Event ID: 4631**

|             |                                                                                                                   |
|-------------|-------------------------------------------------------------------------------------------------------------------|
| Message     | Error rebooting switch, reboot command: <code>&lt;command&gt;</code> , error received: <code>&lt;error&gt;</code> |
| Category    | REST                                                                                                              |
| Severity    | Error                                                                                                             |
| Description | Logs an error if a reboot fails.                                                                                  |

**Event ID: 4632**

|             |                                                                                                                                                                                                |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Connection to Aruba Central on location <code>&lt;central_location&gt;</code> on VRF <code>&lt;vrf&gt;</code> with Source IP <code>&lt;source_ip&gt;</code> has been successfully established. |
| Category    | REST                                                                                                                                                                                           |
| Severity    | Information                                                                                                                                                                                    |
| Description | Connection is established with Aruba Central.                                                                                                                                                  |

**Event ID: 4633**

|             |                                                                                                                                                                                                                                                            |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Connection to Aruba Central on location <code>&lt;central_location&gt;</code> on VRF <code>&lt;vrf&gt;</code> and Source IP <code>&lt;source_ip&gt;</code> has been closed by Aruba Central. Requesting new Aruba Central location from CLI/DHCP/Activate. |
| Category    | REST                                                                                                                                                                                                                                                       |
| Severity    | Information                                                                                                                                                                                                                                                |
| Description | Connection to Aruba Central has been closed by Aruba Central. Request to get new location from CLI/DHCP/Activate.                                                                                                                                          |

**Event ID: 4634**

|             |                                                                                                                                                                                                                   |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Connection to Aruba Central on location <code>&lt;central_location&gt;</code> on VRF <code>&lt;vrf&gt;</code> and Source IP <code>&lt;source_ip&gt;</code> has been closed by Aruba Central. Trying to reconnect. |
| Category    | REST                                                                                                                                                                                                              |
| Severity    | Information                                                                                                                                                                                                       |
| Description | Connection to Aruba Central has been closed by Aruba Central. Trying to reconnect.                                                                                                                                |

**Event ID: 4635**

|         |                                                                                                                                                     |
|---------|-----------------------------------------------------------------------------------------------------------------------------------------------------|
| Message | Received Aruba Central location <code>&lt;central_location&gt;</code> on VRF <code>&lt;vrf&gt;</code> with Source IP <code>&lt;source_ip&gt;</code> |
|---------|-----------------------------------------------------------------------------------------------------------------------------------------------------|

|             |                                      |
|-------------|--------------------------------------|
| Category    | REST                                 |
| Severity    | Information                          |
| Description | Received new Aruba Central location. |

#### Event ID: 4636

|             |                                                                                                                                                                                                                       |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Received new Aruba Central location. Closing existing connection with Aruba Central on location <code>&lt;central_location&gt;</code> on VRF <code>&lt;vrf&gt;</code> with Source IP <code>&lt;source_ip&gt;</code> . |
| Category    | REST                                                                                                                                                                                                                  |
| Severity    | Information                                                                                                                                                                                                           |
| Description | Received new Aruba Central location. Closing existing connection with Aruba Central.                                                                                                                                  |

#### Event ID: 4637

|             |                                                                                                                                                                                       |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Internal error. Closing connection to Aruba Central on location <code>&lt;central_location&gt;</code> on VRF <code>&lt;vrf&gt;</code> with Source IP <code>&lt;source_ip&gt;</code> . |
| Category    | REST                                                                                                                                                                                  |
| Severity    | Error                                                                                                                                                                                 |
| Description | Internal error. Closing connection to Aruba Central.                                                                                                                                  |

#### Event ID: 4638

|             |                                                                                          |
|-------------|------------------------------------------------------------------------------------------|
| Message     | Waiting for Aruba Central location from CLI/DHCP/Aruba Activate Server.                  |
| Category    | REST                                                                                     |
| Severity    | Information                                                                              |
| Description | Waiting for Aruba Central location from Central Source (CLI/DHCP/Aruba Activate Server). |

#### Event ID: 4639

|             |                                                                                                                                                               |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Connecting to Aruba Central on location <code>&lt;central_location&gt;</code> on VRF <code>&lt;vrf&gt;</code> with Source IP <code>&lt;source_ip&gt;</code> . |
| Category    | REST                                                                                                                                                          |
| Severity    | Information                                                                                                                                                   |
| Description | Connecting to Aruba Central.                                                                                                                                  |

#### Event ID: 4640

|             |                                                                                                                                                                    |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Failed to connect to Aruba Central on location <code>&lt;central_location&gt;</code> on VRF <code>&lt;vrf&gt;</code> with Source IP <code>&lt;source_ip&gt;</code> |
| Category    | REST                                                                                                                                                               |
| Severity    | Error                                                                                                                                                              |
| Description | Failed to connect to Aruba Central.                                                                                                                                |

#### Event ID: 4641

|             |                                        |
|-------------|----------------------------------------|
| Message     | Aruba Central is disabled.             |
| Category    | REST                                   |
| Severity    | Information                            |
| Description | The Aruba Central feature is disabled. |

#### Event ID: 4642

|             |                                                                                                                                                                                                |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Aruba Central is disabled. Closing connection to Aruba Central on location <code>&lt;central_location&gt;</code> on VRF <code>&lt;vrf&gt;</code> with Source IP <code>&lt;source_ip&gt;</code> |
| Category    | REST                                                                                                                                                                                           |
| Severity    | Information                                                                                                                                                                                    |
| Description | The Aruba Central feature is disabled.                                                                                                                                                         |

#### Event ID: 4643

|             |                                       |
|-------------|---------------------------------------|
| Message     | Aruba Central is enabled.             |
| Category    | REST                                  |
| Severity    | Information                           |
| Description | The Aruba Central feature is enabled. |

#### Event ID: 4645

|             |                                                                                                             |
|-------------|-------------------------------------------------------------------------------------------------------------|
| Message     | Aruba Activate server <code>&lt;activate_address&gt;</code> is reachable via VRF <code>&lt;vrf&gt;</code> . |
| Category    | REST                                                                                                        |
| Severity    | Information                                                                                                 |
| Description | Aruba Activate server is reachable via an active VRF.                                                       |

#### Event ID: 4646

|             |                                                                                      |
|-------------|--------------------------------------------------------------------------------------|
| Message     | Aruba Activate server <activate_address> is not reachable through any supported VRF. |
| Category    | REST                                                                                 |
| Severity    | Information                                                                          |
| Description | Aruba Activate server is not reachable through any supported VRF.                    |

#### Event ID: 4647

|             |                                         |
|-------------|-----------------------------------------|
| Message     | Switch time is synced with NTP Servers. |
| Category    | REST                                    |
| Severity    | Information                             |
| Description | Switch time is synced with NTP Servers. |

#### Event ID: 4648

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | Switch time is synced with Aruba Activate Server <activate_address>. |
| Category    | REST                                                                 |
| Severity    | Information                                                          |
| Description | Switch time is synced with Aruba Activate Server.                    |

#### Event ID: 4649

|             |                                                                                         |
|-------------|-----------------------------------------------------------------------------------------|
| Message     | Unable to sync switch time with Aruba Activate Server <activate_address> via VRF <vrf>. |
| Category    | REST                                                                                    |
| Severity    | Error                                                                                   |
| Description | Unable to sync switch time with Aruba Activate Server.                                  |

#### Event ID: 4650

|             |                                                                                                |
|-------------|------------------------------------------------------------------------------------------------|
| Message     | Unable to fetch Aruba Central location <central_location> from <central_source> via VRF <vrf>. |
| Category    | REST                                                                                           |
| Severity    | Information                                                                                    |
| Description | Unable to fetch Aruba Central location from Central Source (CLI/DHCP/Aruba Activate Server).   |

#### Event ID: 4651

|             |                                                                                                                                                             |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Aruba Central location <code>&lt;central_location&gt;</code> successfully fetched from <code>&lt;central_source&gt;</code> via VRF <code>&lt;vrf&gt;</code> |
| Category    | REST                                                                                                                                                        |
| Severity    | Information                                                                                                                                                 |
| Description | Aruba Central location successfully fetched from Central Source (CLI/DHCP/Aruba Activate Server) via VRF.                                                   |

#### Event ID: 4652 (Severity: Warning)

|             |                                                                                                                                                                                         |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Aruba Central connected, any config change through rest <code>&lt;rest_operation&gt;</code> operation may not be persistent. If central reapplies the config, change can be overwritten |
| Category    | REST                                                                                                                                                                                    |
| Severity    | Warning                                                                                                                                                                                 |
| Description | Aruba Central connected, any config change through rest may not be persistent, aruba central can overwrite the change                                                                   |

#### Event ID: 4653

|             |                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------|
| Message     | User <code>&lt;user&gt;</code> has configured <code>&lt;mode&gt;</code> for configuration lockdown |
| Category    | REST                                                                                               |
| Severity    | Information                                                                                        |
| Description | Logs a message when a user changes the REST configuration lockdown mode                            |

#### Event ID: 4654

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | Aruba Central support mode is <code>&lt;mode&gt;</code> for a vtysh session |
| Category    | REST                                                                        |
| Severity    | Information                                                                 |
| Description | Logs a message when a Aruba Central support mode is enabled or disabled     |



The following are the events related to self test.

#### Event ID: 4501

|             |                                                                  |
|-------------|------------------------------------------------------------------|
| Message     | Selftest has started on subsystem <code>&lt;subsystem&gt;</code> |
| Category    | Self Test                                                        |
| Severity    | Information                                                      |
| Description | logs the start of selftest on a particular subsystem             |

#### Event ID: 4502

|             |                                                                    |
|-------------|--------------------------------------------------------------------|
| Message     | Selftest has completed on subsystem <code>&lt;subsystem&gt;</code> |
| Category    | Self Test                                                          |
| Severity    | Information                                                        |
| Description | logs the completion of selftest on a particular subsystem          |

#### Event ID: 4503

|             |                                                                                                                  |
|-------------|------------------------------------------------------------------------------------------------------------------|
| Message     | Selftest has failed on subsystem <code>&lt;subsystem&gt;</code> with error code <code>&lt;value&gt;': yes</code> |
| Category    | Self Test                                                                                                        |
| Severity    | Error                                                                                                            |
| Description | logs the selftest failure of a particular subsystem                                                              |

#### Event ID: 4504

|             |                                                                                                                                   |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------|
| Message     | Selftest has failed on <code>&lt;stack&gt;/&lt;slot&gt;/&lt;interface&gt;</code> with error code <code>&lt;value&gt;': yes</code> |
| Category    | Self Test                                                                                                                         |
| Severity    | Error                                                                                                                             |
| Description | logs the port selftest failure on a given subsystem                                                                               |

The following are the events related to sFlow.

#### Event ID: 1001

|             |                                                                                       |
|-------------|---------------------------------------------------------------------------------------|
| Message     | Failed to <code>&lt;operation&gt;</code> host sFlow agent: <code>&lt;error&gt;</code> |
| Category    | sFlow                                                                                 |
| Severity    | Error                                                                                 |
| Description | Log a failure when trying to start/stop/restart host sFlow daemon.                    |

#### Event ID: 1002

|             |                                                                                                                               |
|-------------|-------------------------------------------------------------------------------------------------------------------------------|
| Message     | Failed to <code>&lt;operation&gt;</code> host sFlow configuration file <code>&lt;file&gt;</code> : <code>&lt;error&gt;</code> |
| Category    | sFlow                                                                                                                         |
| Severity    | Error                                                                                                                         |
| Description | Log a failure when trying to read/write to host sFlow configuration file.                                                     |

#### Event ID: 1003

|             |                                                                                                                                   |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------|
| Message     | Failed to <code>&lt;operation&gt;</code> sFlow configuration from bridge <code>&lt;bridge&gt;</code> : <code>&lt;error&gt;</code> |
| Category    | sFlow                                                                                                                             |
| Severity    | Error                                                                                                                             |
| Description | Log a failure when trying to configure sFlow on SIM OVS.                                                                          |

#### Event ID: 1004

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | Failed to delete all iptable rules: <code>&lt;error&gt;</code>         |
| Category    | sFlow                                                                  |
| Severity    | Error                                                                  |
| Description | Log a failure when trying to delete all iptable rules added for sFlow. |

#### Event ID: 1005

|             |                                                                                                                                              |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Failed to <code>&lt;operation&gt;</code> <code>&lt;chain&gt;</code> iptable rules for <code>&lt;port&gt;</code> : <code>&lt;error&gt;</code> |
| Category    | sFlow                                                                                                                                        |
| Severity    | Error                                                                                                                                        |
| Description | Log a failure when trying to add/delete an iptable rule for sFlow.                                                                           |

#### Event ID: 1006

|             |                                              |
|-------------|----------------------------------------------|
| Message     | sFlow initialization failed.                 |
| Category    | sFlow                                        |
| Severity    | Error                                        |
| Description | Logs an error if sFlow initialization fails. |

#### Event ID: 1007

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | Invalid packet sent by ASIC in sFlow callback.         |
| Category    | sFlow                                                  |
| Severity    | Error                                                  |
| Description | Logs an error for an invalid packet in sFlow callback. |

#### Event ID: 1008

|             |                                                                   |
|-------------|-------------------------------------------------------------------|
| Message     | Unable to get netdev for interface <code>&lt;interface&gt;</code> |
| Category    | sFlow                                                             |
| Severity    | Error                                                             |
| Description | Logs an error if an interface does not have a netdev class.       |

#### Event ID: 1009

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | Failed to create KNET filter as description is blank          |
| Category    | sFlow                                                         |
| Severity    | Error                                                         |
| Description | Logs an error if the description to create a filter is blank. |

#### Event ID: 1010

|         |                                                             |
|---------|-------------------------------------------------------------|
| Message | Failed to create KNET filter for: <code>&lt;desc&gt;</code> |
|---------|-------------------------------------------------------------|

|             |                                                    |
|-------------|----------------------------------------------------|
| Category    | sFlow                                              |
| Severity    | Error                                              |
| Description | Logs an error if sFlow KNET filter creation fails. |

#### Event ID: 1011

|             |                                          |
|-------------|------------------------------------------|
| Message     | The received sampled packet is null      |
| Category    | sFlow                                    |
| Severity    | Error                                    |
| Description | Logs an error if sampled packet is null. |

#### Event ID: 1012

|             |                                                  |
|-------------|--------------------------------------------------|
| Message     | The sFlow agent is not initialized               |
| Category    | sFlow                                            |
| Severity    | Error                                            |
| Description | Logs an error if sFlow agent is not initialized. |

#### Event ID: 1013

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | The sFlow sampler is not initialized               |
| Category    | sFlow                                              |
| Severity    | Error                                              |
| Description | Logs an error if sFlow sampler is not initialized. |

#### Event ID: 1014

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | Cannot enable/disable sFlow on an invalid port: <port>         |
| Category    | sFlow                                                          |
| Severity    | Error                                                          |
| Description | Logs an error if sFlow is enabled/disabled on an invalid port. |

#### Event ID: 1015

|          |                                                |
|----------|------------------------------------------------|
| Message  | sFlow sampler is not available on port: <port> |
| Category | sFlow                                          |

|             |                                                      |
|-------------|------------------------------------------------------|
| Severity    | Error                                                |
| Description | Logs an error if sFlow sampler is missing on a port. |

#### Event ID: 1016

|             |                                                   |
|-------------|---------------------------------------------------|
| Message     | sFlow receiver is not available                   |
| Category    | sFlow                                             |
| Severity    | Error                                             |
| Description | Logs an error if sFlow receiver is not available. |

#### Event ID: 1017

|             |                                                       |
|-------------|-------------------------------------------------------|
| Message     | Failed to retrieve port configuration: <error>        |
| Category    | sFlow                                                 |
| Severity    | Error                                                 |
| Description | Logs an error if port configuration is not available. |

#### Event ID: 1018

|             |                                                           |
|-------------|-----------------------------------------------------------|
| Message     | Failed to set sampling rate on port <port>: <error>       |
| Category    | sFlow                                                     |
| Severity    | Error                                                     |
| Description | Logs an error if setting a sampling rate on a port fails. |

#### Event ID: 1019

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | Failed to get sampling rate on port <port>: <error>          |
| Category    | sFlow                                                        |
| Severity    | Error                                                        |
| Description | Logs an error if unable to retrieve sampling rate on a port. |

#### Event ID: 1020

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | Invalid agent interface IP address: <ip_address>                           |
| Category    | sFlow                                                                      |
| Severity    | Error                                                                      |
| Description | Logs an error in case of invalid agent interface IP address configuration. |

**Event ID: 1021**

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | Invalid collector IP address: <code>&lt;ip_address&gt;</code>        |
| Category    | sFlow                                                                |
| Severity    | Error                                                                |
| Description | Logs an error in case of invalid collector IP address configuration. |

**Event ID: 1022**

|             |                                                                                                                                   |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------|
| Message     | Failed to get interface statistics for unit <code>&lt;unit&gt;</code> port <code>&lt;port&gt;</code> : <code>&lt;error&gt;</code> |
| Category    | sFlow                                                                                                                             |
| Severity    | Error                                                                                                                             |
| Description | Logs an error if unable to retrieve interface statistics.                                                                         |

**Event ID: 1023**

|             |                               |
|-------------|-------------------------------|
| Message     | sFlow agent created.          |
| Category    | sFlow                         |
| Severity    | Information                   |
| Description | Logs creation of sFlow agent. |

**Event ID: 1024**

|             |                               |
|-------------|-------------------------------|
| Message     | sFlow agent deleted.          |
| Category    | sFlow                         |
| Severity    | Information                   |
| Description | Logs deletion of sFlow agent. |

**Event ID: 1025**

|             |                                                                                                   |
|-------------|---------------------------------------------------------------------------------------------------|
| Message     | Changed sFlow sampling rate from <code>&lt;old_rate&gt;</code> to <code>&lt;new_rate&gt;</code> . |
| Category    | sFlow                                                                                             |
| Severity    | Information                                                                                       |
| Description | Logs a change in sFlow sampling rate.                                                             |

**Event ID: 1026**

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | Set sFlow agents header len to <code>&lt;hdrlen&gt;</code> . |
| Category    | sFlow                                                        |
| Severity    | Information                                                  |
| Description | Logs sFlow agents header length event.                       |

#### Event ID: 1027

|             |                                                       |
|-------------|-------------------------------------------------------|
| Message     | Set sFlow agents IP to <code>&lt;ip_addr&gt;</code> . |
| Category    | sFlow                                                 |
| Severity    | Information                                           |
| Description | Logs setting IP address to sFlow agent.               |

#### Event ID: 1028

|             |                                                                          |
|-------------|--------------------------------------------------------------------------|
| Message     | Set max datagram size on sFlow agent to <code>&lt;dgramsize&gt;</code> . |
| Category    | sFlow                                                                    |
| Severity    | Information                                                              |
| Description | Log setting max datagram size on sFlow agent.                            |

#### Event ID: 1029

|             |                                                                                                                                       |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Add sFlow poller on <code>&lt;port_name&gt;</code> with ifIndex <code>&lt;ifIndex&gt;</code> at interval <code>&lt;intvl&gt;</code> . |
| Category    | sFlow                                                                                                                                 |
| Severity    | Information                                                                                                                           |
| Description | Add sFlow poller on a port.                                                                                                           |

#### Event ID: 1030

|             |                                                       |
|-------------|-------------------------------------------------------|
| Message     | Remove sFlow poller on <code>&lt;ifIndex&gt;</code> . |
| Category    | sFlow                                                 |
| Severity    | Information                                           |
| Description | Delete sFlow poller on a port.                        |

#### Event ID: 1031

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | Set polling interval of <i>&lt;intvl&gt;</i> on sFlow agent. |
| Category    | sFlow                                                        |
| Severity    | Information                                                  |
| Description | Set polling interval for sFlow agent.                        |

## Event ID: 1032

|             |                                                  |
|-------------|--------------------------------------------------|
| Message     | sFlow sampling mode set to <i>&lt;mode&gt;</i> . |
| Category    | sFlow                                            |
| Severity    | Information                                      |
| Description | Logs change in sFlow mode.                       |



The following are the events related to SFTP client.

#### Event ID: 5301

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | SFTP file transfer from <i>&lt;from&gt;</i> to <i>&lt;to&gt;</i> completed. |
| Category    | SFTP Client                                                                 |
| Severity    | Information                                                                 |
| Description | SFTP file transfer completed                                                |

#### Event ID: 5302

|             |                                                                                                   |
|-------------|---------------------------------------------------------------------------------------------------|
| Message     | SFTP file transfer from <i>&lt;from&gt;</i> to <i>&lt;to&gt;</i> failed - <i>&lt;status&gt;</i> . |
| Category    | SFTP Client                                                                                       |
| Severity    | Information                                                                                       |
| Description | SFTP file transfer failed                                                                         |

The following are the events related to smartlink.

#### Event ID: 11301

|             |                                                                                     |
|-------------|-------------------------------------------------------------------------------------|
| Message     | Flush message received on <i>&lt;ifName&gt;</i> with control VLAN <i>&lt;id&gt;</i> |
| Category    | Smartlink                                                                           |
| Severity    | Information                                                                         |
| Description | Event raised when flush message received on interface with control vlan             |

#### Event ID: 11302

|             |                                                                                       |
|-------------|---------------------------------------------------------------------------------------|
| Message     | Active link of the smartlink group <i>&lt;id&gt;</i> changed to <i>&lt;ifName&gt;</i> |
| Category    | Smartlink                                                                             |
| Severity    | Information                                                                           |
| Description | Event raised when active link changed in the smartlink group                          |

#### Event ID: 11303

|             |                                                                                       |
|-------------|---------------------------------------------------------------------------------------|
| Message     | Backup link of the smartlink group <i>&lt;id&gt;</i> changed to <i>&lt;ifName&gt;</i> |
| Category    | Smartlink                                                                             |
| Severity    | Information                                                                           |
| Description | Event raised when backup link changed in the smartlink group                          |

The following are the events related to SNMP.

#### Event ID: 7101

|             |                                                 |
|-------------|-------------------------------------------------|
| Message     | Snmp agent is up and running in namespace <vrf> |
| Category    | SNMP                                            |
| Severity    | Information                                     |
| Description | SNMP agent is enabled.                          |

#### Event ID: 7102

|             |                                                     |
|-------------|-----------------------------------------------------|
| Message     | Snmp sub agent is up and running in namespace <vrf> |
| Category    | SNMP                                                |
| Severity    | Information                                         |
| Description | SNMP sub agent is enabled.                          |

#### Event ID: 7103

|             |                                            |
|-------------|--------------------------------------------|
| Message     | Snmp agent is disabled for namespace <vrf> |
| Category    | SNMP                                       |
| Severity    | Information                                |
| Description | SNMP agent is disabled.                    |

#### Event ID: 7104

|             |                                                |
|-------------|------------------------------------------------|
| Message     | Snmp sub agent is disabled for namespace <vrf> |
| Category    | SNMP                                           |
| Severity    | Information                                    |
| Description | SNMP sub agent is disabled.                    |

#### Event ID: 7105

|             |                                   |
|-------------|-----------------------------------|
| Message     | Failed to poll snmp               |
| Category    | SNMP                              |
| Severity    | Information                       |
| Description | SNMP poll thread creation failed. |

#### Event ID: 7106

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | Snmp and credential manager integration failed     |
| Category    | SNMP                                               |
| Severity    | Information                                        |
| Description | SNMP failed to synchronize with credential manager |

#### Event ID: 7107

|             |                            |
|-------------|----------------------------|
| Message     | Snmp system now configured |
| Category    | SNMP                       |
| Severity    | Information                |
| Description | SNMP system is configured. |

#### Event ID: 7108

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | Snmp and database Integration has been initialized |
| Category    | SNMP                                               |
| Severity    | Information                                        |
| Description | Snmp successfully synchronized with database       |

#### Event ID: 7109

|             |                                           |
|-------------|-------------------------------------------|
| Message     | Successfully initialized all SNMP plugins |
| Category    | SNMP                                      |
| Severity    | Information                               |
| Description | SNMP plugins successfully initialized.    |

#### Event ID: 7110

|         |                            |
|---------|----------------------------|
| Message | Destroyed all SNMP plugins |
|---------|----------------------------|

|             |                                         |
|-------------|-----------------------------------------|
| Category    | SNMP                                    |
| Severity    | Information                             |
| Description | SNMP plugin successfully deinitialized. |

### Event ID: 7111

|             |                                                                 |
|-------------|-----------------------------------------------------------------|
| Message     | SNMP cache sync on-demand is set to: <i>&lt;truth_value&gt;</i> |
| Category    | SNMP                                                            |
| Severity    | Information                                                     |
| Description | SNMP on demand idl sync.                                        |

The following are the events related to SSH client.

#### Event ID: 9001

|             |                                                                                                                                                                                         |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Connection to SSH server <code>&lt;ipaddr&gt;</code> on VRF <code>&lt;vrf_name&gt;</code> is established for user <code>&lt;username&gt;</code> over port <code>&lt;port_num&gt;</code> |
| Category    | SSH client                                                                                                                                                                              |
| Severity    | Information                                                                                                                                                                             |
| Description | SSH client session is successful.                                                                                                                                                       |

#### Event ID: 9002

|             |                                                                                                                                             |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Connection to SSH server <code>&lt;ipaddr&gt;</code> on VRF <code>&lt;vrf_name&gt;</code> over port <code>&lt;port_num&gt;</code> is denied |
| Category    | SSH client                                                                                                                                  |
| Severity    | Error                                                                                                                                       |
| Description | SSH client session is denied                                                                                                                |

#### Event ID: 9003

|             |                                                                                                                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Connection to SSH server <code>&lt;ipaddr&gt;</code> on VRF <code>&lt;vrf_name&gt;</code> is successfully closed for user <code>&lt;username&gt;</code> over port <code>&lt;port_num&gt;</code> |
| Category    | SSH client                                                                                                                                                                                      |
| Severity    | Information                                                                                                                                                                                     |
| Description | SSH client session is successful.                                                                                                                                                               |

The following are the events related to SSH server.

#### Event ID: 5201

|             |                                                |
|-------------|------------------------------------------------|
| Message     | SSH host-key <key_name> is installed.          |
| Category    | SSH server                                     |
| Severity    | Information                                    |
| Description | Logs a message when the SSH host-key generated |

#### Event ID: 5202

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | SSH server is enabled on VRF <vrf_name>.               |
| Category    | SSH server                                             |
| Severity    | Information                                            |
| Description | Logs a message when the SSH server is enabled on a VRF |

#### Event ID: 5203

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | SSH server is disabled on VRF <vrf_name>.               |
| Category    | SSH server                                              |
| Severity    | Information                                             |
| Description | Logs a message when the SSH server is disabled on a VRF |

#### Event ID: 5204

|             |                                                                         |
|-------------|-------------------------------------------------------------------------|
| Message     | SSH client-public-key <key_name> was installed for the user <username>. |
| Category    | SSH server                                                              |
| Severity    | Information                                                             |
| Description | Logs a message when add ssh client-public-key into authorized_keys file |

#### Event ID: 5205

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | SSH client-public-key <key_name> was removed for the user <username>.      |
| Category    | SSH server                                                                 |
| Severity    | Information                                                                |
| Description | Logs a message when delete ssh client-public-key into authorized_keys file |

### Event ID: 5207

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | An internal error occurred while reading the SSH host-key <key_name>. |
| Category    | SSH server                                                            |
| Severity    | Information                                                           |
| Description | Logs a message when the SSH host-key is corrupted                     |

### Event ID: 5208

|             |                                                                                      |
|-------------|--------------------------------------------------------------------------------------|
| Message     | Failed to enable SSH server on VRF <vrf_name>. Admin password is not set.            |
| Category    | SSH server                                                                           |
| Severity    | Error                                                                                |
| Description | Logs a message when a user tries to enable SSH server without setting admin password |



The following are the events related to supportability.

### Event ID: 1201 (Severity: Critical)

|             |                                                                              |
|-------------|------------------------------------------------------------------------------|
| Message     | <code>&lt;process&gt; crashed due to &lt;signal&gt;,&lt;timestamp&gt;</code> |
| Category    | Supportability                                                               |
| Severity    | Critical                                                                     |
| Description | A daemon has crashed and generated core dump                                 |

### Event ID: 1202

|             |                                    |
|-------------|------------------------------------|
| Message     | <code>Kernel panic occurred</code> |
| Category    | Supportability                     |
| Severity    | Error                              |
| Description | Logs kernel crash                  |

### Event ID: 1203

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | <code>Kernel failed to compress vmcore. Error log:&lt;err_desc&gt;</code> |
| Category    | Supportability                                                            |
| Severity    | Error                                                                     |
| Description | Logs kernel failed to compress vmcore                                     |

### Event ID: 1204

|             |                                                                                                                      |
|-------------|----------------------------------------------------------------------------------------------------------------------|
| Message     | <code>Kernel panic occurred and secondary kernel failed to save uncompressed core. Error log:&lt;err_desc&gt;</code> |
| Category    | Supportability                                                                                                       |
| Severity    | Error                                                                                                                |
| Description | Logs kernel panic occurred and secondary kernel core failed to save uncompressed core                                |

### Event ID: 1205

|             |                                                                   |
|-------------|-------------------------------------------------------------------|
| Message     | Kernel panic occurred and system is restored back to normal state |
| Category    | Supportability                                                    |
| Severity    | Error                                                             |
| Description | Logs kernel panic occurred                                        |

#### Event ID: 1206 (Severity: Critical)

|             |                                                       |
|-------------|-------------------------------------------------------|
| Message     | Module rebooted. Reason: <reason>, Boot-ID: <boot_id> |
| Category    | Supportability                                        |
| Severity    | Critical                                              |
| Description | Logs reboot information                               |

#### Event ID: 1207 (Severity: Warning)

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | Available system memory is back to normal state                        |
| Category    | Supportability                                                         |
| Severity    | Warning                                                                |
| Description | Event raised when available system memory is restored to normal level. |

#### Event ID: 1208

|             |                                                                   |
|-------------|-------------------------------------------------------------------|
| Message     | High system memory usage detected                                 |
| Category    | Supportability                                                    |
| Severity    | Error                                                             |
| Description | Event raised when system memory usage goes beyond high threshold. |

#### Event ID: 1209 (Severity: Emergency)

|             |                                                                   |
|-------------|-------------------------------------------------------------------|
| Message     | Available system memory is critically low': yes                   |
| Category    | Supportability                                                    |
| Severity    | Emergency                                                         |
| Description | Event raised when system memory usage crosses critical threshold. |

#### Event ID: 1210 (Severity: Warning)

|         |                                              |
|---------|----------------------------------------------|
| Message | Memory reservation for reboot library failed |
|---------|----------------------------------------------|

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Category    | Supportability                                                 |
| Severity    | Warning                                                        |
| Description | Event raised when memory reservation for reboot library fails. |

### Event ID: 1211 (Severity: Emergency)

|             |                                                  |
|-------------|--------------------------------------------------|
| Message     | Unable to get current system memory usage        |
| Category    | Supportability                                   |
| Severity    | Emergency                                        |
| Description | Event raised when system memory read is failing. |

### Event ID: 1212 (Severity: Emergency)

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | Available system memory is critically low. Reboot will be triggered soon. |
| Category    | Supportability                                                            |
| Severity    | Emergency                                                                 |
| Description | Available memory is critically low, system will be rebooted.              |

### Event ID: 1213

|             |                                                                               |
|-------------|-------------------------------------------------------------------------------|
| Message     | RMON alarm <index> - Rising threshold value of <threshold> reached for <oid>. |
| Category    | Supportability                                                                |
| Severity    | Information                                                                   |
| Description | Event raised when the sampled value has reached the rising threshold.         |

### Event ID: 1214

|             |                                                                                |
|-------------|--------------------------------------------------------------------------------|
| Message     | RMON alarm <index> - Falling threshold value of <threshold> reached for <oid>. |
| Category    | Supportability                                                                 |
| Severity    | Information                                                                    |
| Description | Event raised when the sampled value has reached the falling threshold.         |

### Event ID: 1215

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | <code>&lt;process&gt; exiting. Reason: &lt;reason&gt;</code> |
| Category    | Supportability                                               |
| Severity    | Error                                                        |
| Description | A process is exiting due to an unrecoverable error           |

### Event ID: 1216 (Severity: Emergency)

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | <code>&lt;process&gt; exiting. Reason: &lt;reason&gt;</code> |
| Category    | Supportability                                               |
| Severity    | Emergency                                                    |
| Description | A critical process is exiting due to an unrecoverable error  |

### Event ID: 1217

|             |                                              |
|-------------|----------------------------------------------|
| Message     | <code>Coredump(s) are deleted by user</code> |
| Category    | Supportability                               |
| Severity    | Information                                  |
| Description | Coredump(s) are deleted by user              |

### Event ID: 1218

|             |                                                                                |
|-------------|--------------------------------------------------------------------------------|
| Message     | <code>Remote logging to &lt;remote_host&gt; over &lt;vrf&gt; vrf added.</code> |
| Category    | Supportability                                                                 |
| Severity    | Information                                                                    |
| Description | Event raised when a new syslog server is added for remote logging.             |

### Event ID: 1219

|             |                                                                                  |
|-------------|----------------------------------------------------------------------------------|
| Message     | <code>Remote logging to &lt;remote_host&gt; over &lt;vrf&gt; vrf removed.</code> |
| Category    | Supportability                                                                   |
| Severity    | Information                                                                      |
| Description | Event raised when a syslog server is removed from remote logging.                |

### Event ID: 1220

|         |                                                                                                    |
|---------|----------------------------------------------------------------------------------------------------|
| Message | <code>Configuration of remote logging to &lt;remote_host&gt; over &lt;vrf&gt; vrf modified.</code> |
|---------|----------------------------------------------------------------------------------------------------|

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Category    | Supportability                                                         |
| Severity    | Information                                                            |
| Description | Event raised when an existing syslog server configuration is modified. |

### Event ID: 1221

|             |                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------|
| Message     | Watchdog timeout is increased due to high memory usage                                             |
| Category    | Supportability                                                                                     |
| Severity    | Information                                                                                        |
| Description | Event raised when available RAM memory goes below the threshold and watchdog timeout is increased. |

### Event ID: 1222

|             |                                                                                                                               |
|-------------|-------------------------------------------------------------------------------------------------------------------------------|
| Message     | Watchdog timeout is restored to default value                                                                                 |
| Category    | Supportability                                                                                                                |
| Severity    | Information                                                                                                                   |
| Description | Event raised when the available RAM memory is restored to normal range and the watchdog timeout is restored to default value. |

### Event ID: 1223 (Severity: Warning)

|             |                                                                                                         |
|-------------|---------------------------------------------------------------------------------------------------------|
| Message     | The <log_type> buffer is almost full.': yes                                                             |
| Category    | Supportability                                                                                          |
| Severity    | Warning                                                                                                 |
| Description | Event raised the log buffer is almost full. User can copy these logs before the logs being overwritten. |

### Event ID: 1224 (Severity: Warning)

|             |                                                                          |
|-------------|--------------------------------------------------------------------------|
| Message     | The <log_type> buffer has wrapped, older logs will be overwritten.': yes |
| Category    | Supportability                                                           |
| Severity    | Warning                                                                  |
| Description | Event raised the log buffer has wrapped; older logs will be overwritten. |

### Event ID: 1225

|             |                                                                                                                                                         |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Collection of support-files named <code>&lt;name&gt;</code> of type <code>&lt;type&gt;</code> is requested for the module <code>&lt;module&gt;</code> . |
| Category    | Supportability                                                                                                                                          |
| Severity    | Information                                                                                                                                             |
| Description | Event raised when support-files collection is requested.                                                                                                |

#### Event ID: 1226

|             |                                                                          |
|-------------|--------------------------------------------------------------------------|
| Message     | Support-files named <code>&lt;name&gt;</code> is requested for deletion. |
| Category    | Supportability                                                           |
| Severity    | Information                                                              |
| Description | Event raised when a request received to delete given support-files.      |

#### Event ID: 1227

|             |                                                           |
|-------------|-----------------------------------------------------------|
| Message     | Support-files named <code>&lt;name&gt;</code> is deleted. |
| Category    | Supportability                                            |
| Severity    | Information                                               |
| Description | Event raised when support-files is deleted.               |

#### Event ID: 1228

|             |                                                                                                         |
|-------------|---------------------------------------------------------------------------------------------------------|
| Message     | Collection of support-files named <code>&lt;name&gt;</code> failed due to <code>&lt;reason&gt;</code> . |
| Category    | Supportability                                                                                          |
| Severity    | Error                                                                                                   |
| Description | Event raised when collection support-files failed.                                                      |

#### Event ID: 1229

|             |                                                                                                       |
|-------------|-------------------------------------------------------------------------------------------------------|
| Message     | Deletion of support-files named <code>&lt;name&gt;</code> failed due to <code>&lt;reason&gt;</code> . |
| Category    | Supportability                                                                                        |
| Severity    | Error                                                                                                 |
| Description | Event raised when failed to delete a given support-files.                                             |

#### Event ID: 1230

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | Collection of support-files named <name> is <state>.         |
| Category    | Supportability                                               |
| Severity    | Information                                                  |
| Description | Event raised when collection of support-files state changes. |

### Event ID: 1231

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | Syslog client restarted due to configuration change.                      |
| Category    | Supportability                                                            |
| Severity    | Information                                                               |
| Description | Event raised when remote syslog is restarted due to configuration change. |

The following are the events related to SYS.

#### Event ID: 701

|             |                                                   |
|-------------|---------------------------------------------------|
| Message     | Failed to read FRU data from base system          |
| Category    | SYS                                               |
| Severity    | Information                                       |
| Description | Log when failed to read FRU data from base system |

#### Event ID: 702

|             |                                    |
|-------------|------------------------------------|
| Message     | Failed to read FRU header          |
| Category    | SYS                                |
| Severity    | Information                        |
| Description | Log when failed to read FRU header |

#### Event ID: 703

|             |                                   |
|-------------|-----------------------------------|
| Message     | Error reading FRU EEPROM Header   |
| Category    | SYS                               |
| Severity    | Information                       |
| Description | log when FRU EEPROM Header failed |

#### Event ID: 704

|             |                                       |
|-------------|---------------------------------------|
| Message     | Failed to initialize devices          |
| Category    | SYS                                   |
| Severity    | Information                           |
| Description | Log when failed to initialize devices |

#### Event ID: 705



|             |                                       |
|-------------|---------------------------------------|
| Message     | Failed to allocate memory for <value> |
| Category    | SYS                                   |
| Severity    | Information                           |
| Description | Log when failed to allocate memory    |

#### Event ID: 706

|             |                                                |
|-------------|------------------------------------------------|
| Message     | Initiating system reboot                       |
| Category    | SYS                                            |
| Severity    | Information                                    |
| Description | Indicates that the chassis is about to reboot. |

#### Event ID: 707

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | Initiating chassis thermal reboot                                      |
| Category    | SYS                                                                    |
| Severity    | Error                                                                  |
| Description | Indicates that the chassis experienced a thermal event and will reboot |

#### Event ID: 708

|             |                                                                                    |
|-------------|------------------------------------------------------------------------------------|
| Message     | Invalid Device Version Programmed. Please check MFG data programmed on the device. |
| Category    | SYS                                                                                |
| Severity    | Error                                                                              |
| Description | Indicates invalid device version is programmed on the device                       |

#### Event ID: 709

|             |                                                                          |
|-------------|--------------------------------------------------------------------------|
| Message     | Failed to read assembly revision                                         |
| Category    | SYS                                                                      |
| Severity    | Error                                                                    |
| Description | Indicates device has failed to read assembly revision that is programmed |

The following are the events related to SYSMON.

#### Event ID: 6301

|             |                                                                                                           |
|-------------|-----------------------------------------------------------------------------------------------------------|
| Message     | System resource utilization poll interval is changed to <code>&lt;poll&gt;</code> '<br>throttle_count: 40 |
| Category    | SYSMON                                                                                                    |
| Severity    | Information                                                                                               |
| Description | System resource utilization poll change event                                                             |

#### Event ID: 6302 (Severity: Warning)

|             |                                                                               |
|-------------|-------------------------------------------------------------------------------|
| Message     | Failed to read system memory usage for module <code>&lt;module_num&gt;</code> |
| Category    | SYSMON                                                                        |
| Severity    | Warning                                                                       |
| Description | Warns a user when system memory usage read failed                             |

#### Event ID: 6303

|             |                                                                                                            |
|-------------|------------------------------------------------------------------------------------------------------------|
| Message     | Current system memory usage for module <code>&lt;module_num&gt;</code> is <code>&lt;mem_usage&gt;</code> % |
| Category    | SYSMON                                                                                                     |
| Severity    | Information                                                                                                |
| Description | Reports current system memory usage in percentage                                                          |

#### Event ID: 6304 (Severity: Warning)

|             |                                                                                                                                                                     |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Storage utilization for <code>&lt;partition_name&gt;</code> partition is at <code>&lt;utilization&gt;</code> %<br>in module <code>&lt;module_name&gt;</code> ': yes |
| Category    | SYSMON                                                                                                                                                              |
| Severity    | Warning                                                                                                                                                             |
| Description | Warns a user when the storage utilization has exceeded the warning limit.                                                                                           |

#### Event ID: 6305

|             |                                                                                                                           |
|-------------|---------------------------------------------------------------------------------------------------------------------------|
| Message     | Storage <partition_name> partition high utilization alert. Utilization is at <utilization>% in module <module_name>': yes |
| Category    | SYSMON                                                                                                                    |
| Severity    | Error                                                                                                                     |
| Description | Raises high storage utilization alert when the utilization crosses higher utilization limit.                              |

### Event ID: 6306 (Severity: Warning)

|             |                                                                                                                                           |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Excessive write to <partition_name> partition in module <module_name> observed. <mem_usage>GB written over past <unit_count> <unit>': yes |
| Category    | SYSMON                                                                                                                                    |
| Severity    | Warning                                                                                                                                   |
| Description | Warns a user when higher write to the storage observed                                                                                    |

### Event ID: 6307 (Severity: Warning)

|             |                                                                                                                     |
|-------------|---------------------------------------------------------------------------------------------------------------------|
| Message     | Excessive write to swap in module <module_name> observed. <mem_usage>GB written over past <unit_count> <unit>': yes |
| Category    | SYSMON                                                                                                              |
| Severity    | Warning                                                                                                             |
| Description | Warns a user when higher write to the swap observed.                                                                |

### Event ID: 6308

|             |                                                                                                                                           |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Excessive write to <partition_name> partition in module <module_name> observed. <mem_usage>GB written over past <unit_count> <unit>': yes |
| Category    | SYSMON                                                                                                                                    |
| Severity    | Error                                                                                                                                     |
| Description | Warns a user when excessive write to the storage observed                                                                                 |

### Event ID: 6309

|             |                                                                                                                     |
|-------------|---------------------------------------------------------------------------------------------------------------------|
| Message     | Excessive write to swap in module <module_name> observed. <mem_usage>GB written over past <unit_count> <unit>': yes |
| Category    | SYSMON                                                                                                              |
| Severity    | Error                                                                                                               |
| Description | Warns a user when excessive write to the swap observed.                                                             |

The following are the events related to TCAM.

#### Event ID: 10201

|             |                                   |
|-------------|-----------------------------------|
| Message     | "Policer installation has failed" |
| Category    | TCAM                              |
| Severity    | Error                             |
| Description | Policer installation failure      |

#### Event ID: 10202

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | "TCAM entry installation has failed in table <table_name>" |
| Category    | TCAM                                                       |
| Severity    | Error                                                      |
| Description | TCAM entry installation failure                            |

#### Event ID: 10203

|             |                                                      |
|-------------|------------------------------------------------------|
| Message     | "Installation of TCAM table <table_name> has failed" |
| Category    | TCAM                                                 |
| Severity    | Error                                                |
| Description | TCAM table installation failure                      |

#### Event ID: 10204

|             |                                                                          |
|-------------|--------------------------------------------------------------------------|
| Message     | "High-capacity TCAM/LPM entry installation failed in table <table_name>" |
| Category    | TCAM                                                                     |
| Severity    | Error                                                                    |
| Description | High-capacity TCAM/LPM entry installation failure                        |

#### Event ID: 10205

|             |                                                                 |
|-------------|-----------------------------------------------------------------|
| Message     | "High-capacity TCAM/LPM table <table_name> installation failed" |
| Category    | TCAM                                                            |
| Severity    | Error                                                           |
| Description | High-capacity TCAM/LPM table installation failure               |

#### Event ID: 10206

|             |                                   |
|-------------|-----------------------------------|
| Message     | "Counter installation has failed" |
| Category    | TCAM                              |
| Severity    | Error                             |
| Description | TCAM Counter installation failure |

#### Event ID: 10207

|             |                                         |
|-------------|-----------------------------------------|
| Message     | "Range Checker installation has failed" |
| Category    | TCAM                                    |
| Severity    | Error                                   |
| Description | TCAM Range Checker installation failure |

#### Event ID: 10208

|             |                                     |
|-------------|-------------------------------------|
| Message     | "Policer uninstallation has failed" |
| Category    | TCAM                                |
| Severity    | Error                               |
| Description | Policer uninstallation failure      |

#### Event ID: 10209

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | "TCAM entry uninstallation has failed in table <table_name>" |
| Category    | TCAM                                                         |
| Severity    | Error                                                        |
| Description | TCAM entry uninstallation failure                            |

#### Event ID: 10210

|         |                                                                            |
|---------|----------------------------------------------------------------------------|
| Message | "High-capacity TCAM/LPM entry uninstallation failed in table <table_name>" |
|---------|----------------------------------------------------------------------------|

|             |                                                     |
|-------------|-----------------------------------------------------|
| Category    | TCAM                                                |
| Severity    | Error                                               |
| Description | High-capacity TCAM/LPM entry uninstallation failure |

#### Event ID: 10211

|             |                                                      |
|-------------|------------------------------------------------------|
| Message     | "High-capacity TCAM/LPM table uninstallation failed" |
| Category    | TCAM                                                 |
| Severity    | Error                                                |
| Description | High-capacity TCAM/LPM table uninstallation failure  |

#### Event ID: 10212

|             |                                     |
|-------------|-------------------------------------|
| Message     | "Counter uninstallation has failed" |
| Category    | TCAM                                |
| Severity    | Error                               |
| Description | TCAM Counter uninstallation failure |

#### Event ID: 10213

|             |                                           |
|-------------|-------------------------------------------|
| Message     | "Range Checker uninstallation has failed" |
| Category    | TCAM                                      |
| Severity    | Error                                     |
| Description | TCAM Range Checker uninstallation failure |

#### Event ID: 10214

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | "TCAM Context Group selectors have been exhausted" |
| Category    | TCAM                                               |
| Severity    | Error                                              |
| Description | TCAM Context Group selectors have been exhausted   |

#### Event ID: 10215

|          |                                              |
|----------|----------------------------------------------|
| Message  | "TCAM Context Group IDs have been exhausted" |
| Category | TCAM                                         |

|             |                                            |
|-------------|--------------------------------------------|
| Severity    | Error                                      |
| Description | TCAM Context Group IDs have been exhausted |

The following are the events related to temperature.

#### Event ID: 801 (Severity: Warning)

|             |                                            |
|-------------|--------------------------------------------|
| Message     | Unrecognized sensor type <type>            |
| Category    | Temperature                                |
| Severity    | Warning                                    |
| Description | Log event when sensor type is unrecognized |

#### Event ID: 802 (Severity: Warning)

|             |                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------|
| Message     | Module <module> shutdown initiated for sensor <name> with critical temperature, <temp> degC.': yes |
| Category    | Temperature                                                                                        |
| Severity    | Warning                                                                                            |
| Description | Log event when sensor temperature is above the critical threshold                                  |

#### Event ID: 803 (Severity: Warning)

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | Over-temperature for sensor <name>, <temp> degC.': yes                    |
| Category    | Temperature                                                               |
| Severity    | Warning                                                                   |
| Description | Log event when sensor temperature is above the over-temperature threshold |

#### Event ID: 804

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | Sensor <name> back to safe temperature, <temp> degC.         |
| Category    | Temperature                                                  |
| Severity    | Information                                                  |
| Description | Log event when a sensor returns to safe operating conditions |

#### Event ID: 805



|             |                                                                                 |
|-------------|---------------------------------------------------------------------------------|
| Message     | System derate changed from <code>&lt;old&gt;</code> to <code>&lt;new&gt;</code> |
| Category    | Temperature                                                                     |
| Severity    | Information                                                                     |
| Description | Log when the system derate changes.                                             |

### Event ID: 806 (Severity: Warning)

|             |                                                                                               |
|-------------|-----------------------------------------------------------------------------------------------|
| Message     | Ambient temperature for sensor <code>&lt;name&gt;</code> above <code>&lt;temp&gt;</code> degC |
| Category    | Temperature                                                                                   |
| Severity    | Warning                                                                                       |
| Description | Log when ambient temperature is above the ambient temperature limits.                         |

### Event ID: 807

|             |                                                                                                                                                            |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Ambient temperature for sensor <code>&lt;name&gt;</code> back to safe temperature, between <code>&lt;t_low&gt;</code> and <code>&lt;t_high&gt;</code> degC |
| Category    | Temperature                                                                                                                                                |
| Severity    | Information                                                                                                                                                |
| Description | Log when ambient temperature returns to safe operating conditions.                                                                                         |

### Event ID: 808

|             |                                                                                                                  |
|-------------|------------------------------------------------------------------------------------------------------------------|
| Message     | Sensor <code>&lt;name&gt;</code> <code>&lt;limit_type&gt;</code> limit configuration <code>&lt;status&gt;</code> |
| Category    | Temperature                                                                                                      |
| Severity    | Information                                                                                                      |
| Description | Log failures in configuring sensor temperature warning/critical limits.                                          |

### Event ID: 809 (Severity: Warning)

|             |                                                                                                                                            |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Ambient temperature <code>&lt;temp&gt;</code> degC is above the commercial grade transceiver limit of <code>&lt;limit_high&gt;</code> degC |
| Category    | Temperature                                                                                                                                |
| Severity    | Warning                                                                                                                                    |
| Description | Log when ambient temperature is above commercial grade transceiver upper limit when non-industrial transceivers are installed.             |

### Event ID: 810 (Severity: Warning)

|             |                                                                                                                                           |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Ambient temperature <code>&lt;temp&gt;</code> degC is below the commercial grade transceiver range of <code>&lt;limit_low&gt;</code> degC |
| Category    | Temperature                                                                                                                               |
| Severity    | Warning                                                                                                                                   |
| Description | Log when ambient temperature is below commercial grade transceiver lower limit when non-industrial transceivers are installed.            |

#### Event ID: 811

|             |                                                                                                                                                                                       |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Ambient temperature <code>&lt;temp&gt;</code> degC returned to within the commercial grade transceiver range of <code>&lt;limit_low&gt;</code> – <code>&lt;limit_high&gt;</code> degC |
| Category    | Temperature                                                                                                                                                                           |
| Severity    | Information                                                                                                                                                                           |
| Description | Log when ambient temperature returns to commercial grade transceiver range when non-industrial transceivers are installed.                                                            |

#### Event ID: 812 (Severity: Warning)

|             |                                                                                               |
|-------------|-----------------------------------------------------------------------------------------------|
| Message     | Ambient temperature for sensor <code>&lt;name&gt;</code> below <code>&lt;temp&gt;</code> degC |
| Category    | Temperature                                                                                   |
| Severity    | Warning                                                                                       |
| Description | Log when ambient temperature is below the ambient temperature limits.                         |

#### Event ID: 813 (Severity: Warning)

|             |                                                                                               |
|-------------|-----------------------------------------------------------------------------------------------|
| Message     | Under-temperature for sensor <code>&lt;name&gt;</code> , <code>&lt;temp&gt;</code> degC.: yes |
| Category    | Temperature                                                                                   |
| Severity    | Warning                                                                                       |
| Description | Log event when sensor temperature is below the under-temperature threshold                    |

#### Event ID: 814 (Severity: Warning)

|             |                                                                                                                                                                |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Module <code>&lt;module&gt;</code> shutdown initiated for sensor <code>&lt;name&gt;</code> with low critical temperature, <code>&lt;temp&gt;</code> degC.: yes |
| Category    | Temperature                                                                                                                                                    |
| Severity    | Warning                                                                                                                                                        |
| Description | Log event when sensor temperature is below the low critical threshold                                                                                          |

The following are the events related to time management.

#### Event ID: 6201

|             |                                                                                       |
|-------------|---------------------------------------------------------------------------------------|
| Message     | System timezone changed from <code>&lt;oldtz&gt;</code> to <code>&lt;newtz&gt;</code> |
| Category    | Time management                                                                       |
| Severity    | Information                                                                           |
| Description | Change the system timezone                                                            |

#### Event ID: 6202

|             |                                                                                              |
|-------------|----------------------------------------------------------------------------------------------|
| Message     | System date/time changed from <code>&lt;old_time&gt;</code> to <code>&lt;new_time&gt;</code> |
| Category    | Time management                                                                              |
| Severity    | Information                                                                                  |
| Description | Change the system date/time                                                                  |

The following are the events related to transceiver.

#### Event ID: 3801

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | <code>allow-unsupported-transceiver feature enabled</code> |
| Category    | Transceiver                                                |
| Severity    | Information                                                |
| Description | Event raised when unsupported transceiver mode is enabled  |

#### Event ID: 3802

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | <code>allow-unsupported-transceiver feature disabled</code> |
| Category    | Transceiver                                                 |
| Severity    | Information                                                 |
| Description | Event raised when unsupported transceiver mode is disabled  |

#### Event ID: 3803

|             |                                                                                                             |
|-------------|-------------------------------------------------------------------------------------------------------------|
| Message     | <code>allow-unsupported-transceiver feature enabled: Unsupported transceivers found in: &lt;list&gt;</code> |
| Category    | Transceiver                                                                                                 |
| Severity    | Information                                                                                                 |
| Description | Event raised to list unsupported transceivers in unsupported transceiver mode                               |

#### Event ID: 3804

|             |                                                                          |
|-------------|--------------------------------------------------------------------------|
| Message     | <code>Transceiver hot-swap insert for interface &lt;interface&gt;</code> |
| Category    | Transceiver                                                              |
| Severity    | Information                                                              |
| Description | Event raised to indicate transceiver hotswap insertion                   |

#### Event ID: 3805

|             |                                                       |
|-------------|-------------------------------------------------------|
| Message     | Transceiver hot-swap remove for interface <interface> |
| Category    | Transceiver                                           |
| Severity    | Information                                           |
| Description | Event raised to indicate transceiver hotswap removal  |

#### Event ID: 3806 (Severity: Warning)

|             |                                                                                              |
|-------------|----------------------------------------------------------------------------------------------|
| Message     | Interface <interface> transceiver attempted link recovery <count> times' throttle_count: 100 |
| Category    | Transceiver                                                                                  |
| Severity    | Warning                                                                                      |
| Description | Event raised to indicate transceiver link recovery attempts                                  |

#### Event ID: 3807

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | <path>                                                              |
| Category    | Transceiver                                                         |
| Severity    | Information                                                         |
| Description | Event raised to indicate detection path of unsupported transceivers |

#### Event ID: 3808

|             |                                                                                                   |
|-------------|---------------------------------------------------------------------------------------------------|
| Message     | Transceiver <xcvr_desc> inserted in <interface> is <status>. <reason>                             |
| Category    | Transceiver                                                                                       |
| Severity    | Information                                                                                       |
| Description | Event raised to indicate status of transceivers that are allowed to be operational and its reason |

#### Event ID: 3809 (Severity: Warning)

|             |                                                                                                       |
|-------------|-------------------------------------------------------------------------------------------------------|
| Message     | Transceiver <xcvr_desc> inserted in <interface> is <status>. <reason>                                 |
| Category    | Transceiver                                                                                           |
| Severity    | Warning                                                                                               |
| Description | Event raised to indicate status of transceivers that are not allowed to be operational and its reason |

#### Event ID: 3810 (Severity: Warning)

|             |                                                                    |
|-------------|--------------------------------------------------------------------|
| Message     | Unknown transceiver inserted in interface <i>&lt;interface&gt;</i> |
| Category    | Transceiver                                                        |
| Severity    | Warning                                                            |
| Description | Event raised to indicate an unknown transceiver was inserted       |

#### Event ID: 3811 (Severity: Warning)

|             |                                                                                                                                      |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Transceiver in <i>&lt;interface&gt;</i> is incompatible with the interface group speed                                               |
| Category    | Transceiver                                                                                                                          |
| Severity    | Warning                                                                                                                              |
| Description | Event raised to indicate a transceiver was inserted in a port that is a member of a group configured to operate at a different speed |

#### Event ID: 3812

|             |                                                                                                                           |
|-------------|---------------------------------------------------------------------------------------------------------------------------|
| Message     | Adapter <i>&lt;adapter_desc&gt;</i> inserted in <i>&lt;interface&gt;</i> is <i>&lt;status&gt;</i> . <i>&lt;reason&gt;</i> |
| Category    | Transceiver                                                                                                               |
| Severity    | Information                                                                                                               |
| Description | Event raised to indicate status of adapters that are allowed to be operational and its reason                             |

#### Event ID: 3813 (Severity: Warning)

|             |                                                                                                                           |
|-------------|---------------------------------------------------------------------------------------------------------------------------|
| Message     | Adapter <i>&lt;adapter_desc&gt;</i> inserted in <i>&lt;interface&gt;</i> is <i>&lt;status&gt;</i> . <i>&lt;reason&gt;</i> |
| Category    | Transceiver                                                                                                               |
| Severity    | Warning                                                                                                                   |
| Description | Event raised to indicate status of adapters that are not allowed to be operational and its reason                         |

The following are the events related to UDLD.

#### Event ID: 4101

|             |                                                   |
|-------------|---------------------------------------------------|
| Message     | UDLD is enabled on interface: <i>&lt;intf&gt;</i> |
| Category    | UDLD                                              |
| Severity    | Information                                       |
| Description | Event raised when UDLD is enabled                 |

#### Event ID: 4102

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | UDLD is disabled on interface: <i>&lt;intf&gt;</i> |
| Category    | UDLD                                               |
| Severity    | Information                                        |
| Description | Event raised when UDLD is disabled                 |

#### Event ID: 4103

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | UDLD interface <i>&lt;intf&gt;</i> is unblocked        |
| Category    | UDLD                                                   |
| Severity    | Information                                            |
| Description | Event raised when UDLD sets the interface as unblocked |

#### Event ID: 4104

|             |                                                      |
|-------------|------------------------------------------------------|
| Message     | UDLD interface <i>&lt;intf&gt;</i> is blocked        |
| Category    | UDLD                                                 |
| Severity    | Error                                                |
| Description | Event raised when UDLD sets the interface as blocked |

#### Event ID: 4105

|             |                                                                                           |
|-------------|-------------------------------------------------------------------------------------------|
| Message     | UDLD interface <code>&lt;intf&gt;</code> is undetermined                                  |
| Category    | UDLD                                                                                      |
| Severity    | Error                                                                                     |
| Description | Event raised when UDLD moves from bidirectional state to undetermined (RFC5171 mode only) |

#### Event ID: 4106 (Severity: Warning)

|             |                                                                                                                        |
|-------------|------------------------------------------------------------------------------------------------------------------------|
| Message     | UDLD interface <code>&lt;intf&gt;</code> interval <code>&lt;intvl_a&gt;</code> clamped to <code>&lt;intvl_b&gt;</code> |
| Category    | UDLD                                                                                                                   |
| Severity    | Warning                                                                                                                |
| Description | Logs a warning when UDLD clamps the interval when operating in RFC5171 mode                                            |

#### Event ID: 4107

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | UDLD link is enabled on interface: <code>&lt;intf&gt;</code> |
| Category    | UDLD                                                         |
| Severity    | Information                                                  |
| Description | Event raised when UDLD link is enabled                       |

#### Event ID: 4108

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | UDLD link is disabled on interface: <code>&lt;intf&gt;</code> |
| Category    | UDLD                                                          |
| Severity    | Information                                                   |
| Description | Event raised when UDLD link is disabled                       |



The following are the events related to UDP Broadcast Forwarder.

### Event ID: 3601

|             |                                                                         |
|-------------|-------------------------------------------------------------------------|
| Message     | UDP Broadcast Forwarder Enabled                                         |
| Category    | UDP Broadcast Forwarder                                                 |
| Severity    | Information                                                             |
| Description | This command enables the UDP Broadcast Forwarder feature in the device. |

### Event ID: 3602

|             |                                                                          |
|-------------|--------------------------------------------------------------------------|
| Message     | UDP Broadcast Forwarder Disabled                                         |
| Category    | UDP Broadcast Forwarder                                                  |
| Severity    | Information                                                              |
| Description | This command disables the UDP Broadcast Forwarder feature in the device. |

The following are the events related to UFD.

#### Event ID: 12001 (Severity: Critical)

|             |                                                                                          |
|-------------|------------------------------------------------------------------------------------------|
| Message     | Uplink Failure Detection session-id <id>, state changed from <from_state> to <to_state>. |
| Category    | UFD                                                                                      |
| Severity    | Critical                                                                                 |
| Description | Event reported when Links-to-Disable go down.                                            |

#### Event ID: 12002

|             |                                                                                          |
|-------------|------------------------------------------------------------------------------------------|
| Message     | Uplink Failure Detection session-id <id>, state changed from <from_state> to <to_state>. |
| Category    | UFD                                                                                      |
| Severity    | Information                                                                              |
| Description | Event reported when Links-to-Disable ports are restored.                                 |

The following are the events related to user management.

### Event ID: 4701

|             |                                                       |
|-------------|-------------------------------------------------------|
| Message     | User <user> added <added_user> with role <user_role>  |
| Category    | User management                                       |
| Severity    | Information                                           |
| Description | Logs a message when a new user is added to the switch |

### Event ID: 4702

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | User <user> deleted <deleted_user> with role <user_role> |
| Category    | User management                                          |
| Severity    | Information                                              |
| Description | Logs a message when a user is deleted from the switch    |

### Event ID: 4703

|             |                                                     |
|-------------|-----------------------------------------------------|
| Message     | User <username> successfully changed password       |
| Category    | User management                                     |
| Severity    | Information                                         |
| Description | Logs a message when a user changes his/her password |

### Event ID: 4704

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | User <username> password change failed                      |
| Category    | User management                                             |
| Severity    | Error                                                       |
| Description | Logs a message when a user fails to change his/her password |

### Event ID: 4705

|             |                                                 |
|-------------|-------------------------------------------------|
| Message     | User <username> set export password             |
| Category    | User management                                 |
| Severity    | Information                                     |
| Description | Logs a message when a user sets export password |

### Event ID: 4706

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | User <username> restored default export password            |
| Category    | User management                                             |
| Severity    | Information                                                 |
| Description | Logs a message when a user restores default export password |

The following are the events related to user-based tunnels.

### Event ID: 9701

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | Tunnel Node Server SAC (<sac_ip>) is selected as (<state>) |
| Category    | User-based tunnels                                         |
| Severity    | Information                                                |
| Description | Event raised when controller is selected as Active/Standby |

### Event ID: 9702

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | Tunnel Node Server Heartbeat has failed for SAC (<sac_ip>) |
| Category    | User-based tunnels                                         |
| Severity    | Error                                                      |
| Description | Event raised when heartbeat not received from a SAC        |

### Event ID: 9703

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | Tunnel Node Server keepalive has failed for UAC (<uac_ip>) |
| Category    | User-based tunnels                                         |
| Severity    | Error                                                      |
| Description | Event raised when keepalive not received from a UAC        |

### Event ID: 9704

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | Tunnel Node Server SAC bootstrapping has reinitialized to (<sac_ip>) |
| Category    | User-based tunnels                                                   |
| Severity    | Information                                                          |
| Description | Event raised when SAC bootstrapping to a SAC is re-initialized       |

### Event ID: 9705

|             |                                                                          |
|-------------|--------------------------------------------------------------------------|
| Message     | Tunnel Node Server PAPI key has mismatched                               |
| Category    | User-based tunnels                                                       |
| Severity    | Error                                                                    |
| Description | Event raised when papi msg key sent and received is different ({key_id}) |

### Event ID: 9706 (Severity: Critical)

|             |                                                |
|-------------|------------------------------------------------|
| Message     | Tunnel Node Server UAC node is down (<uac_ip>) |
| Category    | User-based tunnels                             |
| Severity    | Critical                                       |
| Description | Event raised when UAC node is down             |

### Event ID: 9707

|             |                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------|
| Message     | Tunnel is Created - Gre Key (<gre_key>) VRF (<vrf>) Source IP (<src_ip>) Destination IP (<dst_ip>) |
| Category    | User-based tunnels                                                                                 |
| Severity    | Information                                                                                        |
| Description | Event raised when user based tunnel is created                                                     |

### Event ID: 9708

|             |                                                                                                             |
|-------------|-------------------------------------------------------------------------------------------------------------|
| Message     | Tunnel Creation has Failed - Gre Key (<gre_key>) VRF (<vrf>) Source IP (<src_ip>) Destination IP (<dst_ip>) |
| Category    | User-based tunnels                                                                                          |
| Severity    | Error                                                                                                       |
| Description | Event raised when user based tunnel creation fails                                                          |

### Event ID: 9709

|             |                                                |
|-------------|------------------------------------------------|
| Message     | Tunnel is Deleted - Tunnel Id (<tunnel_id>)    |
| Category    | User-based tunnels                             |
| Severity    | Information                                    |
| Description | Event raised when user based tunnel is deleted |

### Event ID: 9710

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | Tunnel Deletion has Failed - Tunnel Id (< tunnel_id >) |
| Category    | User-based tunnels                                     |
| Severity    | Error                                                  |
| Description | Event raised when user based tunnel deletion fails     |

#### Event ID: 9711

|             |                                                                                                                   |
|-------------|-------------------------------------------------------------------------------------------------------------------|
| Message     | Tunnel is UP - Tunnel Id (< tunnel_id >) Gre Key (< gre_key >) Source IP (< src_ip >) Destination IP (< dst_ip >) |
| Category    | User-based tunnels                                                                                                |
| Severity    | Information                                                                                                       |
| Description | Event raised when user based tunnel state is up                                                                   |

#### Event ID: 9712

|             |                                                                                                                     |
|-------------|---------------------------------------------------------------------------------------------------------------------|
| Message     | Tunnel is DOWN - Tunnel Id (< tunnel_id >) Gre Key (< gre_key >) Source IP (< src_ip >) Destination IP (< dst_ip >) |
| Category    | User-based tunnels                                                                                                  |
| Severity    | Error                                                                                                               |
| Description | Event raised when user based tunnel state is down                                                                   |

#### Event ID: 9713

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | Client (< client_mac >) is bound to tunnel id (< tunnel_id >) |
| Category    | User-based tunnels                                            |
| Severity    | Information                                                   |
| Description | Event raised when user is gets binded to tunnel               |

#### Event ID: 9714

|             |                                                                         |
|-------------|-------------------------------------------------------------------------|
| Message     | Client (< client_mac >) binding to tunnel id (< tunnel_id >) has failed |
| Category    | User-based tunnels                                                      |
| Severity    | Error                                                                   |
| Description | Event raised when user bind to tunnel id failed                         |

#### Event ID: 9715

|             |                                                 |
|-------------|-------------------------------------------------|
| Message     | Client (<client_mac>) is removed from tunnel.   |
| Category    | User-based tunnels                              |
| Severity    | Information                                     |
| Description | Event raised when user is gets binded to tunnel |

#### Event ID: 9716

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | Client (<client_mac>) unbinding to tunnel id (<tunnel_id>) has failed |
| Category    | User-based tunnels                                                    |
| Severity    | Error                                                                 |
| Description | Event raised when user unbind to tunnel id failed                     |

#### Event ID: 9717

|             |                                                                                                   |
|-------------|---------------------------------------------------------------------------------------------------|
| Message     | Client (<client_mac>) is getting modified to bind to tunnel id (<tunnel_id>)' throttle_count: 100 |
| Category    | User-based tunnels                                                                                |
| Severity    | Information                                                                                       |
| Description | Event raised when already binded user to a tunnel gets modified                                   |

#### Event ID: 9718

|             |                                                                                               |
|-------------|-----------------------------------------------------------------------------------------------|
| Message     | Modification of Client (<client_mac>) binded to (<tunnel_id>) has failed' throttle_count: 100 |
| Category    | User-based tunnels                                                                            |
| Severity    | Error                                                                                         |
| Description | Event raised when modification of already binded user to a tunnel fails                       |

#### Event ID: 9719

|             |                                                                                                                |
|-------------|----------------------------------------------------------------------------------------------------------------|
| Message     | NFD port (<nfd_id>) is created for client (<client_mac>) vlan id (<vlan_id>) port (<port>) ecmp id (<ecmp_id>) |
| Category    | User-based tunnels                                                                                             |
| Severity    | Information                                                                                                    |
| Description | Event raised on NFD port creation                                                                              |

#### Event ID: 9720



|             |                                                                                                                         |
|-------------|-------------------------------------------------------------------------------------------------------------------------|
| Message     | NFD port (<nfd_id>) creation for client (<client_mac>) vlan id (<vlan_id>) port (<port>) ecmp id (<ecmp_id>) has failed |
| Category    | User-based tunnels                                                                                                      |
| Severity    | Error                                                                                                                   |
| Description | Event raised on NFD port creation failure                                                                               |

#### Event ID: 9721

|             |                                                       |
|-------------|-------------------------------------------------------|
| Message     | NFD port (<nfd_id>) is deleted for ecmp id(<ecmp_id>) |
| Category    | User-based tunnels                                    |
| Severity    | Information                                           |
| Description | Event raised on NFD port deletion                     |

#### Event ID: 9722

|             |                                                                 |
|-------------|-----------------------------------------------------------------|
| Message     | NFD port (<nfd_id>) deletion for ecmp id (<ecmp_id>) has failed |
| Category    | User-based tunnels                                              |
| Severity    | Error                                                           |
| Description | Event raised when NFD port deletion fails                       |

#### Event ID: 9723

|             |                                               |
|-------------|-----------------------------------------------|
| Message     | ECMP group is created for ecmp id (<ecmp_id>) |
| Category    | User-based tunnels                            |
| Severity    | Information                                   |
| Description | Event raised on ECMP group creation           |

#### Event ID: 9724

|             |                                                        |
|-------------|--------------------------------------------------------|
| Message     | ECMP group creation for ecmp id (<ecmp_id>) has failed |
| Category    | User-based tunnels                                     |
| Severity    | Error                                                  |
| Description | Event raised on ECMP group creation failure            |

#### Event ID: 9725

|             |                                               |
|-------------|-----------------------------------------------|
| Message     | ECMP group is deleted for ecmp id (<ecmp_id>) |
| Category    | User-based tunnels                            |
| Severity    | Information                                   |
| Description | Event raised on ECMP group deletion           |

#### Event ID: 9726

|             |                                                       |
|-------------|-------------------------------------------------------|
| Message     | ECMP group deletion for ecmp id(<ecmp_id>) has failed |
| Category    | User-based tunnels                                    |
| Severity    | Error                                                 |
| Description | Event raised when ECMP group deletion fails           |

#### Event ID: 9727

|             |                                                                                                                          |
|-------------|--------------------------------------------------------------------------------------------------------------------------|
| Message     | MDestRx Tunnel is Created - Gre Key (<gre_key>) VLAN (<vlan>) VRF (<vrf>) Source IP (<src_ip>) Destination IP (<dst_ip>) |
| Category    | User-based tunnels                                                                                                       |
| Severity    | Information                                                                                                              |
| Description | Event raised when mdest rx user based tunnel is created                                                                  |

#### Event ID: 9728

|             |                                                                                                                                   |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------|
| Message     | MDestRx Tunnel Creation has Failed - Gre Key (<gre_key>) VLAN (<vlan>) VRF (<vrf>) Source IP (<src_ip>) Destination IP (<dst_ip>) |
| Category    | User-based tunnels                                                                                                                |
| Severity    | Error                                                                                                                             |
| Description | Event raised when mdest rx user based tunnel creation fails                                                                       |

#### Event ID: 9729

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | MDest Rx Tunnel is Deleted - Tunnel Id (<tunnel_id>)    |
| Category    | User-based tunnels                                      |
| Severity    | Information                                             |
| Description | Event raised when mdest rx user based tunnel is deleted |

#### Event ID: 9730

|             |                                                                 |
|-------------|-----------------------------------------------------------------|
| Message     | MDest Rx Tunnel Deletion has Failed - Tunnel Id (< tunnel_id >) |
| Category    | User-based tunnels                                              |
| Severity    | Error                                                           |
| Description | Event raised when mdest rx user based tunnel deletion fails     |

#### Event ID: 9731

|             |                                                                                                                              |
|-------------|------------------------------------------------------------------------------------------------------------------------------|
| Message     | MDestRx Tunnel is UP - Tunnel Id (< tunnel_id >) Gre Key (< gre_key >)<br>Source IP (< src_ip >) Destination IP (< dst_ip >) |
| Category    | User-based tunnels                                                                                                           |
| Severity    | Information                                                                                                                  |
| Description | Event raised when mdest rx user based tunnel state is up                                                                     |

#### Event ID: 9732

|             |                                                                                                                                |
|-------------|--------------------------------------------------------------------------------------------------------------------------------|
| Message     | MDestRx Tunnel is DOWN - Tunnel Id (< tunnel_id >) Gre Key (< gre_key >)<br>Source IP (< src_ip >) Destination IP (< dst_ip >) |
| Category    | User-based tunnels                                                                                                             |
| Severity    | Error                                                                                                                          |
| Description | Event raised when mdest rx user based tunnel state is down                                                                     |

#### Event ID: 9733

|             |                                                                                          |
|-------------|------------------------------------------------------------------------------------------|
| Message     | User bootstrap is failed for client (< mac_addr >) on port (< port >) due to < reason >. |
| Category    | User-based tunnels                                                                       |
| Severity    | Error                                                                                    |
| Description | Event raised when user bootstrap is failed                                               |

The following are the events related to VSX.

### Event ID: 7001

|             |                                   |
|-------------|-----------------------------------|
| Message     | VSX ISL port <port> is down       |
| Category    | Virtual Switching Extension (VSX) |
| Severity    | Information                       |
| Description | VSX ISL link is down.             |

### Event ID: 7002

|             |                                   |
|-------------|-----------------------------------|
| Message     | VSX ISL port <port> is up         |
| Category    | Virtual Switching Extension (VSX) |
| Severity    | Information                       |
| Description | VSX ISL link is up.               |

### Event ID: 7003

|             |                                               |
|-------------|-----------------------------------------------|
| Message     | VSX ISL port <port> is In-Sync with the peer. |
| Category    | Virtual Switching Extension (VSX)             |
| Severity    | Information                                   |
| Description | VSX ISL is In Sync with the peer.             |

### Event ID: 7004

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | VSX ISL port <port> is Out-Of-Sync with the peer: <reason> |
| Category    | Virtual Switching Extension (VSX)                          |
| Severity    | Error                                                      |
| Description | VSX ISL is Out-Of-Sync with the peer                       |

### Event ID: 7005 (Severity: Warning)

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | VSX Keepalive failed                               |
| Category    | Virtual Switching Extension (VSX)                  |
| Severity    | Warning                                            |
| Description | VSX Keepalive is not able to reach the peer device |

#### Event ID: 7006

|             |                                                |
|-------------|------------------------------------------------|
| Message     | VSX Keepalive succeeded                        |
| Category    | Virtual Switching Extension (VSX)              |
| Severity    | Information                                    |
| Description | VSX Keepalive is able to reach the peer device |

#### Event ID: 7007

|             |                                                                                    |
|-------------|------------------------------------------------------------------------------------|
| Message     | VSX role is primary                                                                |
| Category    | Virtual Switching Extension (VSX)                                                  |
| Severity    | Information                                                                        |
| Description | Operational role of this device derived based on device priority of the 2 devices. |

#### Event ID: 7008

|             |                                                                                    |
|-------------|------------------------------------------------------------------------------------|
| Message     | VSX role is secondary                                                              |
| Category    | Virtual Switching Extension (VSX)                                                  |
| Severity    | Information                                                                        |
| Description | Operational role of this device derived based on device priority of the 2 devices. |

#### Event ID: 7009

|             |                                                                                         |
|-------------|-----------------------------------------------------------------------------------------|
| Message     | VSX Software version mismatch: peer version <peer_sw_ver>, local version <local_sw_ver> |
| Category    | Virtual Switching Extension (VSX)                                                       |
| Severity    | Information                                                                             |
| Description | VSX Software version mismatch: peer sw version is not same as local sw version.         |

#### Event ID: 7010

|         |                                                                   |
|---------|-------------------------------------------------------------------|
| Message | VSX Device mismatch: peer device <peer_device_type>, local device |
|---------|-------------------------------------------------------------------|

|             |                                                                              |
|-------------|------------------------------------------------------------------------------|
|             | <code>&lt;local_device_type&gt;</code>                                       |
| Category    | Virtual Switching Extension (VSX)                                            |
| Severity    | Information                                                                  |
| Description | VSX Device type mismatch: peer device type is not same as local device type. |

#### Event ID: 7011

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | <code>VSX &lt;vsx_id&gt; state local up, remote down</code> |
| Category    | Virtual Switching Extension (VSX)                           |
| Severity    | Information                                                 |
| Description | VSX local up remote down.                                   |

#### Event ID: 7012

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | <code>VSX &lt;vsx_id&gt; state local down, remote up</code> |
| Category    | Virtual Switching Extension (VSX)                           |
| Severity    | Information                                                 |
| Description | VSX local down remote up.                                   |

#### Event ID: 7013

|             |                                                           |
|-------------|-----------------------------------------------------------|
| Message     | <code>VSX &lt;vsx_id&gt; state local up, remote up</code> |
| Category    | Virtual Switching Extension (VSX)                         |
| Severity    | Information                                               |
| Description | VSX local up remote up.                                   |

#### Event ID: 7014

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | <code>VSX &lt;vsx_id&gt; state local down, remote down</code> |
| Category    | Virtual Switching Extension (VSX)                             |
| Severity    | Information                                                   |
| Description | VSX local down remote down.                                   |

#### Event ID: 7015

|         |                                                           |
|---------|-----------------------------------------------------------|
| Message | <code>VSX ISL sliding window parameters are reset.</code> |
|---------|-----------------------------------------------------------|

|             |                                                |
|-------------|------------------------------------------------|
| Category    | Virtual Switching Extension (VSX)              |
| Severity    | Information                                    |
| Description | VSX resetting the ISL protocol sliding window. |

#### Event ID: 7016

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | VSX own ISL hello packet received, ignoring the packet. |
| Category    | Virtual Switching Extension (VSX)                       |
| Severity    | Information                                             |
| Description | VSX switch receives own ISL hello packet from network.  |

#### Event ID: 7017

|             |                                                                                                                 |
|-------------|-----------------------------------------------------------------------------------------------------------------|
| Message     | Rebooting the VSX <code>&lt;vsx_role&gt;</code> device with newly updated <code>&lt;bank_name&gt;</code> image. |
| Category    | Virtual Switching Extension (VSX)                                                                               |
| Severity    | Information                                                                                                     |
| Description | Switch reboot due to VSX software update.                                                                       |

#### Event ID: 7018

|             |                                                                                                                                                                                            |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | VSX primary ISL version <code>&lt;primary_version&gt;</code> dose not match with VSX secondary ISL version <code>&lt;secondary_version&gt;</code> . Performing a non-hitless image update. |
| Category    | Virtual Switching Extension (VSX)                                                                                                                                                          |
| Severity    | Information                                                                                                                                                                                |
| Description | VSX inter-switch-link protocol version mismatch after secondary reboot.                                                                                                                    |

#### Event ID: 7019

|             |                                                                                            |
|-------------|--------------------------------------------------------------------------------------------|
| Message     | VSX <code>&lt;vsx_role&gt;</code> image update failed due to <code>&lt;reason&gt;</code> . |
| Category    | Virtual Switching Extension (VSX)                                                          |
| Severity    | Error                                                                                      |
| Description | VSX image update failed.                                                                   |

#### Event ID: 7020

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | ISL out-of-sync and keepalive is in established                      |
| Category    | Virtual Switching Extension (VSX)                                    |
| Severity    | Information                                                          |
| Description | ISL out-of-sync and keepalive is in established, handled split brain |

#### Event ID: 7021

|             |                                           |
|-------------|-------------------------------------------|
| Message     | ISL out-of-sync and keepalive also failed |
| Category    | Virtual Switching Extension (VSX)         |
| Severity    | Information                               |
| Description | ISL out-of-sync and keepalive also failed |

#### Event ID: 7022

|             |                                   |
|-------------|-----------------------------------|
| Message     | Linkup delay timer started        |
| Category    | Virtual Switching Extension (VSX) |
| Severity    | Information                       |
| Description | Linkup delay timer started        |

#### Event ID: 7023

|             |                                   |
|-------------|-----------------------------------|
| Message     | Linkup delay timer expired        |
| Category    | Virtual Switching Extension (VSX) |
| Severity    | Information                       |
| Description | Linkup delay timer expired        |

#### Event ID: 7024

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | VSX <vsx_role> state changed from <prev_state> to <state>. |
| Category    | Virtual Switching Extension (VSX)                          |
| Severity    | Information                                                |
| Description | VSX software update state change.                          |

#### Event ID: 7025

|         |                       |
|---------|-----------------------|
| Message | Bailout timer started |
|---------|-----------------------|



|             |                                   |
|-------------|-----------------------------------|
| Category    | Virtual Switching Extension (VSX) |
| Severity    | Information                       |
| Description | Bailout timer started             |

#### Event ID: 7026

|             |                                    |
|-------------|------------------------------------|
| Message     | <code>Bailout timer expired</code> |
| Category    | Virtual Switching Extension (VSX)  |
| Severity    | Information                        |
| Description | Bailout timer expired              |

#### Event ID: 7027

|             |                                    |
|-------------|------------------------------------|
| Message     | <code>Bailout timer stopped</code> |
| Category    | Virtual Switching Extension (VSX)  |
| Severity    | Information                        |
| Description | Bailout timer stopped              |

#### Event ID: 7028

|             |                                         |
|-------------|-----------------------------------------|
| Message     | <code>Linkup-delay timer stopped</code> |
| Category    | Virtual Switching Extension (VSX)       |
| Severity    | Information                             |
| Description | Linkup-delay timer stopped              |

#### Event ID: 7029

|             |                                                                                                                                            |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>VSX device roles are inconsistent: local VSX device role &lt;local_vsx_role&gt;, peer VSX device role &lt;peer_vsx_role&gt;</code>   |
| Category    | Virtual Switching Extension (VSX)                                                                                                          |
| Severity    | Error                                                                                                                                      |
| Description | VSX device roles are said to be consistent only if one VSX device is configured as primary and other VSX device is configured as secondary |

#### Event ID: 7029

|         |                                                                                     |
|---------|-------------------------------------------------------------------------------------|
| Message | <code>VSX &lt;vsx_role&gt; state changed to &lt;state&gt;-&lt;sub_state&gt;.</code> |
|---------|-------------------------------------------------------------------------------------|

|             |                                       |
|-------------|---------------------------------------|
| Category    | Virtual Switching Extension (VSX)     |
| Severity    | Information                           |
| Description | VSX software update sub-state change. |

#### Event ID: 7030

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | VSX Keepalive is configured without creating VRF         |
| Category    | Virtual Switching Extension (VSX)                        |
| Severity    | Information                                              |
| Description | VRF needs to be created before configuring VSX Keepalive |

#### Event ID: 7031

|             |                                                                    |
|-------------|--------------------------------------------------------------------|
| Message     | VSX Keepalive is configured without configuring IP address         |
| Category    | Virtual Switching Extension (VSX)                                  |
| Severity    | Information                                                        |
| Description | IP address needs to be configured before configuring VSX Keepalive |

#### Event ID: 7032

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | Active-gateway is enabled on <port>. Cannot program Active-forwarding |
| Category    | Virtual Switching Extension (VSX)                                     |
| Severity    | Error                                                                 |
| Description | Failed to program active-forwarding.                                  |

#### Event ID: 7033

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | Active-forwarding is enabled on <port>. Cannot program Active-gateway |
| Category    | Virtual Switching Extension (VSX)                                     |
| Severity    | Error                                                                 |
| Description | Failed to program active-gateway.                                     |

#### Event ID: 7034

|          |                                                      |
|----------|------------------------------------------------------|
| Message  | Netdev <ifname> configured with ipv4 address <value> |
| Category | Virtual Switching Extension (VSX)                    |

|             |                                                     |
|-------------|-----------------------------------------------------|
| Severity    | Information                                         |
| Description | programmed active-gateway IP4 address successfully. |

### Event ID: 7035

|             |                                                      |
|-------------|------------------------------------------------------|
| Message     | Netdev <ifname> configured with ipv6 address <value> |
| Category    | Virtual Switching Extension (VSX)                    |
| Severity    | Information                                          |
| Description | programmed active-gateway IP6 address successfully.  |

The following are the events related to VSF.

### Event ID: 9901

|             |                                               |
|-------------|-----------------------------------------------|
| Message     | Member <i>&lt;member_id&gt;</i> boot complete |
| Category    | Virtual Switching Framework (VSF)             |
| Severity    | Information                                   |
| Description | log event for member boot complete            |

### Event ID: 9902

|             |                                                |
|-------------|------------------------------------------------|
| Message     | Standby <i>&lt;member_id&gt;</i> boot complete |
| Category    | Virtual Switching Framework (VSF)              |
| Severity    | Information                                    |
| Description | log event for standby boot complete            |

### Event ID: 9903

|             |                                               |
|-------------|-----------------------------------------------|
| Message     | Master <i>&lt;member_id&gt;</i> boot complete |
| Category    | Virtual Switching Framework (VSF)             |
| Severity    | Information                                   |
| Description | log event for Master boot complete            |

### Event ID: 9905

|             |                                              |
|-------------|----------------------------------------------|
| Message     | Resetting member <i>&lt;member_id&gt;</i>    |
| Category    | Virtual Switching Framework (VSF)            |
| Severity    | Information                                  |
| Description | Event log indicates that member is resetting |

### Event ID: 9906 (Severity: Warning)

|             |                                                                                |
|-------------|--------------------------------------------------------------------------------|
| Message     | Member <member_id> conflict detected on link <link>                            |
| Category    | Virtual Switching Framework (VSF)                                              |
| Severity    | Warning                                                                        |
| Description | Event log for Failed processing Hello packet because of member number conflict |

#### Event ID: 9907 (Severity: Warning)

|             |                                                                    |
|-------------|--------------------------------------------------------------------|
| Message     | Incompatible version detected                                      |
| Category    | Virtual Switching Framework (VSF)                                  |
| Severity    | Warning                                                            |
| Description | Event log for indicates that we got a packet with a diff proto ver |

#### Event ID: 9908

|             |                                          |
|-------------|------------------------------------------|
| Message     | Topology is <topo_type>                  |
| Category    | Virtual Switching Framework (VSF)        |
| Severity    | Information                              |
| Description | Event log indicates the current topology |

#### Event ID: 9910

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | Member <member_id> removed                                          |
| Category    | Virtual Switching Framework (VSF)                                   |
| Severity    | Information                                                         |
| Description | Event log indicates the member has been removed due to user request |

#### Event ID: 9911 (Severity: Warning)

|             |                                                                                                       |
|-------------|-------------------------------------------------------------------------------------------------------|
| Message     | Maximum number of switches in the stack has reached. Cannot add MAC <mac_address> product type <type> |
| Category    | Virtual Switching Framework (VSF)                                                                     |
| Severity    | Warning                                                                                               |
| Description | Event log indicates that we would exceed the MAX switches if we add this new switch                   |

#### Event ID: 9912

|             |                                                                         |
|-------------|-------------------------------------------------------------------------|
| Message     | Stack state is no-split with master id <member_id>' throttle_count: 100 |
| Category    | Virtual Switching Framework (VSF)                                       |
| Severity    | Information                                                             |
| Description | log event for stack state active                                        |

### Event ID: 9913 (Severity: Warning)

|             |                                       |
|-------------|---------------------------------------|
| Message     | Lost member <member_id> with <reason> |
| Category    | Virtual Switching Framework (VSF)     |
| Severity    | Warning                               |
| Description | Event log for lost member             |

### Event ID: 9914

|             |                                             |
|-------------|---------------------------------------------|
| Message     | Reboot of MAC <mac_address> status-<status> |
| Category    | Virtual Switching Framework (VSF)           |
| Severity    | Information                                 |
| Description | Event log for status of a reboot request    |

### Event ID: 9915

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | Member <member_id> elected as commander reason-<reason> |
| Category    | Virtual Switching Framework (VSF)                       |
| Severity    | Information                                             |
| Description | log event for the switch won as master                  |

### Event ID: 9916

|             |                                                       |
|-------------|-------------------------------------------------------|
| Message     | Member <member_id> elected as standby reason-<reason> |
| Category    | Virtual Switching Framework (VSF)                     |
| Severity    | Information                                           |
| Description | log event for the switch won as standby               |

### Event ID: 9917 (Severity: Warning)

|         |                                                                                          |
|---------|------------------------------------------------------------------------------------------|
| Message | Switch with MAC <mac_address> cannot join stack due to incorrect product id <product_id> |
|---------|------------------------------------------------------------------------------------------|

|             |                                                                                 |
|-------------|---------------------------------------------------------------------------------|
| Category    | Virtual Switching Framework (VSF)                                               |
| Severity    | Warning                                                                         |
| Description | log event for the member was not allowed to join due to a mismatched product-id |

### Event ID: 9919 (Severity: Warning)

|             |                                                                                                                                                                                                                               |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Found Unsupported switch with MAC <code>&lt;mac_address&gt;</code> and Product type <code>&lt;product_type&gt;</code> , connected to switch with MAC <code>&lt;mac_addr&gt;</code> on stack port <code>&lt;port_id&gt;</code> |
| Category    | Virtual Switching Framework (VSF)                                                                                                                                                                                             |
| Severity    | Warning                                                                                                                                                                                                                       |
| Description | log event for switch running on a different platform and trying to join the stack                                                                                                                                             |

### Event ID: 9920 (Severity: Warning)

|             |                                                           |
|-------------|-----------------------------------------------------------|
| Message     | Heart beat lost for member <code>&lt;member_id&gt;</code> |
| Category    | Virtual Switching Framework (VSF)                         |
| Severity    | Warning                                                   |
| Description | log event for heart beat lost                             |

### Event ID: 9921 (Severity: Warning)

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | OS version mismatch detected for member <code>&lt;member_id&gt;</code> |
| Category    | Virtual Switching Framework (VSF)                                      |
| Severity    | Warning                                                                |
| Description | log event when os_version_mismatch happened on standby and member      |

### Event ID: 9922 (Severity: Warning)

|             |                                                                                 |
|-------------|---------------------------------------------------------------------------------|
| Message     | Attempt to connect member <code>&lt;member_id&gt;</code> from a different stack |
| Category    | Virtual Switching Framework (VSF)                                               |
| Severity    | Warning                                                                         |
| Description | log event when member attempt to connect to a different stack                   |

### Event ID: 9923

|         |                                          |
|---------|------------------------------------------|
| Message | VSF link <code>&lt;link&gt;</code> is up |
|---------|------------------------------------------|

|             |                                   |
|-------------|-----------------------------------|
| Category    | Virtual Switching Framework (VSF) |
| Severity    | Information                       |
| Description | log event when vsf link is up     |

#### Event ID: 9924

|             |                                   |
|-------------|-----------------------------------|
| Message     | VSF link <link> is down           |
| Category    | Virtual Switching Framework (VSF) |
| Severity    | Information                       |
| Description | log event when vsf link is down   |

#### Event ID: 9925 (Severity: Warning)

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | Invalid MAC <mac_address> detected on link <link> with peer MAC <mac_add> |
| Category    | Virtual Switching Framework (VSF)                                         |
| Severity    | Warning                                                                   |
| Description | log event when different MAC address on the same link                     |

#### Event ID: 9926 (Severity: Warning)

|             |                                                     |
|-------------|-----------------------------------------------------|
| Message     | 2 member loop detected on ring topology             |
| Category    | Virtual Switching Framework (VSF)                   |
| Severity    | Warning                                             |
| Description | log event when there is a 2 member loop in topology |

#### Event ID: 9927

|             |                                                                 |
|-------------|-----------------------------------------------------------------|
| Message     | Fragment with master <member_id> is Active' throttle_count: 100 |
| Category    | Virtual Switching Framework (VSF)                               |
| Severity    | Information                                                     |
| Description | log event for active fragment                                   |

#### Event ID: 9928

|         |                                              |
|---------|----------------------------------------------|
| Message | Fragment with master <member_id> is Inactive |
|---------|----------------------------------------------|



|             |                                   |
|-------------|-----------------------------------|
| Category    | Virtual Switching Framework (VSF) |
| Severity    | Information                       |
| Description | log event for Inactive fragment   |

#### Event ID: 9929

|             |                                              |
|-------------|----------------------------------------------|
| Message     | Active fragment detection timeout            |
| Category    | Virtual Switching Framework (VSF)            |
| Severity    | Information                                  |
| Description | log event for active stack detection timeout |

#### Event ID: 9930

|             |                                               |
|-------------|-----------------------------------------------|
| Message     | Member <member_id> is configured as Secondary |
| Category    | Virtual Switching Framework (VSF)             |
| Severity    | Information                                   |
| Description | log event for standby configuration           |

#### Event ID: 9931

|             |                                       |
|-------------|---------------------------------------|
| Message     | Secondary configuration removed       |
| Category    | Virtual Switching Framework (VSF)     |
| Severity    | Information                           |
| Description | log event for standby unconfiguration |

#### Event ID: 9932

|             |                                                                                                            |
|-------------|------------------------------------------------------------------------------------------------------------|
| Message     | Attempt to connect a member with MAC <mac_address> and product type <product_id> having different airflows |
| Category    | Virtual Switching Framework (VSF)                                                                          |
| Severity    | Information                                                                                                |
| Description | log event when Mater SKU device joins the stack                                                            |

#### Event ID: 9933 (Severity: Warning)

|         |                                     |
|---------|-------------------------------------|
| Message | Peer timeout on interface <port_id> |
|---------|-------------------------------------|

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Category    | Virtual Switching Framework (VSF)                            |
| Severity    | Warning                                                      |
| Description | log event for peer time out as it did not receive any packet |

#### Event ID: 9934 (Severity: Warning)

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | Loop detected on interface <code>&lt;port_id&gt;</code> |
| Category    | Virtual Switching Framework (VSF)                       |
| Severity    | Warning                                                 |
| Description | log event for loop detection in link                    |

#### Event ID: 9935 (Severity: Warning)

|             |                                                                                               |
|-------------|-----------------------------------------------------------------------------------------------|
| Message     | Interface <code>&lt;port_id&gt;</code> detected a peer with a different VSF handshake version |
| Category    | Virtual Switching Framework (VSF)                                                             |
| Severity    | Warning                                                                                       |
| Description | log event when peer switch is in different VSF handshake version                              |

#### Event ID: 9936

|             |                                                                                    |
|-------------|------------------------------------------------------------------------------------|
| Message     | Interface <code>&lt;port_id&gt;</code> added to VSF link <code>&lt;link&gt;</code> |
| Category    | Virtual Switching Framework (VSF)                                                  |
| Severity    | Information                                                                        |
| Description | log event when interface added to a particular link                                |

#### Event ID: 9937

|             |                                                                                        |
|-------------|----------------------------------------------------------------------------------------|
| Message     | Interface <code>&lt;port_id&gt;</code> removed from VSF link <code>&lt;link&gt;</code> |
| Category    | Virtual Switching Framework (VSF)                                                      |
| Severity    | Information                                                                            |
| Description | log event when interface removed from a particular link                                |

#### Event ID: 9938 (Severity: Warning)

|         |                                                                                                                                                                               |
|---------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message | Switch with mac <code>&lt;mac_address&gt;</code> not able to autojoin as it is connected on interface <code>&lt;port&gt;</code> which is a non default autojoin VSF interface |
|---------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|

|             |                                                                                                       |
|-------------|-------------------------------------------------------------------------------------------------------|
| Category    | Virtual Switching Framework (VSF)                                                                     |
| Severity    | Warning                                                                                               |
| Description | log event when the switch is not able to autojoin as it is connected with a non default VSF interface |

#### Event ID: 9939 (Severity: Warning)

|             |                                                                                                                                                                                                                  |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Switch with MAC <code>&lt;mac_address&gt;</code> not able to autojoin as it is connected on interface <code>&lt;port&gt;</code> which is not provisioned on the master for member <code>&lt;member_id&gt;</code> |
| Category    | Virtual Switching Framework (VSF)                                                                                                                                                                                |
| Severity    | Warning                                                                                                                                                                                                          |
| Description | log event when there is an inconsistency detected between masters provisioned VSF link configuration and the interface on which switch is attempting to autojoin                                                 |

#### Event ID: 9940 (Severity: Warning)

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | Switch with MAC <code>&lt;mac_address&gt;</code> is not autojoin eligible |
| Category    | Virtual Switching Framework (VSF)                                         |
| Severity    | Warning                                                                   |
| Description | log event when peer switch is not autojoin eligible                       |

#### Event ID: 9941 (Severity: Warning)

|             |                                                                                                           |
|-------------|-----------------------------------------------------------------------------------------------------------|
| Message     | Switch with MAC <code>&lt;mac_address&gt;</code> attempting to autojoin via multiple interfaces           |
| Category    | Virtual Switching Framework (VSF)                                                                         |
| Severity    | Warning                                                                                                   |
| Description | log event when there is more than one interface physically connected to same switch VSF link for autojoin |

#### Event ID: 9942 (Severity: Warning)

|             |                                                                                                                 |
|-------------|-----------------------------------------------------------------------------------------------------------------|
| Message     | Switch with MAC <code>&lt;mac_address&gt;</code> failed to autojoin as there is no free member number available |
| Category    | Virtual Switching Framework (VSF)                                                                               |
| Severity    | Warning                                                                                                         |
| Description | log even when switch is not allowed to autojoin because of insufficient resources                               |

#### Event ID: 9943 (Severity: Warning)

|             |                                                                                                                                        |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Switch with mac <code>&lt;mac_address&gt;</code> failed to autojoin on link <code>&lt;link&gt;</code> , port <code>&lt;port&gt;</code> |
| Category    | Virtual Switching Framework (VSF)                                                                                                      |
| Severity    | Warning                                                                                                                                |
| Description | log event when two different switches are attempting to autojoin by connecting to the same VSF link on the peer                        |

#### Event ID: 9944 (Severity: Warning)

|             |                                                                                                                                                                                                      |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Switch has VSF configurations present. Force autojoin will not take into effect. Remove all VSF configurations followed by unconfiguring and reconfiguring force autojoin for it to take into effect |
| Category    | Virtual Switching Framework (VSF)                                                                                                                                                                    |
| Severity    | Warning                                                                                                                                                                                              |
| Description | log event when VSF force autojoin fails as VSF configurations exists                                                                                                                                 |

#### Event ID: 9945

|             |                                              |
|-------------|----------------------------------------------|
| Message     | VSF force autojoin enabled                   |
| Category    | Virtual Switching Framework (VSF)            |
| Severity    | Information                                  |
| Description | log event when VSF force autojoin is enabled |

#### Event ID: 9946

|             |                                               |
|-------------|-----------------------------------------------|
| Message     | VSF force autojoin disabled                   |
| Category    | Virtual Switching Framework (VSF)             |
| Severity    | Information                                   |
| Description | log event when VSF force autojoin is disabled |

#### Event ID: 9947 (Severity: Warning)

|             |                                                                                                                                                                                                         |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Switch with MAC <code>&lt;mac_addr1&gt;</code> failed to autojoin. Connect the device <code>&lt;mac_addr2&gt;</code> to member <code>&lt;mbr_id&gt;</code> link <code>&lt;link_id&gt;</code> to proceed |
| Category    | Virtual Switching Framework (VSF)                                                                                                                                                                       |
| Severity    | Warning                                                                                                                                                                                                 |
| Description | log event when member connected to an unsupported interface                                                                                                                                             |

#### Event ID: 9948 (Severity: Warning)

|             |                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------|
| Message     | Interface <port_id> in VSF link <link> detected a peer with inconsistent VSF link configuration |
| Category    | Virtual Switching Framework (VSF)                                                               |
| Severity    | Warning                                                                                         |
| Description | log event when interface is in inconsistent link configuration error                            |

#### Event ID: 9949

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | Secondary member changed from <old_standby_id> to <new_standby_id>          |
| Category    | Virtual Switching Framework (VSF)                                           |
| Severity    | Information                                                                 |
| Description | log event when existing secondary changes to new specified secondary member |

The following are the events related to VLAN.

#### Event ID: 2101

|             |                                                                  |
|-------------|------------------------------------------------------------------|
| Message     | VLAN <vid> created in hardware                                   |
| Category    | VLAN                                                             |
| Severity    | Information                                                      |
| Description | This log event informs the user that VLAN is created in Hardware |

#### Event ID: 2102

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | Failed to create VLAN <vid> in Hardware                              |
| Category    | VLAN                                                                 |
| Severity    | Error                                                                |
| Description | This log event informs the user that VLAN is not created in Hardware |

#### Event ID: 2103

|             |                                                                    |
|-------------|--------------------------------------------------------------------|
| Message     | VLAN <vid> removed from hardware                                   |
| Category    | VLAN                                                               |
| Severity    | Information                                                        |
| Description | This log event informs the user that VLAN is removed from Hardware |

#### Event ID: 2104

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | Failed to remove VLAN <vid> from hardware                              |
| Category    | VLAN                                                                   |
| Severity    | Error                                                                  |
| Description | This log event informs the user that VLAN is not removed from Hardware |

#### Event ID: 2105

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | Internal VLAN <vid> is allocated to port <port>                |
| Category    | VLAN                                                           |
| Severity    | Information                                                    |
| Description | This log event informs that internal VLAN is allocated to port |

#### Event ID: 2106

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | Failed to allocate internal VLAN to port <port>            |
| Category    | VLAN                                                       |
| Severity    | Error                                                      |
| Description | This log event informs that internal VLAN is not allocated |

#### Event ID: 2107

|             |                                                                                                           |
|-------------|-----------------------------------------------------------------------------------------------------------|
| Message     | The mode for port <port> changed from <from> to <to> on VLAN <vid>                                        |
| Category    | VLAN                                                                                                      |
| Severity    | Information                                                                                               |
| Description | This log event informs that the port mode has changed from one of the trunk types to access or vice versa |

#### Event ID: 2108

|             |                                                                                   |
|-------------|-----------------------------------------------------------------------------------|
| Message     | Created Mac based VLAN entry. VLAN <vid> is mapped to client <mac> on port <port> |
| Category    | VLAN                                                                              |
| Severity    | Information                                                                       |
| Description | This log event informs the user that Mac based VLAN is created in Hardware        |

#### Event ID: 2109

|             |                                                                                |
|-------------|--------------------------------------------------------------------------------|
| Message     | Failed to create Mac based VLAN entry for <mac> with VLAN <vid> on port <port> |
| Category    | VLAN                                                                           |
| Severity    | Error                                                                          |
| Description | This log event informs the user that Mac based VLAN is not created in Hardware |

#### Event ID: 2110

|             |                                                                              |
|-------------|------------------------------------------------------------------------------|
| Message     | Deleted Mac based VLAN entry for <mac> with VLAN <vid> on port <port>        |
| Category    | VLAN                                                                         |
| Severity    | Information                                                                  |
| Description | This log event informs the user that MAC based VLAN is removed from Hardware |

#### Event ID: 2111

|             |                                                                                  |
|-------------|----------------------------------------------------------------------------------|
| Message     | Failed to remove Mac based VLAN entry for <mac> with VLAN <vid> on port <port>   |
| Category    | VLAN                                                                             |
| Severity    | Error                                                                            |
| Description | This log event informs the user that MAC based VLAN is not removed from Hardware |

#### Event ID: 2112

|             |                                                                                   |
|-------------|-----------------------------------------------------------------------------------|
| Message     | Updated MAC based VLAN entry. VLAN <vid> is mapped to client <mac> on port <port> |
| Category    | VLAN                                                                              |
| Severity    | Information                                                                       |
| Description | This log event informs the user that MAC based VLAN is updated in Hardware        |

#### Event ID: 2113

|             |                                                                                |
|-------------|--------------------------------------------------------------------------------|
| Message     | Failed to update Mac based VLAN entry for <mac> with VLAN <vid> on port <port> |
| Category    | VLAN                                                                           |
| Severity    | Error                                                                          |
| Description | This log event informs the user that MAC based VLAN is not updated in Hardware |

#### Event ID: 2114

|             |                                                            |
|-------------|------------------------------------------------------------|
| Message     | Internal VLAN changed to <vlan>                            |
| Category    | VLAN                                                       |
| Severity    | Information                                                |
| Description | This log event informs that internal VLAN range is changed |

#### Event ID: 2115



|             |                                                                          |
|-------------|--------------------------------------------------------------------------|
| Message     | VLAN <vid> is down due to pvlan misconfig reason <reason>                |
| Category    | VLAN                                                                     |
| Severity    | Information                                                              |
| Description | This log event informs the user that VLAN is down due to pvlan misconfig |

### Event ID: 2116

|             |                                                                             |
|-------------|-----------------------------------------------------------------------------|
| Message     | VLAN <vid> is recovered from pvlan misconfig                                |
| Category    | VLAN                                                                        |
| Severity    | Information                                                                 |
| Description | This log event informs the user that VLAN is recovered from pvlan misconfig |

The following are the events related to VLAN interface.

#### Event ID: 1601

|             |                                                                          |
|-------------|--------------------------------------------------------------------------|
| Message     | Vlaninterface vlan<vlan>, failed to create an l3 interface, error: <err> |
| Category    | VLAN Interface                                                           |
| Severity    | Error                                                                    |
| Description | logs errors while creating vlaninterface.                                |

#### Event ID: 1602

|             |                                     |
|-------------|-------------------------------------|
| Message     | Vlan Interface <interface>, created |
| Category    | VLAN Interface                      |
| Severity    | Information                         |
| Description | logs to create vlan interface.      |

The following are the events related to VRF.

### Event ID: 6401

|             |                                                          |
|-------------|----------------------------------------------------------|
| Message     | VRF with vrf name <vrf_name> is configured in the switch |
| Category    | VRF                                                      |
| Severity    | Information                                              |
| Description | Logs a message when VRF is configured in the switch      |

### Event ID: 6402

|             |                                                                |
|-------------|----------------------------------------------------------------|
| Message     | Failed to configure VRF with vrf name <vrf_name> in the switch |
| Category    | VRF                                                            |
| Severity    | Error                                                          |
| Description | Logs a message when VRF configuration failed in the switch     |

### Event ID: 6403

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | VRF with vrf name <vrf_name> is deleted from the switch |
| Category    | VRF                                                     |
| Severity    | Information                                             |
| Description | Logs a message when VRF is deleted from the switch      |

### Event ID: 6404

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | Failed to delete VRF with vrf name <vrf_name> from the switch |
| Category    | VRF                                                           |
| Severity    | Error                                                         |
| Description | Logs a message when VRF deletion failed in the switch         |

The following are the events related to VRF Manager.

#### Event ID: 5401

|          |                                   |
|----------|-----------------------------------|
| Message  | Created a vrf entity <vrf_entity> |
| Category | VRF Manager                       |
| Severity | Information                       |

#### Event ID: 5402

|          |                                   |
|----------|-----------------------------------|
| Message  | Deleted a vrf entity <vrf_entity> |
| Category | VRF Manager                       |
| Severity | Information                       |

#### Event ID: 5403

|          |                                         |
|----------|-----------------------------------------|
| Message  | vrf entity creation failed <vrf_entity> |
| Category | VRF Manager                             |
| Severity | Error                                   |

The following are the events related to VRRP.

### Event ID: 3701

|             |                                      |
|-------------|--------------------------------------|
| Message     | VRRP has been enabled on this router |
| Category    | VRRP                                 |
| Severity    | Information                          |
| Description | Logs VRRP global enable event        |

### Event ID: 3702

|             |                                       |
|-------------|---------------------------------------|
| Message     | VRRP has been disabled on this router |
| Category    | VRRP                                  |
| Severity    | Information                           |
| Description | Logs VRRP global disable event        |

### Event ID: 3703

|             |                                                                                                              |
|-------------|--------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;inet_type&gt; virtual router &lt;vrid&gt; on interface &lt;interface&gt; has taken owner IP</code> |
| Category    | VRRP                                                                                                         |
| Severity    | Information                                                                                                  |
| Description | Logs virtual router has taken control of owner IP                                                            |

### Event ID: 3704

|             |                                                                                                               |
|-------------|---------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;inet_type&gt; virtual router &lt;vrid&gt; on interface &lt;interface&gt; has taken backup IP</code> |
| Category    | VRRP                                                                                                          |
| Severity    | Information                                                                                                   |
| Description | Logs virtual router has taken control of backup IP                                                            |

### Event ID: 3705

|             |                                                                                                          |
|-------------|----------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;inet_type&gt; virtual router &lt;vrid&gt; on interface &lt;interface&gt; lost backup IP</code> |
| Category    | VRRP                                                                                                     |
| Severity    | Information                                                                                              |
| Description | Logs virtual router has lost control of backup IP                                                        |

#### Event ID: 3706

|             |                                                                                                   |
|-------------|---------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;inet_type&gt; virtual router &lt;vrid&gt; created on interface &lt;interface&gt;</code> |
| Category    | VRRP                                                                                              |
| Severity    | Information                                                                                       |
| Description | Logs creation of virtual router on interface                                                      |

#### Event ID: 3707

|             |                                                                                                     |
|-------------|-----------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;inet_type&gt; virtual router &lt;vrid&gt; deleted from interface &lt;interface&gt;</code> |
| Category    | VRRP                                                                                                |
| Severity    | Information                                                                                         |
| Description | Logs deletion of virtual router from interface                                                      |

#### Event ID: 3708

|             |                                                                                                                          |
|-------------|--------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; address &lt;address&gt; is added to virtual router &lt;vrid&gt; on interface &lt;interface&gt;</code> |
| Category    | VRRP                                                                                                                     |
| Severity    | Information                                                                                                              |
| Description | Logs addition of IP address to virtual router                                                                            |

#### Event ID: 3709

|             |                                                                                                                              |
|-------------|------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;type&gt; address &lt;address&gt; is deleted from virtual router &lt;vrid&gt; on interface &lt;interface&gt;</code> |
| Category    | VRRP                                                                                                                         |
| Severity    | Information                                                                                                                  |
| Description | Logs deletion of IP address from virtual router                                                                              |

#### Event ID: 3710

|             |                                                                                                                            |
|-------------|----------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;inet_type&gt; virtual router &lt;vrid&gt; version changed to &lt;value&gt; on interface &lt;interface&gt;</code> |
| Category    | VRRP                                                                                                                       |
| Severity    | Information                                                                                                                |
| Description | Logs version change for virtual router                                                                                     |

#### Event ID: 3711

|             |                                                                                                                                                            |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;inet_type&gt; virtual router &lt;vrid&gt; advertisement interval has changed to &lt;value&gt; milliseconds on interface &lt;interface&gt;</code> |
| Category    | VRRP                                                                                                                                                       |
| Severity    | Information                                                                                                                                                |
| Description | Logs advertisement timer has changed for virtual router                                                                                                    |

#### Event ID: 3712

|             |                                                                                                                                                   |
|-------------|---------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;inet_type&gt; virtual router &lt;vrid&gt; preempt delay time has changed to &lt;value&gt; seconds on interface &lt;interface&gt;</code> |
| Category    | VRRP                                                                                                                                              |
| Severity    | Information                                                                                                                                       |
| Description | Logs preempt delay timer has changed for virtual router                                                                                           |

#### Event ID: 3713

|             |                                                                                                                                                    |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;inet_type&gt; virtual router &lt;vrid&gt; state change from &lt;old_state&gt; to &lt;new_state&gt; on interface &lt;interface&gt;</code> |
| Category    | VRRP                                                                                                                                               |
| Severity    | Information                                                                                                                                        |
| Description | Logs state has changed for virtual router on interface                                                                                             |

#### Event ID: 3714

|             |                                                                                                                      |
|-------------|----------------------------------------------------------------------------------------------------------------------|
| Message     | <code>Enabled preempt option for &lt;inet_type&gt; virtual router &lt;vrid&gt; on interface &lt;interface&gt;</code> |
| Category    | VRRP                                                                                                                 |
| Severity    | Information                                                                                                          |
| Description | Logs preempt option has been enabled for virtual router                                                              |

#### Event ID: 3715

|             |                                                                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Enabled virtual IP ping for <code>&lt;inet_type&gt;</code> virtual router <code>&lt;vrid&gt;</code> on interface <code>&lt;interface&gt;</code> |
| Category    | VRRP                                                                                                                                            |
| Severity    | Information                                                                                                                                     |
| Description | Logs virtual IP ping has been enabled for virtual router                                                                                        |

#### Event ID: 3716

|             |                                                                                                                             |
|-------------|-----------------------------------------------------------------------------------------------------------------------------|
| Message     | Enabled <code>&lt;inet_type&gt;</code> virtual router <code>&lt;vrid&gt;</code> on interface <code>&lt;interface&gt;</code> |
| Category    | VRRP                                                                                                                        |
| Severity    | Information                                                                                                                 |
| Description | Logs virtual router has been enabled on interface                                                                           |

#### Event ID: 3717

|             |                                                                                                                                                 |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Disabled preempt option for <code>&lt;inet_type&gt;</code> virtual router <code>&lt;vrid&gt;</code> on interface <code>&lt;interface&gt;</code> |
| Category    | VRRP                                                                                                                                            |
| Severity    | Information                                                                                                                                     |
| Description | Logs preempt option has been disabled for virtual router                                                                                        |

#### Event ID: 3718

|             |                                                                                                                                                  |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | Disabled virtual IP ping for <code>&lt;inet_type&gt;</code> virtual router <code>&lt;vrid&gt;</code> on interface <code>&lt;interface&gt;</code> |
| Category    | VRRP                                                                                                                                             |
| Severity    | Information                                                                                                                                      |
| Description | Logs virtual IP ping has been disabled for virtual router                                                                                        |

#### Event ID: 3719

|             |                                                                                                                              |
|-------------|------------------------------------------------------------------------------------------------------------------------------|
| Message     | Disabled <code>&lt;inet_type&gt;</code> virtual router <code>&lt;vrid&gt;</code> on interface <code>&lt;interface&gt;</code> |
| Category    | VRRP                                                                                                                         |
| Severity    | Information                                                                                                                  |
| Description | Logs virtual router has been disabled on interface                                                                           |

#### Event ID: 3720



|             |                                                                                                                             |
|-------------|-----------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;inet_type&gt; virtual router &lt;vrid&gt; priority changed to &lt;value&gt; on interface &lt;interface&gt;</code> |
| Category    | VRRP                                                                                                                        |
| Severity    | Information                                                                                                                 |
| Description | Logs priority has been changed for virtual router                                                                           |

#### Event ID: 3721

|             |                                                                                                                         |
|-------------|-------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;inet_type&gt; virtual router &lt;vrid&gt; mode changed to &lt;value&gt; on interface &lt;interface&gt;</code> |
| Category    | VRRP                                                                                                                    |
| Severity    | Information                                                                                                             |
| Description | Logs virtual router mode has been changed                                                                               |

#### Event ID: 3722

|             |                                                                                                          |
|-------------|----------------------------------------------------------------------------------------------------------|
| Message     | <code>Track object &lt;track&gt; is associated with &lt;inet_type&gt; virtual router &lt;vrid&gt;</code> |
| Category    | VRRP                                                                                                     |
| Severity    | Information                                                                                              |
| Description | Logs track object has been associated with virtual router                                                |

#### Event ID: 3723

|             |                                                                                                             |
|-------------|-------------------------------------------------------------------------------------------------------------|
| Message     | <code>Track object &lt;track&gt; is de-associated from &lt;inet_type&gt; virtual router &lt;vrid&gt;</code> |
| Category    | VRRP                                                                                                        |
| Severity    | Information                                                                                                 |
| Description | Logs track object has been de-associated from virtual router                                                |

#### Event ID: 3724

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | <code>Track object &lt;track&gt; is created</code> |
| Category    | VRRP                                               |
| Severity    | Information                                        |
| Description | Logs track object has been created                 |

#### Event ID: 3725

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | Track object <code>&lt;track&gt;</code> is deleted |
| Category    | VRRP                                               |
| Severity    | Information                                        |
| Description | Logs track object has been deleted                 |

#### Event ID: 3726

|             |                                                                                                                        |
|-------------|------------------------------------------------------------------------------------------------------------------------|
| Message     | Track object <code>&lt;track&gt;</code> state changed <code>&lt;old_state&gt;</code> to <code>&lt;new_state&gt;</code> |
| Category    | VRRP                                                                                                                   |
| Severity    | Information                                                                                                            |
| Description | Logs track object state change                                                                                         |

#### Event ID: 3727

|             |                                                                                                  |
|-------------|--------------------------------------------------------------------------------------------------|
| Message     | Track object <code>&lt;track&gt;</code> associated with interface <code>&lt;interface&gt;</code> |
| Category    | VRRP                                                                                             |
| Severity    | Information                                                                                      |
| Description | Logs track object association with interface                                                     |

#### Event ID: 3728

|             |                                                                                                                                                                       |
|-------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;inet_type&gt;</code> virtual router <code>&lt;vrid&gt;</code> recieved packet with authentication type mismatch on interface <code>&lt;interface&gt;</code> |
| Category    | VRRP                                                                                                                                                                  |
| Severity    | Information                                                                                                                                                           |
| Description | Logs authentication failures on virtual router                                                                                                                        |

#### Event ID: 3729

|             |                                                                                                                                                                      |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Message     | <code>&lt;inet_type&gt;</code> virtual router <code>&lt;vrid&gt;</code> recieved packet with authentication key mismatch on interface <code>&lt;interface&gt;</code> |
| Category    | VRRP                                                                                                                                                                 |
| Severity    | Information                                                                                                                                                          |
| Description | Logs authentication failures on virtual router                                                                                                                       |

The following are the events related to VSX sync.

#### Event ID: 7601

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | Configuration sync error: <id>                                      |
| Category    | VSX Sync                                                            |
| Severity    | Error                                                               |
| Description | Logs event when error in synchronizing config between two VSX peers |

#### Event ID: 7602

|             |                                                    |
|-------------|----------------------------------------------------|
| Message     | Configuration sync update: <id>                    |
| Category    | VSX Sync                                           |
| Severity    | Information                                        |
| Description | Logs event when there is an update for config sync |

#### Event ID: 7603

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | Configuration-persistence: <id>                                           |
| Category    | VSX Sync                                                                  |
| Severity    | Information                                                               |
| Description | Logs event when config is copied to startup-config on any of the VSX peer |

The following are the events related to VXLAN agent.

#### Event ID: 12403

|             |                                                                              |
|-------------|------------------------------------------------------------------------------|
| Message     | Netvp add failed for vni_id: <vni_id>, tunnel_id: <tunnel_id>, vlan: <vlan>. |
| Category    | VXLAN agent                                                                  |
| Severity    | Error                                                                        |
| Description | Event raised when netvp add fails in agent                                   |

The following are the events related to VXLAN.

### Event ID: 8101

|             |                                      |
|-------------|--------------------------------------|
| Message     | VNI id <vni_id> creation failed      |
| Category    | VXLAN                                |
| Severity    | Error                                |
| Description | Event raised when VNI creation fails |

### Event ID: 8102

|             |                               |
|-------------|-------------------------------|
| Message     | VNI id <vni_id> created       |
| Category    | VXLAN                         |
| Severity    | Information                   |
| Description | Event raised when VNI created |

### Event ID: 8103

|             |                                      |
|-------------|--------------------------------------|
| Message     | VNI id <vni_id> deletion fails       |
| Category    | VXLAN                                |
| Severity    | Error                                |
| Description | Event raised when VNI deletion fails |

### Event ID: 8104

|             |                                  |
|-------------|----------------------------------|
| Message     | VNI id <vni_id> has been deleted |
| Category    | VXLAN                            |
| Severity    | Information                      |
| Description | Event raised when VNI is deleted |

### Event ID: 8105

|             |                                        |
|-------------|----------------------------------------|
| Message     | Vtep-Peer <vtep_peer> is created       |
| Category    | VXLAN                                  |
| Severity    | Information                            |
| Description | Event raised when Vtep-Peer is created |

#### Event ID: 8106

|             |                                              |
|-------------|----------------------------------------------|
| Message     | Vtep-Peer <vtep_peer> has been deleted       |
| Category    | VXLAN                                        |
| Severity    | Information                                  |
| Description | Event raised when Vtep-Peer has been deleted |

#### Event ID: 8107

|             |                                            |
|-------------|--------------------------------------------|
| Message     | Vtep-Peer <vtep_peer> deletion failed      |
| Category    | VXLAN                                      |
| Severity    | Error                                      |
| Description | Event raised when Vtep-Peer deletion fails |

#### Event ID: 8108

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | Access-Port with vlan <vlan_id> and port <port_name> has been created |
| Category    | VXLAN                                                                 |
| Severity    | Information                                                           |
| Description | Event raised when Access-Port has been created                        |

#### Event ID: 8109

|             |                                                                       |
|-------------|-----------------------------------------------------------------------|
| Message     | Access-Port with port <port_name> and vlan <vlan_id> has been deleted |
| Category    | VXLAN                                                                 |
| Severity    | Information                                                           |
| Description | Event raised when Access-Port has been deleted                        |

#### Event ID: 8110

|         |                                       |
|---------|---------------------------------------|
| Message | Vtep-Peer <vtep> state is operational |
|---------|---------------------------------------|

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Category    | VXLAN                                                        |
| Severity    | Information                                                  |
| Description | Event raised when Vtep-Peer status is changed to operational |

#### Event ID: 8111

|             |                                                                      |
|-------------|----------------------------------------------------------------------|
| Message     | Vtep-Peer <vtep> state is configuration_error                        |
| Category    | VXLAN                                                                |
| Severity    | Information                                                          |
| Description | Event raised when Vtep-Peer status is changed to configuration error |

#### Event ID: 8112

|             |                                                                        |
|-------------|------------------------------------------------------------------------|
| Message     | Vtep-Peer <vtep> state is no_hw_resources                              |
| Category    | VXLAN                                                                  |
| Severity    | Information                                                            |
| Description | Event raised when Vtep-Peer status is changed to no hardware resources |

#### Event ID: 8113

|             |                                                             |
|-------------|-------------------------------------------------------------|
| Message     | Vtep-Peer <vtep> state is activating                        |
| Category    | VXLAN                                                       |
| Severity    | Information                                                 |
| Description | Event raised when Vtep-Peer status is changed to activating |

#### Event ID: 8114

|             |                                                       |
|-------------|-------------------------------------------------------|
| Message     | Tunnel <remote_ip> added to hardware                  |
| Category    | VXLAN                                                 |
| Severity    | Information                                           |
| Description | Event raised when a VxLAN tunnel is added to hardware |

#### Event ID: 8115

|          |                                          |
|----------|------------------------------------------|
| Message  | Tunnel <remote_ip> deleted from hardware |
| Category | VXLAN                                    |

|             |                                                           |
|-------------|-----------------------------------------------------------|
| Severity    | Information                                               |
| Description | Event raised when a VxLAN tunnel is deleted from hardware |

### Event ID: 8116

|             |                                                                    |
|-------------|--------------------------------------------------------------------|
| Message     | Tunnel <i>&lt;remote_ip&gt;</i> delete deferred                    |
| Category    | VXLAN                                                              |
| Severity    | Information                                                        |
| Description | Event raised when a VxLAN tunnel has its deletion deferred by L3PD |

### Event ID: 8117

|             |                                                                     |
|-------------|---------------------------------------------------------------------|
| Message     | Tunnel <i>&lt;remote_ip&gt;</i> deferred delete canceled            |
| Category    | VXLAN                                                               |
| Severity    | Information                                                         |
| Description | Event raised when a VxLAN tunnel has its deferred deletion canceled |



The following are the events related to zero touch provisioning.

### Event ID: 8701

|             |                                   |
|-------------|-----------------------------------|
| Message     | ZTP service has started           |
| Category    | Zero touch provisioning           |
| Severity    | Information                       |
| Description | Log event when ZTP service starts |

### Event ID: 8702

|             |                                  |
|-------------|----------------------------------|
| Message     | ZTP service has stopped          |
| Category    | Zero touch provisioning          |
| Severity    | Information                      |
| Description | Log event when ZTP service stops |

### Event ID: 8703

|             |                                                 |
|-------------|-------------------------------------------------|
| Message     | ZTP service status changed to in-progress       |
| Category    | Zero touch provisioning                         |
| Severity    | Information                                     |
| Description | Log event when ZTP change status to in-progress |

### Event ID: 8704

|             |                                             |
|-------------|---------------------------------------------|
| Message     | ZTP service status changed to success       |
| Category    | Zero touch provisioning                     |
| Severity    | Information                                 |
| Description | Log event when ZTP change status to success |

### Event ID: 8705 (Severity: Critical)

|             |                                                                            |
|-------------|----------------------------------------------------------------------------|
| Message     | ZTP service status changed to failed because of invalid configuration file |
| Category    | Zero touch provisioning                                                    |
| Severity    | Critical                                                                   |
| Description | Log event when ZTP fails because of invalid config file                    |

#### Event ID: 8706 (Severity: Critical)

|             |                                                                    |
|-------------|--------------------------------------------------------------------|
| Message     | ZTP service status changed to failed because of invalid image file |
| Category    | Zero touch provisioning                                            |
| Severity    | Critical                                                           |
| Description | Log event when ZTP fails because of invalid image file             |

#### Event ID: 8707 (Severity: Warning)

|             |                                                                         |
|-------------|-------------------------------------------------------------------------|
| Message     | ZTP service status changed to failed because TFTP info is not available |
| Category    | Zero touch provisioning                                                 |
| Severity    | Warning                                                                 |
| Description | Log event when ZTP fails because no TFTP info is available              |

#### Event ID: 8708 (Severity: Warning)

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | ZTP service status changed to failed because TFTP server is not reachable |
| Category    | Zero touch provisioning                                                   |
| Severity    | Warning                                                                   |
| Description | Log event when ZTP fails because TFTP server is not reachable             |

#### Event ID: 8709 (Severity: Critical)

|             |                                                                                   |
|-------------|-----------------------------------------------------------------------------------|
| Message     | ZTP service status changed to failed because of non-default startup configuration |
| Category    | Zero touch provisioning                                                           |
| Severity    | Critical                                                                          |
| Description | Log event when ZTP failed because of non-default startup config                   |

#### Event ID: 8710 (Severity: Critical)

|             |                                                                                |
|-------------|--------------------------------------------------------------------------------|
| Message     | ZTP service status changed to failed because running configuration is modified |
| Category    | Zero touch provisioning                                                        |
| Severity    | Critical                                                                       |
| Description | Log event when ZTP failed because of modified running config                   |

#### Event ID: 8711 (Severity: Warning)

|             |                                                         |
|-------------|---------------------------------------------------------|
| Message     | ZTP service status changed to failed because of timeout |
| Category    | Zero touch provisioning                                 |
| Severity    | Warning                                                 |
| Description | Log event when ZTP failed because of timeout            |

#### Event ID: 8712

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | ZTP: Image file not provided                                 |
| Category    | Zero touch provisioning                                      |
| Severity    | Information                                                  |
| Description | Logs related to ZTP configurations - image file not provided |

#### Event ID: 8713

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | ZTP: Config file not provided                                 |
| Category    | Zero touch provisioning                                       |
| Severity    | Information                                                   |
| Description | Logs related to ztp configurations - config file not provided |

#### Event ID: 8714

|             |                                                                    |
|-------------|--------------------------------------------------------------------|
| Message     | ZTP: TFTP server option not provided                               |
| Category    | Zero touch provisioning                                            |
| Severity    | Information                                                        |
| Description | Logs related to ztp configurations - TFTP server name not provided |

#### Event ID: 8715

|             |                                                                               |
|-------------|-------------------------------------------------------------------------------|
| Message     | ZTP: Exceeded max path length of TFTP server                                  |
| Category    | Zero touch provisioning                                                       |
| Severity    | Error                                                                         |
| Description | Logs related to ztp configurations - path length exceeded of TFTP server name |

#### Event ID: 8718

|             |                                                       |
|-------------|-------------------------------------------------------|
| Message     | ZTP: Received TFTP server <tftp_ip> from dhcp server  |
| Category    | Zero touch provisioning                               |
| Severity    | Information                                           |
| Description | Logs related to ztp configurations - TFTP IP received |

#### Event ID: 8719

|             |                                                              |
|-------------|--------------------------------------------------------------|
| Message     | ZTP: Received image file <image_file> from dhcp server       |
| Category    | Zero touch provisioning                                      |
| Severity    | Information                                                  |
| Description | Logs related to ztp configurations - Image filename received |

#### Event ID: 8720

|             |                                                               |
|-------------|---------------------------------------------------------------|
| Message     | ZTP: Received config file <config_file> from dhcp server      |
| Category    | Zero touch provisioning                                       |
| Severity    | Information                                                   |
| Description | Logs related to ztp configurations - Config filename received |

#### Event ID: 8721

|             |                                                                          |
|-------------|--------------------------------------------------------------------------|
| Message     | ZTP: Received Aruba Central location <central_location> from DHCP server |
| Category    | Zero touch provisioning                                                  |
| Severity    | Information                                                              |
| Description | Logs related to ztp configurations - Aruba Central FQDN or IPv4 received |

#### Event ID: 8723

|             |                                                                              |
|-------------|------------------------------------------------------------------------------|
| Message     | ZTP: Aruba Central location option not provided                              |
| Category    | Zero touch provisioning                                                      |
| Severity    | Information                                                                  |
| Description | Logs related to ztp configurations - Aruba Central FQDN or IPv4 not provided |

#### Event ID: 8724

|             |                                                                                              |
|-------------|----------------------------------------------------------------------------------------------|
| Message     | ZTP: Received HTTP proxy location <code>&lt;http_proxy_location&gt;</code> from DHCP server. |
| Category    | Zero touch provisioning                                                                      |
| Severity    | Information                                                                                  |
| Description | Logs related to ztp configurations - Aruba HTTP proxy FQDN or IPv4 received                  |

#### Event ID: 8726

|             |                                                                           |
|-------------|---------------------------------------------------------------------------|
| Message     | ZTP: HTTP proxy location was not received in the DHCP offer.              |
| Category    | Zero touch provisioning                                                   |
| Severity    | Information                                                               |
| Description | Logs related to ztp configurations - HTTP Proxy FQDN or IPv4 not provided |

#### Event ID: 8727 (Severity: Critical)

|             |                                                                                                                        |
|-------------|------------------------------------------------------------------------------------------------------------------------|
| Message     | ZTP service status changed to failed because <code>&lt;filename&gt;</code> file download encountered unexpected error. |
| Category    | Zero touch provisioning                                                                                                |
| Severity    | Critical                                                                                                               |
| Description | Log event when ZTP fails because of unexpected error in config/image file download                                     |

#### Event ID: 8728 (Severity: Critical)

|             |                                                                                                         |
|-------------|---------------------------------------------------------------------------------------------------------|
| Message     | ZTP service status changed to failed because <code>&lt;filename&gt;</code> file did not get downloaded. |
| Category    | Zero touch provisioning                                                                                 |
| Severity    | Critical                                                                                                |
| Description | Log event when ZTP fails because of config/image file download error                                    |

#### Event ID: 8729 (Severity: Critical)

|             |                                                                                                                          |
|-------------|--------------------------------------------------------------------------------------------------------------------------|
| Message     | ZTP service status changed to failed because the downloaded configuration could not be copied to start-up configuration. |
| Category    | Zero touch provisioning                                                                                                  |
| Severity    | Critical                                                                                                                 |
| Description | Log event when ZTP fails because downloaded config did not get copied to start-up config                                 |

### Accessing Aruba Support

|                         |                                                                                                                                                                                      |
|-------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Aruba Support Services  | <a href="https://www.arubanetworks.com/support-services/">https://www.arubanetworks.com/support-services/</a>                                                                        |
| Aruba Support Portal    | <a href="https://asp.arubanetworks.com/">https://asp.arubanetworks.com/</a>                                                                                                          |
| North America telephone | 1-800-943-4526 (US & Canada Toll-Free Number)<br>+1-408-754-1200 (Primary - Toll Number)<br>+1-650-385-6582 (Backup - Toll Number - Use only when all other numbers are not working) |
| International telephone | <a href="https://www.arubanetworks.com/support-services/contact-support/">https://www.arubanetworks.com/support-services/contact-support/</a>                                        |

Be sure to collect the following information before contacting Support:

- Technical support registration number (if applicable)
- Product name, model or version, and serial number
- Operating system name and version
- Firmware version
- Error messages
- Product-specific reports and logs
- Add-on products or components
- Third-party products or components

#### Other useful sites

Other websites that can be used to find information:

|                                           |                                                                                                                                       |
|-------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------|
| Airheads social forums and Knowledge Base | <a href="https://community.arubanetworks.com/">https://community.arubanetworks.com/</a>                                               |
| Software licensing                        | <a href="https://lms.arubanetworks.com/">https://lms.arubanetworks.com/</a>                                                           |
| End-of-Life information                   | <a href="https://www.arubanetworks.com/support-services/end-of-life/">https://www.arubanetworks.com/support-services/end-of-life/</a> |
| Aruba software and documentation          | <a href="https://asp.arubanetworks.com/downloads">https://asp.arubanetworks.com/downloads</a>                                         |

### Accessing Updates

You can access updates from the Aruba Support Portal or the HPE My Networking Website.

#### Aruba Support Portal

<https://asp.arubanetworks.com/downloads>

If you are unable to find your product in the Aruba Support Portal, you may need to search My Networking, where older networking products can be found:

## My Networking

<https://www.hpe.com/networking/support>

To view and update your entitlements, and to link your contracts and warranties with your profile, go to the Hewlett Packard Enterprise Support Center **More Information on Access to Support Materials** page:

<https://support.hpe.com/portal/site/hpsc/aae/home/>

Access to some updates might require product entitlement when accessed through the Hewlett Packard Enterprise Support Center. You must have an HP Passport set up with relevant entitlements.

Some software products provide a mechanism for accessing software updates through the product interface. Review your product documentation to identify the recommended software update method.

To subscribe to eNewsletters and alerts:

<https://asp.arubanetworks.com/notifications/subscriptions> (requires an active Aruba Support Portal (ASP) account to manage subscriptions). Security notices are viewable without an ASP account.

## Warranty information

To view warranty information for your product, go to <https://www.arubanetworks.com/support-services/product-warranties/>.

## Regulatory Information

To view the regulatory information for your product, view the *Safety and Compliance Information for Server, Storage, Power, Networking, and Rack Products*, available at <https://www.hpe.com/support/Safety-Compliance-EnterpriseProducts>

### Additional regulatory information

Aruba is committed to providing our customers with information about the chemical substances in our products as needed to comply with legal requirements, environmental data (company programs, product recycling, energy efficiency), and safety information and compliance data, (RoHS and WEEE). For more information, see <https://www.arubanetworks.com/company/about-us/environmental-citizenship/>.

## Documentation feedback

Aruba is committed to providing documentation that meets your needs. To help us improve the documentation, send any errors, suggestions, or comments to Documentation Feedback ([docsfeedback-switching@hpe.com](mailto:docsfeedback-switching@hpe.com)). When submitting your feedback, include the document title, part number, edition, and publication date located on the front cover of the document. For online help content, include the product name, product version, help edition, and publication date located on the legal notices page.