

Knowlus Hangup Causes

From Knowlus Wiki

9XX is the call related hangup cause series. 5XX is fax related and rest are general.

HANGUP CAUSES

Cause	Enumeration	Description
100-110	Unknown	Raised when No HangUp Event is recieved by platform from FreeSwitch .
111		SessionDoesNotExist
150		Max concurrency reached
200	REQUESTED_CHAN_UNAVAIL	This cause is returned when the other side of the interface cannot provide the circuit or channel indicated by the requesting entity.
500		Delivered
501		The CED tone exceeded 5s
502		Timed out waiting for initial communication
503		Timed out waiting for the first message
504		Timed out waiting for procedural interrupt
505		The HDLC carrier did not stop in a timely manner
506		Failed to train with any of the compatible modems
507		Operator intervention failed
508		Far end is not compatible
509		Far end is not able to receive
510		Far end is not able to transmit
511		Far end cannot receive at the resolution of the image
512		Far end cannot receive at the size of image
513		Unexpected message received
514		Received bad response to DCS or training
515		Received a DCN from remote after sending a page
516		Invalid ECM response received from receiver
517		Received a DCN while waiting for a DIS
518		Invalid response after sending a page
519		Received other than DIS while waiting for DIS
520		Received no response to DCS, training or TCF
521		No response after sending a page
522		Timed out waiting for receiver ready (ECM mode)
523		Invalid ECM response received from transmitter
524		DCS received while waiting for DTC
525		Unexpected command after page received
526		Carrier lost during fax receive
527		Timed out while waiting for EOL (end Of line)
528		Timed out while waiting for first line

529	Timer T2 expired while waiting for DCN
530	Timer T2 expired while waiting for phase D
531	Timed out waiting for receiver ready (ECM mode)
532	Timer T2 expired while waiting for fax page
531	Timed out waiting for receiver ready (ECM mode)
532	Timer T2 expired while waiting for next fax page
533	Timer T2 expired while waiting for RR command
534	Timer T2 expired while waiting for NSS, DCS or MCF
535	Unexpected DCN while waiting for DCS or DIS
536	Unexpected DCN while waiting for image data
537	Unexpected DCN while waiting for EOM, EOP or MPS
538	Unexpected DCN after EOM or MPS sequence
539	Unexpected DCN after RR/RNR sequence
540	Unexpected DCN after requested retransmission
541	TIFF/F file cannot be opened
542	TIFF/F page not found
543	TIFF/F format is not compatible
544	TIFF/F page number tag missing
545	Incorrect values for TIFF/F tags
546	Bad TIFF/F header - incorrect values in fields
547	Cannot allocate memory for more pages
548	Disconnected after permitted retries
549	The call dropped prematurely
550	Poll not accepted
551	Far end's ident is not acceptable
552	Far end's sub-address is not acceptable
553	Far end's selective polling address is not acceptable
554	Far end's polled sub-address is not acceptable
555	Far end's sender identification is not acceptable
556	Far end's password is not acceptable
557	Far end's transmitting subscriber internet address is not acceptable
558	Far end's internet routing address is not acceptable
559	Far end's calling subscriber internet address is not acceptable
560	Far end's internet selective polling address is not acceptable
561	Far end's called subscriber internet address is not acceptable
601	Bad number format
701	Credit unavailable
702	User cancelled order
703	Stop time reached
704	Fax pages unavailable
801	Preprocess error
802	Preprocess error (P)
803	Preprocess error(Plan is Expired)
804	Preprocess error(Missing Attachment)

805		Preprocess error
806		Preprocess error(Unsupported File Format)
807		Preprocess error(Wrong Number)
808		Preprocess error(No active Plan)
809		Preprocess error(No Credits)
900	NORMAL_CLEARING	
901	NO_ROUTE_DESTINATION	This cause indicates that the called party cannot be reached because the network through which the call has been routed does not serve the destination desired. This cause is supported on a network dependent basis.
902	USER BUSY	This cause is used to indicate that the called party is unable to accept another call because the user busy condition has been encountered. This cause value may be generated by the called user or by the network. In the case of user determined user busy it is noted that the user equipment is compatible with the call.
903	NO_USER_RESPONSE	This cause is used when a called party does not respond to a call establishment message with either an alerting or connect indication within the prescribed period of time allocated.
904	NO_ANSWER	This cause is used when the called party has been alerted but does not respond with a connect indication within a prescribed period of time. Note - This cause is not necessarily generated by Q.931 procedures but may be generated by internal network timers.
905	CALL_REJECTED	This cause indicates that the equipment sending this cause does not wish to accept this call, although it could have accepted the call because the equipment sending this cause is neither busy nor incompatible. The network may also generate this cause, indicating that the call was cleared due to a supplementary service constraint. The diagnostic field may contain additional information about the supplementary service and reason for rejection.
906	NUMBER_CHANGED	This cause is returned to a calling party when the called party number indicated by the calling party is no longer assigned, The new called party number may optionally be included in the diagnostic field. If a network does not support this cause, cause no: 1, unallocated (unassigned) number shall be used.
907	DESTINATION_OUT_OF_ORDER	This cause indicates that the destination indicated by the user cannot be reached because the interface to the destination is not functioning correctly. The term "not functioning correctly" indicates that a signal message was unable to be delivered to the remote party; e.g. a physical layer or data link layer failure at the remote party, or user equipment off-line.
908	INVALID_NUMBER_FORMAT	This cause indicates that the called party cannot be reached because the called party number is not in a valid format or is not complete.
909	NETWORK_OUT_OF_ORDER	This cause indicates that the network is not functioning correctly and that the condition is likely to last a relatively long period of time e.g. immediately re-attempting the call is not likely to be successful.
910	NORMAL_TEMPORARY_FAILURE	This cause indicates that the network is not functioning correctly and that the condition is not likely to last a long period of time; e.g. the user may wish to try another call attempt almost immediately.
911	ORIGINATOR_CANCEL	
		This cause indicates that a procedure has been initiated by the expiration of a timer in association with error handling procedures. This is often associated with NAT problems. Ensure that "NAT Mapping Enable" is turned on in your ATA. If it is not NAT related

912	RECOVERY_ON_TIMER_EXPIRE	it can sometimes be provider related, make sure to ensure another outbound provider does not solve the problem. FreeSWITCH also returns this when the remote party sends a 408 for call expired.
913	PROTOCOL_ERROR	This cause is used to report a protocol error event only when no other cause in the protocol error class applies.
914	NORMAL_CIRCUIT_CONGESTION	This cause indicates that there is no appropriate circuit/channel presently available to handle the call.
916	NORMAL_UNSPECIFIED	all failure information indicating the failure of a call due to the lapse of a timeout or a fault not covered by specific causes (examples: expiry of timers Q.764 not covered by specific causes, release of interconnected circuit.
917	SUBSCRIBER_ABSENT	This cause value is used when a mobile station has logged off, radio contact is not obtained with a mobile station or if a personal telecommunication user is temporarily not addressable at any user-network interface. Sofia SIP will normally raise USER_NOT_REGISTERED in such situations.
918	FREESWITCH_TIMEOUT	
919	UNALLOCATED_NUMBER	This cause indicates that the called party cannot be reached because, although the called party number is in a valid format, it is not currently allocated (assigned).
920	INTERWORKING	This cause indicates that an interworking call (usually a call to SW56 service) has ended.
921	SWITCH_CONGESTION	This cause indicates that the switching equipment generating this cause is experiencing a period of high traffic.
923	DNC_FAILED	
924	CRASH	
925	SYSTEM_SHUTDOWN	
926	LOSE_RACE	
927	MANAGER_REQUEST	This cause is used when you send an api command to make it hangup. For example <code>uuid_kill <uuid></code>
928	BLIND_TRANSFER	
929	ATTENDED_TRANSFER	
930	ALLOTTED_TIMEOUT	
931	USER_CHALLENGE	
932	MEDIA_TIMEOUT	
933	PICKED_OFF	This cause means the call was picked up by intercepting it from another extension (i.e. dialing <code>**ext_number</code> from another extension).
934	USER_NOT_REGISTERED	This means you tried to originate a call to a SIP user who forgot to register.
935	PROGRESS_TIMEOUT	This is the maximum time we will wait before we get media (whether its early media, ringing or answer) e.g. maximum PDD before abandoning the route -- the time from Sending the INVITE to receiving the first ringing response for example: a SIP/2.0 180 Ringing or 183. Typical fixed lines have a PDD of under 3 seconds, and mobiles of under 8 seconds. More on http://wiki.freeswitch.org/wiki/Channel_Variables#progress_timeout

800	INVALID_IE_CONTENTS	This cause indicates that the equipment sending this cause has received an information element which it has implemented; however, one or more fields in the I.E. are coded in such a way which has not been implemented by the equipment sending this cause.
936	INCOMPATIBLE_DESTINATION	This cause indicates that the equipment sending this cause has received a request to establish a call which has low layer compatibility, high layer compatibility or other compatibility attributes (e.g. data rate) which cannot be accommodated.
940	FACILITY_REJECTED	This cause is returned when a supplementary service requested by the user cannot be provided by the network.
1548		Delivered*
1549		Delivered*
2548		Fax-Tone Not Received
2549		Fax-Tone Not Received
3548		Fax-Tone Not Received
3549		Fax-Tone Not Received

Retry Cases in TDM

SYSTEM_ERRORS = (101,102,103,104,105,106,107,108,109,110, 200, 901, 903, 905, 907, 909, 911, 912, 913, 914, 915, 917,

Retry Cases in SIP

SIP_RETRY_CASES = (200, 905, 910, 914, 919, 920, 921)

Retrieved from "http://wiki.knowlarity.com/index.php?title=Knowlus_Hangup_Causes&oldid=14546"