=== GNB (1785495871) ===


```
cu_cp:
  amf:
    addr: 10.53.1.2
    port: 38412
    bind_addr: 10.53.1.3
    supported_tracking_areas:
      - tac: 7
        plmn_list:
          - plmn: "21401"
            tai_slice_support_list:
              - sst: 1
  inactivity_timer: 7200

ru_sdr:
  device_driver: zmq
  device_args: tx_port=tcp://127.0.0.1:2000,rx_port=tcp://127.0.0.1:2001,base_srate=30.72e6
  srate: 30.72e6
  tx_gain: 75
  rx_gain: 75

cell_cfg:
  dl_arfcn: 633334
  band: 78
  channel_bandwidth_MHz: 20
  common_scs: 30
  plmn: "21401"
  tac: 7
  pdcch:
    common:
      ss0_index: 0
      coreset0_index: 6
    dedicated:
      ss2_type: common
      dci_format_0_1_and_1_1: false
  prach:
    prach_config_index: 1
  pdsch:
    mcs_table: qam64
  pusch:
    mcs_table: qam64

log:
  filename: /tmp/gnb.log
  all_level: info
  hex_max_size: 0

pcap:
  mac_enable: false
  mac_filename: /tmp/gnb_mac.pcap
  ngap_enable: false
  ngap_filename: /tmp/gnb_ngap.pcap
  e2ap_enable: true
  e2ap_du_filename: /tmp/gnb_du_e2ap.pcap
  e2ap_cu_cp_filename: /tmp/gnb_cu_cp_e2ap.pcap
  e2ap_cu_up_filename: /tmp/gnb_cu_up_e2ap.pcap

metrics:
  layers:
    enable_rlc: true
    enable_sched: true
  periodicity:
    du_report_period: 1000
```

=== UE (1785495871) ===

```
[rf]
freq_offset = 0
tx_gain = 50
rx_gain = 40
srate = 30.72e6
nof_antennas = 1

device_name = zmq
device_args = tx_port=tcp://127.0.0.1:2001,rx_port=tcp://127.0.0.1:2000,base_srate=30.72e6


[rat.eutra]
dl_earfcn = 2850
nof_carriers = 0

[rat.nr]
bands = 78
nof_carriers = 1

max_nof_prb = 106
nof_prb = 106
dl_nr_arfcn = 633334
ssb_nr_arfcn = 633304


[pcap]
enable = none
mac_filename = /tmp/ue_mac.pcap
mac_nr_filename = /tmp/ue_mac_nr.pcap
nas_filename = /tmp/ue_nas.pcap

[log]
all_level = info
phy_lib_level = none
all_hex_limit = 32
filename = /tmp/ue.log
file_max_size = -1

[usim]
mode = soft
algo = milenage
opc  = 63BFA50EE6523365FF14C1F45F88737D
k    = 00112233445566778899aabbccddeeff
imsi = 214010000000002
imei = 353490069873319

[rrc]
release = 15
ue_category = 4

[nas]
apn = srsapn
apn_protocol = ipv4

[gw]
netns = ue1
ip_devname = tun_srsue
ip_netmask = 255.255.255.0

[gui]
enable = false
```

=== DOCKER (1785495871) ===

```
#
# Copyright 2021-2026 Software Radio Systems Limited
#
# This file is part of srsRAN
#
# srsRAN is free software: you can redistribute it and/or modify
# it under the terms of the GNU Affero General Public License as
# published by the Free Software Foundation, either version 3 of
# the License, or (at your option) any later version.
#
# srsRAN is distributed in the hope that it will be useful,
# but WITHOUT ANY WARRANTY; without even the implied warranty of
# MERCHANTABILITY or FITNESS FOR A PARTICULAR PURPOSE. See the
# GNU Affero General Public License for more details.
#
# A copy of the GNU Affero General Public License can be found in
# the LICENSE file in the top-level directory of this distribution
# and at http://www.gnu.org/licenses/.
#

services:
  5gc:
    container_name: open5gs_5gc
    build:
      context: open5gs
      target: open5gs
      args:
        OS_VERSION: "22.04"
        OPEN5GS_VERSION: "v2.7.0"
    environment:
      - MONGODB_IP=127.0.0.1
      - OPEN5GS_IP=10.53.1.2
      - UE_IP_BASE=10.45.0
      - UPF_ADVERTISE_IP=10.53.1.2
      - DEBUG=false
      - SUBSCRIBER_DB=214010000000002,112233445566778899OOaabbccddeeff,opc,63BFA50EE6523365FF14C1F45F88737D,8000,9,10.
      - NETWORK_NAME_FULL=srsRAN
      - NETWORK_NAME_SHORT=srsRAN
      - TZ=Europe/Madrid
    privileged: true
    ports:
      - "9898:9999/tcp"
    # Uncomment port to use the 5gc from outside the docker network
#      - "38412:38412/sctp"
 #     - "2152:2152/udp"
    command: 5gc -c open5gs-5gc.yml
    healthcheck:
      test: [ "CMD-SHELL", "nc -z 127.0.0.20 7777" ]
      interval: 3s
      timeout: 1s
      retries: 60
    networks:
      ran:
        ipv4_address: ${OPEN5GS_IP:-10.53.1.2}

  gnb:
    container_name: srsran_gnb
    # Build info
    image: srsran/gnb
    build:
      context: ..
      dockerfile: docker/Dockerfile
      args:
        OS_VERSION: "24.04"
```

```yaml
    # privileged mode is requred only for accessing usb devices
    privileged: true
    # Extra capabilities always required
    cap_add:
      - SYS_NICE
      - CAP_SYS_PTRACE
    volumes:
      # Access USB to use some SDRs
      - /dev/bus/usb/:/dev/bus/usb/
      # Sharing images between the host and the pod.
      # It's also possible to download the images inside the pod
      - /usr/share/uhd/images:/usr/share/uhd/images
      # Save logs and more into gnb-storage
      - gnb-storage:/tmp
    # It creates a file/folder into /config_name inside the container
    # Its content would be the value of the file used to create the config
    configs:
      - gnb_config.yml
      - gnb_compose_config.yml
    # Customize your desired network mode.
    # current netowrk configuration creastes a private netwoek with both containers attached
    # An alterantive would be `network: host"`. That would expose your host network into the container. It's the easie
    networks:
      ran:
        ipv4_address: ${GNB_IP:-10.53.1.3}
      metrics:
        ipv4_address: 172.19.1.3
    # Start GNB container after 5gc is up and running
    depends_on:
      5gc:
        condition: service_healthy
    # Command to run into the final container
    command: gnb -c /gnb_config.yml -c /gnb_compose_config.yml

configs:
  gnb_config.yml:
    file: gnb_zmq.yaml # Path to your desired config file
  gnb_compose_config.yml:
    content: |
      cu_cp:
        amf:
          addr: ${OPEN5GS_IP:-10.53.1.2}
          bind_addr: 0.0.0.0
      metrics:
        autostart_stdout_metrics: true
        enable_json: true
      remote_control:
        bind_addr: 0.0.0.0
        enabled: true

volumes:
  gnb-storage:

networks:
  ran:
    ipam:
      driver: default
      config:
        - subnet: 10.53.1.0/24
  metrics:
    ipam:
      driver: default
      config:
        - subnet: 172.19.1.0/24
```

=== NOTAS (1785495871) ===

1. PLMN (21401) y IMSI (214010000000002) actualizados en gNB, UE y SUBSCRIBER_DB (Regla 1, 7a).
2. Banda 78, ancho de banda 20 MHz, dl_arfcn (633334) y ssb_nr_arfcn (633304) configurados (Regla 2).
3. common_scs (30) y srate (30.72e6) ajustados para 20 MHz en Banda 78 (Regla 2, 3).
4. K y OPC actualizados en UE y SUBSCRIBER_DB, verificando el orden (Regla 7b).
5. bind_addr en gnb_zmq.yaml a 10.53.1.3 y en gnb_compose_config.yml a 0.0.0.0 (Regla 5).
6. Bloque ru_sdr copiado, ajustando srate según Regla 2 (prioridad sobre Regla 6 inmutable de srate).
7. Puertos ZMQ cruzados verificados (Regla 4).