

=== GNB (1780331701) ===

cu_cp:

```
amf:
  addr: 10.53.1.2          # The address or hostname of the AMF.
  port: 38412
  bind_addr: 10.53.1.3     # A local IP that the gNB binds to for traffic from the AMF.
  supported_tracking_areas:
    - tac: 7
      plmn_list:
        - plmn: "00101"
          tai_slice_support_list:
            - sst: 1 # Valor estandarizado para eMBB (referencia: ejemplos_configuraciones_5g.pdf - Pag 152, 226)
  inactivity_timer: 60     # Sets the UE/PDU Session/DRB inactivity timer to 60 seconds (1 minute).
```

ru_sdr:

```
device_driver: zmq         # The RF driver name.
device_args: tx_port=tcp://127.0.0.1:2000,rx_port=tcp://127.0.0.1:2001,base_srate=11.52e6 # Optionally pass argument
srate: 11.52              # RF sample rate might need to be adjusted according to selected bandwidth.
tx_gain: 75               # Transmit gain of the RF might need to adjusted to the given situation.
rx_gain: 75               # Receive gain of the RF might need to adjusted to the given situation.
```

cell_cfg:

```
dl_arfcn: 368500          # ARFCN of the downlink carrier (center frequency).
band: 3                   # The NR band.
channel_bandwidth_MHz: 10 # Bandwith in MHz. Number of PRBs will be automatically derived.
common_scs: 15            # Subcarrier spacing in kHz used for data.
plmn: "00101"            # PLMN broadcasted by the gNB.
tac: 7                    # Tracking area code (needs to match the core configuration).
pdccch:
  common:
    ss0_index: 0          # Set search space zero index to match srsUE capabilities
    coreset0_index: 6     # Set search CORESET Zero index to match srsUE capabilities
  dedicated:
    ss2_type: common      # Search Space type, has to be set to common
    dci_format_0_1_and_1_1: false # Set correct DCI format (fallback)
prach:
  prach_config_index: 1   # Sets PRACH config to match what is expected by srsUE
pdsch:
  mcs_table: qam64        # Sets PDSCH MCS to 64 QAM
pusch:
  mcs_table: qam64        # Sets PUSCH MCS to 64 QAM
```

log:

```
filename: /tmp/gnb.log    # Path of the log file.
all_level: info           # Logging level applied to all layers.
hex_max_size: 0
```

pcap:

```
mac_enable: false        # Set to true to enable MAC-layer PCAPs.
mac_filename: /tmp/gnb_mac.pcap # Path where the MAC PCAP is stored.
ngap_enable: true         # Set to true to enable NGAP PCAPs.
ngap_filename: /tmp/gnb_ngap.pcap # Path where the NGAP PCAP is stored.
e2ap_enable: false       # Set to true to enable E2AP PCAPs.
e2ap_du_filename: /tmp/gnb_du_e2ap.pcap # Path where the DU E2AP PCAP is stored.
e2ap_cu_cp_filename: /tmp/gnb_cu_cp_e2ap.pcap # Path where the CU-CP E2AP PCAP is stored.
e2ap_cu_up_filename: /tmp/gnb_cu_up_e2ap.pcap # Path where the CU-UP E2AP PCAP is stored.
```

metrics:

```
layers:
  enable_rlc: true        # Enable RLC metrics
  enable_sched: true      # Enable DU scheduler metrics
periodicity:
  du_report_period: 400   # Set DU statistics report period to 400ms
```

=== UE (1780331701) ===

```
[rf]
freq_offset = 0
tx_gain = 50
rx_gain = 40
srate = 11.52e6
nof_antennas = 1

device_name = zmq
device_args = tx_port=tcp://127.0.0.1:2001,rx_port=tcp://127.0.0.1:2000,base_srate=11.52e6

[rat.eutra]
dl_eurfcn = 2850
nof_carriers = 0

[rat.nr]
bands = 3
nof_carriers = 1

max_nof_prb = 52
nof_prb = 52

[pcap]
enable = none
mac_filename = /tmp/ue_mac.pcap
mac_nr_filename = /tmp/ue_mac_nr.pcap
nas_filename = /tmp/ue_nas.pcap

[log]
all_level = info
phy_lib_level = none
all_hex_limit = 32
filename = /tmp/ue.log
file_max_size = -1

[usim]
mode = soft
algo = milenage
opc = 112233445566778899aabbccddeeff00
k = 00aabbccddeeff112233445566778899
imsi = 0010100000000001
imei = 353490069873319

[rrc]
release = 15
ue_category = 4

[nas]
apn = srsapn
apn_protocol = ipv4

[gw]
netns = ue1
ip_devname = tun_srsue
ip_netmask = 255.255.255.0

[gui]
enable = false
```

=== DOCKER (1780331701) ===

```
#
# Copyright 2021-2026 Software Radio Systems Limited
#
# This file is part of srsRAN
#
# srsRAN is free software: you can redistribute it and/or modify
# it under the terms of the GNU Affero General Public License as
# published by the Free Software Foundation, either version 3 of
# the License, or (at your option) any later version.
#
# srsRAN is distributed in the hope that it will be useful,
# but WITHOUT ANY WARRANTY; without even the implied warranty of
# MERCHANTABILITY or FITNESS FOR A PARTICULAR PURPOSE. See the
# GNU Affero General Public License for more details.
#
# A copy of the GNU Affero General Public License can be found in
# the LICENSE file in the top-level directory of this distribution
# and at http://www.gnu.org/licenses/.
#
```

services:

```
5gc:
  container_name: open5gs_5gc
  build:
    context: open5gs
    target: open5gs
    args:
      OS_VERSION: "22.04"
      OPEN5GS_VERSION: "v2.7.0"
  env_file:
    - ${OPEN_5GS_ENV_FILE:-open5gs/open5gs.env}
  privileged: true
  ports:
    - "9898:9999/tcp"
  # Uncomment port to use the 5gc from outside the docker network
  # - "38412:38412/sctp"
  # - "2152:2152/udp"
  command: 5gc -c open5gs-5gc.yml
  healthcheck:
    test: [ "CMD-SHELL", "nc -z 127.0.0.20 7777" ]
    interval: 3s
    timeout: 1s
    retries: 60
  networks:
    ran:
      ipv4_address: ${OPEN5GS_IP:-10.53.1.2}
```

```
gnb:
  container_name: srsran_gnb
  # Build info
  image: srsran/gnb
  build:
    context: ..
    dockerfile: docker/Dockerfile
    args:
      OS_VERSION: "24.04"
  # privileged mode is required only for accessing usb devices
  privileged: true
  # Extra capabilities always required
  cap_add:
    - SYS_NICE
    - CAP_SYS_PTRACE
  volumes:
    # Access USB to use some SDRs
```

```

- /dev/bus/usb/:/dev/bus/usb/
# Sharing images between the host and the pod.
# It's also possible to download the images inside the pod
- /usr/share/uhd/images:/usr/share/uhd/images
# Save logs and more into gnb-storage
- gnb-storage:/tmp
# It creates a file/folder into /config_name inside the container
# Its content would be the value of the file used to create the config
configs:
  - gnb_config.yml
  - gnb_compose_config.yml
# Customize your desired network mode.
# current netowrk configuration creastes a private netwoek with both containers attached
# An alterantive would be `network: host`. That would expose your host network into the container. It's the easie
networks:
  ran:
    ipv4_address: ${GNB_IP:-10.53.1.3}
  metrics:
    ipv4_address: 172.19.1.3
# Start GNB container after 5gc is up and running
depends_on:
  5gc:
    condition: service_healthy
# Command to run into the final container
command: gnb -c /gnb_config.yml -c /gnb_compose_config.yml

configs:
  gnb_config.yml:
    file: ${GNB_CONFIG_PATH:-gnb.yml} # Path to your desired config file
  gnb_compose_config.yml:
    content: |
      cu_cp:
        amf:
          addr: ${OPEN5GS_IP:-10.53.1.2}
          bind_addr: 0.0.0.0
        metrics:
          autostart_stdout_metrics: true
          enable_json: true
        remote_control:
          bind_addr: 0.0.0.0
          enabled: true

volumes:
  gnb-storage:

networks:
  ran:
    ipam:
      driver: default
      config:
        - subnet: 10.53.1.0/24
  metrics:
    ipam:
      driver: default
      config:
        - subnet: 172.19.1.0/24

```

=== NOTAS (1780331701) ===

1. ****PLMN Coherencia (Regla 1):**** MCC "001", MNC "01" (PLMN "00101") aplicado en gNB y UE (IMSI). TAC 7 consistente.
2. ****Frecuencia y Banda (Regla 2):**** Banda 3, dl_arfcn 368500, dentro del rango [361000, 376000].
3. ****SCS Coherencia (Regla 3):**** common_scs 15 kHz en gNB.
4. ****Puertos ZMQ (Regla 4):**** Puertos 2000 y 2001 cruzados entre gNB y UE.
5. ****bind_addr (Regla 5):**** gNB (gnb.yml) usa 10.53.1.3; gnb_compose_config usa 0.0.0.0.
6. ****ru_sdr (Regla 6):**** Bloque ru_sdr copiado exactamente del CAG, incluyendo srate 11.52e6.
7. ****SST:**** Se usó `sst: 1` para eMBB, referenciando ejemplos del RAG.
8. ****inactivity_timer:**** Configurado a 60 segundos (1 minuto).
9. ****Métricas y PCAP:**** RLC, scheduler DU activados con 400ms de reporte. NGAP PCAP habilitado en gNB.
10. ****UE PRB:**** Ajustado a 52 PRBs para 10 MHz de ancho de banda y 15 kHz SCS.