

=== GNB (1785511955) ===

```
#
# Copyright 2021-2026 Software Radio Systems Limited
#
# This file is part of srsRAN
#
# srsRAN is free software: you can redistribute it and/or modify
# it under the terms of the GNU Affero General Public License as
# published by the Free Software Foundation, either version 3 of
# the License, or (at your option) any later version.
#
# srsRAN is distributed in the hope that it will be useful,
# but WITHOUT ANY WARRANTY; without even the implied warranty of
# MERCHANTABILITY or FITNESS FOR A PARTICULAR PURPOSE. See the
# GNU Affero General Public License for more details.
#
# A copy of the GNU Affero General Public License can be found in
# the LICENSE file in the top-level directory of this distribution
# and at http://www.gnu.org/licenses/.
#

cu_cp:
  amf:
    addr: 10.53.1.2          # The address or hostname of the AMF.
    port: 38412
    bind_addr: 10.53.1.1    # A local IP that the gNB binds to for traffic from the AMF.
    supported_tracking_areas:
      - tac: 7
      plmn_list:
        - plmn: "21401"
      tai_slice_support_list:
        - sst: 1
    inactivity_timer: 7200  # Sets the UE/PDU Session/DRB inactivity timer to 7200 seconds. Supported: [1 - 7200]

ru_sdr:
  device_driver: zmq        # The RF driver name.
  device_args: tx_port=tcp://127.0.0.1:2000,rx_port=tcp://127.0.0.1:2001,base_srate=11.52e6 # Optionally pass argument
  srate: 11.52             # RF sample rate might need to be adjusted according to selected bandwidth.
  tx_gain: 75              # Transmit gain of the RF might need to adjusted to the given situation.
  rx_gain: 75              # Receive gain of the RF might need to adjusted to the given situation.

cell_cfg:
  dl_arfcn: 632000         # ARFCN of the downlink carrier (center frequency).
  band: 78                 # The NR band.
  channel_bandwidth_MHz: 20 # Bandwidth in MHz. Number of PRBs will be automatically derived.
  common_scs: 15           # Subcarrier spacing in kHz used for data.
  plmn: "21401"           # PLMN broadcasted by the gNB.
  tac: 7                   # Tracking area code (needs to match the core configuration).
  pdccch:
    common:
      ss0_index: 0          # Set search space zero index to match srsUE capabilities
      coresets0_index: 6    # Set search CORESET Zero index to match srsUE capabilities
    dedicated:
      ss2_type: common      # Search Space type, has to be set to common
      dci_format_0_1_and_1_1: false # Set correct DCI format (fallback)
  prach:
    prach_config_index: 1   # Sets PRACH config to match what is expected by srsUE
  pdsch:
    mcs_table: qam64        # Sets PDSCH MCS to 64 QAM
  pusched:
    mcs_table: qam64        # Sets PUSCH MCS to 64 QAM

log:
  filename: /tmp/gnb.log    # Path of the log file.
  all_level: info          # Logging level applied to all layers.
```

hex_max_size: 0

pcap:

mac_enable: false # Set to true to enable MAC-layer PCAPs.
mac_filename: /tmp/gnb_mac.pcap # Path where the MAC PCAP is stored.
ngap_enable: false # Set to true to enable NGAP PCAPs.
ngap_filename: /tmp/gnb_ngap.pcap # Path where the NGAP PCAP is stored.
e2ap_enable: true # Set to true to enable E2AP PCAPs.
e2ap_du_filename: /tmp/gnb_du_e2ap.pcap # Path where the DU E2AP PCAP is stored.
e2ap_cu_cp_filename: /tmp/gnb_cu_cp_e2ap.pcap # Path where the CU-CP E2AP PCAP is stored.
e2ap_cu_up_filename: /tmp/gnb_cu_up_e2ap.pcap # Path where the CU-UP E2AP PCAP is stored.

metrics:

layers:

enable_rlc: true # Enable RLC metrics
enable_sched: true # Enable DU scheduler metrics

periodicity:

du_report_period: 1000 # Set DU statistics report period to 1s

=== UE (1785511955) ===

```
[rf]
freq_offset = 0
tx_gain = 50
rx_gain = 40
srate = 11.52e6
nof_antennas = 1

device_name = zmq
device_args = tx_port=tcp://127.0.0.1:2001,rx_port=tcp://127.0.0.1:2000,base_srate=11.52e6

[rat.eutra]
dl_eurfcn = 2850
nof_carriers = 0

[rat.nr]
bands = 78
nof_carriers = 1

max_nof_prb = 106
nof_prb = 106

[pcap]
enable = none
mac_filename = /tmp/ue_mac.pcap
mac_nr_filename = /tmp/ue_mac_nr.pcap
nas_filename = /tmp/ue_nas.pcap

[log]
all_level = info
phy_lib_level = none
all_hex_limit = 32
filename = /tmp/ue.log
file_max_size = -1

[usim]
mode = soft
algo = milenage
opc = 63BFA50EE6523365FF14C1F45F88737D
k = 6677889900aabbccddeeff11223344556
imsi = 214010000000007
imei = 353490069873319

[rrc]
release = 15
ue_category = 4

[nas]
apn = srsapn
apn_protocol = ipv4

[gw]
netns = ue1
ip_devname = tun_srsue
ip_netmask = 255.255.255.0

[gui]
enable = false
```

=== DOCKER (1785511955) ===

```
#
# Copyright 2021-2026 Software Radio Systems Limited
#
# This file is part of srsRAN
#
# srsRAN is free software: you can redistribute it and/or modify
# it under the terms of the GNU Affero General Public License as
# published by the Free Software Foundation, either version 3 of
# the License, or (at your option) any later version.
#
# srsRAN is distributed in the hope that it will be useful,
# but WITHOUT ANY WARRANTY; without even the implied warranty of
# MERCHANTABILITY or FITNESS FOR A PARTICULAR PURPOSE. See the
# GNU Affero General Public License for more details.
#
# A copy of the GNU Affero General Public License can be found in
# the LICENSE file in the top-level directory of this distribution
# and at http://www.gnu.org/licenses/.
#
```

services:

```
  5gc:
    container_name: open5gs_5gc
    build:
      context: open5gs
      target: open5gs
      args:
        OS_VERSION: "22.04"
        OPEN5GS_VERSION: "v2.7.0"
    environment:
      - MONGODB_IP=127.0.0.1
      - OPEN5GS_IP=10.53.1.2
      - UE_IP_BASE=10.45.0
      - UPF_ADVERTISE_IP=10.53.1.2
      - DEBUG=false
      - SUBSCRIBER_DB=214010000000007,6677889900aabbccddeeff11223344556,opc,63BFA50EE6523365FF14C1F45F88737D,8000,9,10
      - NETWORK_NAME_FULL=srsRAN
      - NETWORK_NAME_SHORT=srsRAN
      - TZ=Europe/Madrid
    privileged: true
    ports:
      - "9898:9999/tcp"
    # Uncomment port to use the 5gc from outside the docker network
    # - "38412:38412/sctp"
    # - "2152:2152/udp"
    command: 5gc -c open5gs-5gc.yml
    healthcheck:
      test: [ "CMD-SHELL", "nc -z 127.0.0.20 7777" ]
      interval: 3s
      timeout: 1s
      retries: 60
    networks:
      ran:
        ipv4_address: ${OPEN5GS_IP:-10.53.1.2}

  gnb:
    container_name: srsran_gnb
    # Build info
    image: srsran/gnb
    build:
      context: ..
      dockerfile: docker/Dockerfile
      args:
        OS_VERSION: "24.04"
```

```

# privileged mode is required only for accessing usb devices
privileged: true
# Extra capabilities always required
cap_add:
  - SYS_NICE
  - CAP_SYS_PTRACE
volumes:
  # Access USB to use some SDRs
  - /dev/bus/usb/:/dev/bus/usb/
  # Sharing images between the host and the pod.
  # It's also possible to download the images inside the pod
  - /usr/share/uhd/images:/usr/share/uhd/images
  # Save logs and more into gnb-storage
  - gnb-storage:/tmp
# It creates a file/folder into /config_name inside the container
# Its content would be the value of the file used to create the config
configs:
  - gnb_config.yml
  - gnb_compose_config.yml
# Customize your desired network mode.
# current network configuration creates a private network with both containers attached
# An alternative would be `network: host`. That would expose your host network into the container. It's the easiest
networks:
  ran:
    ipv4_address: ${GNB_IP:-10.53.1.3}
  metrics:
    ipv4_address: 172.19.1.3
# Start GNB container after 5gc is up and running
depends_on:
  5gc:
    condition: service_healthy
# Command to run into the final container
command: gnb -c /gnb_config.yml -c /gnb_compose_config.yml

configs:
  gnb_config.yml:
    file: ${GNB_CONFIG_PATH:-../configs/gnb_rf_b200_tdd_n78_20mhz.yml} # Path to your desired config file
  gnb_compose_config.yml:
    content: |
      cu_cp:
        amf:
          addr: ${OPEN5GS_IP:-10.53.1.2}
          bind_addr: 0.0.0.0
      metrics:
        autostart_stdout_metrics: true
        enable_json: true
      remote_control:
        bind_addr: 0.0.0.0
        enabled: true

volumes:
  gnb-storage:

networks:
  ran:
    ipam:
      driver: default
      config:
        - subnet: 10.53.1.0/24
  metrics:
    ipam:
      driver: default
      config:
        - subnet: 172.19.1.0/24

```

=== NOTAS (1785511955) ===

1. PLMN (MCC=214, MNC=01) configurado como "21401" en gNB y Core, y en IMSI del UE (REGLA 1, 7a).
2. Banda 78 y dl_arfcn 632000 (válido para Banda 78) aplicados (REGLA 2).
3. common_scs se mantiene en 15 kHz (REGLA 3).
4. Puertos ZMQ cruzados entre gNB y UE según template (REGLA 4).
5. bind_addr de gNB se configuró como 10.53.1.1 en gnb_zmq.yaml y 0.0.0.0 en gnb_compose_config.yml, este último prevalece.
6. Bloque ru_sdr copiado exactamente del CAG, manteniendo srates 11.52e6 a pesar del ancho de banda de 20 MHz solicitado.
7. IMSI, K, OPC y IP estática configurados según REGLA 7b y la petición del usuario.