

=== GNB (1785922188) ===

This configuration file example shows how to configure the srsRAN Project gNB to allow srsUE to connect to it.
This specific example uses ZMQ in place of a USRP for the RF-frontend, and creates an FDD cell with 10 MHz bandwidth
To run the srsRAN Project gNB with this config, use the following command:
sudo ./gnb -c gnb_zmq.yaml

```
cu_cp:
  amf:
    addr: 10.53.1.2          # The address or hostname of the AMF.
    port: 38412
    bind_addr: 10.53.1.1    # A local IP that the gNB binds to for traffic from the AMF.
    supported_tracking_areas:
      - tac: 7
      plmn_list:
        - plmn: "00101"
      tai_slice_support_list:
        - sst: 1            # eMBB (enhanced Mobile Broadband) - 3GPP TS 23.501, Table 5.15.2.2-1
    inactivity_timer: 7200  # Sets the UE/PDU Session/DRB inactivity timer to 7200 seconds. Supported: [1 - 7200]

ru_sdr:
  device_driver: zmq        # The RF driver name.
  device_args: tx_port=tcp://127.0.0.1:2000,rx_port=tcp://127.0.0.1:2001,base_srate=11.52e6 # Optionally pass argument
  srate: 11.52             # RF sample rate might need to be adjusted according to selected bandwidth.
  tx_gain: 75              # Transmit gain of the RF might need to adjusted to the given situation.
  rx_gain: 75              # Receive gain of the RF might need to adjusted to the given situation.

cell_cfg:
  dl_arfcn: 368500         # ARFCN of the downlink carrier (center frequency).
  band: 3                  # The NR band.
  channel_bandwidth_MHz: 10 # Bandwidth in MHz. Number of PRBs will be automatically derived.
  common_scs: 15           # Subcarrier spacing in kHz used for data.
  plmn: "00101"           # PLMN broadcasted by the gNB.
  tac: 7                   # Tracking area code (needs to match the core configuration).
  pdcch:
    common:
      ss0_index: 0         # Set search space zero index to match srsUE capabilities
      coresets0_index: 6   # Set search CORESET Zero index to match srsUE capabilities
    dedicated:
      ss2_type: common     # Search Space type, has to be set to common
      dci_format_0_1_and_1_1: false # Set correct DCI format (fallback)
  prach:
    prach_config_index: 1  # Sets PRACH config to match what is expected by srsUE
  pdsch:
    mcs_table: qam64       # Sets PDSCH MCS to 64 QAM
  pusch:
    mcs_table: qam64       # Sets PUSCH MCS to 64 QAM

log:
  filename: /tmp/gnb.log   # Path of the log file.
  all_level: info          # Logging level applied to all layers.
  hex_max_size: 0

pcap:
  mac_enable: false        # Set to true to enable MAC-layer PCAPs.
  mac_filename: /tmp/gnb_mac.pcap # Path where the MAC PCAP is stored.
  ngap_enable: true        # Set to true to enable NGAP PCAPs.
  ngap_filename: /tmp/gnb_ngap.pcap # Path where the NGAP PCAP is stored.
  e2ap_enable: true        # Set to true to enable E2AP PCAPs.
  e2ap_du_filename: /tmp/gnb_du_e2ap.pcap # Path where the DU E2AP PCAP is stored.
  e2ap_cu_cp_filename: /tmp/gnb_cu_cp_e2ap.pcap # Path where the CU-CP E2AP PCAP is stored.
  e2ap_cu_up_filename: /tmp/gnb_cu_up_e2ap.pcap # Path where the CU-UP E2AP PCAP is stored.

#e2:
# enable_du_e2: true       # Enable DU E2 agent (one for each DU instance)
# e2sm_kpm_enabled: true   # Enable KPM service module
```

```
# e2sm_rc_enabled: true          # Enable RC service module
# addr: 127.0.0.1                # RIC IP address
#bind_addr: 127.0.0.100         # A local IP that the E2 agent binds to for traffic from the RIC. ONLY required if
# port: 36421                    # RIC port

metrics:
  layers:
    enable_rlc: true             # Enable RLC metrics
    enable_sched: true           # Enable DU scheduler metrics
  periodicity:
    du_report_period: 400        # Set DU statistics report period to 400ms
```

=== UE (1785922188) ===

```
[rf]
freq_offset = 0
tx_gain = 50
rx_gain = 40
srate = 11.52e6
nof_antennas = 1

device_name = zmq
device_args = tx_port=tcp://127.0.0.1:2001,rx_port=tcp://127.0.0.1:2000,base_srate=11.52e6

[rat.eutra]
dl_eurfcn = 2850
nof_carriers = 0

[rat.nr]
bands = 3
nof_carriers = 1

max_nof_prb = 52
nof_prb = 52

[pcap]
enable = none
mac_filename = /tmp/ue_mac.pcap
mac_nr_filename = /tmp/ue_mac_nr.pcap
nas_filename = /tmp/ue_nas.pcap

[log]
all_level = info
phy_lib_level = none
all_hex_limit = 32
filename = /tmp/ue.log
file_max_size = -1

[usim]
mode = soft
algo = milenage
opc = 112233445566778899aabbccddeeff00
k = 00aabbccddeeff112233445566778899
imsi = 0010100000000001
imei = 353490069873319

[rrc]
release = 15
ue_category = 4

[nas]
apn = srsapn
apn_protocol = ipv4

[gw]
netns = ue1
ip_devname = tun_srsue
ip_netmask = 255.255.255.0

[gui]
enable = false
```

=== DOCKER (1785922188) ===

```
#
# Copyright 2021-2026 Software Radio Systems Limited
#
# This file is part of srsRAN
#
# srsRAN is free software: you can redistribute it and/or modify
# it under the terms of the GNU Affero General Public License as
# published by the Free Software Foundation, either version 3 of
# the License, or (at your option) any later version.
#
# srsRAN is distributed in the hope that it will be useful,
# but WITHOUT ANY WARRANTY; without even the implied warranty of
# MERCHANTABILITY or FITNESS FOR A PARTICULAR PURPOSE. See the
# GNU Affero General Public License for more details.
#
# A copy of the GNU Affero General Public License can be found in
# the LICENSE file in the top-level directory of this distribution
# and at http://www.gnu.org/licenses/.
#
```

services:

```
  5gc:
    container_name: open5gs_5gc
    build:
      context: open5gs
      target: open5gs
      args:
        OS_VERSION: "22.04"
        OPEN5GS_VERSION: "v2.7.0"
    environment:
      - MONGODB_IP=127.0.0.1
      - OPEN5GS_IP=10.53.1.2
      - UE_IP_BASE=10.45.0
      - UPF_ADVERTISE_IP=10.53.1.2
      - DEBUG=false
      - SUBSCRIBER_DB=001010000000001,00aabbccddeeff112233445566778899,opc,112233445566778899aabbccddeeff00,8000,9,10.
      - NETWORK_NAME_FULL=srsRAN
      - NETWORK_NAME_SHORT=srsRAN
      - TZ=Europe/Madrid
    privileged: true
    ports:
      - "9898:9999/tcp"
    # Uncomment port to use the 5gc from outside the docker network
    # - "38412:38412/sctp"
    # - "2152:2152/udp"
    command: 5gc -c open5gs-5gc.yml
    healthcheck:
      test: [ "CMD-SHELL", "nc -z 127.0.0.20 7777" ]
      interval: 3s
      timeout: 1s
      retries: 60
    networks:
      ran:
        ipv4_address: ${OPEN5GS_IP:-10.53.1.2}

  gnb:
    container_name: srsran_gnb
    # Build info
    image: srsran/gnb
    build:
      context: ..
      dockerfile: docker/Dockerfile
      args:
        OS_VERSION: "24.04"
```

```

# privileged mode is required only for accessing usb devices
privileged: true
# Extra capabilities always required
cap_add:
  - SYS_NICE
  - CAP_SYS_PTRACE
volumes:
  # Access USB to use some SDRs
  - /dev/bus/usb/:/dev/bus/usb/
  # Sharing images between the host and the pod.
  # It's also possible to download the images inside the pod
  - /usr/share/uhd/images:/usr/share/uhd/images
  # Save logs and more into gnb-storage
  - gnb-storage:/tmp
# It creates a file/folder into /config_name inside the container
# Its content would be the value of the file used to create the config
configs:
  - gnb_config.yml
  - gnb_compose_config.yml
# Customize your desired network mode.
# current network configuration creates a private network with both containers attached
# An alternative would be `network: host`. That would expose your host network into the container. It's the easiest
networks:
  ran:
    ipv4_address: ${GNB_IP:-10.53.1.1}
  metrics:
    ipv4_address: 172.19.1.3
# Start GNB container after 5gc is up and running
depends_on:
  5gc:
    condition: service_healthy
# Command to run into the final container
command: gnb -c /gnb_config.yml -c /gnb_compose_config.yml

configs:
  gnb_config.yml:
    file: ${GNB_CONFIG_PATH:-../configs/gnb_zmq.yml} # Path to your desired config file
  gnb_compose_config.yml:
    content: |
      cu_cp:
        amf:
          addr: ${OPEN5GS_IP:-10.53.1.2}
          bind_addr: 0.0.0.0
      metrics:
        autostart_stdout_metrics: true
        enable_json: true
      remote_control:
        bind_addr: 0.0.0.0
        enabled: true

volumes:
  gnb-storage:

networks:
  ran:
    ipam:
      driver: default
      config:
        - subnet: 10.53.1.0/24
  metrics:
    ipam:
      driver: default
      config:
        - subnet: 172.19.1.0/24

```

=== NOTAS (1785922188) ===

- PLMN (MCC 001, MNC 01, TAC 7) y IPs (gNB 10.53.1.1, 5GC 10.53.1.2) aplicados consistentemente en los tres archivos.
- `bind\_addr` configurado según REGLA 5: 10.53.1.1 en gNB YAML y 0.0.0.0 en docker-compose override.
- Bloque `ru\_sdr` copiado del CAG, ajustando los puertos ZMQ según REGLA 4 y manteniendo `base\_srate` y `device\_driver`.
- IMSI, K y OPC sincronizados entre UE y SUBSCRIBER_DB, siguiendo el formato de REGLA 7.
- SST para eMBB (1) añadido con referencia a 3GPP TS 23.501, Table 5.15.2.2-1.
- Métricas RLC y scheduler DU habilitadas con periodo de 400ms.
- Capturas PCAP de NGAP habilitadas en gNB.
- `channel\_bandwidth\_MHz` ajustado a 10 MHz y `max\_nof\_prb`/`nof\_prb` a 52 para el UE.