Polynomial-time simulation of non-Clifford quantum error correction

Arthur Pesah

FU Berlin

GitHub

mark-koch/
merlin-sim

Joint work with



Serban Cercelescu
Oxford



Mark Koch
Oxford

arXiv

2610.06811

Overview

Most magic-state preparation protocols can be simulated in polynomial-time

Overview

Most magic-state preparation protocols can be simulated in polynomial-time

1 **Most magic-state preparation protocols**

Circuits made of CNOT, T, Paulis, Z measurements and *compatible* X measurements.

Examples:

- Magic state distillation and cultivation based on applying a logical 3rd level non-Clifford gate to a code.
- Code switching between 3D and 2D codes.

Overview

Most magic-state preparation protocols can be simulated in polynomial-time

1. Most magic-state preparation protocols
2. **Simulated**

Maintain state representation throughout the circuit.
Two representations: Schrödinger (phase polynomials) and Heisenberg (generalized stabilizer group).

Can compute the following:

- Pauli expectation values and amplitudes
- Measurement samples
- State equality

Overview

Most magic-state preparation protocols can be simulated in polynomial-time

1. Most magic-state preparation protocols
2. Simulated
3. **Polynomial time**

Polynomial-time complexity in the number of qubits and circuit depth
No exponential in the number of T gates!

Outline

1. The phase polynomial representation
2. Compatible measurements
3. DCP stabilizer formalism
4. Benchmarking our simulator

1 The phase polynomial representation

Phase polynomial states

Unitary gate set: the third-order CNOT-dihedral group $G_3 = \langle \text{CNOT}, T, X \rangle$

Phase polynomial states

Unitary gate set: the third-order CNOT-dihedral group $G_3 = \langle \text{CNOT}, T, X \rangle$

Commuting T through the CNOTs: all diagonal non-Clifford gates of the third-level, i.e. T, CS, CCZ

Phase polynomial states

Unitary gate set: the third-order CNOT-dihedral group $G_3 = \langle \text{CNOT}, T, X \rangle$

Commuting T through the CNOTs: all diagonal non-Clifford gates of the third-level, i.e. T, CS, CCZ

Initial state: $|0\rangle^{\otimes n} |+\rangle^{\otimes m}$

Phase polynomial states

Unitary gate set: the third-order CNOT-dihedral group $G_3 = \langle \text{CNOT}, T, X \rangle$

Commuting T through the CNOTs: all diagonal non-Clifford gates of the third-level, i.e. T, CS, CCZ

Initial state: $|0\rangle^{\otimes n} |+\rangle^{\otimes m}$

Question: what happens when we apply G_3 gates to $|0\rangle^{\otimes n} |+\rangle^{\otimes m}$?

$$U |0\rangle^{\otimes n} |+\rangle^{\otimes m} = \sum_{y \in \mathbb{F}_2^m} U |x\rangle$$

with $|x\rangle = |0\rangle^{\otimes n} |y\rangle$

Phase polynomial states

Unitary gate set: the third-order CNOT-dihedral group $G_3 = \langle \text{CNOT}, T, X \rangle$

Commuting T through the CNOTs: all diagonal non-Clifford gates of the third-level, i.e. T, CS, CCZ

Initial state: $|0\rangle^{\otimes n} |+\rangle^{\otimes m}$

Question: what happens when we apply G_3 gates to $|0\rangle^{\otimes n} |+\rangle^{\otimes m}$?

$$U |0\rangle^{\otimes n} |+\rangle^{\otimes m} = \sum_{y \in \mathbb{F}_2^m} U |x\rangle$$

with $|x\rangle = |0\rangle^{\otimes n} |y\rangle$

New question: what is $U |x\rangle$ for $U \in G_3$?

Phase polynomial states

X operators: $X(b)\,|x\rangle = |x + b\rangle$

Phase polynomial states

X operators: $X(b)\,|x\rangle = |x + b\rangle$

CNOT operators: $U_C\,|x\rangle = |Ax\rangle$

Phase polynomial states

X operators: $X(b)\,|x\rangle = |x + b\rangle$

CNOT operators: $U_C\,|x\rangle = |Ax\rangle$

Diagonal non-Clifford operators: for $\omega = e^{i\pi/4}$, we have

$$T_i\,|x\rangle = \omega^{x_i}\,|x\rangle$$

$$CS_{i,j}\,|x\rangle = \omega^{2x_i x_j}\,|x\rangle$$

$$CCZ_{i,j,k}\,|x\rangle = \omega^{4x_i x_j x_k}\,|x\rangle$$

Phase polynomial states

X operators: $X(b)\,|x\rangle = |x + b\rangle$

CNOT operators: $U_C\,|x\rangle = |Ax\rangle$

Diagonal non-Clifford operators: for $\omega = e^{i\pi/4}$, we have

$$\left.\begin{aligned} T_i\,|x\rangle &= \omega^{x_i}\,|x\rangle \\ CS_{i,j}\,|x\rangle &= \omega^{2x_ix_j}\,|x\rangle \\ CCZ_{i,j,k}\,|x\rangle &= \omega^{4x_ix_jx_k}\,|x\rangle \end{aligned}\right\} \quad \Rightarrow \quad U_D\,|x\rangle = \omega^{f(x)}\,|x\rangle$$

for a so-called **third-order phase polynomial**:

$$f(x) = \sum_i a_i x_i + 2\sum_{i<j} b_{ij} x_i x_j + 4\sum_{i<j<k} c_{ijk} x_i x_j x_k$$

Phase polynomial states

Therefore, for $U \in G_3$ we have

$$U|x\rangle = U_D X(b) U_C |x\rangle = \omega^{f(Ax+b)} |Ax+b\rangle$$

Phase polynomial states

Therefore, for $U \in G_3$ we have

$$U|x\rangle = U_D X(b) U_C |x\rangle = \omega^{f(Ax+b)} |Ax+b\rangle$$

Our state: $U \in G_3$ applied to $|0\rangle^{\otimes n} |+\rangle^{\otimes m}$ gives

$$U|0\rangle^{\otimes n} |+\rangle^{\otimes m} \propto \sum_{y \in \mathbb{F}_2^m} U|0\rangle^{\otimes n} |y\rangle$$

Phase polynomial states

Therefore, for $U \in G_3$ we have

$$U|x\rangle = U_D X(b) U_C |x\rangle = \omega^{f(Ax+b)} |Ax+b\rangle$$

Our state: $U \in G_3$ applied to $|0\rangle^{\otimes n} |+\rangle^{\otimes m}$ gives

$$\begin{aligned} U|0\rangle^{\otimes n} |+\rangle^{\otimes m} &\propto \sum_{y \in \mathbb{F}_2^m} U|0\rangle^{\otimes n} |y\rangle \\ &\propto \sum_{y \in \mathbb{F}_2^m} \omega^{f(A\tilde{y}+b)} |A\tilde{y}+b\rangle \qquad \text{with } \tilde{y} = (0, y) \end{aligned}$$

Phase polynomial states

Therefore, for $U \in G_3$ we have

$$U|x\rangle = U_D X(b) U_C |x\rangle = \omega^{f(Ax+b)} |Ax+b\rangle$$

Our state: $U \in G_3$ applied to $|0\rangle^{\otimes n} |+\rangle^{\otimes m}$ gives

$$\begin{aligned} U|0\rangle^{\otimes n} |+\rangle^{\otimes m} &\propto \sum_{y \in \mathbb{F}_2^m} U|0\rangle^{\otimes n} |y\rangle \\ &\propto \sum_{y \in \mathbb{F}_2^m} \omega^{f(A\tilde{y}+b)} |A\tilde{y}+b\rangle \qquad \text{with } \tilde{y} = (0, y) \\ &\propto \sum_{x \in S} \omega^{q(x)} |x\rangle \end{aligned}$$

with S an affine subspace of $\mathbb{F}_2^{n+m}$ and q a third-order phase polynomial.

Phase polynomial states

Definition (3PP state): a third-order phase polynomial (3PP) state is a state of the form

$$|\psi\rangle \propto \sum_{x \in S} \omega^{q(x)} |x\rangle$$

with S an affine subspace and q a third-order phase polynomial.

Phase polynomial states

Definition (3PP state): a third-order phase polynomial (3PP) state is a state of the form

$$|\psi\rangle \propto \sum_{x \in S} \omega^{q(x)} |x\rangle$$

with S an affine subspace and q a third-order phase polynomial.

Property: 3PP states are efficient to store

- $O(N^2)$ parameters for S (generator matrix and offset)
- $O(N^3)$ parameters for q (coefficients of the polynomial)

Phase polynomial states

Definition (3PP state): a third-order phase polynomial (3PP) state is a state of the form

$$|\psi\rangle \propto \sum_{x \in S} \omega^{q(x)} |x\rangle$$

with S an affine subspace and q a third-order phase polynomial.

Property: 3PP states are efficient to store

- $O(N^2)$ parameters for S (generator matrix and offset)
- $O(N^3)$ parameters for q (coefficients of the polynomial)

Claim: also efficient to update under CNOT-dihedral gates

Phase polynomial states

Definition (3PP state): a third-order phase polynomial (3PP) state is a state of the form

$$|\psi\rangle \propto \sum_{x \in S} \omega^{q(x)} |x\rangle$$

with S an affine subspace and q a third-order phase polynomial.

Property: 3PP states are efficient to store

- $O(N^2)$ parameters for S (generator matrix and offset)
- $O(N^3)$ parameters for q (coefficients of the polynomial)

Claim: also efficient to update under CNOT-dihedral gates

Question: but what about measurements?

2 Compatible measurements

Compatible measurements: Z measurements

Definition (compatible measurement): the measurement of 3PP state $|\psi\rangle$ is **compatible** with $|\psi\rangle$ if the post-measurement state is still a 3PP state (for every measurement outcome).

Compatible measurements: Z measurements

Definition (compatible measurement): the measurement of 3PP state $|\psi\rangle$ is **compatible** with $|\psi\rangle$ if the post-measurement state is still a 3PP state (for every measurement outcome).

Theorem: Z measurements are always compatible.

Compatible measurements: Z measurements

Definition (compatible measurement): the measurement of 3PP state $|\psi\rangle$ is **compatible** with $|\psi\rangle$ if the post-measurement state is still a 3PP state (for every measurement outcome).

Theorem: Z measurements are always compatible.

Proof: we apply the projector $\Pi^\mu = \frac{1}{2}(I + (-1)^\mu Z(v))$ to a 3PP state $|\psi\rangle$:

$$\Pi_\mu |\psi\rangle \propto \sum_{x \in S} \omega^{q(x)} |x\rangle + \sum_{x \in S} \omega^{q(x)} (-1)^\mu Z(v) |x\rangle$$

Compatible measurements: Z measurements

Definition (compatible measurement): the measurement of 3PP state $|\psi\rangle$ is **compatible** with $|\psi\rangle$ if the post-measurement state is still a 3PP state (for every measurement outcome).

Theorem: Z measurements are always compatible.

Proof: we apply the projector $\Pi^\mu = \frac{1}{2}(I + (-1)^\mu Z(v))$ to a 3PP state $|\psi\rangle$:

$$\Pi_\mu |\psi\rangle \propto \sum_{x \in S} \omega^{q(x)} |x\rangle + \sum_{x \in S} \omega^{q(x)} (-1)^\mu Z(v) |x\rangle$$

Using $Z(v)|x\rangle = (-1)^{v \cdot x} |x\rangle$, we get:

$$\Pi_\mu |\psi\rangle \propto \sum_{x \in S} \omega^{q(x)} (1 + (-1)^{\mu + v \cdot x}) |x\rangle$$

Compatible measurements: Z measurements

Definition (compatible measurement): the measurement of 3PP state $|\psi\rangle$ is **compatible** with $|\psi\rangle$ if the post-measurement state is still a 3PP state (for every measurement outcome).

Theorem: Z measurements are always compatible.

Proof: we apply the projector $\Pi^\mu = \frac{1}{2}(I + (-1)^\mu Z(v))$ to a 3PP state $|\psi\rangle$:

$$\Pi_\mu |\psi\rangle \propto \sum_{x \in S} \omega^{q(x)} |x\rangle + \sum_{x \in S} \omega^{q(x)} (-1)^\mu Z(v) |x\rangle$$

Using $Z(v)|x\rangle = (-1)^{v \cdot x} |x\rangle$, we get:

$$\Pi_\mu |\psi\rangle \propto \sum_{x \in S} \omega^{q(x)} (1 + (-1)^{\mu + v \cdot x}) |x\rangle$$

$\Rightarrow$ Doesn't change the phase polynomial, but reduces the support to $S \cap \{x : v \cdot x = \mu\}$.

Compatible measurements: Z measurements

Definition (compatible measurement): the measurement of 3PP state $|\psi\rangle$ is **compatible** with $|\psi\rangle$ if the post-measurement state is still a 3PP state (for every measurement outcome).

Theorem: Z measurements are always compatible.

Proof: we apply the projector $\Pi^\mu = \frac{1}{2}(I + (-1)^\mu Z(v))$ to a 3PP state $|\psi\rangle$:

$$\Pi_\mu |\psi\rangle \propto \sum_{x \in S} \omega^{q(x)} |x\rangle + \sum_{x \in S} \omega^{q(x)} (-1)^\mu Z(v) |x\rangle$$

Using $Z(v)|x\rangle = (-1)^{v \cdot x} |x\rangle$, we get:

$$\Pi_\mu |\psi\rangle \propto \sum_{x \in S} \omega^{q(x)} (1 + (-1)^{\mu + v \cdot x}) |x\rangle$$


$\Rightarrow$ Doesn't change the phase polynomial, but reduces the support to $S \cap \{x : v \cdot x = \mu\}$.

$\Rightarrow$ Still a 3PP state!

Compatible measurements: X measurements

Observation 1: not every X measurement can be compatible.


Otherwise, we would get universality through a measurement-based Hadamard gadget:



Compatible measurements: X measurements

Observation 1: not every X measurement can be compatible.

Otherwise, we would get universality through a measurement-based Hadamard gadget:




Observation 2: compatibility depends on the state.

Compatible measurements: X measurements

Observation 1: not every X measurement can be compatible.

Otherwise, we would get universality through a measurement-based Hadamard gadget:



Observation 2: compatibility depends on the state.

For the Hadamard gadget, with $|T\rangle = T|+\rangle$:


$$H|0\rangle = |+\rangle \quad \text{(compatible)}, \qquad H|T\rangle \propto \cos\tfrac{\pi}{8}|0\rangle - i\sin\tfrac{\pi}{8}|1\rangle \quad \text{(incompatible)}.$$

The latter has unequal amplitude magnitudes, so it is not a 3PP state.

Compatible measurements: X measurements

Observation 1: not every X measurement can be compatible.

Otherwise, we would get universality through a measurement-based Hadamard gadget:



Observation 2: compatibility depends on the state.

For the Hadamard gadget, with $|T\rangle = T|+\rangle$:

$$H|0\rangle = |+\rangle \quad \text{(compatible)}, \qquad H|T\rangle \propto \cos\tfrac{\pi}{8}|0\rangle - i\sin\tfrac{\pi}{8}|1\rangle \quad \text{(incompatible)}.$$

The latter has unequal amplitude magnitudes, so it is not a 3PP state.

Question: which X measurements are compatible with a state $|\psi\rangle$ specified by $(S, q(x))$?

Compatible X measurements: support and phase

Claim: compatibility of measuring $X(v)$ is determined by whether $S = S + v$ and, if so, by the form of $\Delta_v q(x) = q(x+v) - q(x) \pmod 8$ on S.

Compatible X measurements: support and phase

Claim: compatibility of measuring $X(v)$ is determined by whether $S = S + v$ and, if so, by the form of $\Delta_v q(x) = q(x+v) - q(x) \pmod 8$ on S.

Indeed: applying $\Pi_\mu = \frac{1}{2}(I + (-1)^\mu X(v))$ gives

$$\Pi_\mu |\psi\rangle \propto \sum_{x \in S} \omega^{q(x)} |x\rangle + (-1)^\mu \sum_{x \in S} \omega^{q(x)} |x+v\rangle .$$

Compatible X measurements: support and phase

Claim: compatibility of measuring $X(v)$ is determined by whether $S = S + v$ and, if so, by the form of $\Delta_v q(x) = q(x+v) - q(x) \pmod 8$ on S.

Indeed: applying $\Pi_\mu = \frac{1}{2}(I + (-1)^\mu X(v))$ gives

$$\Pi_\mu |\psi\rangle \propto \sum_{x \in S} \omega^{q(x)} |x\rangle + (-1)^\mu \sum_{x \in S} \omega^{q(x)} |x+v\rangle .$$

If $S \neq S + v$: the two copies are disjoint, so there is no interference. Their union is affine and the relative sign adds an affine phase. $\Rightarrow$ Always compatible!

Compatible X measurements: support and phase

Claim: compatibility of measuring $X(v)$ is determined by whether $S = S + v$ and, if so, by the form of $\Delta_v q(x) = q(x+v) - q(x) \pmod 8$ on S.

Indeed: applying $\Pi_\mu = \frac{1}{2}(I + (-1)^\mu X(v))$ gives

$$\Pi_\mu |\psi\rangle \propto \sum_{x \in S} \omega^{q(x)} |x\rangle + (-1)^\mu \sum_{x \in S} \omega^{q(x)} |x+v\rangle .$$

If $S \neq S + v$: the two copies are disjoint, so there is no interference. Their union is affine and the relative sign adds an affine phase. $\Rightarrow$ Always compatible!

If $S = S + v$: relabeling the second sum gives

$$\begin{aligned} \Pi_\mu |\psi\rangle &\propto \sum_{x \in S} \omega^{q(x)} + (-1)^\mu \omega^{q(x+v)} |x\rangle \\ &\propto \sum_{x \in S} \omega^{q(x)} \left(1 + \omega^{\Delta_v q(x) + 4\mu}\right) |x\rangle \end{aligned}$$

Classification of compatible X measurements

Theorem: measuring $X(v)$ on a 3PP state (S, q) is compatible iff

1. $S \neq S + v$, or
2. $S = S + v$ and one of the following holds on S (modulo 8):

(2a) $\Delta_v q(x) = 4f(x)$, f affine,

(2b) $\Delta_v q(x) = 2 + 4g(x)$, $2g$ a third-order phase polynomial,

(2c) $\Delta_v q(x) = (-1)^{h(x)} d$, h affine, $d \in \{1, 3, 5, 7\}$.

Classification of compatible X measurements

Theorem: measuring $X(v)$ on a 3PP state (S, q) is compatible iff

1. $S \neq S + v$, or
2. $S = S + v$ and one of the following holds on S (modulo 8):

(2a) $\Delta_v q(x) = 4f(x)$, f affine,

(2b) $\Delta_v q(x) = 2 + 4g(x)$, $2g$ a third-order phase polynomial,

(2c) $\Delta_v q(x) = (-1)^{h(x)} d$, h affine, $d \in \{1, 3, 5, 7\}$.

Example 1 (deterministic measurement): $X(v)\,|\psi\rangle = (-1)^{\mu}\,|\psi\rangle \;\Rightarrow$ case (2a).

Classification of compatible X measurements

Theorem: measuring $X(v)$ on a 3PP state (S, q) is compatible iff

1. $S \neq S + v$, or
2. $S = S + v$ and one of the following holds on S (modulo 8):

$$\textbf{(2a)} \quad \Delta_v q(x) = 4f(x), \qquad f \text{ affine},$$

$$\textbf{(2b)} \quad \Delta_v q(x) = 2 + 4g(x), \quad 2g \text{ a third-order phase polynomial},$$

$$\textbf{(2c)} \quad \Delta_v q(x) = (-1)^{h(x)} d, \quad h \text{ affine}, \quad d \in \{1, 3, 5, 7\}.$$

Example 1 (deterministic measurement): $X(v)\,|\psi\rangle = (-1)^{\mu}\,|\psi\rangle \;\Rightarrow$ case (2a).

Proof: $X(v)$ shifts the support, so $S + v = S$. Matching amplitudes at $x \in S$ gives

$$\omega^{q(x+v)} = (-1)^{\mu}\omega^{q(x)} \;\Rightarrow\; q(x+v) = q(x) + 4\mu \pmod 8 \;\Rightarrow\; \Delta_v q(x) = 4\mu \pmod 8.$$

Thus $\Delta_v q = 4f$ with $f(x) = \mu$ constant, hence affine: case (2a).

Classification of compatible X measurements

Theorem: measuring $X(v)$ on a 3PP state (S, q) is compatible iff

1. $S \neq S + v$, or
2. $S = S + v$ and one of the following holds on S (modulo 8):

(2a) $\Delta_v q(x) = 4f(x)$, f affine,

(2b) $\Delta_v q(x) = 2 + 4g(x)$, $2g$ a third-order phase polynomial,

(2c) $\Delta_v q(x) = (-1)^{h(x)} d$, h affine, $d \in \{1, 3, 5, 7\}$.

Example 2 (anticommuting Z stabilizer): if $Z(w)\,|\psi\rangle = |\psi\rangle$ and $Z(w)$ anticommutes with $X(v)$, measuring $X(v)$ is compatible: case (1).

Classification of compatible X measurements

Theorem: measuring $X(v)$ on a 3PP state (S, q) is compatible iff

1. $S \neq S + v$, or
2. $S = S + v$ and one of the following holds on S (modulo 8):

$$\textbf{(2a)} \quad \Delta_v q(x) = 4f(x), \qquad f \text{ affine},$$

$$\textbf{(2b)} \quad \Delta_v q(x) = 2 + 4g(x), \quad 2g \text{ a third-order phase polynomial},$$

$$\textbf{(2c)} \quad \Delta_v q(x) = (-1)^{h(x)} d, \quad h \text{ affine}, \quad d \in \{1, 3, 5, 7\}.$$

Example 2 (anticommuting Z stabilizer): if $Z(w)\,|\psi\rangle = |\psi\rangle$ and $Z(w)$ anticommutes with $X(v)$, measuring $X(v)$ is compatible: case (1).

Proof: for $x \in S$, $Z(w)\,|\psi\rangle = |\psi\rangle$ gives $w \cdot x = 0$. Anticommutation gives $w \cdot v = 1$. Thus:

$$w \cdot (x + v) = 0 + 1 \neq 0 \pmod 2 \;\Rightarrow\; x + v \notin S \;\Rightarrow\; S \neq S + v.$$

Application to quantum error correction

Problem: we need to look at the compatibility of QEC measurements with **noisy** states.

Application to quantum error correction

Problem: we need to look at the compatibility of QEC measurements with **noisy** states.

Question: what noise model should we consider?

Application to quantum error correction

Problem: we need to look at the compatibility of QEC measurements with **noisy** states.

Question: what noise model should we consider?

Observation 1: in a CNOT-dihedral circuit (i.e. X, T,CNOT), Pauli errors propagate into **diagonal Clifford and Pauli (DCP)** gates. Example:

- $TXT^\dagger = e^{-i\pi/4}SX$
- $(\mathrm{CCZ})X(\mathrm{CCZ})^\dagger = X\ \mathrm{CZ}$

Application to quantum error correction

Problem: we need to look at the compatibility of QEC measurements with **noisy** states.

Question: what noise model should we consider?

Observation 1: in a CNOT-dihedral circuit (i.e. X, T,CNOT), Pauli errors propagate into **diagonal Clifford and Pauli (DCP)** gates. Example:

- $TXT^\dagger = e^{-i\pi/4}SX$
- $(\mathrm{CCZ})X(\mathrm{CCZ})^\dagger = X\ \mathrm{CZ}$

Observation 2: CNOT-dihedral circuits preserve DCP errors. Indeed:

1. Pauli part of the DCP error: propagate into a new DCP operator
2. Diagonal part of the DCP error: turn into another diagonal operator (due to CNOTs)

Application to quantum error correction

Problem: we need to look at the compatibility of QEC measurements with **noisy** states.

Question: what noise model should we consider?

Observation 1: in a CNOT-dihedral circuit (i.e. X, T,CNOT), Pauli errors propagate into **diagonal Clifford and Pauli (DCP)** gates. Example:

- $TXT^\dagger = e^{-i\pi/4}SX$
- $(\mathrm{CCZ})X(\mathrm{CCZ})^\dagger = X\ \mathrm{CZ}$

Observation 2: CNOT-dihedral circuits preserve DCP errors. Indeed:

1. Pauli part of the DCP error: propagate into a new DCP operator
2. Diagonal part of the DCP error: turn into another diagonal operator (due to CNOTs)

Noise model: DCP errors at every circuit location

Application to quantum error correction

Theorem (measurement compatibility under noise): assume

1. Circuit made of CNOT-dihedral gates and compatible measurements
2. Every ideal X measurement is either deterministic, or anticommutes with a current Z stabilizer

Then, all measurements remain compatible under arbitrary inserted DCP faults.

Application to quantum error correction

Theorem (measurement compatibility under noise): assume

1. Circuit made of CNOT-dihedral gates and compatible measurements
2. Every ideal X measurement is either deterministic, or anticommutes with a current Z stabilizer

Then, all measurements remain compatible under arbitrary inserted DCP faults.

Examples:

- **Distillation and non-Clifford computation**: logical CNOT-dihedral gates on CSS codes, followed by ideally deterministic checks.
- **DCP checks in cultivation**: controlled-DCP gates give deterministic ancilla X readouts.
- **CSS gauge fixing and code switching**: new X checks are fixed or anticommute with a current Z constraint.

3 DCP stabilizer formalism

DCP stabilizer formalism

Question: can we come up with a stabilizer picture for 3PP states?

Observation: if we start with a state stabilized by a Pauli operator S, and apply a gate $U \in G_3$, then the new state is stabilized by $S' = USU^\dagger$, **which is a DCP operator**.
$\Rightarrow$ Let's look at states stabilized by a group of DCP operators. We call these **DCP states**.

Example: $|00\rangle$ is stabilized by $\mathcal{S}_{\text{DCP}} = \langle S_1, S_2, \text{CZ}_{12} \rangle$. Interestingly:

1. It has $m = 3$ independent generators, but $n = 2$ qubits. Contrasts with Pauli case, where $n = m$.
2. It is also uniquely stabilized by some dim-2 subgroups of $\mathcal{S}_{\text{DCP}}$: $\langle Z_1, Z_2 \rangle$, $\langle Z_1, S_2 \rangle$,$\langle S_1, Z_2 \rangle$, etc.

Questions:

1. Is every DCP state uniquely stabilized by an n-dimensional DCP subgroup?
2. What is the link between DCP states and 3PP states?
3. Can we build a *DCP tableau simulator*, with update rules for compatible measurements?

From phase polynomials to stabilizers

Theorem: DCP states are exactly the 3PP states.

From phase polynomials to stabilizers

Theorem: DCP states are exactly the 3PP states.

First direction: every 3PP state is a DCP state. By Proposition 1, it can be prepared as

$$|\psi\rangle = U\,|\phi\rangle\,, \qquad |\phi\rangle = |0\rangle^{\otimes(n-r)}\,|+\rangle^{\otimes r}\,, \quad U \in G_3.$$

From phase polynomials to stabilizers

Theorem: DCP states are exactly the 3PP states.

First direction: every 3PP state is a DCP state. By Proposition 1, it can be prepared as

$$|\psi\rangle = U\,|\phi\rangle\,, \qquad |\phi\rangle = |0\rangle^{\otimes(n-r)}\,|+\rangle^{\otimes r}\,, \quad U \in G_3.$$

The product state $|\phi\rangle$ is uniquely specified by n Pauli stabilizers $P_1, \ldots, P_n$. Conjugate them through the preparation circuit:

$$g_i = UP_iU^\dagger, \qquad g_i\,|\psi\rangle = UP_i\,|\phi\rangle = |\psi\rangle\,.$$

From phase polynomials to stabilizers

Theorem: DCP states are exactly the 3PP states.

First direction: every 3PP state is a DCP state. By Proposition 1, it can be prepared as

$$|\psi\rangle = U\,|\phi\rangle\,, \qquad |\phi\rangle = |0\rangle^{\otimes(n-r)}\,|+\rangle^{\otimes r}\,, \quad U \in G_3.$$

The product state $|\phi\rangle$ is uniquely specified by n Pauli stabilizers $P_1, \ldots, P_n$. Conjugate them through the preparation circuit:

$$g_i = UP_iU^\dagger, \qquad g_i\,|\psi\rangle = UP_i\,|\phi\rangle = |\psi\rangle\,.$$

Why DCP? Conjugating Paulis by CNOT-dihedral gates gives DCP operators. Unitary conjugation also preserves the uniquely fixed state.

From phase polynomials to stabilizers

Theorem: DCP states are exactly the 3PP states.

First direction: every 3PP state is a DCP state. By Proposition 1, it can be prepared as

$$|\psi\rangle = U|\phi\rangle, \qquad |\phi\rangle = |0\rangle^{\otimes(n-r)}|+\rangle^{\otimes r}, \quad U \in G_3.$$

The product state $|\phi\rangle$ is uniquely specified by n Pauli stabilizers $P_1, \ldots, P_n$. Conjugate them through the preparation circuit:

$$g_i = UP_iU^\dagger, \qquad g_i|\psi\rangle = UP_i|\phi\rangle = |\psi\rangle.$$

Why DCP? Conjugating Paulis by CNOT-dihedral gates gives DCP operators. Unitary conjugation also preserves the uniquely fixed state.

Answer to the first question: n independent commuting DCP generators suffice.

From stabilizers to support and phases

Let G uniquely fix $|\psi\rangle$. Write its elements as $DX(v)$, with D diagonal Clifford.

From stabilizers to support and phases

Let G uniquely fix $|\psi\rangle$. Write its elements as $DX(v)$, with D diagonal Clifford.

Support: collect all available shifts,

$$X(G) = \{v : DX(v) \in G \text{ for some diagonal } D\}.$$

A nonzero amplitude at x_0 forces nonzero amplitudes at every $x_0 + v$. Uniqueness forces a single such affine support: $S = x_0 + X(G)$. The diagonal stabilizers constrain which offset x_0 is allowed.

From stabilizers to support and phases

Let G uniquely fix $|\psi\rangle$. Write its elements as $DX(v)$, with D diagonal Clifford.

Support: collect all available shifts,

$$X(G) = \{v : DX(v) \in G \text{ for some diagonal } D\}.$$

A nonzero amplitude at x_0 forces nonzero amplitudes at every $x_0 + v$. Uniqueness forces a single such affine support: $S = x_0 + X(G)$. The diagonal stabilizers constrain which offset x_0 is allowed.

Phases: choose stabilizers $g_i = D_i X(v_i)$ for a basis of $X(G)$. If $D_i |x\rangle = \omega^{d_i(x)} |x\rangle$, their stabilizer equations fix

$$q(x + v_i) - q(x) = -d_i(x) \pmod 8 \qquad (x \in S).$$

From stabilizers to support and phases

Let G uniquely fix $|\psi\rangle$. Write its elements as $DX(v)$, with D diagonal Clifford.

Support: collect all available shifts,

$$X(G) = \{v : DX(v) \in G \text{ for some diagonal } D\}.$$

A nonzero amplitude at x_0 forces nonzero amplitudes at every $x_0 + v$. Uniqueness forces a single such affine support: $S = x_0 + X(G)$. The diagonal stabilizers constrain which offset x_0 is allowed.

Phases: choose stabilizers $g_i = D_i X(v_i)$ for a basis of $X(G)$. If $D_i |x\rangle = \omega^{d_i(x)} |x\rangle$, their stabilizer equations fix

$$q(x + v_i) - q(x) = -d_i(x) \pmod 8 \qquad (x \in S).$$

Combine the quadratic Clifford phases along a path from x_0. Each binary choice of shift adds one factor, giving a third-order phase polynomial. $\Rightarrow$ A 3PP state!

Updating the DCP stabilizers

Unitary gates: conjugate each generator. For $U \in G_3$, the result is still DCP:

$$g_i \longmapsto U g_i U^\dagger.$$

Updating the DCP stabilizers

Unitary gates: conjugate each generator. For $U \in G_3$, the result is still DCP:

$$g_i \longmapsto U g_i U^\dagger.$$

Z **measurements**: every DCP operator commutes or anticommutes with $Z(w)$. Keep the commuting stabilizers and add the measured $\pm Z(w)$. A deterministic measurement leaves the state unchanged, as in the Pauli case.

Updating the DCP stabilizers

Unitary gates: conjugate each generator. For $U \in G_3$, the result is still DCP:

$$g_i \longmapsto U g_i U^\dagger.$$

Z measurements: every DCP operator commutes or anticommutes with $Z(w)$. Keep the commuting stabilizers and add the measured $\pm Z(w)$. A deterministic measurement leaves the state unchanged, as in the Pauli case.

X measurements: first check whether $v \in X(G)$. If not, $S \neq S + v$ and the measurement is always compatible. Otherwise choose $g = DX(v) \in G$, with $D|x\rangle = \omega^{d(x)}|x\rangle$. Since $g|\psi\rangle = |\psi\rangle$,

$$X(v)|\psi\rangle = D^{-1}|\psi\rangle \quad \Rightarrow \quad \Delta_v q(x) = -d(x) \pmod 8 \quad (x \in S).$$

Read the phase difference directly from G, then use the classification theorem.

Updating the DCP stabilizers

Unitary gates: conjugate each generator. For $U \in G_3$, the result is still DCP:

$$g_i \longmapsto U g_i U^\dagger.$$

Z measurements: every DCP operator commutes or anticommutes with $Z(w)$. Keep the commuting stabilizers and add the measured $\pm Z(w)$. A deterministic measurement leaves the state unchanged, as in the Pauli case.

X measurements: first check whether $v \in X(G)$. If not, $S \neq S + v$ and the measurement is always compatible. Otherwise choose $g = DX(v) \in G$, with $D|x\rangle = \omega^{d(x)}|x\rangle$. Since $g|\psi\rangle = |\psi\rangle$,

$$X(v)|\psi\rangle = D^{-1}|\psi\rangle \quad \Rightarrow \quad \Delta_v q(x) = -d(x) \pmod 8 \quad (x \in S).$$

Read the phase difference directly from G, then use the classification theorem.

Result: compatibility tests and tableau updates take polynomial time.

4 Benchmarking our simulator

Future work

1. There are still a few circuits that evade our simulation method (e.g. H-based cultivation, some more complicated distillation protocols, etc.). Can we extend our method to cover these cases?
2. Can we formalize a notion of **"DCP detector error model"** for non-Clifford circuits?
3. Can we build a theory of **"DCP codes"**, generalizing XP codes?
4. Can we construct an interesting **resource theory** based on 3PP states? A "DCP polytope" generalizing the stabilizer polytope?
5. Is there any application to **learning theory**?
6. What concrete non-Clifford protocols should we start comparing and benchmarking using Merlin?

2610.06811 mark-koch/merlin-sim