

Amplitude-Robust Qubit Spectroscopy Using Echo-Root-Lorentzian Pulse Shapes

Asaf A. Solonnikov and Nadav Katz

The Racah Institute of Physics, The Hebrew University of Jerusalem, Israel

(Dated: July 21, 2026)

We present a qubit spectroscopy method based on Lorentzian-derived drive pulses that maintains narrow spectral features at drive amplitudes exceeding those used in conventional spectroscopy by more than three orders of magnitude, thereby enhancing robustness against amplitude variations. Specifically, we employ a root-Lorentzian envelope with a π -phase inversion at its peak, which introduces an echo-like symmetry that cancels on-resonant Rabi oscillations while preserving the spectral response. This approach suppresses conventional power broadening and enables high-resolution spectroscopy using pulses shorter than durations required by standard techniques. We experimentally demonstrate this method on a superconducting qubit platform and observe qualitative agreement with numerical simulations, highlighting its potential for rapid and calibration-robust qubit frequency characterization.

Accurate frequency characterization of a quantum two-level system (qubit) is essential for calibrating high-fidelity control in fault-tolerant quantum processors. In many physical implementations, such as superconducting circuits and semiconductor quantum dots, the qubit is realized within an inherently multilevel structure with discrete energy levels, allowing two levels to be selected to form an effective computational subspace that mimics atomic systems via their quantized energy spectrum [1, 2]. Spectroscopic identification of the transition frequency is therefore routinely performed by applying resonant control fields and monitoring the resulting population dynamics [3–5]. Spectroscopic resolution in direct population spectroscopy of coherently driven two-level systems is constrained by decoherence. In the absence of technical noise, stochastic phase fluctuations induce homogeneous broadening of the transition frequency, leading to a minimum resolvable linewidth that scales inversely with the coherence time T_2 , as described by the Bloch equations [6, 7]. This establishes the so-called T_2 limit for conventional direct spectroscopy.

In practice, however, driven spectroscopy introduces an additional trade-off between signal robustness and spectral resolution. When finite-amplitude control pulses are applied, the system dynamics deviate from the idealized two-level response due to coherent Rabi oscillations and coupling to noncomputational levels. Increasing the drive amplitude improves signal contrast and robustness against state-preparation and measurement errors, but simultaneously induces power broadening, resulting in a linewidth that scales with the instantaneous Rabi frequency. Consequently, conventional square-pulse and continuous-wave spectroscopic techniques must operate at low drive amplitudes to maintain resolution approaching the decoherence-limited linewidth set by T_2 , creating a severe practical trade-off between precision and robustness. Smooth temporal envelopes can weaken this broadening, and powers-of-Lorentzian pulses have been shown theoretically and experimentally to exhibit power narrowing [8, 9].

Ramsey interferometry provides a standard alternative to direct spectroscopy and, in principle, enables frequency estimation at the T_2 limit. Achieving such resolution, however, requires long interrogation times and sufficiently dense temporal sampling to resolve the resulting interference fringes. Moreover, Ramsey measurements are susceptible to systematic biases: asymmetries in the exponential decay envelope—arising, for example, from pulse miscalibration—can shift the apparent resonance peak in the frequency domain. Additional effects such as phase fluctuations or unintended AC Stark shifts during the control pulses introduce further distortions, ultimately biasing the extracted transition frequency [10, 11].

Alternative protocols can evade a probe- T_2 resolution bound by using inter-shot phase correlations, external clock references, dynamical decoupling, or tailored filter functions [12–17]. These approaches address different sensing settings and typically require repeated correlations, extended interrogation times, a stable external reference, or additional control resources. Here, we address the resolution-robustness trade-off within direct driven population spectroscopy by employing adiabatically engineered Lorentzian-derived drive pulses with a π -phase inversion at their peak. Unlike prior Lorentzian-pulse power-narrowing demonstrations, this echo-like structure suppresses on-resonant Rabi oscillations while preserving the off-resonant spectral response, maintaining narrow frequency features at drive amplitudes exceeding those used in conventional spectroscopy by more than three orders of magnitude.

Here, we propose a spectroscopic method for probing the qubit transition frequency using arbitrarily shaped drive pulses, specifically an echo-root-Lorentzian pulse. Previous theoretical work showed that Lorentzian pulses exhibit power narrowing, complementary to the conventional power broadening observed for constant drives, as a consequence of their adiabatic properties [8]. Power narrowing with powers-of-Lorentzian pulses was subsequently demonstrated experimentally on IBM Quantum, including the cutoff broadening introduced by truncat-




Figure 1. Pulse waveform and echo-cancellation mechanism. (a) Signed echo-root-Lorentzian drive envelope with a π phase inversion at the pulse midpoint. (b) Normalized magnitude of the waveform Fourier spectrum, showing the spectral null at zero frequency produced by the phase inversion. (c) Simulated excited-state population during the pulse at resonance and at non-resonant detunings of $\Delta/2\pi = 0.20$ and 1.00 MHz, using $T_1 = 9999 \mu\text{s}$. At resonance, the evolution accumulated during the first half is reversed during the second half, whereas finite detuning prevents complete cancellation.

ing the pulse wings [9]. In this work, we extend this framework to longer pulse durations approaching the T_1 timescale and introduce a π -phase jump at the pulse peak. The resulting echo property effectively cancels the net pulse area while preserving the adiabatic properties of the drive. This phase inversion reverses the coherent phase accumulation at resonance, suppressing on-resonant excitation while maintaining an off-resonant spectral response across the frequency domain, and thus making resonance distinguishable.

We define the echo-root-Lorentzian drive from the order- n generalized Lorentzian envelope as

$$L^{(n)}(t) = \frac{1}{\left[1 + \left(\frac{t}{\tau}\right)^2\right]^n}, \quad (1)$$

$$L_{\text{echo}}^{(1/2)}(t) := L^{(1/2)}(t) \text{sgn}(t). \quad (2)$$

where τ sets the characteristic pulse duration and n controls the algebraic decay of the wings. Throughout the theory, Δ and Ω are angular frequencies. Plotted axes are labeled $\Delta/(2\pi)$ and $\Omega_0/(2\pi)$. We denote an angular-frequency full width at half maximum by Γ_ω and its value in hertz by $\Gamma_f = \Gamma_\omega/(2\pi)$.

For the untruncated, plain generalized Lorentzian and $n > 1/2$, the usual adiabatic-breakdown estimate gives [8]

$$\Delta_b \tau \propto (\Omega_0 \tau)^{-\frac{1}{2n-1}}, \quad (3)$$

where Δ_b is the angular detuning at which adiabatic following ceases and Ω_0 is the peak angular Rabi frequency. The exponent grows without bound as $n \rightarrow 1/2^+$, so within its domain this asymptotic result predicts the steepest power-narrowing trend at the root-Lorentzian boundary. Exactly at $n = 1/2$, however, Eq. (3) is

singular and cannot be evaluated: it does not predict a zero linewidth or an infinite resolution. Finite truncation, decoherence, and the echo phase inversion regularize the response, and the FWHM Γ_f used below is therefore obtained from the complete simulated or measured spectrum. This interpretation is consistent with the power narrowing and cutoff broadening observed for powers of Lorentzian pulses by Mihov and Vitanov [9]. In contrast, a square pulse exhibits conventional power broadening, with $\Gamma_\omega \propto \Omega_0$ at large drive. The derivation and the marginal $n = 1/2$ limit are detailed in the Supplemental Material [18]. Numerical spectroscopy maps for matched root-Lorentzian and echo-root-Lorentzian pulses are shown at broad and narrow detuning scales in Fig. 2. All three rows use $L = 20 \mu\text{s}$; the Lorentzian-derived pulses use $c = 0.002$, and the columns span 50 and 1 MHz, respectively, with matched model parameters. Independent measurements on qubit q1 on 2026-06-28 give $T_1 = 51.24 \pm 0.73 \mu\text{s}$ and a Ramsey time $T_2^* = 7.31 \pm 0.13 \mu\text{s}$ (Supplemental coherence-characterization section). No Hahn-echo decay was acquired for this data set, so the Letter does not assign the Ramsey result to a measured Hahn-echo T_2 . For a conservative measurement-linked transverse reference, we set $T_{2,\text{eff}} = T_2^* = 7.31 \mu\text{s}$, corresponding to $\Gamma_{f,T_2} = 1/(\pi T_{2,\text{eff}}) = 43.5 \text{ kHz}$. The calculation in Fig. 2 uses these measurement-linked coherence parameters; $T_{2,\text{eff}}$ is not presented as independent Hahn-echo evidence.

Square pulses exhibit pronounced power broadening even at low drive amplitudes compared to Lorentzian-type pulses, with substantial linewidth expansion observed over three orders of magnitude in amplitude. In contrast, the root-Lorentzian pulse displays the characteristic power-narrowing behavior and maintains a nar-




Figure 2. Three-state transmon simulation at two frequency scales for 20 μ s pulses. The color scale is the final $|e\rangle$ population; the $|f\rangle$ population is evolved independently but is not added to P_e . The model uses anharmonicity $\alpha/2\pi = -200$ MHz. The upper row shows the broad 50 MHz domain (-25 to $+25$ MHz), and the lower row shows the narrow 1 MHz domain (-0.5 to $+0.5$ MHz). In the narrow panels, the paired black-edged white dashed lines at $\Delta/(2\pi) = \pm\Gamma_{f,T_2}/2$ enclose the coherence-limited FWHM; no reference line is drawn in the broad panels. From left to right, the columns show the constant, root-Lorentzian, and echo-root-Lorentzian protocols; the shaped pulses use relative endpoint amplitude $c = 0.002$. All six panels use the same coherence parameters, peak-Rabi grid, and probability scale. The comparison exposes conventional power broadening for the constant pulse, amplitude-dependent coherent structure for the ordinary root-Lorentzian pulse, and the narrow resonance-centered depletion feature preserved by the echo phase inversion.

row linewidth. However, for pulse durations comparable to the qubit lifetime T_1 , coherent oscillations arise for both square and root-Lorentzian pulses, resulting in amplitude-dependent linewidth variations that hinder precise spectral extraction.

Introducing a π phase inversion at the peak of the root-Lorentzian envelope partitions the drive into two sequential segments of opposite phase, such that the corresponding forward and backward evolutions cancel exactly at zero detuning. This echo-like structure suppresses resonant Rabi oscillations while preserving the off-resonant spectral response, producing a sharp depletion feature centered at the qubit transition frequency. In the frequency domain (Fig. 1), this manifests as a splitting of the spectral response accompanied by a null at resonance, rendering the measured linewidth largely insensitive to drive amplitude. This mechanism can be viewed as a Loschmidt-echo-like evolution, in which reversibility is achieved only on resonance, while detuning or decoherence breaks the cancellation and restores ex-

citation [19, 20]. Combined with the adiabatic following ensured by the Lorentzian envelope, this interference effect suppresses both power broadening and coherent Rabi oscillations, enabling narrow spectroscopy over a broad range of drive strengths and with pulse durations substantially shorter than those required by standard spectroscopy or Ramsey interferometry. Numerical state-evolution maps illustrating the resonant cancellation and detuned response are presented in the Supplemental Material [18].

Figure 3(a)–(f) resolves the two-dimensional maps into fixed-amplitude spectra. The three rows compare the same peak Rabi frequencies for the ordinary and echo protocols, making the echo-induced central depletion and its persistence with increasing drive amplitude explicit.

To suppress residual power broadening at large drive amplitudes, the pulse envelope must satisfy requirements on its cutoff behavior. Truncation introduces a residual endpoint drive $\Omega_c = c\Omega_0$ and a corresponding cutoff-broadening contribution [9, 21, 22]. The relevant weak-




Figure 3. Simulated spectra and resolution-contrast performance. (a)–(f) Final excited-state probability P_e versus detuning for 20 μs root-Lorentzian (left) and echo-root-Lorentzian (right) pulses with $c = 0.002$. From top to bottom, $\Omega_0/2\pi = 2.5, 10$, and 40 MHz. Solid curves are simulations; markers are deterministic noisy placeholders without uncertainty bars. (g) FWHM in coherence-limit units $\Gamma_f/\Gamma_{f,T_2}$, (h) normalized resolution $R = \Gamma_{f,T_2}/\Gamma_f$, and (i) contrast-weighted resolution $Q = AR$ versus peak Rabi frequency for echo-root-Lorentzian pulses with $L = 10, 20, 30$, and 40 μs . Colored continuous lines are fits to noise-free simulations; colored markers are fits to simulations after adding Gaussian noise with $\sigma_P = 0.002$ (see 4103), included as data-like placeholders rather than measured points. The red curve is the noise-free constant-drive Torrey result; dashed lines mark $\Gamma_f/\Gamma_{f,T_2} = 1$, $R = 1$, and $Q = 0.10$. Accepted noisy fits require $A/\sigma_P \geq 3$, $\Gamma_f/2\pi \leq 0.12$ MHz, and $|\Delta_c|/2\pi \leq 0.05$ MHz.

saturation condition is $s_c = \Omega_c^2 T_1 T_2 \ll 1$, or $\Omega_c \ll 1/\sqrt{T_1 T_2}$; the inequality therefore points toward *smaller*, not larger, endpoint amplitudes. The relative cutoff c cannot be specified independently of Ω_0 , T_1 , and T_2 . Our cutoff sweeps and high-amplitude measurements are reported in the Supplemental Material [18].

At the core of assessing pulse quality and identifying optimal operating regimes lies the spectral response of the driven qubit. We find that the echo pulse yields spectroscopic features with markedly reduced linewidths over a well-defined region of parameter space. We therefore choose pulse durations shorter than the qubit lifetime T_1 but long enough that Fourier broadening does not dominate.

Figure 3(g)–(i) quantifies this duration tradeoff at fixed cutoff $c = 0.002$. For each L , independent Gaussian noise with standard deviation $\sigma_P = 0.002$ is added to every simulated population sample before fitting. We retain a fitted feature only when its contrast satisfies $A/\sigma_P \geq 3$, in addition to the centered-line width and position gates. Consequently, the noisy marker series disappear at low drive when the spectroscopic signal is not distinguishable from the imposed noise, while the continuous noise-free simulation curves remain visible.

The longer pulses yield larger normalized resolution after the signal becomes resolvable, but their contrast-weighted operating windows contract. In this noise model, the 30- and 40 μs curves remain below $Q = 0.10$, whereas the 10- and 20 μs pulses retain accepted high-drive regions above threshold. Pulse duration must therefore be selected jointly with contrast and experimental noise, rather than by linewidth alone.

This constitutes an additional advantage of the echo protocol. While both constant and simple Lorentzian pulses exhibit coherent Rabi oscillations that persist even for pulse durations comparable to or exceeding T_1 , the intrinsic π -phase inversion of the echo pulse suppresses these coherence-induced oscillations. As a result, the spectral response remains smooth and well-behaved, enabling reliable linewidth extraction in regimes where standard and Lorentzian pulses display pronounced oscillatory distortions; see the additional high-amplitude data in the Supplemental Material [18].

Finally, the use of formally infinite-support pulses introduces a three-dimensional design space comprising pulse duration, drive amplitude, and cutoff level. The corresponding cutoff-amplitude simulations and their resolution-signal analysis are reported in the Supple-

mental Material [18]. In conclusion, the echo-root-Lorentzian pulse combines adiabatic shaping with a π -phase inversion to provide high-resolution spectroscopy over an amplitude range spanning roughly three orders of magnitude. This broad operating window, maintained even near neighboring qubit transitions, makes the protocol well suited to precision qubit characterization and establishes phase-sensitive off-resonant response as a practical alternative to population-transfer spectroscopy.

-
- [1] A. Blais, R.-S. Huang, A. Wallraff, S. M. Girvin, and R. J. Schoelkopf, Cavity quantum electrodynamics for superconducting electrical circuits: An architecture for quantum computation, *Phys. Rev. A* **69**, 062320 (2004).
 - [2] J. Koch, T. M. Yu, J. Gambetta, A. A. Houck, D. I. Schuster, J. Majer, A. Blais, M. H. Devoret, S. M. Girvin, and R. J. Schoelkopf, Charge-insensitive qubit design derived from the cooper pair box, *Phys. Rev. A* **76**, 042319 (2007).
 - [3] H. Paik, D. I. Schuster, L. S. Bishop, G. Kirchmair, G. Catelani, A. P. Sears, B. R. Johnson, M. J. Reagor, L. Frunzio, L. I. Glazman, S. M. Girvin, M. H. Devoret, and R. J. Schoelkopf, Observation of high coherence in josephson junction qubits measured in a three-dimensional circuit qed architecture, *Phys. Rev. Lett.* **107**, 240501 (2011).
 - [4] L. B. Nguyen, Y.-H. Lin, A. Somoroff, R. Mencia, N. Grabon, and V. E. Manucharyan, High-coherence fluxonium qubit, *Phys. Rev. X* **9**, 041041 (2019).
 - [5] S. Kim, H. Terai, T. Yamashita, W. Qiu, T. Fuse, F. Yoshihara, S. Ashhab, K. Inomata, and K. Semba, Enhanced coherence of all-nitride superconducting qubits epitaxially grown on silicon substrate, *Communications Materials* **2**, 98 (2021).
 - [6] F. Bloch, Nuclear induction, *Phys. Rev.* **70**, 460 (1946).
 - [7] S. Zienau, Optical resonance and two level atoms, *Physics Bulletin* **26**, 545 (1975).
 - [8] I. I. Boradjiev and N. V. Vitanov, Power narrowing in coherent atomic excitation by smoothly shaped pulsed fields, *Optics Communications* **288**, 91 (2013).
 - [9] I. S. Mihov and N. V. Vitanov, Defying conventional wisdom in spectroscopy: Power narrowing on IBM quantum, *Physical Review Letters* **132**, 020802 (2024), arXiv:2308.14187 [quant-ph].
 - [10] N. F. Ramsey, A molecular beam resonance method with separated oscillating fields, *Phys. Rev.* **78**, 695 (1950).
 - [11] J. W. Pollock, V. I. Yudin, M. Shuker, M. Y. Basalaev, A. V. Taichenachev, X. Liu, J. Kitching, and E. A. Donley, ac stark shifts of dark resonances probed with ramsey spectroscopy, *Phys. Rev. A* **98**, 053424 (2018).
 - [12] A. Rotem, T. Gefen, S. Oviedo-Casado, J. Prior, S. Schmitt, Y. Burak, L. McGuinness, F. Jelezko, and A. Retzker, Limits on spectral resolution measurements by quantum probes, *Phys. Rev. Lett.* **122**, 060503 (2019).
 - [13] T. Gefen, A. Rotem, and A. Retzker, Overcoming resolution limits with quantum sensing, *Nature Communications* **10**, 4992 (2019).
 - [14] Q. Cao, G. T. Genov, Y. Chu, J. Cai, Y. Liu, A. Retzker, and F. Jelezko, Overcoming frequency resolution limits using a solid-state spin quantum sensor, *Physical Review Letters* **135**, 10.1103/llfg-s4rr (2025).
 - [15] T. Gefen, M. Khodas, L. P. McGuinness, F. Jelezko, and A. Retzker, Quantum spectroscopy of single spins assisted by a classical clock (2016), arXiv:1612.07225 [quant-ph].
 - [16] J. Bylander, S. Gustavsson, F. Yan, F. Yoshihara, K. Harrabi, G. Fitch, D. G. Cory, Y. Nakamura, J.-S. Tsai, and W. D. Oliver, Noise spectroscopy through dynamical decoupling with a superconducting flux qubit, *Nature Physics* **7**, 565 (2011), arXiv:1101.4707 [cond-mat.supr-con].
 - [17] J. T. Iosue, P. Titum, T. Lin, C. Lau, and L. M. Norris, Superresolution in quantum noise spectroscopy via filter design (2026), arXiv:2602.11275 [quant-ph].
 - [18] See Supplemental Material at [URL will be inserted by publisher] for the experimental setup, coherence-limit and adiabatic-basis derivations, pulse-cutoff analysis, and additional high-amplitude data.
 - [19] T. Gorin, T. Prosen, T. H. Seligman, and M. Žnidarič, Dynamics of loschmidt echoes and fidelity decay, *Physics Reports* **435**, 33–156 (2006).
 - [20] A. Peres, Stability of quantum motion in chaotic and regular systems, *Phys. Rev. A* **30**, 1610 (1984).
 - [21] I. I. Boradjiev and N. V. Vitanov, Control of qubits by shaped pulses of finite duration, *Physical Review A* **88**, 013402 (2013).
 - [22] I. S. Mihov and N. V. Vitanov, Qubit dynamics driven by smooth pulses of finite duration (2024), arXiv:2404.12236 [quant-ph].
 - [23] Quantum Machines, OPX1000 front end modules: Microwave FEM, https://docs.quantum-machines.co/latest/docs/Guides/opx1000_fems/ (2026), accessed 19 July 2026.
 - [24] Quantum Machines, Demodulation and measurement, <https://docs.quantum-machines.co/latest/docs/Guides/demod/> (2026), accessed 19 July 2026.