1001 1010

Problem # 1: Multiple choice question. **[7 x 1pt]**

1) What is the content of AL after performing the following assembly instructions?

```
STD
MOV AL, 4Ch
SHL AL, 1
```

A. 26h
B. 54h
C. 98h
D. None of the above

2) What is the content of AL after performing the following assembly instructions?

```
CLD
MOV CL, 2
MOV AL, 0DEh
SHR AL, CL
```

A. 78h
B. 37h
C. 7Bh
D. None of the above

3) What is the content of DL after performing the following assembly instructions?

```
MOV DL, -12
SHL DL, 3
```

A. 60h
B. 0A0h
C. 0FCh
D. None of the above

4) What is the content of DL after performing the following assembly instructions?

```
MOV DL, 80h
SAR DL, 3
```

A. 0F0h
B. 00h
C. 10h
D. None of the above

are the contents of BL and Carry Flag (CF) after performing the following assen
tions?

```
CLC
MOV CL, 1
MOV BL, 11100011b
RCL  BL, CL
RCR  BL, 2
```

A. 0E1h, CF=1
B. 0C6h, CF=1
C. BL=71h, CF=1
D. None of the above

6) What is the content of DL after performing the following assembly instructions?

```
MOV DL, 5Ch
ROR DL, 3
```

A. 0E1h
B. 8Bh
C. 0E2h
D. None of the above

7) What are the values of DX and Carry Flag (CF) after executing the following 80 assembly instruction sequence?

```
X DW 1000h
MOV AX, 0A52h
MUL X
```

A. DX=0Ah, CF=1
B. DX=0Ah, CF=0
C. DX=0h, CF=0
D. DX=0A5h,

*** Write the correct answers of the problem # 1 in the table below:

Q1	Q2	Q3	Q4	Q5	Q6	Q7

Problem # 2: Write the contents of the AX, BX, and DX after executing the f
8086 instruction sequence. **[3pts]**

```
Num1 DB  -105
Num2 DW 1000h
MOV AL, Num1
CBW
MOV BL,9
IDIV BL
MOV BX, AX
MOV DX, 89h
MOV AX, 5016h
DIV Num2
```

AX= BX= DX=

Good Luck