# ***Interrupt***

- ***INT 10H, 02H (SETTING CURSOR)***
  - ***MOV AH, 02H***
  - ***MOV DH, (number of row)***
  - ***MOV DL, (number of column)***
  - ***MOV BH, (page number, 0 for default)***
  - ***INT 10H***
- ***INT 10H, 06H (SCREEN UP CLEARING)***
  - ***MOV AH,06H***
  - ***MOV AL, (number of lines to scroll)***
  - ***MOV BH, (color, reverse video, blinking)***
    - ***4bit = Background***
    - ***4bit = Foreground***
  - ***MOV CX, (starting ➔ CH: row, CL: column)***
    - ***UPPER LEFT CORNER***
  - ***Mov DX, (ending ➔ DH: row, DL: column)***
    - ***LOWER RIGHT CORNER***
- ***INT 10H, 07H (SCREEN DOWN CLEARING)***
  - ***MOV AH,06H***
  - ***MOV AL, (number of lines to scroll)***
  - ***MOV BH, (color, reverse video, blinking)***
    - ***4bit = Background***
    - ***4bit = Foreground***
  - ***MOV CX, (starting ➔ CH: row, CL: column)***
    - ***UPPER LEFT CORNER***
  - ***Mov DX, (ending ➔ DH: row, DL: column)***
    - ***LOWER RIGHT CORNER***



# Interrupt

- **INT 21H, 01H (INPUT FOR 1 CHAR)**
  - MOV AH,01H
  - INT 21H
    - AL = INPUT ➔ ASCII CODE
- **INT 21H,02H (OUTPUT FOR 1 CHAR)**
  - MOV AH, 02H
  - MOV DL, (what I need to print [ascii])
    - 0DH (return to first row)
    - 0AH (new line)
    - 09H (tap)
  - INT 21H
- **INT 21H,0AH (INPUT FOR MANY CHAR)**
  - X DB 10, ?, 10 DUP(?) (example for 10)
  - MOV AH,0AH
  - LEA DX,X
  - INT 21H
- **INT 21H,09H (OUTPUT FOR MANY CHAR)**
  - MOV AH,09H
  - X DB “AL BALQA UNI”,”$”
  - LEA DX,X
  - INT 21H

