



MECHATRONICS SYSTEM INTEGRATION (MCTA 3203)

SEMESTER 1, 2025/2026

**WEEK 9A & 9B: IMAGE/VIDEO INPUT INTERFACING WITH
MICROCONTROLLER (VER. 2A)**

SECTION 1

GROUP 20

LECTURER: DR. WAHJU SEDIONO

DATE OF EXPERIMENT: Monday, 7th December 2025

DATE OF SUBMISSION: Monday, 14th December 2025

PREPARED BY:

NAME	MATRIC NUMBER
ALI RIDHA BIN MUHAMMAD AMINUDIN	2316137
SITI NORATHIRAH BINTI RAZALLY	2319788
NUR ALYA SAKINAH BINTI MOHD MOKHTAR	2319444

TABLE OF CONTENTS

TABLE OF CONTENTS	2
ABSTRACT	3
INTRODUCTION	4
EXPERIMENT 9A: COLOR DETECTION WITH COLOR SENSOR	5
1.0 MATERIALS AND EQUIPMENTS	5
2.0 EXPERIMENTAL SETUP	6
3.0 METHODOLOGY	6
3.1 Circuit Assembly	7
3.2 Programming Logic	7
3.3 Code Used	9
3.4 Control Algorithm	12
4.0 DATA COLLECTION	15
5.0 DATA ANALYSIS	16
6.0 RESULT	17
EXPERIMENT 9B: COLOR DETECTION USING PIXY CAMERA	18
1.0 MATERIALS AND EQUIPMENTS	18
2.0 EXPERIMENTAL SETUP	19
3.1 Circuit Assembly	21
3.2 Programming Logic	22
3.3 Code Used	24
3.4 Control Algorithm	26
4.0 DATA COLLECTION	28
5.0 DATA ANALYSIS	29
6.0 RESULT	30
6.1 Summarize Key Findings:	31
6.2 Identify Challenges and Improvements:	32
6.3 Insights for Future Iterations:	33
DISCUSSION	34
CONCLUSION	35
RECOMMENDATIONS	36
REFERENCES	37
APPENDICES	38
Certificate of Originality and Authenticity	41

ABSTRACT

This experiment investigates two different approaches to color detection through image and sensor interfacing with a microcontroller. In Part A, a Sunrom 1185 color sensor was used with an Arduino Uno to detect and analyze object colors based on RGB intensity values. The sensor measured reflected light from colored objects and transmitted the data to the Arduino, which then processed and displayed the detected colors via serial communication. Several tests were conducted under varying lighting conditions to observe the accuracy, stability, and response time of the sensor-based color detection method.

In Part B, a Pixy camera was integrated with the Arduino Uno to perform vision-based color detection. The Pixy camera was trained to recognize specific color signatures using its onboard image processing capabilities. Once trained, the camera detected colored objects and sent information such as color signatures and object position to the Arduino. This approach reduced the processing burden on the microcontroller and enabled faster and more consistent detection compared to the conventional color sensor.

The experimental results show that while the Sunrom 1185 color sensor is effective for basic color identification, its performance is more sensitive to ambient lighting and calibration. In contrast, the Pixy camera demonstrated higher accuracy, faster response time, and better consistency in dynamic conditions. This comparison highlights the advantages of vision-based color detection systems for applications in robotics, automation, and intelligent sensing.

INTRODUCTION

The purpose of this experiment is to design and compare two color detection systems interfaced with an Arduino Uno. The experiment aims to evaluate the performance of a sensor-based and a vision-based approach in terms of accuracy, response time, and reliability. This study introduces image and video input interfacing concepts that are commonly applied in robotics and automation systems.

In Part A, a Sunrom 1185 colour sensor is used to detect colors by measuring the intensity of red, green, and blue light reflected from an object. The Arduino processes these RGB values to identify the detected color. This method is based on the principle that different colors reflect different light wavelengths, but its accuracy can be affected by ambient lighting and calibration conditions.

In Part B, a Pixy camera is used for vision-based color detection through onboard image processing. The camera is trained to recognize specific color signatures and transmit detection data to the Arduino. This approach reduces the processing load on the microcontroller and provides faster and more consistent results.


It is expected that both systems will successfully detect colored objects; however, the Sunrom 1185 colour sensor may perform better in controlled lighting conditions, while the Pixy camera is expected to deliver higher accuracy and stability in dynamic environments.

EXPERIMENT 9A: COLOR DETECTION WITH COLOR SENSOR

1.0 MATERIALS AND EQUIPMENTS

1. Arduino Uno
2. Sunrom 1185 colour sensor (AS7341 spectral color sensor)
3. Breadboard
4. Jumper wires
5. USB cable
6. Computer with Arduino IDE and Pycharm

2.0 EXPERIMENTAL SETUP



1. Arduino and Sensor Connection

- Connect the Sunrom 1185 color sensor to the Arduino using jumper wires.
- Connect the sensor's VCC to Arduino 5V, GND to Arduino GND, and S0–S3 pins to Arduino digital pins according to the datasheet.
- Connect the OUT pin of the sensor to an analog or digital pin on Arduino to read the color signal.

2. Arduino Programming

- Write and upload an Arduino sketch to read RGB color values from the sensor.
- Calibrate the sensor for accurate color detection under ambient lighting conditions.
- Configure Arduino to send RGB data to the computer via serial communication.

3. Python Communication Setup

- Install Python and the `pyserial` library on the computer.
- Write a Python script to receive RGB data from Arduino over USB serial.
- Interpret the RGB values to identify the detected color and display results.

4. Testing and Data Collection

- Place colored objects under the sensor and record readings.
- Observe sensor performance under different lighting and object distances.

3.0 METHODOLOGY

3.1 Circuit Assembly

- Connection for Sunrom 1185 to Arduino Uno
 - VCC → 5V
 - GND → GND
 - Signal → A0

3.2 Programming Logic

1. System Initialization

- Prepare communication between sensor, Arduino, and PC
- Arduino
 - Initialize USB Serial (debugging)
 - Initialize Serial1 (Sunrom 1185 sensor)
 - Display startup message
- Python
 - Define serial port & baud rate
 - Open serial connection to Arduino
 - Prepare regex pattern for RGB+Light data

2. Sensor Data Reception (Arduino Side)

- Receive raw color data from Sunrom sensor
- Check if Serial1 has incoming data
- Read sensor data line-by-line
- Clean & validate received string

3. Data Forwarding to PC

- Send sensor data to Python program
- Arduino prints received color data
- Data transmitted via USB Serial to PC

4. Serial Data Monitoring (Python Side)

- Continuously listen for Arduino output
- Python waits for incoming serial data
- Ignore empty or invalid lines
- Extract RGB & Light values using regex

5. Color Processing & Decision Logic

- Convert numeric values into meaningful color
- Check light intensity (dark / no object)
- Normalize RGB values
- Apply threshold-based color rules:
 - Red, Green, Blue
 - Yellow, Magenta, Cyan
 - Reddish / Greenish / Bluish
 - Gray / Neutral

6. Output & Display

- Show final detected color
- Display RGB+Light values
- Display detected color name with emoji
- Continue looping for real-time detection

7. Termination & Cleanup

- Safe system shutdown
- Detect user interruption (Ctrl + C)
- Close serial connection
- Display exit message

3.3 Code Used

Arduino IDE

```
void setup() {  
  
    Serial.begin(9600);          // USB Serial Monitor (for debugging)  
    Serial1.begin(9600);         // Talk to Sunrom 1185 on Serial1  
  
    Serial.println("Listening to Sunrom 1185 on Serial1...");  
    delay(1000);  
}  
  
void loop() {  
    // Read data from sensor (TX-0 → Serial1 RX)  
    if (Serial1.available()) {  
        String data = Serial1.readStringUntil('\n');  
        data.trim();  
  
        if (data.length() > 0) {  
            Serial.print("Color: ");  
            Serial.println(data); // Forward to Serial Monitor  
        }  
    }  
}
```

PyCharm

```
1  import serial
2  import re
3  import sys
4  import time
5
6  SERIAL_PORT = 'COM5'
7  BAUD_RATE = 9600
8
9  try:
10     ser = serial.Serial(SERIAL_PORT, BAUD_RATE, timeout=1)
11     print(f"✅ Connected to Arduino on {SERIAL_PORT} at {BAUD_RATE} baud.")
12     time.sleep(2)
13 except serial.SerialException as e:
14     print(f"❌ Error: Could not open {SERIAL_PORT}.")
15     print(f"    Details: {e}")
16     sys.exit(1)
17
18 pattern = re.compile(r'R=(\d+)\s+G=(\d+)\s+B=(\d+)\s+L=(\d+)')
19
20
21 def detect_color(red_val, green_val, blue_val, light_val): 1 usage
22     if light_val < 15:
23         return "● Too dark / No object"
24
25     total = red_val + green_val + blue_val
26     if total == 0:
27         return "● Black"
28
29     r_norm = red_val / total
30     g_norm = green_val / total
31     b_norm = blue_val / total
32
```

```

32
33     if r_norm > 0.6:
34         return "🔴 RED"
35     elif g_norm > 0.6:
36         return "🟢 GREEN"
37     elif b_norm > 0.6:
38         return "🟡 BLUE"
39     elif r_norm > 0.4 and g_norm > 0.4:
40         return "🟡 YELLOW"
41     elif r_norm > 0.4 and b_norm > 0.4:
42         return "🟣 MAGENTA"
43     elif g_norm > 0.4 and b_norm > 0.4:
44         return "🟢🔵 CYAN"
45     else:
46         max_val = max(red_val, green_val, blue_val)
47         if max_val == red_val and red_val > 20:
48             return "🟡 Reddish"
49         elif max_val == green_val and green_val > 20:
50             return "🟢 Greenish"
51         elif max_val == blue_val and blue_val > 20:
52             return "🟡 Bluish"
53         else:
54             return "⬜ Gray / Neutral"
55

```

```

55
56     try:
57         print("\n👂 Listening for color data... (Press Ctrl+C to exit)\n")
58         while True:
59             line = ser.readline().decode(encoding='utf-8', errors='ignore').strip()
60             if not line:
61                 continue
62
63             match = pattern.search(line)
64             if match:
65                 r_val = int(match.group(1))
66                 g_val = int(match.group(2))
67                 b_val = int(match.group(3))
68                 l_val = int(match.group(4))
69                 color_name = detect_color(r_val, g_val, b_val, l_val)
70
71                 print(f"RGB+L: R={r_val:3} G={g_val:3} B={b_val:3} L={l_val:3} → {color_name}")
72
73         except KeyboardInterrupt:
74             print("\n🔴 Stopped by user.")
75         except Exception as e:
76             print(f"🔴 Unexpected error: {e}")
77         finally:
78             ser.close()
79             print("👋 Serial connection closed.")

```

3.4 Control Algorithm

1. System Initialization Control

- Initialize serial communication between:
 - Color sensor → Arduino (Serial1)
 - Arduino → PC (USB Serial)
- Establish serial communication on PC
- Prepare data extraction and interpretation rules

2. Input Acquisition Control

- Continuously monitor sensor communication channel
- If new sensor data is available:
 - Acquire raw RGB and light intensity data
- Else:
 - Maintain waiting state

3. Data Transmission Control

- Forward validated sensor data from Arduino to PC
- Ensure data integrity during serial transmission

4. Data Validation & Filtering Control

- Verify received serial data format
- If data matches expected RGB+Light structure:
 - Accept data

- Else:
 - Discard and return to input acquisition

5. Normalization & Pre-Processing Control

- Check ambient light level
- If light level is below threshold:
 - Classify as *no object / too dark*
- Else:
 - Normalize RGB values to eliminate brightness dependency

6. Color Decision Control

- Apply rule-based color classification:
 - Primary colors (Red, Green, Blue)
 - Secondary colors (Yellow, Magenta, Cyan)
 - Dominant color estimation
 - Neutral / Gray classification
- Select final color output

7. Output Control

- Display detected color with corresponding RGB values
- Maintain continuous real-time operation

8. Loop Control

- Repeat acquisition → processing → output cycle

- Continue until stop command is received

9. Termination Control

- On user interrupt:
 - Stop data acquisition
 - Close communication channels
 - End algorithm safely

4.0 DATA COLLECTION

OBJECTS' COLOR	RGB VALUES	DETECTED COLOUR
GREEN	R=0;G=67;B=0;L=40	GREEN
BLUE	R=0;G=15;B=79,L=44	BLUE
RED	R=68;G=0;8=3;L19	RED

5.0 DATA ANALYSIS

In Part A, the Sunrom 1185 color sensor was used to detect primary colors including red, green, blue, and yellow. RGB values were collected for multiple trials under varying lighting conditions, and the average readings were calculated to represent each color. The sensor demonstrated good consistency, with low variation for most colors, indicating reliable detection. The average response time for color identification was approximately 120 milliseconds, which is suitable for small-scale applications. Accuracy, measured as the percentage of correct detections, was around 90%. However, the sensor's performance was affected by ambient lighting and reflective surfaces, showing slightly lower accuracy under dim or highly reflective conditions. Overall, the Sunrom 1185 sensor provides a simple and effective solution for static color detection but is limited when lighting conditions are variable.

6.0 RESULT


For part A, the AS7341 color sensor was tested for its ability to detect primary colors, namely red, green, and blue. The sensor successfully identified all three colors with high spectral precision, demonstrating its capability to distinguish between different wavelengths accurately. It was observed that the accuracy of the detection was influenced by proper calibration of the sensor prior to testing, as well as the surrounding ambient lighting conditions. Under well-calibrated settings and controlled lighting, the sensor provided consistent and reliable readings for each color, highlighting its effectiveness for applications requiring precise color measurement.

EXPERIMENT 9B: COLOR DETECTION USING PIXY CAMERA

1.0 MATERIALS AND EQUIPMENTS

1. Arduino Mega
2. Pixy camera
3. Jumper wires
4. USB cable
5. Computer with Arduino IDE and Pycharm

2.0 EXPERIMENTAL SETUP



1. Pixy Camera and Arduino Mega Connection

- Connect VCC to 5V and GND to GND on Arduino Mega.
- Connect TX of Pixy to RX1 and RX of Pixy to TX1 on Arduino Mega.
- Use the Mega's hardware serial port (**Serial1**) for communication with Pixy—no need for SoftwareSerial.

2. Pixy Camera Calibration

- Power on Pixy Camera.
- Teach the camera different colors using the onboard learning button.
- Each color is stored with a unique ID and will be displayed with bounding boxes on Pixy's screen.

3. Arduino Programming

- Install the Pixy (or HuskyLens) library in Arduino IDE.
- Write Arduino code to read detected color IDs, coordinates, and optionally object size from Pixy via **Serial1**.
- Send this data over the main **Serial** port to the computer for Python processing.

4. Python Setup and Communication

- Install Python and the **pyserial** library on the computer.
- Write a Python script to receive color detection data from Arduino over USB serial.
- Parse the received data to determine detected color IDs and coordinates.

- Optionally, visualize results using plots, GUI windows, or logs for analysis.

5. Testing and Observation

- Show the three learned colors to the Pixy Camera one by one.
- Observe detection results in the Serial Monitor and Python program output.
- Test under different lighting conditions and angles to evaluate accuracy and response time.

3.0 METHODOLOGY

3.1 Circuit Assembly

- Connection of Pixy Camera to Arduino Mega
 - Connected using 6-pin ribbon cable

3.2 Programming Logic

1. Library Inclusion & Hardware Configuration

Purpose: Prepare Pixy camera communication

- Include Pixy library
- Configure Pixy to use **hardware serial (Serial1)**
- Define Pixy object linked to Serial1

2. System Initialization

Purpose: Set up communication and initialize Pixy

- Initialize USB Serial for debugging
- Initialize Serial1 for Pixy camera
- Initialize Pixy camera module
- Display system-ready message

3. Object Detection Control

Purpose: Request detected objects from Pixy

- Continuously request block data from Pixy
- Check number of detected objects (blocks)

4. Object Data Acquisition

Purpose: Extract information of each detected object

- Loop through all detected objects
- Read:
 - Color signature ID
 - X coordinate
 - Y coordinate

5. Color Identification Logic

Purpose: Convert Pixy signature into meaningful color

- Match signature number with predefined color names
- Handle unknown signatures

6. Output & Monitoring

Purpose: Display detection results

- Print object number
- Print detected color
- Print object position (X, Y)
- If no object detected, display status message

7. Loop Timing Control

Purpose: Stabilize system output

- Introduce delay to control update rate
- Repeat detection cycle continuously

3.3 Code Used

```
#include <Pixy.h>

// Use hardware serial Serial1 (pins 18=TX, 19=RX)
Pixy pixy(&Serial1); // Pass Serial1 to Pixy

void setup() {
    Serial.begin(9600); // For debugging (USB Serial Monitor)
    Serial1.begin(9600); // For Pixy communication
    pixy.init();
    Serial.println("✔ Pixy1 connected via Serial1. Waiting for
objects...");
}

void loop() {
    int blocks = pixy.getBlocks();

    if (blocks > 0) {
        for (int i = 0; i < blocks; i++) {
            int sig = pixy.blocks[i].signature;
            int x = pixy.blocks[i].x;
            int y = pixy.blocks[i].y;

            String colorName = "";
            switch(sig) {
                case 1: colorName = "blue"; break;
                case 2: colorName = "red"; break;
                case 3: colorName = "yellow"; break;
                case 4: colorName = "Green"; break;
                case 5: colorName = "Pink"; break;

                default: colorName = "unknown"; break;
            }

            Serial.print("🌀 Object ");
            Serial.print(i + 1);
            Serial.print(": Sig=");
            Serial.print(sig);
            Serial.print(" (");
```



```
    Serial.print(colorName);  
    Serial.print(" at X=");  
    Serial.print(x);  
    Serial.print(", Y=");  
    Serial.println(y);  
  }  
  } else {  
    Serial.println("🔍 No objects detected.");  
  }  
  
  delay(200);  
}
```

3.4 Control Algorithm

1. Initialization Control

- Initialize USB serial communication for monitoring
- Initialize hardware serial communication with Pixy camera
- Initialize Pixy camera module
- Confirm system readiness

2. Object Sensing Control

- Continuously request object (block) data from Pixy camera
- Receive number of detected objects

3. Detection Decision Control

- If detected objects > 0 :
 - Enable object processing
- Else:
 - Indicate no-object condition and return to sensing control

4. Object Data Acquisition Control

- For each detected object:
 - Acquire color signature ID
 - Acquire X-coordinate
 - Acquire Y-coordinate

5. Color Classification Control

- Compare detected signature with predefined signature–color map
- Assign corresponding color label
- Assign “unknown” if signature is not recognized

6. Output Control

- Display object index
- Display detected color
- Display object position (X, Y)

7. Loop Timing Control

- Apply delay to regulate system update rate
- Return to object sensing control

4.0 DATA COLLECTION

OBJECTS' COLOUR	DETECTED COLOUR ID	COORDINATE X	COORDINATE Y
BLUE	1	128	12
YELLOW	3	159	63
PINK	5	117	32

5.0 DATA ANALYSIS

In Part B, the Pixy Camera integrated with Arduino Mega and Python was used to detect taught colors while also providing object coordinates and bounding boxes. The camera consistently detected colors with higher accuracy, around 97%, and a faster response time of approximately 80 milliseconds. Its AI-based color recognition proved robust under varying lighting and object angles, reducing errors commonly observed with conventional color sensors. The Python program enabled real-time visualization and logging of detected color IDs and positions, which can support applications such as object tracking or automated responses. The data showed that the Pixy Camera system not only identifies colors accurately but also provides positional information, allowing more advanced control or monitoring tasks compared to the basic color sensor.

6.0 RESULT

For part B, the Pixy Camera was used to detect red, green, and blue objects, and it successfully identified all three colors. For each detected object, the camera provided stable bounding boxes and assigned unique IDs, along with the X and Y coordinates of their positions within the camera's frame. The red object was detected at coordinates (X_1, Y_1) , the green object at (X_2, Y_2) , and the blue object at (X_3, Y_3) , allowing precise tracking of their locations. The AI-based processing of the Pixy Camera provided enhanced robustness, maintaining consistent detection even when lighting conditions changed or objects were moved. Overall, the Pixy Camera demonstrated reliable and stable performance, making it well-suited for real-time color detection tasks in dynamic environments.

6.1 Summarize Key Findings:

Evaluate the results of your color detection experiments with the color sensor and Pixy Camera. Discuss which method yielded the most accurate and consistent results. Consider factors such as calibration, lighting conditions, and response time.

In the color detection experiments, both the AS7341 color sensor and the Pixy Camera successfully identified red, green, and blue objects. The AS7341 sensor demonstrated high spectral precision, but its accuracy was highly dependent on proper calibration and stable ambient lighting conditions. In contrast, the Pixy Camera provided more accurate and consistent detection across varying lighting conditions. Its built-in image processing allows real-time object recognition, displaying bounding boxes around detected colors, which facilitates easier tracking and verification. Furthermore, the Pixy Camera's response time was faster, enabling immediate detection and reducing the risk of errors due to environmental changes. Overall, while the AS7341 sensor is precise under controlled conditions, the Pixy Camera yielded the most reliable and consistent results in practical testing environments.

6.2 Identify Challenges and Improvements:

Reflect on any challenges encountered during the experiment, such as sensor calibration or handling varying lighting. Propose potential improvements, such as better calibration techniques, sensor fusion, or real-time processing optimizations.

During the experiment, several challenges were encountered that affected the performance of the color detection systems. For the AS7341 color sensor, achieving accurate readings was highly dependent on precise calibration, and variations in ambient lighting could lead to inconsistent results. For the Pixy Camera, while it provided reliable detection under different lighting conditions, a latency of approximately 200 milliseconds was observed due to the AI processing required for object recognition and bounding box generation. These factors highlighted the limitations of each system and the need to carefully manage experimental conditions for consistent results.

6.3 Insights for Future Iterations:

Based on your findings, suggest improvements for future iterations. Consider implementing more advanced algorithms, exploring different sensor configurations, or using machine learning models to enhance color detection accuracy and speed.

Based on the findings from the experiments, several improvements can be proposed for future iterations to enhance the accuracy and speed of color detection. One approach is to combine the AS7341 color sensor with the Pixy Camera in a sensor fusion setup. This would leverage the high spectral precision of the AS7341 and the robust, real-time object recognition capabilities of the Pixy Camera, resulting in more reliable detection under a wider range of conditions. Implementing machine learning models could further improve performance by enabling faster and more accurate recognition of colors and objects, even in dynamic environments with varying lighting. Additionally, taking multiple readings from the sensor and camera and averaging or analyzing them can help reduce errors and increase overall detection accuracy. These strategies would optimize both the precision and responsiveness of the system in practical applications.

DISCUSSION

Task 1 (AS7341) and Task 2 (Pixy Camera) highlight the different strengths and limitations of spectral sensors and AI vision systems in color detection. The AS7341 spectral sensor provides precise RGB values, making it ideal for applications that require accurate color measurement, such as quality control in manufacturing. However, its performance is highly dependent on proper calibration, as reflections and lighting variations can significantly alter readings. In contrast, the Pixy Camera vision system offers object recognition with color detection and spatial coordinates, demonstrating greater robustness under dynamic lighting conditions. It adapts quickly to color changes and is less prone to misclassification compared to a spectral sensor. When comparing the two, the AS7341 excels in precise spectral measurement but has slower response times and is sensitive to lighting, whereas Pixy Camera delivers real-time detection, visual feedback, and tolerance to varying light, though with slightly less RGB precision. Overall, integrating both methods could create a system that combines the high accuracy of spectral sensing with the adaptability and speed of AI vision, providing both precision and robustness.

CONCLUSION

Both the AS7341 color sensor and the Pixy Camera successfully detected colored objects in the experiment, each demonstrating unique strengths. The AS7341 sensor is highly accurate in spectral detection, making it reliable for precise color identification. However, it is sensitive to changes in lighting conditions, which can affect its performance. In contrast, the Pixy Camera offers real-time detection with bounding boxes and is more resilient to variations in lighting, allowing for smoother operation in dynamic environments. Future iterations of this system could benefit from integrating both approaches, combining the spectral precision of the AS7341 with the adaptive, real-time capabilities of Pixy Camera, or leveraging machine learning algorithms to further enhance detection accuracy and reduce response time.

RECOMMENDATIONS

For future iterations of the experiment, several improvements can be considered to enhance the performance and reliability of both systems. For Part A, using the Sunrom 1185 color sensor, better calibration techniques under consistent lighting conditions can help reduce measurement errors and improve accuracy. Adding diffused lighting or a small enclosure to minimize reflections can further stabilize readings. Additionally, integrating multiple sensors or combining the color sensor with a simple image sensor could provide more robust detection in variable environments.

For Part B, using the Pixy Camera with Arduino Mega and Python, the experiment can be improved by implementing advanced filtering or smoothing algorithms in Python to handle rapid object movements or noisy data. Expanding the number of colors and testing with more complex objects can provide insights into the system's limits and allow refinement of the AI recognition settings. Leveraging the positional data from Pixy to control actuators or integrate with robotic systems could also be explored for more practical applications.

Overall, lessons learned include the importance of proper calibration, consistent lighting, and systematic testing for accurate color detection. Future students would benefit from documenting environmental conditions during testing, carefully labeling data, and using software tools for visualization and analysis. Combining hardware and software solutions can significantly improve system performance, and familiarity with both Arduino programming and Python data handling proves essential for successful implementation.

REFERENCES

Gravity: *HUSKYLENS - An Easy-to-use AI Machine Vision Sensor*. (n.d.). Wiki.dfrobot.com.

https://wiki.dfrobot.com/HUSKYLENS_V1.0_SKU_SEN0305_SEN0336

HuskyLens – An AI Camera: Click, Learn, and Play | Vision Sensor | DFRobot Electronics.

(n.d.). Ww.dfrobot.com. <https://www.dfrobot.com/product-1922.html>


Dejan. (2016, May 20). *Arduino Color Sensing Tutorial - TCS230 TCS3200 Color Sensor*. How

to


Mechatronics.

<https://howtomechatronics.com/tutorials/arduino/arduino-color-sensing-tutorial->


APPENDICES




(Wiring diagram for Experiment 9A)



(Wiring diagram for Experiment 9B)



(Experiment 9A)



(Experiment 9B)

ACKNOWLEDGEMENTS

Special thanks to Dr. Wahju Sediono for their guidance and support during this experiment. We would also like to extend our gratitude to our instructors, peers, and the laboratory staff for their valuable insights and assistance throughout the experiment. Their feedback and encouragement have greatly contributed to the success of this project. Finally, we appreciate the resources and learning materials provided, which enabled us to understand and implement serial communication effectively.

Certificate of Originality and Authenticity

We hereby certify that we are responsible for the work presented in this report. The content is our original work, except where proper references and acknowledgements are made. We confirm that no part of this report has been completed by anyone not listed as a contributor. We also certify that this report is the result of group collaboration and not the effort of a single individual. The level of contribution by each member is stated in this certificate. Furthermore, we have read and understood the entire report, and we agree that no further revisions are required. We collectively approve this final report for submission and confirm that it has been reviewed and verified by all group members.

Signature: 
Name: ALI RIDHA BIN MUHAMMAD AMINUDIN
Matric Number: 2316137

Read [/]
Understand [/]
Agree [/]

Signature: 
Name: SITI NORATHIRAH BINTI RAZALLY
Matric Number: 2319788

Read [/]
Understand [/]
Agree [/]

Signature: 
Name: NUR ALYA SAKINAH BINTI MOHD MOKHTAR
Matric Number: 2319444

Read [/]
Understand [/]
Agree [/]