

Deploy VMware Cluster with FC (EMC) Storage

To deploy VMware Cluster with FC (EMC) Storage:

1. Click **Templates-> Sample Templates**.
2. Click **Deploy VMware Cluster with FC (EMC) Storage-> Clone**.
The **Clone Template-VMware Cluster with FC (EMC) Storage** window is displayed.
3. In the **Clone Template- VMware Cluster with FC (EMC) Storage** window, edit the following:
 - a. Type a name in the **Template Name** field.
 - b. From the **Template Category** drop-down menu, select a template category. Select the **Create New Category** option if you want to create a new template category.
 - c. In the **Template Description** field, type a description for the template.
 - d. To update the firmware and software while deploying a service using this template, select the **Manage Server Firmware/Software** check box and select a firmware and software repository from the **Use Firmware Repository** drop-down menu.
NOTE: Changing the firmware repository may update the firmware level on servers for this service. Firmware on shared devices is maintained by the global default firmware repository.
 - e. To grant access to standard users to use this templates, select any one of the following options from the **Manage Service Permissions** option:
 - i. **All Standard Users** — Select this option to provide access to all standard users.
 - ii. **Specific Standard Users** — Select this option to provide access to specific users.
Click **+ Add User(s)** to add the users. To remove users added to list, select the user and click **Remove User(s)**.
 - f. Click **Next**.
The **Additional Settings** window is displayed.
 - g. Under **Network Settings**, select a new network from the **Select New Network** drop-down menu.
 - h. Under **OS Settings**, configure the following:
 - i. Type the OS administrator password in the **OS Administrator Password** field.
 - ii. From the **Select New OS Repository** drop-menu, select a new OS repository.
 - i. Under **Server Pool Settings**, select a new server pool from the **Select New Server Pool** drop-down menu.
 - j. Click **Finish**.
4. On the **Template Builder** page, click the storage component, and then click **Edit**.
The **Storage Component** window is displayed.
5. Configure the following settings in the **Storage Component** window:
 - a. Under the **Basic Settings** section, edit the name in the **Component Name** field as required.
 - b. Under the **Associated Resources** section, select **Associate All Resources** or **Associate Selected Resources** to associate all or specific components to the new component.
 - c. Click **Continue**.
 - d. Under the **VNX Storage Settings** section, select or type the following:
 - i. From the **Target VNX** drop-down menu, select the target VNX device.
 - ii. Type the pool name in the **Pool Name** box.
 - iii. Select a storage volume name from the **Storage Volume Name** drop-down menu.

You can create new volume by selecting **Create New Volume** from the **Storage Volume Name** drop-down menu.

- iv. Type the storage size in the **Storage Size** box.
 - v. Type the folder name.
 - vi. Enable or disable the zone configuration on the Brocade FC SAN switch by selecting or clearing the **Configure SAN Switch** check box.
 - vii. From the **Add to VMware Storage DRS Cluster** drop-down menu, select the storage cluster POD name.
6. On the **Template Builder** page, click the server component and click **Edit**. The **Server Component** window is displayed. Configure the following settings in the **Server Component** window:
- i. Under the **Basic Settings** section, edit the name in the **Component Name** field as required.
 - ii. Under the **Associated Resources** section, select **Associate All Resources** or **Associate Selected Resources** to associate all or specific components to the new component.
 - iii. Click **Continue**.
 - iv. Select any one of the following:
 - i. **Import Configuration from Reference Server** — select to import the configuration from an existing server.
 - ii. **Import from Existing Template** — select to import the configuration from a server component in an existing template.
 - iii. **Upload Server Configuration Profile** — select this option to configure the component based on a configuration profile available on the system.
 - v. Under **OS Settings**, configure the following:
 - i. If you select the **Auto-generate Host Name** check box, a **Host Name Template** field is displayed.
In the **Host Name Template** box, type the unique host name for deployment.
 - ii. From the **OS Image** drop-down menu, select the OS image.
 - iii. Edit the **Administrator Password**.
 - iv. In the **NTP Server** box, specify the IP address of the NTP server for time synchronization.
If you want to add more than one NTP server in the OS section of a server component, make sure to separate the IP addresses using comma (,).
 - v. Enable or disable the local storage for VMware vSAN by selecting or clearing the **Local storage for VMware vSAN** check box.
If you enable the **Local storage for VMware vSAN**, select one of the following **Local Storage Type**:
 - **All flash**
 - **Hybrid**
 - vi. Under the **Hardware Settings** section, select the following:
 - i. **Target Boot Device** — select the boot device such as local hard drive or SD card from the drop-down menu.
 - ii. **Server Pool** — select the pool from which the servers are selected during deployment.

- vii. Under the **BIOS Settings** section, select the following:
 - i. **System Profile** — select the system power and performance profile for the server.
 - ii. **User Accessible USB Ports** — select the server ports that are accessible by the user.
 - iii. **Number of Cores per Processor** — select the number of enabled cores per processor.
 - iv. **Virtualization Technology** — select **Enabled** to enable the additional hardware capabilities provided by virtualization technology.
 - v. **Logical Processor** — each processor core supports up to two logical processors. If set to **Enabled**, the BIOS reports all logical processors. If set to **Disabled**, the BIOS reports only one logical processor per core.
 - vi. **Execute Disable** — allows you to enable or disable the Execute Disable bit.
 - vii. **Node Interleaving** — if the system is configured with matching memory, set the option to **Enabled**. If set to **Disabled**, the system supports non-uniform memory architecture memory configurations.
 - viii. Under the **Network Settings** section, select the following:
 - i. **Add New Interface** — Click to create an interface based on the specified the **Fabric Type**, **Port Layout**, **Partitioning**, and **Redundancy**.
 - ii. **Identity Pool** — Select the pool from which the virtual identities must be selected during deployment.
 - ix. Click **Save**.
- 7. On the **Template Builder** page, select the **VMware cluster** component, click **Edit**.
The **Cluster component** window is displayed
- 8. Configure the following settings in the **Cluster Component** window:
 - a. Under the **Basic Settings** section, edit the name in the **Component Name** field as required.
 - b. Under the **Associated Resources** section, select **Associate All Resources** or **Associate Selected Resources** to associate all or specific components to the new component.
 - c. Click **Continue**.
 - d. Under **Cluster Settings**, configure the following:
 - i. From the **Target Virtual Machine Manager** drop-down list, make sure that you select virtual machine manager.
 - ii. Select the data center name from the **Data Center Name** drop-down menu.
 - iii. Type the new data center name in the **New data center name** box.
 - iv. Select one of the following **Switch Type**:
 - **Distributed**
 - **Standard**
 - v. Enable or disable the highly available cluster (HA) by selecting or clearing the **Cluster HA Enabled** check box.
 - vi. Enable or disable the distributed resource scheduler (DRS) by selecting or clearing the **Cluster DRS Enabled** check box.
 - vii. Enable or disable the VMware vSAN by selecting or clearing the **Enable VMware vSAN** check box.
 - viii. Enable or disable the Storage DRS by selecting or clearing the **Storage DRS Enabled** check box.
If Storage DRS is set to enabled, do the following:

- I. Type the storage POD name in the **Storage Cluster Name** box.
 - II. Select data stores to add data center.
 - ix. Click **Save**.
9. Click **Publish Template**.
Template is ready to be deployed.