Table 30. Typical current consumption in Run depending on code executed (continued)

Symbol	Parameter	Conditions General(1)	Conditions Code	Conditions Fetch from(2)	Typ 25 °C	Unit	Typ 25 °C	Unit
$I_{DD(Run)}$	Supply current in Run mode	$f_{HCLK} = f_{HSI48/HSIDIV}$ = 48 MHz (HSIDIV = 1)	Reduced code(3)	Flash memory	3.75	mA	78.1	µA/MHz
			Coremark		3.50		72.9	
			Dhrystone		3.55		74.0	
			Fibonacci		2.75		57.3	
			WhileLoop		2.15		44.8	
			Reduced code(3)	SRAM	3.15		65.6	
			Coremark		3.05		63.5	
			Dhrystone		3.05		63.5	
			Fibonacci		3.20		66.7	
			WhileLoop		2.50		52.1	
		$f_{HCLK} = f_{HSI48/HSIDIV}$ = 12 MHz (HSIDIV = 4)	Reduced code(3)	Flash memory	1.45		120.8	
			Coremark		1.40		116.7	
			Dhrystone		1.40		116.7	
			Fibonacci		1.15		95.8	
			WhileLoop		1.00		83.3	
			Reduced code(3)	SRAM	1.30		108.3	
			Coremark		1.25		104.2	
			Dhrystone		1.25		104.2	
			Fibonacci		1.30		108.3	
			WhileLoop		1.10		91.7	
		$f_{HCLK} = f_{HSI48/HSIDIV}$ = 3 MHz (HSIDIV = 16)	Reduced code(3)	Flash memory	0.855	µA	285.0	µA/MHz
			Coremark		0.835		278.3	
			Dhrystone		0.835		278.3	
			Fibonacci		0.780		260.0	
			WhileLoop		0.745		248.3	
			Reduced code(3)	SRAM	0.810		270.0	
			Coremark		0.800		266.7	
			Dhrystone		0.800		266.7	
			Fibonacci		0.810		270.0	
			WhileLoop		0.770		256.7	

1. V_{DD} = 3.0 V, all peripherals disabled
2. Prefetch and cache enabled when fetching from flash
3. Reduced code used for characterization results provided in *Table 28*.