Table 30. Typical current consumption in Run depending on code executed (continued)

Symbol	Parameter	Conditions			Typ	Unit	Typ	Unit
		General[1]	Code	Fetch from[2]	25 °C		25 °C	
$I_{DD(Run)}$	Supply current in Run mode	$f_{HCLK} = f_{HSI48/HSIDIV}$ = 48 MHz (HSIDIV = 1)	Reduced code	Flash memory	4.25	mA	88.5	µA/MHz
			Coremark		3.90		81.3	
			Dhrystone		4.00		83.3	
			Fibonacci		3.20		66.7	
			WhileLoop		2.15		44.8	
			Reduced code	SRAM	3.35		69.8	
			Coremark		3.20		66.7	
			Dhrystone		3.20		66.7	
			Fibonacci		3.40		70.8	
			WhileLoop		2.50		52.1	
		$f_{HCLK} = f_{HSI48/HSIDIV}$ = 12 MHz (HSIDIV = 4)	Reduced code	Flash memory	1.50		125.0	
			Coremark		1.40		116.7	
			Dhrystone		1.40		116.7	
			Fibonacci		1.15		95.8	
			WhileLoop		0.89		73.8	
			Reduced code	SRAM	1.20		100.0	
			Coremark		1.15		95.8	
			Dhrystone		1.15		95.8	
			Fibonacci		1.20		100.0	
			WhileLoop		0.99		82.1	
		$f_{HCLK} = f_{HSI48/HSIDIV}$ = 3 MHz (HSIDIV = 16)	Reduced code	Flash memory	0.735		245.0	
			Coremark		0.710		236.7	
			Dhrystone		0.710		236.7	
			Fibonacci		0.650		216.7	
			WhileLoop		0.585		195.0	
			Reduced code	SRAM	0.660		220.0	
			Coremark		0.650		216.7	
			Dhrystone		0.650		216.7	
			Fibonacci		0.665		221.7	
			WhileLoop		0.610		203.3	