Table 30. Typical current consumption in Run depending on code executed (continued)

Symbol	Parameter	Conditions			Typ	Unit	Typ	Unit
		General[1]	Code	Fetch from[2]	25 °C		25 °C	
$I_{DD(Run)}$	Supply current in Run mode	$f_{HCLK} = f_{HSI48/HSIDIV}$ = 48 MHz (HSIDIV = 1)	Reduced code[3]	Flash memory	3.80	mA	79.2	µA/MHz
			Coremark		3.50		72.9	
			Dhrystone		3.55		74.0	
			Fibonacci		2.70		56.3	
			WhileLoop		1.95		40.6	
			Reduced code[3]	SRAM	3.15		65.6	
			Coremark		2.95		61.5	
			Dhrystone		2.95		61.5	
			Fibonacci		3.15		65.6	
			WhileLoop		2.40		50.0	
		$f_{HCLK} = f_{HSI48/HSIDIV}$ = 12 MHz (HSIDIV = 4)	Reduced code[3]	Flash memory	1.35		112.5	
			Coremark		1.25		104.2	
			Dhrystone		1.25		104.2	
			Fibonacci		1.00		83.3	
			WhileLoop		0.83		69.2	
			Reduced code[3]	SRAM	1.15		95.8	
			Coremark		1.10		91.7	
			Dhrystone		1.05		87.5	
			Fibonacci		1.15		95.8	
			WhileLoop		0.95		78.8	
		$f_{HCLK} = f_{HSI48/HSIDIV}$ = 3 MHz (HSIDIV = 16)	Reduced code[3]	Flash memory	0.675		225.0	µA/MHz
			Coremark		0.650		216.7	
			Dhrystone		0.650		216.7	
			Fibonacci		0.590		196.7	
			WhileLoop		0.550		183.3	
			Reduced code[3]	SRAM	0.625		208.3	
			Coremark		0.610		203.3	
			Dhrystone		0.610		203.3	
			Fibonacci		0.625		208.3	
			WhileLoop		0.580		193.3	

1. V_{DD} = 3.0 V, all peripherals disabled
2. Prefetch and cache enabled when fetching from flash
3. Reduced code used for characterization results provided in *Table 28*.