

Table 30. Typical current consumption in Run depending on code executed (continued)

Symbol	Parameter	Conditions			Typ	Unit	Typ	Unit
		General ⁽¹⁾	Code	Fetch from ⁽²⁾	25 °C		25 °C	
$I_{DD(Run)}$	Supply current in Run mode	$f_{HCLK} = f_{HSI48}/HSIDIV = 48 \text{ MHz}$ (HSIDIV = 1)	Reduced code	Flash memory	4.15	mA	86.5	$\mu\text{A/MHz}$
			Coremark		3.80		79.2	
			Dhrystone		3.85		80.2	
			Fibonacci		3.15		65.6	
			WhileLoop		2.15		44.8	
			Reduced code	SRAM	3.40		70.8	
			Coremark		3.15		65.6	
			Dhrystone		3.15		65.6	
			Fibonacci		3.30		68.8	
			WhileLoop		2.55		53.1	
		$f_{HCLK} = f_{HSI48}/HSIDIV = 12 \text{ MHz}$ (HSIDIV = 4)	Reduced code	Flash memory	1.45		120.8	
			Coremark		1.35		112.5	
			Dhrystone		1.35		112.5	
			Fibonacci		1.10		91.7	
			WhileLoop		0.88		73.3	
			Reduced code	SRAM	1.20		100.0	
			Coremark		1.15		95.8	
			Dhrystone		1.15		95.8	
			Fibonacci		1.20		100.0	
			WhileLoop		0.98		81.7	
		$f_{HCLK} = f_{HSI48}/HSIDIV = 3 \text{ MHz}$ (HSIDIV = 16)	Reduced code	Flash memory	0.705		235.0	
			Coremark		0.680		226.7	
			Dhrystone		0.680		226.7	
			Fibonacci		0.625		208.3	
			WhileLoop		0.565		188.3	
			Reduced code	SRAM	0.645		215.0	
			Coremark		0.630		210.0	
			Dhrystone		0.630		210.0	
			Fibonacci		0.640		213.3	
			WhileLoop		0.590		196.7	

1. $V_{DD} = 3.0 \text{ V}$, all peripherals disabled

2. Prefetch and cache enabled when fetching from flash