

4.3 Alternate functions

Table 12. Alternate functions

Port		AF0	AF1	AF2	AF3	AF4	AF5	AF6	AF7	AF8	AF9	AF10	AF11	AF12	AF13	AF14	AF15
		SYS	LPTIM1/ TIM1/2	I3C1/ TIM1/8/12/15	I3C1/LPTIM1/ LPUART1/ TIM8	I2C1/I3C1/ LPTIM1/SPI1/ I2S1/TIM15/ USART1/2	I3C1/LPTIM1/ SPI1/I2S1/ SPI2/ I2S2/SYS	FDCAN2/ SPI1/ I2S1/SPI2/ I2S2/UART4	SPI2/I2S2/ USART1/2	I2C1/ LPUART1/ UART4/5	FDCAN1/2/ I2C1/ SPI2/I2S2	CRS	USART1	-	TIM8/USB_	COMP1/2/ TIM2/UART5	SYS
Port A	PA0	-	TIM2_CH1	-	TIM8_ETR	TIM15_BKIN	SPI2_RDY	SPI1_RDY	USART2_CTS / USART2_NSS	UART4_TX	SPI2_NSS/ I2S2_WS	-	-	-	-	TIM2_ETR	EVENTOUT
	PA1	-	TIM2_CH2	-	TIM8_BKIN	TIM15_CH1N	LPTIM1_IN1	-	USART2_RTS	UART4_RX	-	-	-	-	-	-	EVENTOUT
	PA2	-	TIM2_CH3	-	LPUART1_RX	TIM15_CH1	LPTIM1_IN2	-	USART2_TX	-	-	-	-	-	-	COMP2_OUT	EVENTOUT
	PA3	-	TIM2_CH4	-	LPUART1_TX	TIM15_CH2	SPI2_NSS/ I2S2_WS	SPI2_MOSI/ I2S2_SDO	USART2_RX	-	-	-	-	-	-	COMP1_OUT	EVENTOUT
	PA4	-	TIM1_BKIN2	-	-	SPI1_MOSI/ I2S1_SDO	SPI1_NSS/ I2S1_WS	SPI2_NSS/ I2S2_WS	USART2_CK	-	-	-	-	-	-	-	EVENTOUT
	PA5	-	TIM2_CH1	TIM1_CH3	TIM8_CH1N	-	SPI1_SCK/ I2S1_CK	SPI2_SCK/ I2S2_CK	USART1_CTS / USART1_NSS	-	-	-	-	-	-	TIM2_ETR	EVENTOUT
	PA6	-	TIM1_BKIN	-	TIM8_BKIN	-	SPI1_MISO/ I2S1_SDI	-	USART1_TX	LPUART1_RT S	-	-	-	-	-	-	EVENTOUT
	PA7	-	TIM1_CH1N	-	TIM8_CH1N	TIM15_CH1	SPI1_MOSI/ I2S1_SDO	SPI2_MISO/ I2S2_SDI	USART1_RX	LPUART1_CT S	-	-	-	-	-	COMP2_OUT	EVENTOUT
	PA8	MCO1	TIM1_CH1	I3C1_SDA	TIM8_BKIN2	TIM15_CH2	SPI1_RDY	SPI2_MOSI/ I2S2_SDO	USART1_CK	-	I2C1_SCL	-	-	-	USB_SOF	TIM2_CH4	EVENTOUT
	PA9	MCO2	TIM1_CH2	I3C1_SCL	LPUART1_TX	TIM15_CH1N	SPI2_SCK/ I2S2_CK	-	USART1_TX	-	I2C1_SMBA	-	-	-	TIM8_CH2N	-	EVENTOUT
	PA10	-	TIM1_CH3	-	LPUART1_RX	-	-	-	USART1_RX	-	FDCAN2_TX	-	-	-	-	-	EVENTOUT
	PA11	-	TIM1_CH4	-	LPUART1_CT S	USART2_TX	SPI2_NSS/ I2S2_WS	UART4_RX	USART1_CTS / USART1_NSS	I2C1_SCL	FDCAN1_RX	-	-	-	-	-	EVENTOUT
	PA12	-	TIM1_ETR	-	LPUART1_RT S	USART2_RX	SPI2_SCK/ I2S2_CK	UART4_TX	USART1_RTS	I2C1_SDA	FDCAN1_TX	-	-	-	-	COMP2_OUT	EVENTOUT
	PA13	JTMS/SWDIO	-	-	-	-	-	-	-	-	-	-	-	-	-	COMP1_OUT	EVENTOUT
	PA14	JTCK/SWCLK	-	-	-	-	-	-	-	-	-	-	-	-	-	-	EVENTOUT
	PA15	JTDI	TIM2_CH1	TIM1_CH2N	LPTIM1_ETR	I2C1_SMBA	SPI1_NSS/ I2S1_WS	SPI2_NSS/ I2S2_WS	USART2_CK	UART4_RTS	-	-	USART1_TX	-	TIM8_CH4N	TIM2_ETR	EVENTOUT
Port B	PB0	-	TIM1_CH2N	-	TIM8_CH2N	-	SPI1_MISO/ I2S1_SDI	-	USART2_TX	UART4_CTS	-	-	-	-	-	-	EVENTOUT
	PB1	-	TIM1_CH3N	-	TIM8_CH3N	-	SPI2_NSS/ I2S2_WS	-	USART2_RX	-	-	-	-	-	-	COMP1_OUT	EVENTOUT
	PB2	RTC_OUT2	-	-	TIM8_CH4N	SPI1_RDY	LPTIM1_CH1	SPI2_SCK/ I2S2_CK	SPI2_MOSI/ I2S2_SDO	-	-	-	-	-	-	-	EVENTOUT
	PB3	JTDO/ TRACESWO	TIM2_CH2	-	I3C1_SDA	I2C1_SDA	SPI1_SCK/ I2S1_CK	FDCAN2_RX	USART1_CK	LPUART1_TX	I2C1_SCL	CRS_SYNC	USART1_TX	-	TIM8_CH1	UART5_RTS	EVENTOUT
	PB4	NJTRST	-	TIM15_CH1	I3C1_SCL	LPTIM1_CH2	SPI1_MISO/ I2S1_SDI	FDCAN2_TX	SPI2_NSS/ I2S2_WS	LPUART1_CT S	I2C1_SDA	-	USART1_RX	-	TIM8_CH2	UART5_CTS	EVENTOUT
	PB5	-	-	-	I3C1_SDA	I2C1_SMBA	SPI1_MOSI/ I2S1_SDO	-	-	LPUART1_RT S	FDCAN2_RX	-	USART1_CK	-	TIM8_CH3	UART5_RX	EVENTOUT
	PB6	-	-	-	I3C1_SCL	I2C1_SCL	-	SPI1_MISO/ I2S1_SDI	USART1_TX	LPUART1_TX	FDCAN2_TX	-	USART1_CTS / USART1_NSS	-	TIM8_CH4	UART5_TX	EVENTOUT

