

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
CMRR	Common mode rejection ratio	-	-	70	-	dB
PSRR	Power supply rejection ratio	$C_{LOAD} \leq 50\text{pf}$ / $R_{LOAD} \geq 4\text{ k}\Omega^{(1)}$ at 1 kHz, $V_{com}=V_{DDA}/2$	-	70	-	dB
GBW	Gain bandwidth Product	$200\text{mV} \leq \text{Output dynamic range} \leq V_{DDA} - 200\text{mV}$	3	20		MHz
SR	Slew rate (from 10% and 90% of output voltage)	Normal mode	4	7.5	-	V/ μs
		High-speed mode	35	65	-	
AO	Open loop gain	$200\text{mV} \leq \text{Output dynamic range} \leq V_{DDA} - 200\text{mV}$	58	100		dB
ϕ_m	Phase margin	-	-	60	-	°
GM	Gain margin	-	-	11	-	dB
V_{OHSAT}	High saturation voltage	$I_{load}=\text{max}$ or $R_{LOAD}=\text{min}^{(1)}$, Input at V_{DDA}	$V_{DDA} - 100\text{mV}$	-	-	mV
V_{OLSAT}	Low saturation voltage	$I_{load}=\text{max}$ or $R_{LOAD}=\text{min}^{(1)}$, Input at 0 V	-	-	100	
t_{WAKEUP}	Wake up time from OFF state	Normal mode $C_{LOAD} \leq 50\text{pf}$, $R_{LOAD} \geq 4\text{ k}\Omega^{(1)}$, follower configuration	-	1.1	2.0	μs
		High speed $C_{LOAD} \leq 50\text{pf}$, $R_{LOAD} \geq 4\text{ k}\Omega^{(1)}$, follower configuration	-	1.1	2.0	
PGA gain	Non inverting gain error value	PGA gain = 2	-1		1	%
		PGA Gain = 4	-1		1	
		PGA Gain = 8	-1		1	
		PGA Gain = 16	-1		1	
	Inverting gain error value	PGA Gain = 2	-1		1.4	
		PGA Gain = 4	-1		1	
		PGA Gain = 8	-1		1	
		PGA Gain = 16	-1		1	
Rnetwork	R2/R1 internal resistance values in non-inverting PGA mode ⁽²⁾	PGA Gain = 2	-	10/10	-	k Ω / k Ω
		PGA Gain = 4	-	30/10	-	
		PGA Gain = 8	-	70/10	-	
		PGA Gain = 16	-	150/10	-	
	R2/R1 internal resistance values in inverting PGA mode ⁽²⁾	PGA Gain = -1	-	10/10	-	
		PGA Gain = -3	-	30/10	-	
		PGA Gain = -7	-	70/10	-	
		PGA Gain = -15	-	150/10	-	
Delta R	Resistance variation (R1 or R2)	-	-15	-	15	%
PGA BW	PGA bandwidth for different non inverting gain	Gain = 2	-	GBW/2	-	MHz
		Gain = 4	-	GBW/4	-	
		Gain = 8	-	GBW/8	-	
		Gain = 16	-	GBW/16	-	
	PGA bandwidth for different inverting gain	Gain = -1	-	GBW/2	-	