

Port	AF0		AF1	AF2	AF3	AF4	AF5	AF6	AF7	AF8	AF9	AF10	AF11	AF12	AF13	AF14	AF15
	SYS	LPTIM1/ TIM1/2/17	I3C1/ TIM1/3/4/5/8/12/15	I3C1/LPTIM1/ LPUART1/ TIM1/5/8	I2C1/2/I3C1/ LPTIM1/ SPI1/I2S1/ SPI2/I2S2/ SPI3/I2S3/ TIM15/ USART1/2	I2C1/2/I3C1/ LPTIM1/ SPI1/I2S1/ SPI2/I2S2/ SPI3/I2S3/ TIM15/ USART1/2	I3C1/ LPTIM1/ SPI1/I2S1/ SPI2/I2S2/ SPI3/I2S3/ TIM15/ USART1/2	SPI1/I2S1/ SPI2/I2S2/ SPI3/I2S3/ UART4	SPI2/I2S2/ SPI3/I2S3/ UART7/ USART1/2/3/6/ XSP1	I2C2/ LPUART1/ TIM5/UART4/5	FDCAN1/2/ I2C1/2/SPI2/ I2S2/XSP1	CRS/ETH1_TIM16/ UART7	USART1/3/ XSP1	ETH1_	ETH1_TIM8/ USB_	COMP/TIM2/ UART5	SYS
Port B	PB8	-	TIM17_CH1	TIM4_CH3	I3C1_SCL	I2C1_SCL	-	SPI3_NSS/ I2S3_WS	-	UART4_RX	FDCAN1_RX	ETH1_MII_TXD3	XSP11_NCS1	-	-	-	EVENTOUT
	PB9	-		TIM4_CH4	I3C1_SDA	I2C1_SDA	SPI2_NSS/ I2S2_WS	SPI3_SCK/ I2S3_CK	-	UART4_TX	FDCAN1_TX	-	-	-	-	-	EVENTOUT
	PB10	-	TIM2_CH3	TIM8_CH1	LPTIM1_IN1	I2C2_SCL	SPI2_SCK/ I2S2_CK	-	USART3_TX	-	XSP11_NCS1	ETH1_MII_RX_ER	-	-	-	-	EVENTOUT
	PB12	-	TIM1_BKIN	TIM8_CH3		I2C2_SDA	SPI2_NSS/ I2S2_WS	-	USART3_CK	-	FDCAN2_RX	ETH1_MII_TXD0/ ETH1_RMII_TXD0	XSP11_NCLK	-	-	UART5_RX	EVENTOUT
	PB13	-	TIM1_CH1N	TIM8_CH2	LPTIM1_CH1	I2C2_SMBA	SPI2_SCK/ I2S2_CK	-	USART3_CTS/ USART3_NSS	LPUART1_RX	FDCAN2_TX	ETH1_MII_TX_EN/ ETH1_RMII_TX_EN	XSP11_DQS	-	-	UART5_TX	EVENTOUT
	PB14	-	TIM1_CH2N	TIM12_CH1	TIM8_CH2N	USART1_TX	SPI2_MISO/ I2S2_SDI	-	USART3_RTS	UART4_RTS	-	-	-	-	-		EVENTOUT
	PB15	RTC_REFIN	TIM1_CH3N	TIM12_CH2	TIM8_CH3N	USART1_RX	SPI2_MOS/ I2S2_SDO	SPI1_MOS/ I2S1_SDO	SPI3_MOS/ I2S3_SDO	UART4_CTS	XSP11_IO0	ETH1_MII_TXD1/ ETH1_RMII_TXD1	XSP11_CLK	-	-	UART5_RX	EVENTOUT
Port C	PC0	-	-	-	-	-	-	-	SPI2_RDY	-	-	TIM16_BKIN	XSP11_IO7	-	-	-	EVENTOUT
	PC1	TRACED0	-	-	-	-	SPI2_MOS/ I2S2_SDO	-	-	-	XSP11_IO4	ETH1_MDC	XSP11_IO6	-	-	-	EVENTOUT
	PC2	PWR_CSLEEP	TIM17_CH1	TIM4_CH4	-	-	SPI2_MISO/ I2S2_SDI	-	-	-	XSP11_IO2	ETH1_MII_TXD2	XSP11_IO5	-	-	-	EVENTOUT
	PC3	PWR_CSTOP	-	-	LPUART1_TX	-	SPI2_MOS/ I2S2_SDO	-	XSP11_IO6	-	XSP11_IO0	ETH1_MII_TX_CLK	XSP11_IO4	-	-	-	EVENTOUT
	PC4	-	TIM2_CH4	-	TIM8_BKIN	-	I2S1_MCK	-	USART3_RX	-	-	TIM16_CH1	-	ETH1_MII_RXD0/ ETH1_RMII_RXD0	-	-	EVENTOUT
	PC5	-	TIM1_CH4N	-	TIM8_BKIN2	-	-	-	-	-	-	TIM16_CH1N	XSP11_DQS	-	ETH1_MII_RXD1/ ETH1_RMII_RXD1	COMP1_OUT	EVENTOUT
	PC6	-	-	TIM3_CH1	TIM8_CH1	-	I2S2_MCK	-	USART6_TX	-	XSP11_IO5	-	XSP11_IO3	-	-	-	EVENTOUT
	PC7	-	-	TIM3_CH2	TIM8_CH2	-	-	I2S3_MCK	USART6_RX	-	XSP11_IO6	-	XSP11_IO4	-	-	-	EVENTOUT
	PC8	TRACED1	-	TIM3_CH3	TIM8_CH3	-	-	-	USART6_CK	UART5_RTS	-	-	-	-	-	-	EVENTOUT
	PC9	MCO2	-	TIM3_CH4	TIM8_CH4	-	AUDIOCLK	-	XSP11_IO0	UART5_CTS	I2C1_SDA	-	XSP11_IO5	-	-	-	EVENTOUT
	PC10	-	-	-	TIM8_CH1N	I3C1_SCL	-	SPI3_SCK/ I2S3_CK	USART3_TX	UART4_TX	XSP11_IO1	ETH1_MII_TXD0/ ETH1_RMII_TXD0	-	-	-	-	EVENTOUT
	PC11	-	-	-	TIM8_CH2N	I3C1_SDA	-	SPI3_MISO/ I2S3_SDI	USART3_RX	UART4_RX	XSP11_NCS1	-	-	-	-	-	EVENTOUT
	PC12	TRACED3	-	TIM15_CH1	TIM8_CH3N	-	-	SPI3_MOS/ I2S3_SDO	USART3_CK	UART5_TX	-	ETH1_PPS_OUT	-	-	-	-	EVENTOUT
	PC13	-	-	-	-	-	-	-	-	-	FDCAN1_TX	-	-	-	-	-	EVENTOUT
	PC14	-	-	TIM12_CH1	-	-	-	-	-	-	FDCAN1_RX	-	-	-	-	-	EVENTOUT
	PC15	-	-	TIM12_CH2	-	-	-	-	-	-	-	-	-	-	-	-	EVENTOUT
Port D	PD0	-	-	-	TIM8_CH4N	-	-	-	-	UART4_RX	FDCAN1_RX	-	XSP11_NCS2	-	-	-	EVENTOUT
	PD1	-	-	-	-	-	-	-	-	UART4_TX	FDCAN1_TX	ETH1_MII_RX_DV/ ETH1_RMII_CRS_DV	-	-	-	-	EVENTOUT
	PD2	TRACED2	-	TIM3_ETR	-	TIM15_BKIN	-	-	-	UART5_RX	XSP11_NCS2	-	-	-	-	-	EVENTOUT
	PD3	-	-	-	-	-	SPI2_SCK/ I2S2_CK	-	USART2_CTS/ USART2_NSS	-	-	-	-	-	-	-	EVENTOUT
	PD4	-	-	-	-	-	-	-	USART2_RTS	-	-	ETH1_CLK	XSP11_IO4	-	-	-	EVENTOUT
	PD5	-	TIM1_CH4N	-	-	-	SPI2_RDY	-	USART2_TX	-	FDCAN1_TX	ETH1_MII_CRS	XSP11_IO5	-	-	-	EVENTOUT

