III. Methodology

This section describes the design from the overall architecture down to the individual mechanisms. The whole design follows one rule: the robot must stop whenever any part of the system above the motors fails, and nothing added for the operator or the victim may weaken that guarantee. Sections III-B to III-E set out the system architecture, the network, the hardware and the software that runs on it. Sections III-F to III-H then follow the stop guarantee upward through the tiers: the firmware enforces it (Section III-F), the control server feeds it safely (Section III-G), and supervision restores service after a failure without bypassing it (Section III-H). Section III-I decides which operator holds control, and Section III-J builds victim interaction on that decision while keeping it apart from the stop path. Section III-K adds localisation for the operator.

A. Design Rationale and Relation to Research Questions

This chapter describes the system design: the structure, mechanisms and design choices that realise the stop guarantee stated above. The procedures and metrics that validate the design belong to Section 4 (Experimental Setup) and the measurements to Section 5 (Results); this chapter does not repeat them, but cross-references the relevant Section 4 and Section 5 subsection, and the raw data under `tools/eval/`, at each point where a design choice has an empirical test. Each design pillar below is traced to the Section 1.3 research question that motivates it and to the Section 5 subsection that evaluates it **[VERIFY: confirm the RQ labels below against the research questions defined in Section 1.3]**.

- Firmware dead-man and ramp-stop (Section III-F2) → RQ1 → Section 5.1
- P1 single-writer serial link and session resume (Section III-G) → RQ2 → Sections 5.1, 5.3
- P3 process isolation and supervision (Section III-H) → RQ3 → Section 5.4
- WebRTC two-way victim path (Section III-J) → RQ4 → Sections 5.2, 5.5
- GPS and offline map (Section III-K) → RQ4 → Section 5.6

B. System Architecture

The architecture applies the design rule by separating the system into tiers that can fail on their own, in the layered style of prior teleoperated search-and-rescue systems [1], [2]. The system has four tiers: an Arduino UNO for real-time control, a Raspberry Pi 4, a local Wi-Fi network, and a browser dashboard (Figure 1). The Pi runs three separate Python processes: P1 (control server) links the dashboard to the Arduino, checks every drive command and collects telemetry and GPS; P2 (media server) streams the robot's camera and microphone to the operator and carries the operator's voice, video and text to the robot's screen; and P3 (watchdog) starts P1 and P2 and restarts either one if it crashes or stops responding. Control and media use separate transports that end in separate processes, so a media failure leaves driving and stopping intact.

Figure 2 follows one drive command through every tier and the telemetry that returns. A held key sends one motion command; while it is held, heartbeats keep the dead-man armed, and releasing the key sends a stop.

P2 and P3 take no part in this loop: media never carries a drive or stop command, and the watchdog only supervises the processes from outside, so a failure in either cannot delay a stop.

C. Network Configuration

The two transports in Figure 1 run over one local network, which also makes the robot independent of the internet: no part of the deployment evaluated here reaches outside the Wi-Fi cell. The Pi and the operator laptop join the existing Wi-Fi network, an 802.11n cell on the 2.4 GHz band on channel 10 (2457 MHz) with a 20 MHz operating width. Both hold addresses in the same /24 subnet, so traffic between them is neither routed nor address-translated, which is what lets the media path of Section III-J2 rely on host candidates alone. The Pi uses its on-board radio (Figure 5) and takes its address from the router by DHCP: in the deployment measured here it held 192.168.0.105 in 192.168.0.0/24 with the router at 192.168.0.1, on a lease rather than a reservation, so the operator reads the current address off the Pi (`ip addr show wlan0`) before opening the dashboard. The project supplies no network configuration of its own, neither an access point nor a DHCP reservation nor a static address, so the subnet is whatever the router hands out. The router stays with the operator at the staging point, so the robot works within one radio cell, and extending that reach with a repeater or a second radio is outside the scope of this work (Section 6.3). Table 1 lists the services on the Pi and Table Table 1a the load and the timing the network has to carry.

Control and media use different transports for different reasons. Commands and telemetry run over TCP, because ordered delivery together with the sequence check of Section III-F1 keeps a stale command from overtaking a newer one, and the cost of a retransmission is bounded: a command that does not arrive within the dead-man window stops the robot instead of leaving it to run on a stale one (Section III-F2). Media runs over UDP, where a lost packet costs picture or voice quality but never delays a command. The dead-man window therefore sets the only hard requirement the network must meet, and the budgets in Table Table 1a follow from it.

Four intervals bear on the dead-man window, and none of them is a count of the others. The dashboard sends a heartbeat every 500 ms for as long as it holds the controller role, whether or not the robot is being driven; a drive command is sent once when a key or button goes down and a stop once when it is released, with keyboard auto-repeat suppressed, so a sustained drive is carried by the heartbeat rather than by repeated commands. The firmware re-arms its dead-man timer on any arming command it accepts, heartbeats included, and stops the motors once 2000 ms pass with none: an absolute window measured from the last accepted command, not a threshold of missed heartbeats. Independently of that window the firmware emits a telemetry frame every 500 ms and a compact heartbeat line every 1000 ms, but both are outbound reports and neither re-arms the timer. A 2000 ms window spans

Fig. 1: Overall system architecture.

TABLE 1: Network services on the Pi.

Port	Process	Protocol	Carries
TCP 8080	P1	HTTP and WebSocket	Dashboard files, control and telemetry, session settings, GPS track, offline map tiles, ICE configuration (Section III-J2), health
TCP 8443	P2	HTTP (no TLS)	WebRTC offer and answer, Robot Screen page, health
UDP, negotiated by ICE	P2	WebRTC	Audio, video and data channel
Localhost only	P1, P2	HTTP	Controller address query; Robot Screen connection

Table 1a. Network load and timing requirements.

Quantity	Value	Set by
Video, robot to operator	640x480 at 10 fps, 500 kbps target	Section III-J1, Table 12
Audio, each direction	Opus 32 kbps, 60 ms packets	Table 14
Telemetry snapshots	5 per second from P1, one JSON object each; the firmware frames behind them arrive every 500 ms	Section III-G2
Commands and heartbeats	Heartbeat every 500 ms from the controller; one drive command per press and per release; servo commands are not rate limited	Sections III-F1 and III-G
Steady-state load per operator	Under 1 Mbit/s	Sum of the rows above
Hard delivery deadline	2000 ms since the last arming command	Dead-man, Section III-F2
Operator-side link timeout	3000 ms without telemetry gives mission state STOP, counted in 500 ms steps	Table 10
Socket keep-alive	Ping every 20 s, 20 s timeout	P1 WebSocket server
Reconnect back-off	1 s, doubling, capped at 30 s	Section III-H1

four heartbeat periods, so an occasional lost heartbeat does not stop the robot.

The load stays well inside the capacity of an ordinary indoor Wi-Fi link: at the staging point the link negotiated 58.5 Mbit/s receive and 72.2 Mbit/s transmit at a signal level of about -47 dBm, more than fifty times the steady-state demand, so the network is sized by latency and loss rather than by throughput, and Section 5.3 reports how both degrade with distance; the dashboard bundle and the offline map tiles are one-off transfers at the start of a session. The keep-alive in Table Table 1a reclaims a silently dead socket only after up to 40 s, so liveness for safety is not enforced at this layer but by the dead-man at 2000 ms and by the dashboard's 3000 ms telemetry timeout; the keep-alive only frees the socket.

Fig. 2: End-to-end control loop: command down, telemetry up.

Browsers allow microphone and camera capture only in a secure context, and neither port carries TLS (Table 1), so the operator's browser has to be told to treat the Pi's origin as trusted, through the insecure-origin exception recorded in the operator manual. Push-to-talk and the operator camera depend on that manual step, which is a deployment workaround rather than a configured transport security measure (Section 6.3); images and text work without it.

D. Hardware Platform

The hardware is chosen so that the lowest tier can stop the robot by itself: the Arduino drives the motor drivers directly and can disable them with one output. Table 2 lists the components, and Figure 3 shows how they connect and how power is distributed. The motor supply and the Pi supply are separate, so motor current surges cannot reset the Pi.

The Arduino pins used by the firmware are shown in Figure 4 and detailed in Table 3. Each BTS7960 drives forward on one PWM input and reverse on the other, with only one active at a time; both drivers share one enable line, so one output disables all propulsion.

The Pi ports and GPIO header pins used by the project are shown in Figure 5 and listed in Table 4.

The GPS uses the Pi's primary UART with the serial login console disabled.

E. Software Architecture

The software is organised around the same tiers as the hardware in Section III-D. This section gives its structure; Sections III-F to III-K describe each part in detail.

The software forms three layers, each written in the language that suits its hardware, over a shared module that the three Pi processes have in common (Table 5). The three layers share no code and talk only through three defined interfaces: the serial command protocol between firmware and P1, the control WebSocket between the dashboard and P1, and WebRTC between the dashboard and P2. Each layer can therefore be built, tested and replaced on its own.

On the Pi, systemd starts only the watchdog, which spawns the control and media servers as child processes (Figure 6). P1 holds every interface that can move the robot; P2 holds every media device; the Robot Screen kiosk runs in the desktop session.

The dashboard is a single-page React application served by P1 (Figure 7). Its interface components hold no network code; they read state from, and send actions through, a small set of hooks. Each hook owns one connection to one server, so a lost media connection leaves the drive controls and telemetry working.

Each layer can also run without its hardware. A development mode (the `MOCK_HARDWARE` setting) replaces the serial link with an in-process Arduino emulator that mirrors the firmware's framing, command validation, dead-man timer and telemetry cadence; replaces the GPS with a synthetic track; and replaces the camera and microphone with a synthetic video pattern and silence. The full control, telemetry, supervision and media stack therefore runs on a development machine with no robot attached, which is how the software is tested away from the hardware.

F. Real-Time Firmware and Fail-Safe Control

The firmware holds the authority to stop the robot, so it must stop the motors without help from the Pi or the network. The firmware defines five operating modes (Figure 8): BOOT, READY, ACTIVE, PANIC, and a reserved latched operator-stop mode, ESTOP. Motion is accepted only in READY and ACTIVE with no fault set; telemetry reports READY as 1, ACTIVE as 2 and all other modes (BOOT, PANIC and ESTOP) as 3.

1) Task Scheduling and Command Validation: A cooperative scheduler, rather than a pre-emptive RTOS on the ATmega328P [3], runs the periodic tasks in Table 6 from the main loop, with timing based on unsigned millisecond differences so that counter rollover does not break it. The command parser is polled on every loop pass and checks each command in four stages before it acts (Figure 9).

The telemetry period (`TELEMETRY_PERIOD_MS` = 500 ms in `arduino/config.h`) and the ramp step (`MOTOR_RAMP_STEP` = 15) are the two firmware constants that bound the empirical stop-time distribution reported in Section 5.1.

The Pi control server applies a tighter safety cap before sending: speed is clamped to 0-180 (keeping the 14.8 V battery under the motor's $\sim$12 V rating) and angles to 0-180, and motion and servo commands whose sequence number is not higher than the last one from that client are rejected.

2) Dead-Man Timer and Stop-Time Guarantee: Every command that passes stages 1 to 3 re-arms the dead-man timer, including heartbeats; this dead-man (watchdog) pattern, in which loss of a periodic command forces the actuators to a safe state, is a standard fail-safe for teleoperated mobile robots [2]. When the timer expires, the supervisor sets the PWM outputs to zero and pulls the shared enable line low at once, without

TABLE 2: Hardware components.

Component	Part	Function
Edge computer	Raspberry Pi 4 Model B, 4 GB	Runs P1, P2, P3 and the Robot Screen
Microcontroller	Arduino UNO (ATmega328P, 16 MHz)	Real-time control and sensing
Motor drivers	2 x BTS7960	One driver per side
Drive motors	4 x 25GA-370 geared DC motor with encoder, 12 V, 60 RPM no-load, 65 mm wheels	Differential (skid) steering, left and right pairs
Camera servos	2 x TowerPro SG90 micro servo, about 1.8 kgf-cm stall torque at 4.8 V, 180 deg	Pan and tilt, 0-180 deg, home at 90 deg
Range sensor	HC-SR04	Forward range, 0-400 cm
Temperature and humidity	DHT11	degC and % RH
Gas sensor	MQ-136	Raw 10-bit value 0-1023, uncalibrated
GPS receiver	NEO-6M	Position, fix, satellite count
Camera and microphone	USB webcam with built-in microphone	640x480 video at 10 fps; 48 kHz audio
Robot display	7-inch HDMI display, 1024x600	Victim-facing Robot Screen
Speaker	Speaker	Operator voice to the victim
Battery	4S Li-ion pack, 14.8 V nominal, 16.8 V full, continuous discharge limited by the 4S 40 A BMS **[NEEDS SPEC: nominal capacity Ah]**	Motor and logic power
Battery management	4S 40 A BMS	Pack protection
Buck converters	2 x buck converter, 8 V and 5 V outputs	8 V to the Arduino barrel jack; 5 V to the servos
Pi supply	Remax 50000 mAh USB power bank	Separate supply for the Pi

Fig. 3: Hardware interconnection and power distribution. Thick lines carry power; thin lines carry signals, labelled with the interface and its direction. The Pi and the Arduino are the two hubs, and the separate motor and Pi supplies are grouped on the left.

ramping (Figure 10). The worst-case stop time after the last command is:

$$t_{stop} \leq T_{DM} + T_S + J \tag{1}$$

where $T_{DM} = 2000$ ms is the dead-man window, $T_S = 10$

Fig. 4: Arduino UNO pin diagram. Every line is drawn from the Arduino outwards to the device it serves, so an arrowhead marks the connection and not the signal direction. Direction is given in the label instead, read from the Arduino's side: "out" leaves the pin and "in" arrives at it, and a label with both names the outgoing pin first. Table 3 gives the full pin map.

TABLE 3: Arduino UNO pin map.

Pin	Mode	Signal	Notes
D0, D1	UART over USB	Serial link to the Pi	115200 baud, newline-terminated ASCII
D3	Output	Tilt servo pulse	ServoTimer2Plus library on Timer2, 0-180 deg
D4	Digital output	Enable for both BTS7960 drivers	Low at boot and on emergency stop
D5	PWM output	Left driver, forward	0-255
D6	PWM output	Left driver, reverse	0-255
D7	Digital output	HC-SR04 trigger	10 us pulse every 50 ms
D8	Digital input	HC-SR04 echo	25 ms timeout; distance = pulse width / 58
D9	PWM output	Right driver, forward	0-255; Timer1 left free for these pins
D10	PWM output	Right driver, reverse	0-255
D11	Output	Pan servo pulse	ServoTimer2Plus library on Timer2, 0-180 deg
D13	Digital output	On-board status LED	Toggles every 1000 ms
A2	Digital I/O, pull-up	DHT11 single-wire data	Read every 2000 ms, checksum verified
A3	Analog input	MQ-136 output	10-bit ADC; raw value reported in telemetry
Barrel jack	Power input	8 V from buck converter	–
5 V, GND	Power output	Supply for HC-SR04, DHT11 and MQ-136	Shared by the three sensors

ms is the supervisor period, and J is the longest single loop pass, set mainly by the 25 ms echo timeout and the 20 ms DHT11 start pulse.

The bound is validated empirically in Section 5.1 using the 240 fps video measurement (`tools/eval/record.py latency_video`) and the WebSocket probe (`tools/eval/wslatency.py`), with the quantisation caveat discussed in Section 4.2.

An ordinary stop command ramps the motors down instead:

$$t_{ramp} = \left\lceil \frac{u}{\Delta u} \right\rceil T_M \tag{2}$$

where u is the current PWM value, $\Delta u = 15$ is the ramp step and $T_M = 10$ ms is the motor service period; this gives 120 ms from the 180 cap and 170 ms from 255.

3) Redundant Stop Paths: Table 7 lists every path that stops the motors. The firmware's only automatic stop is the deadman; every other row is an operator action or a P1 action, and the firmware itself never stops the motors on a sensor reading.

Fig. 5: Raspberry Pi 4 port and GPIO diagram. Every line is drawn from the Pi outwards to the device it serves, so an arrowhead marks the connection and not the direction. Direction is given in the label instead, read from the Pi's side: "out" leaves the port or pin and "in" arrives at it. The thick lines carry power, and the Pi's own supply arrives on USB-C. Table 4 gives the full connection list.

TABLE 4: Raspberry Pi 4 connections.

Pi interface	Connected to	Use
USB-A	Arduino UNO	USB serial, 115200 baud
USB-A	USB webcam with microphone	Video capture and audio capture
Header pin 1 (3.3 V)	GPS VCC	GPS supply
Header pin 6 (GND)	GPS GND	Ground
Header pin 8 (GPIO 14, TXD)	GPS RX	UART, 9600 baud
Header pin 10 (GPIO 15, RXD)	GPS TX	UART, 9600 baud
Micro-HDMI 0	Robot display	Robot Screen
3.5 mm jack	Speaker	Default audio output
USB-C	USB power bank	Pi supply
On-board Wi-Fi	Wi-Fi router	Dashboard, control and media traffic

The MQ-136 gas sensor is advisory: its reading is published to the operator in telemetry and is not used to stop the motors.

G. P1 Control Server and Telemetry

The firmware stops the robot when commands cease, but it assumes that the commands it does receive come from one source and arrive in order. P1 provides that assumption and returns the robot's state to the operator. P1 owns the serial link, the GPS receiver and the control WebSocket.

1) Safe Startup and Single-Writer Serial Link: P1 takes an exclusive, non-blocking lock on a file in a memory-backed directory before it opens any hardware; the kernel releases the lock when the process exits for any reason. The serial port is then opened in exclusive mode, and one asynchronous lock serialises all writes. Figure 11 shows the start-up handshake.

2) Telemetry Pipeline and Session Resume: The firmware sends a frame every 500 ms; P1 broadcasts a snapshot of the latest valid frame every 200 ms on an absolute schedule, merged with GPS and link status (Figure 12). A frame is dropped if any field fails the checks in Table 8; there is no retransmission.

Because the P1 broadcast runs on an absolute sched-

TABLE 5: Software stack.

Layer	Runs on	Language	Main frameworks	Main modules
Firmware	Arduino UNO	C++	Arduino core, no RTOS	scheduler, `command_parser`, motors, servos, sensors, telemetry
Backend	Raspberry Pi 4	Python 3, asyncio	FastAPI and uvicorn (P1, P2), aiortc and PyAV (P2), aiohttp (P3)	`serial_bridge`, safety, `websocket_hub`, `gps_reader`, signaling, talkback, supervisor
Common	Raspberry Pi 4, inside P1, P2 and P3	Python 3	standard library only	protocol, config, access, `logging_setup`, `mock_hardware`
Frontend	Operator browser	TypeScript	React 19, Vite, Tailwind CSS, Leaflet with PMTiles	`useControlSocket`, `useWebrtcVideo`, `useTalkback`, DriveControl, EmergencyStop, MapPanel

Fig. 6: Raspberry Pi software architecture and process supervision.

TABLE 6: Firmware tasks.

Task	Period	Work
Motor service	10 ms	Ramp PWM toward target by 15 units per tick
Safety supervisor	10 ms	Dead-man check and fault recovery
Fast sensors	50 ms	HC-SR04 range (25 ms echo timeout)
Slow sensors	2000 ms	DHT11 and MQ-136
Telemetry	500 ms	One 8-field CSV line
Heartbeat	1000 ms	Mode line and status LED toggle

ule with period `TELEMETRY_PERIOD_MS` = 200 ms (`pi/common/protocol.py`), the control-plane latency probe in Section 4 jitters its send phase; a phase-locked sender produces a biased, deceptively tight distribution, as recorded in `tools/eval/README.md` and discussed in Section 6.4.

On reconnect, the dashboard sends the server timestamp of the last snapshot it received; P1 replies with every newer snapshot in the buffer and the size of any gap. The buffer depth and the gap are:

$$D = N{\cdot}T_b = 300{\times}200\ \text{ms} = 60\ \text{s}, \qquad g = \max(0,\ t_{oldest}{-}t_{last}) \tag{3}$$

where N is the buffer size, T_b the broadcast period, t_{oldest} the oldest buffered timestamp and t_{last} the client's last timestamp. The buffer is held in memory, so it does not survive a P1 restart.

Fig. 7: Operator dashboard software architecture.

TABLE 7: Stop paths.

Trigger	Origin	Action	Bound
Drive key or button released	Dashboard via P1	S, ramped stop	One network trip
Emergency stop button	Dashboard via P1	S, sent without the sequence check	One network trip
Controller connection closes	P1	S	On socket close
Another dashboard takes control	P1	S	On takeover
P1 start-up	P1	3 x S, 200 ms apart	Before any other command
P1 shutdown	P1	S	Before the port closes
Command flow stops	Firmware	PWM 0, drivers disabled	t_{stop} above

TABLE 8: Telemetry frame fields and accepted ranges (frame at most 80 characters).

Field	Unit	Accepted range
Temperature	degC	-40 to 125
Humidity	%	0 to 100
Gas	raw ADC	0 to 10000
Range	cm	0 to 500
Pan angle	deg	0 to 180
Tilt angle	deg	0 to 180
Firmware state	–	1 to 3
Uptime	ms	0 to $2^{32} - 1$

H. Fault Tolerance and Supervision

Sections III-F and III-G make each tier fail into a stop; this section describes how failures are detected and how the system returns to service. Fault tolerance is layered (Figure 13). Each layer acts on its own, and a failure that passes every layer above ends at the firmware, which stops the motors.

1) P3 Watchdog: Process Isolation and Supervision: P3 is the only systemd service (restart on failure after 5 s); it spawns P1 and P2 as separate processes with no shared memory and supervises each one with the state machine in Figure 14. The only link between P1 and P2 is a once-per-second localhost query from P2 for the controller's address.

2) Recovery Time Model and Graceful Degradation: The time from a failure to a working process is:

$$T_{rec} = T_{det} + T_p + T_c + T_{init} \tag{4}$$

where T_{det} is the detection time (at most 1 s for a crash, at most $3 \times 10 + 5 = 35$ s for a hang), $T_p = 1$ s is the poll before cooldown, $T_c = 10$ s is the cooldown, and T_{init} is start-up time, which for P1 is 2.0 s + 3 x 0.2 s plus up to 5 s for the handshake. A P1 crash therefore recovers in 14.6 s to 19.6 s plus interpreter start-up; the dashboard adds up to

Fig. 8: Firmware operating modes. ESTOP is a reserved latched operator-stop state: it is defined in the firmware state machine and reported as 3, but is not entered in the current build, where the emergency stop is an ordinary S (Table 7).

Fig. 9: Four-stage firmware-side command validation. The nine opcodes are F, R, L, G (speed), P, T (angle), S, H and ?.

one reconnect back-off step. The constants in this model are validated against the fault-injection measurements of Section 5.4 (`tools/eval/faultinject.py`); the current campaign (10 trials each for F3 P1, F4 P2, F5 P3) is summarised in `tools/eval/results/summary.md`. Table 9 shows how each failure degrades the mission.

P1 reports why it exited through its process exit code, which the watchdog reads to decide how to react. A clean exit, or an exit because a healthy peer already holds the serial lock (code 0), draws no alarm: the watchdog simply waits out the cooldown rather than counting a crash. An unexpected lock error (code 1) or a failed Arduino handshake (code 2) is treated as a crash and respawned. An invalid configuration (code 3) is logged distinctly so that a persistent misconfiguration cannot drive a tight respawn loop. P2 uses the same configuration-invalid code.

Fig. 10: Dead-man trip and recovery.

Fig. 11: P1 start-up handshake. A timeout ends P1 with a handshake-failure exit code.

Fig. 12: Telemetry pipeline.

TABLE 9: Failure effects and recovery.

Failure	Detected by	Effect	Recovery
Operator link lost	Dead-man; socket close	Robot stops; mission STOP	Reconnect with back-off, telemetry replay
P1 crash or hang	P3	No control or telemetry; dead-man stops robot	Respawn; buffered history lost
P2 crash	P3	Video and talk lost; control unaffected; mission DRIVING LIMITED	Respawn; operator retries video
Arduino link error	Serial read or write error	Serial flag false; mission STOP	Reads retried every 0.5 s; port reopened when P1 restarts
Camera fails to open	Media server	Synthetic test pattern sent	Next session
Microphone lost	Media server	Silence sent	Reopen tried every 2 s
GPS port error	P1	No fix; GPS-lost alert bit set	Port reopened after 2 s
Robot Screen browser exits	Kiosk launcher	Victim screen blank	Relaunch after 3 s
P3 crash	systemd	P1 and P2 stop with it; dead-man stops robot	Restart after 5 s, then P1 and P2 respawn

Fig. 13: Layered fault tolerance, from the operator side down to the motors.

Fig. 14: Per-process supervision. Health checks run every 10 s with a 5 s timeout.

Figure 15 shows how one failure, a Wi-Fi drop, passes through the tiers and how the system returns to service without operator action beyond reconnecting.

Fig. 15: Failure chain for a Wi-Fi drop: stop, reconnect, replay, resume.

TABLE 10: Mission state rules (first match wins).

Priority	State	Condition
1	STOP	Control socket down, or serial link down, or no telemetry for more than 3000 ms
2	DRIVING LIMITED	Video link down
3	DRIVING	Firmware reports driving
4	READY	Otherwise

3) Mission State for Operator Awareness: The dashboard reduces link and firmware status to one of four mission states, evaluated in the priority order of Table 10.

I. Access Control and Multi-Operator Arbitration

Because any dashboard may reconnect after a failure (Section III-H), the system must also decide which of several connected dashboards may drive. The decision is made once, in P1, and Section III-J reuses it for victim interaction. A dashboard becomes controller only by presenting the robot's controller key; all others are observers, whose commands, including stop, are rejected. The most recent dashboard with the right key takes the controller slot; the previous holder is demoted and the robot is stopped (Figure 16). P1 and P2 check

Fig. 16: Controller takeover.

TABLE 11: Key check results.

Result	Condition	Role
OK	Key matches (constant-time comparison)	Controller
No key	No key presented; not counted as a failure	Observer
Bad key	Wrong key; failure counted for that host	Observer
Locked	5 failures within 300 s; host refused for 300 s, even with the right key	Observer
Disabled	No key configured on the robot	Observer for everyone

the key in the same way (Table 11), and P2 grants talk only to a keyed session from the host P1 reports as controller.

Failure counters are kept in memory per process. The dashboard discards a refused key so that reconnects do not add to the count. The key travels over plain HTTP and WebSocket. Both P1 and P2 accept requests from any origin (permissive CORS), because the dashboard may be served from the Pi, from a development server or from a content-delivery network, so its origin is not fixed; on the isolated local network this adds no exposure beyond the plain-HTTP key already noted.

Threat model. This design assumes a trusted local network at the staging point: operators are mutually authenticated with the robot by a shared controller key, and no on-path attacker is assumed on the Wi-Fi segment that carries both the plain-HTTP key and the WebSocket control plane. Transport confidentiality beyond WebRTC's own SRTP/DTLS, and defence against a Wi-Fi-adjacent adversary, are out of scope and are discussed in Section 6.3.

J. Two-Way Victim Interaction

With one controller established (Section III-I), the same operator can see, hear and talk to the victim. This path must never delay a stop. The robot carries a display and speaker facing the victim, driven by a kiosk browser (the Robot Screen) on the Pi, and all communication between the operator and the victim runs through P2. Here "P2" names the media process (Section III-E), not a peer-to-peer protocol.

aiortc was chosen over server-oriented WebRTC stacks such as GStreamer's webrtcbin, Janus and mediasoup because it integrates as a single Python process with the P2 asyncio event loop, reuses one PyAV capture across sessions, and needs no separate signalling server, following established use of WebRTC for low-latency teleoperation [4]. Human-subject interaction in this design, namely the Robot Screen used with role-played victims and the usability study with 8 to 12 operators (Section 5.8), is conducted under the ethics statement in Section 4.1.

Media is kept out of P1 because video encoding is the heaviest load on the Pi, and a stall or crash in a codec library must not delay a stop; P2 can also be restarted while P1 keeps driving (Table 9). The only link between them is P2's once-per-second query for the controller's address (Section III-G1); P2 never sends anything to P1 or to the Arduino.

1) The P2 Media Process: P2 is a single Python process built on aiortc, a WebRTC implementation for asyncio, with PyAV (FFmpeg) for capture, decoding and encoding; every peer connection runs on one event loop (Figure 6).

- **Shared capture.** The webcam (V4L2) and the microphone (ALSA) can each be opened only once, so P2 opens each device on first use and fans its frames out to every session. Video is unbuffered, since a viewer needs only the newest frame; audio is buffered per session, since every audio frame matters. If the camera cannot be opened, the session receives a synthetic test pattern; if the microphone is missing or drops off USB, the session receives silence and P2 retries the device every 2 s.
- **Per-session tracks.** Each dashboard session gets its own outbound video and audio track, and a private copy of every camera frame for its own encoder.

Each dashboard opens one peer connection to P2 that carries both directions at once: P2 sends the robot's camera and microphone to the operator, and the operator sends voice, video and text back over the same connection (Figure 17). Any number of dashboards may connect; all receive the robot's media, but only the controller can send to the Robot Screen. Table 12 lists the video parameters.

2) Signalling and Session Lifecycle: The dashboard sends its SDP offer in one HTTP POST, together with its controller key if it has one, and the answer comes back in the HTTP response (Figure 18). There is no separate signalling server and no trickle ICE: P2 finishes gathering its candidates before it replies, so the answer is complete when it arrives. Because both peers are on the same local network, a direct host-to-host path is always available and no TURN relay is needed. The response also reports the key check result (Section III-I), so the dashboard knows at once whether the session can talk or only watch.

The dashboard offers its audio and video in both directions from the start, but sends nothing until the operator chooses to talk or show video; it then attaches the chosen source to the existing sender. Starting or stopping talk or video therefore never needs a second offer and answer.

When a connection fails or closes, P2 removes the session and releases the floor if the session held it; when no session is left, the camera and microphone are closed. P2 keeps no

Fig. 17: Two-way media path (WebRTC). Video is encoded per session as VP8 or H.264, as negotiated with the browser; each session gets its own copy of every camera frame.

TABLE 12: Video parameters.

Parameter	Robot to operator	Operator to robot
Source	USB webcam, V4L2	Laptop camera, still image or shared screen
Resolution and rate	640x480, 10 fps	Camera 640x480 at 10 fps; image 1024x576 at 2 fps; screen at 5 fps
Bitrate target	500 kbps	Chosen by the browser
Codec	VP8 or H.264, negotiated per session	Decoded by P2, re-encoded for the Robot Screen
Encoders	One per dashboard session	One, for the Robot Screen connection
Source loss	Synthetic test pattern	Last frame repeated after 1 s; black frame when no operator video

state that survives a restart, so reconnection is driven by the client. After video has connected once, a later loss is shown to the operator with a retry button rather than hidden by silent reconnects, so the operator knows that the video was interrupted.

Candidate gathering needs no help on this network. The dashboard creates its peer connection with no ICE servers configured, so both sides offer host candidates only, and the single segment of Section III-C makes a direct path available without STUN or a TURN relay. P1 does serve an ICE-configuration endpoint (`GET /api/ice-config`, rate limited to five requests per minute per client) for a deployment that would need STUN, but the dashboard does not read it in the local-network mode evaluated here. An internet-overlay mode, in which the robot would be reached through a relay and the same endpoint would also issue a TURN server, is provided for in the configuration (the `ENABLE_OVERLAY` setting in the watchdog environment) but is not implemented or evaluated in this work; the `turn_status` field carried in each telemetry snapshot therefore reports unavailable throughout.

3) Data Channel Protocol: Each dashboard connection carries one reliable, ordered data channel named ”screen” over the same DTLS connection as the media. It carries short JSON messages for control of the Robot Screen (Table 13); media and drive commands never travel on it. P2 validates every message: malformed messages are dropped, and messages from a session that is not the controller are refused with a view-only reply.

The acknowledgement closes the loop for text: the dashboard marks a message as delivered only when the Robot Screen confirms it, not when it was sent. P2 sends `talk_status` to every dashboard whenever the floor, the

TABLE 13: Data channel messages.

Message	Direction	Purpose
`media_state`	Dashboard to P2 to Robot Screen	Operator is talking or not; which video source is shown
`screen_text`	Dashboard to P2 to Robot Screen	Text message for the victim (at most 280 characters, with a timestamp)
`screen_clear`	Dashboard to P2 to Robot Screen	Remove the text from the screen
`floor_release`	Dashboard to P2	Give up the Robot Screen
`display_mode`	Dashboard to P2	Switch the robot display between the kiosk and the Pi desktop
`talk_status`	P2 to dashboard	Screen online, floor state (free, you, other), display mode, can control
`screen_state`	P2 to Robot Screen	Whether an operator is present, talking or showing video
`screen_ack`	Robot Screen to P2 to dashboard	The text with this timestamp is now shown
`floor_denied`, `view_only`	P2 to dashboard	Request refused: another operator holds the screen, or no controller key

Fig. 18: WebRTC signalling and session set-up between a dashboard and P2.

Fig. 19: Robot Screen floor control. A release clears the screen text and media.

controller or the screen connection changes, so all operators see the same state.

4) Operator-to-Robot Relay and Floor Control: The operator's media does not go from the dashboard to the Robot Screen directly. The kiosk browser connects only to P2, over localhost, and P2 relays the operator's media to it. Floor control and the controller check are therefore enforced in one place, and no remote host can reach the victim's screen or speaker, since the screen endpoint refuses any address other than localhost. The kiosk also keeps one long-lived connection that does not change when operators connect, disconnect or take over.

The cost is one decode and one re-encode on the Pi. The Robot Screen connection has two fixed outbound tracks that always read from the current floor holder: the video track sends the holder's newest frame, repeating the last one after 1 s without a new frame and sending black when there is no operator video; the audio track re-encodes the holder's voice as 48 kHz mono, 60 ms Opus packets (Section III-J5), and sends silence otherwise. Because these tracks never change, talking, switching video sources and handing over the floor need no renegotiation.

Only one session may hold the Robot Screen at a time (Figure 19). Talking follows driving: P2 accepts talk, video and text only from a session that presented the controller key and comes from the address P1 reports as its controller (Section III-I, Figure 16). A takeover therefore moves the talk path to the new driver within about one second. On release, P2 drops any queued operator media, clears the text and tells the screen that no operator is present.

5) Low-Latency Audio on a Constrained CPU: P2 encodes its own 60 ms Opus packets in both directions instead of the usual 20 ms [5], which cuts the packet rate from 50 to 16.7 packets/s and the per-packet work on the event loop to a third. It captures the microphone through a shared ALSA device with a fixed period of 960 frames (20 ms), which gives 50 reads/s against about 511 reads/s for the device's smallest period of 94 frames (Table 14).

K. GPS Localisation and Offline Mapping

The operator also needs to know where the robot is, both to guide it and to report the victim's position to the rescue team, without depending on the internet. P1 reads NMEA sentences from the NEO-6M receiver ([6]; nominal accuracy 2.5 m CEP) on a separate thread, merges the latest fix into each telemetry snapshot (Section III-G2) and adds a track point only after the robot moves at least 10 m, so drift around a stopped robot adds no points (Figure 20). This 10 m filter lies above the receiver's nominal CEP, so the static drift measured for this unit (8.9 m CEP50 over 6888 samples, `tools/eval/results/gps_static.csv`) stays below the threshold and produces no spurious points; the full result

TABLE 14: Audio parameters.

Parameter	Robot to operator	Operator to robot
Format	48 kHz, mono, 16-bit	48 kHz, mono, 16-bit
Codec	Opus, voice mode, 32 kbps	Opus, voice mode, 32 kbps
Packet length	60 ms	60 ms
Capture period and buffer	960 frames (20 ms), 7680 frames (160 ms)	–
Buffering	One queue per session	Inbound queue of 10 frames (about 200 ms); 120 ms start cushion; 400 ms cap
Lateness	Paced by the device	Clock reset when more than 100 ms late, no catch-up burst
Source loss	Silence, reopen every 2 s	Silence until the cushion refills

is reported in Section 5.6. Distance uses the equirectangular approximation:

$$d = R\sqrt{(\Delta\varphi)^2 + (\Delta\lambda\cos\bar{\varphi})^2} \tag{5}$$

where $R = 6371000$ m, $\Delta\varphi$ and $\Delta\lambda$ are the latitude and longitude differences in radians, and $\bar{\varphi}$ is their mean latitude.

At the scales of these trials (under 2 km), the error of this approximation against the haversine formula stays below 0.01 mm at the trial latitude (computed over all bearings; 0.0036 mm at a 2 km baseline), which is negligible beside both the 10 m track filter and the 8.9 m CEP50 of the receiver, while saving two trigonometric evaluations per update.

REFERENCES

[1] J. Casper and R. R. Murphy, "Human-robot interactions during the robot-assisted urban search and rescue response at the world trade center," *IEEE Transactions on Systems, Man, and Cybernetics, Part B (Cybernetics)*, vol. 33, no. 3, pp. 367–385, 2003.

[2] Y. Liu and G. Nejat, "Robotic urban search and rescue: A survey from the control perspective," *Journal of Intelligent & Robotic Systems*, vol. 72, no. 2, pp. 147–165, 2013.

[3] M. J. Pont, *Patterns for Time-Triggered Embedded Systems: Building Reliable Applications with the 8051 Family of Microcontrollers*. Harlow, England: Addison-Wesley, 2001.

[4] Y. Shi, Q. Zou, B.-J. Yi, and S. J. Maeng, "Latency and reliability optimization of a WebRTC-based remote dental surgery system with real-time force feedback," *IEEE Access*, vol. 13, pp. 176 845–176 857, 2025.

[5] J.-M. Valin, K. Vos, and T. B. Terriberry, "Definition of the Opus audio codec," Internet Engineering Task Force, RFC 6716, Sep. 2012.

[6] u-blox AG, "NEO-6 u-blox 6 GPS modules data sheet," u-blox AG, Data Sheet GPS.G6-HW-09005, 2011.

Fig. 20: GPS and map data flow. Online map tiles, when reachable, show outside the offline map area.