FRC SENSOR CAN — REVISION D-2 REGULATED PROTOTYPE

Three fixed-threshold digital inputs. 6–22 V input; regulated 12 V and 5 V sensor power.
STM32F042 + TCAN3413. Digital status and edge counts over a custom team CAN protocol.
Not a CTRE Phoenix-compatible device. Inspect and bench-test prototypes before robot use.

Battery entry and internal supplies

File: power.kicad_sch

Regulated 12 V synchronous buck-boost

File: regulated_12v.kicad_sch

Protected sensor power rails

File: sensor_power.kicad_sch

Controller, clock, debug and status

File: controller.kicad_sch

CAN physical interface and termination

File: can.kicad_sch

Input 1: fixed-threshold digital input

File: input1.kicad_sch

Input 2: fixed-threshold digital input

File: input2.kicad_sch

Input 3: fixed-threshold digital input

File: input3.kicad_sch

Original design — custom WPILib CAN protocol


Sheet: /
File: FRC_Sensor_CAN.kicad_sch

Title: FRC Sensor CAN


Size: A3	Date: 2026-09-08	**Rev: D-2**
KiCad E.D.A. 10.0.6		Id: 1/9

Battery entry and internal supplies


PROTECTED BATTERY ENTRY



500 kHz BUCK / REGULATED 5 V



3.3 V LOGIC SUPPLY



6–22 V input target. Single buck: 5.07 V nominal.
12 V buck-boost supply is on the next sheet.
R1/R2 = 102k / 13.7k, 0.1%. Buck-boost uses external bias from this 5 V rail.
TP1 is ground; use selectors/capacitor pads for rail checks.

Prototype: bench validation required before robot use


Original sensor interface design

Sheet: /Battery entry and internal supplies/
File: power.kicad_sch

Title: SC12 – Battery entry and internal supplies

Size: A3	Date: 2026-09-08	**Rev: D-2**
KiCad E.D.A. 10.0.6		Id: 2/9

Regulated 12 V synchronous buck–boost















































12.011 V nominal; 300 mA useful shared sensor load. R64 sets approximately 0.5 A output current limit.
MODE and DITH grounded: automatic PFM for light–load efficiency. 24.9k sets 781 kHz nominal.
VCC supplied by the 5 V buck; EXTVCC is a LOGIC SELECT input tied low. No extra regulator.
Join AGND to PGND only at C68 negative pad using NT1. Keep ISP/ISN Kelvin traces separate from load copper.
PG goes to MCU PA3 with internal pull–up. Power–good is an indication, not a calibrated rail measurement.
Verify startup, current limiting, compensation, transients and temperature on assembled prototypes.

Prototype: bench validation required before robot use

Original sensor interface design


Sheet: /Regulated 12 V synchronous buck–boost/
File: regulated_12v.kicad_sch

Title: SC12 – Regulated 12 V synchronous buck–boost

Size: A3	Date: 2026–09–08	**Rev: D–2**
KiCad E.D.A. 10.0.6		Id: 3/9

Protected sensor power rails

HARDWARE CURRENT LIMITING; NO FIRMWARE ENABLE









5 V sensor output: TPS2553-1 latch-off version, EN tied to input.
59k current-limit resistor. Cycle board power to clear overload.
FAULT_N goes to MCU PA4, with a firmware-enabled pull-up.
Design target: 300mA combined load on this rail, not per connector.
Do not back-power either sensor supply output.

Prototype: bench validation required before robot use
Original sensor interface design


Sheet: /Protected sensor power rails/
File: sensor_power.kicad_sch

Title: SC12 – Protected sensor power rails


Size: A3	Date: 2026-09-08	**Rev: D-2**
KiCad E.D.A. 10.0.6		Id: 4/9

Controller, clock, debug and status


8 MHz CRYSTAL / PLL x6




RESET / BOOT / SERVICE



LOCAL DECOUPLING





TC2050-IDC-NL mechanical footprint; CUSTOM electrical pinout.
Pin 6 is 3.3 V reference OUTPUT, never a programming power input.
Unused GPIOs are unconnected and initialized to analog mode.
PA3 monitors 12 V PG; PA4 monitors active-low 5 V fault. No rail ADCs.


Prototype: bench validation required before robot use
Original sensor interface design


Sheet: /Controller, clock, debug and status/
File: controller.kicad_sch

Title: SC12 – Controller, clock, debug and status


Size: A3	Date: 2026-09-08	**Rev: D-2**
KiCad E.D.A. 10.0.6		Id: 5/9


CAN physical interface and termination























1 Mbit/s. Bridge JP2 only at a physical CAN trunk end.
TCAN3413 uses 3.3 V for both VCC and VIO.
STB pull-up keeps the bus silent during MCU reset.
CAN ground is shared through the power connection.

SINGLE STATUS INDICATOR



Prototype: bench validation required before robot use

Original sensor interface design


Sheet: /CAN physical interface and termination/
File: can.kicad_sch


Title: SC12 – CAN physical interface and termination


Size: A3	Date: 2026-09-08	**Rev: D-2**
KiCad E.D.A. 10.0.6		Id: 6/9

Input 1: fixed–threshold digital input

REMOVABLE POWER JUMPER / SOLDERED INPUT BIAS















POWER: fit ONE 2 mm cap at 1–2 for 5 V OR 2–3 for regulated 12 V: never connect all three.
BIAS: solder 1–2 for NPN, 2–3 for PNP, leave open for push–pull/external bias.
User fits power headers; no caps at initial bring–up. Voltage–tolerant NPN output required for selected pullup.





0–30 V signal design range; software debounce follows the hardware filter.
Nominal thresholds near 2.0 V rising / 1.65 V falling. Final bounds are in electrical_checks.json.
No analog measurement, 1.8 V logic guarantee or CTRE protocol compatibility.

Prototype: bench validation required before robot use
Original sensor interface design


Sheet: /Input 1: fixed–threshold digital input/
File: input1.kicad_sch

Title: SC12 – Input 1: fixed–threshold digital input

Size: A3	Date: 2026–09–08	**Rev: D–2**
KiCad E.D.A. 10.0.6		Id: 7/9

Input 2: fixed–threshold digital input

REMOVABLE POWER JUMPER / SOLDERED INPUT BIAS



POWER: fit ONE 2 mm cap at 1–2 for 5 V OR 2–3 for regulated 12 V: never connect all three.
BIAS: solder 1–2 for NPN, 2–3 for PNP, leave open for push–pull/external bias.
User fits power headers; no caps at initial bring–up. Voltage–tolerant NPN output required for selected pullup.

The reference divider/filter and comparator power connections are on input1.
One fixed logic–compatible threshold for all three channels; no industrial threshold selector.

0–30 V signal design range; software debounce follows the hardware filter.
Nominal thresholds near 2.0 V rising / 1.65 V falling. Final bounds are in electrical_checks.json.
No analog measurement, 1.8 V logic guarantee or CTRE protocol compatibility.

Prototype: bench validation required before robot use
Original sensor interface design


Sheet: /Input 2: fixed–threshold digital input/
File: input2.kicad_sch

Title: SC12 – Input 2: fixed–threshold digital input

Size: A3	Date: 2026–09–08	**Rev: D–2**
KiCad E.D.A. 10.0.6		Id: 8/9

Input 3: fixed–threshold digital input

REMOVABLE POWER JUMPER / SOLDERED INPUT BIAS



POWER: fit ONE 2 mm cap at 1–2 for 5 V OR 2–3 for regulated 12 V: never connect all three.
BIAS: solder 1–2 for NPN, 2–3 for PNP, leave open for push–pull/external bias.
User fits power headers; no caps at initial bring–up. Voltage–tolerant NPN output required for selected pullup.

The reference divider/filter and comparator power connections are on input1.
One fixed logic–compatible threshold for all three channels; no industrial threshold selector.

0–30 V signal design range; software debounce follows the hardware filter.
Nominal thresholds near 2.0 V rising / 1.65 V falling. Final bounds are in electrical_checks.json.
No analog measurement, 1.8 V logic guarantee or CTRE protocol compatibility.

Prototype: bench validation required before robot use
Original sensor interface design

Sheet: /Input 3: fixed–threshold digital input/		
File: input3.kicad_sch		
Title: SC12 – Input 3: fixed–threshold digital input		
Size: A3	Date: 2026–09–08	**Rev: D–2**
KiCad E.D.A. 10.0.6		Id: 9/9